



ThinkSystem ST250 V2 Messages and Codes Reference



Machine Types: 7D8F and 7D8G

Note

Before using this information and the product it supports, be sure to read and understand the safety information and the safety instructions, which are available at:

http://thinksystem.lenovofiles.com/help/topic/safety_documentation/pdf_files.html

In addition, be sure that you are familiar with the terms and conditions of the Lenovo warranty for your server, which can be found at:

<http://datacentersupport.lenovo.com/warrantylookup>

First Edition (March 2022)

© Copyright Lenovo 2022.

LENOVO and THINKSYSTEM are trademarks of Lenovo. All other trademarks are the property of their respective owners.

LIMITED AND RESTRICTED RIGHTS NOTICE: If data or software is delivered pursuant to a General Services Administration (GSA) contract, use, reproduction, or disclosure is subject to restrictions set forth in Contract No. GS-35F-05925.

Contents

Chapter 1. Introduction 1
Event and alert message format 1

Chapter 2. XClarity Controller events 5
XCC events that automatically notify Support 6
XCC events organized by severity. 7
List of XClarity Controller events 24

Chapter 3. UEFI events 133
UEFI events organized by severity 133
List of UEFI events. 136

Chapter 4. XClarity Provisioning Manager events 153
LXPM events organized by severity 153
List of XClarity Provisioning Manager events 156

Appendix A. Getting help and technical assistance 177
Before you call 177
Collecting service data 178
Contacting Support 179

Index 181

Chapter 1. Introduction

When attempting to resolve issues with your server, the best practice is to begin with the event log of the application that is managing the server:

- If you are managing the server from the Lenovo XClarity Administrator, begin with the Lenovo XClarity Administrator event log.
- If you are using some other management application, begin with the Lenovo XClarity Controller event log.

The event log contains server hardware events that are recorded by the Lenovo XClarity Controller or by UEFI. In addition, events can be generated when you perform diagnostic testing on hard drives or memory through the Lenovo XClarity Provisioning Manager (although these events are not stored in the event log).

Use this section to view the events that can be generated by Lenovo XClarity Controller, UEFI, or the Lenovo XClarity Provisioning Manager. For each event, a user action is available to help you understand what must be done to resolve the issue.

Important:

- Lenovo XClarity Controller (XCC) supported version varies by product. All versions of Lenovo XClarity Controller are referred to as Lenovo XClarity Controller and XCC in this document, unless specified otherwise. To see the XCC version supported by your server, go to https://sysmgt.lenovofiles.com/help/topic/ixcc_frontend/ixcc_overview.html.
- Lenovo XClarity Provisioning Manager (LXPM) supported version varies by product. All versions of Lenovo XClarity Provisioning Manager are referred to as Lenovo XClarity Provisioning Manager and LXPM in this document, unless specified otherwise. To see the LXPM version supported by your server, go to https://sysmgt.lenovofiles.com/help/topic/lxpm_frontend/lxpm_product_page.html.

Event and alert message format

You can use the following content to help you understand the event and alert message format.

The following information is provided for each event message.

Event identifier

A string that uniquely identifies the event or class of events. This is a 12 character string in the following format:

`FQXppnnxxxxc`

where:

- `pp` indicates the product where the event originate, as follows.
 - **CM**. Chassis Management.
 - **HM**. Hardware manager.
 - **PM**. XClarity Provisioning manger - LXPM (LEPT).
 - **SF**. System Firmware.
 - **SP**. Service Processor.
- `nn` identifies the component or system management where the event originated, as follows:
 - Components*
 - **AA**. Canister/Appliance - Contains system components not expected to be serviced by a customer.

- **CA.** Cooling - Fans, blowers, mux cards, policies, chillers/refrigeration, water management units, water pumps, water filtration, air flow sensors, thermal monitors.
- **DA.** Display - Graphics adapters, op panel, monitor/console (including front/back panel, control panel, LCD panel etc).
- **IO.** I/O connectivity - PCI/USB hub, bridge, bus, risers, configuration settings, interconnect, keyboard, mouse, KVM.
- **MA.** Memory - Includes memory modules, memory card, configuration settings, memory controller, redundant modes (mirroring, spare, etc), RAID memory, NVRAM, EPROM.
- **PU.** Processing - Involves the processor, processor cards and system board, configuration settings, and microcode, cache, Trusted Computing Module, processor interconnect (QPI cables).
- **PW.** Power - Can be power supplies, VRMs, VRDs, voltage levels, system power state, policies, batteries, AT power width, TPMD, power controllers, external power, Battery Backup Unit (UPS), PDUs.
- **SB.** System Board - Main system board, associated risers, system planar, mid-planes, backplanes, interconnects.
- **SD.** Client Data Storage Device - Flash storage adapters, drives, cd/dvd drives, SSD, SAS, DASD, Flash storage, tape, volumes, remoteCopy, flashCopy, managed Storage Systems.
- **SR.** Storage RAID - Adapters, configuration, settings, interconnect, arrays, drive enclosures.
- **VD.** VPD - Configuration settings, EPROMs, communication.

Systems Management - FSM, PSM, HMC, FDMC UEFI, CMM, IOMC, CCE, PMC, DPSM, SVC, management of storage, services, IMM, FSP, systems management networking.

- **BR.** Systems Management - Backup/Restore & Failover (HA).
- **BT.** System management - Boot, reboot, hard/warm reset, shutdown.
- **CL.** LEPT Clone.
- **CN.** Systems Management - Console.
- **CP.** Systems Management - Config Patterns.
- **CR.** Systems Management - Core / Virtual Appliance.
- **DD.** Device Driver - AIX, IBM I, Subsystem Device Driver (SDD), IPMI Service.
- **DM.** Systems Management - Data Management.
- **EA.** Vendor Events.
- **EM.** Events Monitoring - LEPT Dash Board.
- **EM.** Systems Management - Events / Monitoring.
- **FC.** Systems Management - FlexCat OS/Config deployment.
- **FW.** System management - Firmware.
- **HA.** Hypervisor - Virtual Components, Boots, Crashes, SRIOV, LPARs.
- **IF.** Interconnect (Fabric) - common, podm, icm, Irim (SWFW major, various minors & functions).
- **II.** Interconnect (Interfaces) - cimp, smis, cli, mapi (SCFG major).
- **IM.** Interconnect (PCI Manager) - pcim (SWFW major, various minors and functions).
- **IN.** Interconnect (Networking) - bos, ethm, fcf, npiv (FCF major plus SWFW major, various minors & functions) data network, network settings, ports, security, adapters, switches, fiber channel, optical ports, Ethernet.
- **IP.** Interconnect (PIE) - tbd.
- **IU.** Interconnect (Utilities / Infrastructure) - util, infr, serv, isds (IBIS major), remote copy (storage).
- **NM.** Network Management - LEPT Welcompage.
- **NM.** Systems Management - Network Management.
- **OH.** OS/Hypervisor Interface - Passing of error logs, partition management, services (time, etc).
- **OS.** LEPT OS Deploy.
- **OS.** OS - Power Linux, AIX IPL, AIX, crash and dump codes, IBM i kernal code, IBM i OS, management of storage.
- **PR.** System management - Entity presence.
- **RC.** Systems Management - Remote Control.
- **SD.** LEPT Storage Test.
- **SE.** Systems Management - Security.
- **SR.** LEPT Raid Setup.

- **SS.** Service & Support - LEPT FFDC Collection.
 - **SS.** Systems Management - Service & Support.
 - **TR.** Time Reference - RTC, Master clock, drawer clocks, NTP.
 - **UN.** Unknown/any entity.
 - **UP.** LEPT Firmware Update.
 - **UP.** Systems Management - Updates.
 - **WD.** System management - Watchdog.
- **xxxx** is an incrementing number of the Sub-System events set.
 - **c** identifies the severity, as follows.
 - **A.** Reserved as Immediate Action.
 - **B.** Unknown / No action.
 - **D.** Reserved - Immediate Decision.
 - **E.** Reserved - Eventual Action.
 - **F.** Warning / No Action.
 - **G.** Warning / Deferred Action.
 - **H.** Minor / Deferred Action.
 - **I.** Information / No Action.
 - **J.** Minor / Immediate Action.
 - **K.** Major / Deferred Action.
 - **L.** Major / Immediate Action.
 - **M.** Critical / Immediate Action.
 - **N.** Fatal / Immediate Action.
 - **W.** Reserved - System Wait.

Chapter 2. XClarity Controller events

When a hardware event is detected by the Lenovo XClarity Controller on the server, the Lenovo XClarity Controller writes that event in the system-event log on the server.

Notes: Event identifier (ID) is a unique identifier used to search for XCC events. The event message may have one or more arguments, which could be replaceable text of FRU name or sensor name to identify the failed component. So one XCC event ID could represent a generic event or similar faults that happened on different hardware components. The general way of problem determination is to locate the event by ID, identify the hardware component by message argument if it contains hardware component name, and then perform actions defined in User Action.

Example:

FQXSPCA0017M: Sensor [SensorElementName] has transitioned to critical from a less severe state where:

- FQXSPCA0017M is the event ID.
- *[SensorElementName]* is a sensor variable, indicating the name of hardware component. It can be CPU, PCI adapter, OCP card or chipset. You can find the event by the event ID FQXSPCA0017M and perform actions defined in User Action for the component.

For additional information about the Lenovo XClarity Controller event log, see “Viewing Event Logs” section in the XCC documentation compatible with your server at https://sysmgmt.lenovofiles.com/help/topic/lxcc_frontend/lxcc_overview.html.

For each event code, the following fields are displayed:

Event identifier

An identifier that uniquely identifies an event.

Event description

The logged message string that appears for an event. When the event string is displayed in the event log, information such as a specific component is displayed. In this documentation, that additional information appears as variables, which include but not limited to the following:

- *[SensorElementName]*, *[ManagedElementName]*, *[ProcessorElementName]*, *[ComputerSystemElementName]*, *[PowerSupplyElementName]*, ...
- *[arg1]*, *[arg2]*, *[arg3]*, *[arg4]*, *[arg5]*...

Explanation

Provides additional information to explain why the event occurred.

Severity

An indication of the level of concern for the condition. The following severities can be displayed.

- **Informational.** The event was recorded for audit purposes, usually a user action or a change of states that is normal behavior.
- **Warning.** The event is not as severe as an error, but if possible, the condition should be corrected before it becomes an error. It might also be a condition that requires additional monitoring or maintenance.
- **Error.** The event is a failure or critical condition that impairs service or an expected function.

Alert Category

Similar events are grouped together in categories. The alert category is in the following format: *severity - device*, where:

- *severity* is one of the following severity levels:
 - **Critical.** A key component in the server is no longer functioning.
 - **Warning.** The event might progress to a critical level.
 - **System.** The event is the result of a system error or a configuration change.
- *device* is the specific device in the server that caused the event to be generated.

Serviceable

Specifies whether user action is required to correct the problem.

CIM Information

Provides the prefix of the message ID and the sequence number that is used by the CIM message registry.

SNMP Trap ID

The SNMP trap ID that is found in the SNMP alert management information base (MIB).

Automatically contact Service

You can configure the Lenovo XClarity Administrator to automatically notify Support (also known as call home) if certain types of errors are encountered. If you have configured this function and this field is set to Yes, Lenovo Support will be notified automatically if the event is generated. While you wait for Lenovo Support to call, you can perform the recommended actions for the event.

Note: This documentation includes references to IBM web sites, products, and information about obtaining service. IBM is Lenovo's preferred service provider for the Lenovo server products.

For more information about enabling Call Home from Lenovo XClarity Administrator, see http://sysmgt.lenovofiles.com/help/topic/com.lenovo.lxca.doc/admin_setupcallhome.html. In addition, see “XCC events that automatically notify Support” on page 6 for a consolidated list of all Lenovo XClarity Controller events that are called home to Lenovo Support.

User Action

Indicates what actions you should perform to solve the event. Perform the steps listed in this section in the order shown until the problem is solved. If you cannot solve the problem after performing all steps, contact Lenovo Support.

XCC events that automatically notify Support

You can configure the XClarity Administrator to automatically notify Support (also known as *call home*) if certain types of errors are encountered. If you have configured this function, see the table for a list of events that automatically notify Support.

Table 1. Events that automatically notify Support

Event ID	Message String
FQXSPeM4014I	The RAID controller has problem with the battery. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])
FQXSPeM4015I	The RAID controller detected unrecoverable error. The controller needs replacement.([arg1],[arg2],[arg3],[arg4],[arg5])
FQXSPeM4025I	One or more virtual drive have problem. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])
FQXSPeM4026I	Drive error was detected by RAID controller. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])

Table 1. Events that automatically notify Support (continued)

Event ID	Message String
FQXSPIO0001L	The connector [PhysicalConnectorElementName] has encountered a configuration error.
FQXSPIO0011N	An Uncorrectable Error has occurred on [SensorElementName].
FQXSPIO0015M	Fault in slot [PhysicalConnectorSystemElementName] on system [ComputerSystemElementName].
FQXSPMA0007L	Scrub Failure for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].
FQXSPMA0008N	Uncorrectable error detected for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].
FQXSPMA0011G	Memory Logging Limit Reached for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].
FQXSPPU0004M	[ProcessorElementName] has Failed with FRB1/BIST condition.
FQXSPPW0002L	[PowerSupplyElementName] has Failed.
FQXSPPW0035M	Numeric sensor [NumericSensorElementName] going low (lower critical) has asserted.
FQXSPPW0047M	Numeric sensor [NumericSensorElementName] going high (upper critical) has asserted.
FQXSPSD0001L	The [StorageVolumeElementName] has a fault.
FQXSPSD0002G	Failure Predicted on [StorageVolumeElementName] for array [ComputerSystemElementName].
FQXSPSD0002L	Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has a fault.
FQXSPSD0003G	Failure Predicted on drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).
FQXSPSD0006L	Array [ComputerSystemElementName] has failed.
FQXSPSD0008L	Array failed on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).
FQXSPSS4004I	Test Call Home Generated by user [arg1].
FQXSPSS4005I	Manual Call Home by user [arg1]: [arg2].

XCC events organized by severity

The following table lists all XCC events, organized by severity (Informational, Error, and Warning).

Table 2. Events organized by severity

Event ID	Message String	Severity
FQXSPBR4000I	Management Controller [arg1]: Configuration restored from a file by user [arg2].	Informational
FQXSPBR4002I	Management Controller [arg1] Reset was caused by restoring default values.	Informational
FQXSPBR4004I	Server timeouts set by user [arg1]: EnableOSWatchdog=[arg2], OSWatchdogTimeout=[arg3], EnableLoaderWatchdog=[arg4], LoaderTimeout=[arg5].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPBR4005I	Management Controller [arg1]: Configuration saved to a file by user [arg2].	Informational
FQXSPBR4006I	Management Controller [arg1]: Configuration restoration from a file by user [arg2] completed.	Informational
FQXSPCA2002I	Numeric sensor [NumericSensorElementName] going low (lower critical) has deasserted.	Informational
FQXSPCA2007I	Numeric sensor [NumericSensorElementName] going high (upper non-critical) has deasserted.	Informational
FQXSPCA2009I	Numeric sensor [NumericSensorElementName] going high (upper critical) has deasserted.	Informational
FQXSPCA2011I	Numeric sensor [NumericSensorElementName] going high (upper non-recoverable) has deasserted.	Informational
FQXSPCA2015I	Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.	Informational
FQXSPCA2017I	Sensor [SensorElementName] has transitioned to a less severe state from critical.	Informational
FQXSPCA2019I	Sensor [SensorElementName] has deasserted the transition to non-recoverable from a less severe state.	Informational
FQXSPCN4000I	Serial Redirection set by user [arg1]: Mode=[arg2], BaudRate=[arg3], StopBits=[arg4], Parity=[arg5], SessionTerminateSequence=[arg6].	Informational
FQXSPCN4001I	Remote Control session started by user [arg1] in [arg2] mode.	Informational
FQXSPCN4002I	User [arg1] has terminated an active console session.	Informational
FQXSPCN4003I	Remote Control session started by user [arg1] in [arg2] mode has been closed.	Informational
FQXSPCR2001I	Sensor [SensorElementName] has deasserted the transition to non-recoverable from a less severe state.	Informational
FQXSPDM4000I	Inventory data changed for device [arg1], new device data hash=[arg2], new master data hash=[arg3] .	Informational
FQXSPDM4001I	Storage [arg1] has changed.	Informational
FQXSPDM4003I	TKLM servers set by user [arg1]: TKLMServer1=[arg2] Port=[arg3], TKLMServer2=[arg4] Port=[arg5], TKLMServer3=[arg6] Port=[arg7], TKLMServer4=[arg8] Port=[arg9].	Informational
FQXSPDM4004I	TKLM servers device group set by user [arg1]: TKLMServerDeviceGroup=[arg2] .	Informational
FQXSPDM4005I	User [arg1] has generated a new encryption key pair and installed a self-signed certificate for the TKLM client.	Informational
FQXSPDM4006I	User [arg1] has generated a new encryption key and certificate signing request for the TKLM client.	Informational
FQXSPDM4007I	User [arg1] has imported a signed certificate for the TKLM client from [arg2].	Informational
FQXSPDM4008I	User [arg1] has imported a server certificate for the TKLM server.	Informational
FQXSPDM4009I	User [arg1] has [arg2] file [arg3] from [arg4].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPDM4010I	Inventory data collecting and processing complete for [arg1], sequence number is [arg2].	Informational
FQXSPEA2001I	Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.	Informational
FQXSPEA2002I	Sensor [SensorElementName] has transitioned to a less severe state from critical.	Informational
FQXSPEA2003I	Link up is detected on port [arg1] of the PCIe device [arg2].	Informational
FQXSPEM0003I	The Log [RecordLogElementName] has been cleared.	Informational
FQXSPEM0004I	The Log [RecordLogElementName] is full.	Informational
FQXSPEM0005I	The Log [RecordLogElementName] is almost full.	Informational
FQXSPEM0009I	The System [ComputerSystemElementName] has generated an auxiliary Log Entry in Log [RecordLogElement].	Informational
FQXSPEM4000I	The [arg1] on system [arg2] cleared by user [arg3].	Informational
FQXSPEM4001I	The [arg1] on system [arg2] is 75% full.	Informational
FQXSPEM4002I	The [arg1] on system [arg2] is 100% full.	Informational
FQXSPEM4003I	LED [arg1] state changed to [arg2] by [arg3].	Informational
FQXSPEM4004I	SNMP [arg1] enabled by user [arg2] .	Informational
FQXSPEM4005I	SNMP [arg1] disabled by user [arg2] .	Informational
FQXSPEM4006I	Alert Configuration Global Event Notification set by user [arg1]: RetryLimit=[arg2], RetryInterval=[arg3], EntryInterval=[arg4].	Informational
FQXSPEM4007I	Alert Recipient Number [arg1] updated: Name=[arg2], DeliveryMethod=[arg3], Address=[arg4], IncludeLog=[arg5], Enabled=[arg6], EnabledAlerts=[arg7], AllowedFilters=[arg8] by user [arg9] from [arg10] at IP address [arg11].	Informational
FQXSPEM4008I	SNMP Traps enabled by user [arg1]: EnabledAlerts=[arg2], AllowedFilters=[arg3] .	Informational
FQXSPEM4009I	The UEFI Definitions have been changed.	Informational
FQXSPEM4010I	UEFI Reported: [arg1].	Informational
FQXSPEM4011I	XCC failed to log previous event [arg1].	Informational
FQXSPEM4012I	User [arg1] made system [arg2] Encapsulation lite Mode.	Informational
FQXSPEM4013I	Battery error was detected by RAID controller. The battery unit needs replacement.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4014I	The RAID controller has problem with the battery. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4015I	The RAID controller detected unrecoverable error. The controller needs replacement.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4016I	The RAID controller detected one or more problems. Please contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPEM4017I	The RAID controller detected one or more possible configuration changes within the subsystem. Please check the drive LED status. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4018I	Enclosure/Chassis issue detected with one or more units. Please check the enclosure/chassis units to repair the problem.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4019I	Connectivity issue detected with the enclosure/chassis. Please check your cable configurations to repair the problem.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4020I	Fan problem detected with the enclosure/chassis. Please check the enclosure/chassis unit fan for correct operation.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4022I	Enclosure/Chassis power supply has problem. Please check the enclosure/chassis unit power supply for correct operation.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4023I	One or more virtual drive are in abnormal status that may cause unavailable virtual drive. Please check the event logs and if events are targeted to the same disk then replace the drive. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4024I	The RAID controller detected one or more possible configuration problem within the subsystem. Please check the event logs and if events are targeted to the same disk then replace the drive. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4025I	One or more virtual drive have problem. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4026I	Drive error was detected by RAID controller. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4027I	Drive error was detected by RAID controller. Please check the event logs and if events are targeted to the same disk then replace the drive. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPEM4028I	The port [arg1] of PCIe device [arg2] at [arg3] has link [arg4].	Informational
FQXSPEM4029I	All PCIe slots on [arg1] may not be functional based upon your current CPU population.	Informational
FQXSPEM4030I	A scheduled operation on the RAID controller has encountered an issue. Refer to RAID Logs under Server Management, Local Storage, for details.([arg1],[arg2],[arg3],[arg4],[arg5])	Informational
FQXSPFC4000I	The bare metal connection process has been started.	Informational
FQXSPFC4001I	The bare metal update application reports a status of [arg1].	Informational
FQXSPFC4002I	System running in setup.	Informational
FQXSPFC4003I	UEFI deployment boot mode is enabled for NextBoot.	Informational
FQXSPFC4004I	UEFI deployment boot mode is enabled for NextAc.	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPFC4005I	UEFI deployment boot mode has been disabled.	Informational
FQXSPFW0003I	The System [ComputerSystemElementName] encountered firmware progress.	Informational
FQXSPIO0000I	The connector [PhysicalConnectorElementName] has been connected.	Informational
FQXSPIO0010I	A Correctable Bus Error has occurred on bus [SensorElementName].	Informational
FQXSPIO2001I	The connector [PhysicalConnectorElementName] configuration error has been repaired.	Informational
FQXSPIO2003I	System [ComputerSystemElementName] has recovered from a diagnostic interrupt.	Informational
FQXSPIO2004I	Bus [SensorElementName] has recovered from a bus timeout.	Informational
FQXSPIO2006I	System [ComputerSystemElementName] has recovered from an NMI.	Informational
FQXSPIO2007I	A PCI PERR recovery has occurred on system [ComputerSystemElementName].	Informational
FQXSPIO2008I	A PCI SERR on system [ComputerSystemElementName] has deasserted.	Informational
FQXSPIO2010I	Bus [SensorElementName] has recovered from a Correctable Bus Error.	Informational
FQXSPMA0001I	Error Detected and Corrected for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Informational
FQXSPMA0022I	Memory sparing initiated for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Informational
FQXSPMA0025I	Sensor [SensorElementName] has asserted.	Informational
FQXSPMA2007I	Scrub Failure for [PhysicalMemoryElementName] on Subsystem [MemoryElementName] has recovered.	Informational
FQXSPMA2010I	[PhysicalMemoryElementName] on Subsystem [MemoryElementName] is no longer Throttled.	Informational
FQXSPMA2012I	An Over-Temperature Condition has been removed on the [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Informational
FQXSPMA2024I	Sensor [SensorElementName] has deasserted.	Informational
FQXSPNM4000I	Management Controller [arg1] Network Initialization Complete.	Informational
FQXSPNM4001I	Ethernet Data Rate modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4002I	Ethernet Duplex setting modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4003I	Ethernet MTU setting modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4004I	Ethernet locally administered MAC address modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4005I	Ethernet interface [arg1] by user [arg2].	Informational
FQXSPNM4006I	Hostname set to [arg1] by user [arg2].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPNM4007I	IP address of network interface modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4008I	IP subnet mask of network interface modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4009I	IP address of default gateway modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4011I	ENET[[arg1]] DHCP-HSTN=[arg2], DN=[arg3], IP@=[arg4], SN=[arg5], GW@=[arg6], DNS1@=[arg7] .	Informational
FQXSPNM4012I	ENET[[arg1]] IP-Cfg:HstName=[arg2], IP@=[arg3] ,NetMsk=[arg4], GW@=[arg5] .	Informational
FQXSPNM4013I	LAN: Ethernet[[arg1]] interface is no longer active.	Informational
FQXSPNM4014I	LAN: Ethernet[[arg1]] interface is now active.	Informational
FQXSPNM4015I	DHCP setting changed to [arg1] by user [arg2].	Informational
FQXSPNM4016I	Domain name set to [arg1] by user [arg2].	Informational
FQXSPNM4017I	Domain Source changed to [arg1] by user [arg2].	Informational
FQXSPNM4018I	DDNS setting changed to [arg1] by user [arg2].	Informational
FQXSPNM4019I	DDNS registration successful. The domain name is [arg1].	Informational
FQXSPNM4020I	IPv6 enabled by user [arg1] .	Informational
FQXSPNM4021I	IPv6 disabled by user [arg1] .	Informational
FQXSPNM4022I	IPv6 static IP configuration enabled by user [arg1].	Informational
FQXSPNM4023I	IPv6 DHCP enabled by user [arg1].	Informational
FQXSPNM4024I	IPv6 stateless auto-configuration enabled by user [arg1].	Informational
FQXSPNM4025I	IPv6 static IP configuration disabled by user [arg1].	Informational
FQXSPNM4026I	IPv6 DHCP disabled by user [arg1].	Informational
FQXSPNM4027I	IPv6 stateless auto-configuration disabled by user [arg1].	Informational
FQXSPNM4028I	ENET[[arg1]] IPv6-LinkLocal:HstName=[arg2], IP@=[arg3] ,Pref=[arg4] .	Informational
FQXSPNM4029I	ENET[[arg1]] IPv6-Static:HstName=[arg2], IP@=[arg3] ,Pref=[arg4], GW@=[arg5] .	Informational
FQXSPNM4030I	ENET[[arg1]] DHCPv6-HSTN=[arg2], DN=[arg3], IP@=[arg4], Pref=[arg5], DNS1@=[arg5].	Informational
FQXSPNM4031I	IPv6 static address of network interface modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4033I	Telnet port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4034I	SSH port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4035I	Web-HTTP port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4036I	Web-HTTPS port number changed from [arg1] to [arg2] by user [arg3].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPNM4037I	CIM/XML HTTP port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4038I	CIM/XML HTTPS port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4039I	SNMP Agent port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4040I	SNMP Traps port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4041I	Syslog port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4042I	Remote Presence port number changed from [arg1] to [arg2] by user [arg3].	Informational
FQXSPNM4043I	SMTP Server set by user [arg1] to [arg2]:[arg3].	Informational
FQXSPNM4044I	Telnet [arg1] by user [arg2].	Informational
FQXSPNM4045I	DNS servers set by user [arg1]: UseAdditionalServers=[arg2], PreferredDNStype=[arg3], IPv4Server1=[arg4], IPv4Server2=[arg5], IPv4Server3=[arg6], IPv6Server1=[arg7], IPv6Server2=[arg8], IPv6Server3=[arg9].	Informational
FQXSPNM4046I	LAN over USB [arg1] by user [arg2].	Informational
FQXSPNM4047I	LAN over USB Port Forwarding set by user [arg1]: ExternalPort=[arg2], USB-LAN port=[arg3].	Informational
FQXSPNM4048I	PXE boot requested by user [arg1].	Informational
FQXSPNM4049I	User [arg1] has initiated a TKLM Server Connection Test to check connectivity to server [arg2].	Informational
FQXSPNM4050I	User [arg1] has initiated an SMTP Server Connection Test.	Informational
FQXSPNM4051I	User [arg1] has set the SMTP Server reverse-path to [arg2].	Informational
FQXSPNM4052I	DHCP specified hostname is set to [arg1] by user [arg2].	Informational
FQXSPNM4053I	DNS discovery of Lenovo XClarity Administrator has been [arg1] by user [arg2].	Informational
FQXSPNM4054I	The hostname from DHCP is [arg1] by user [arg2].	Informational
FQXSPNM4055I	The hostname from DHCP is invalid.	Informational
FQXSPNM4056I	The NTP server address [arg1] is invalid.	Informational
FQXSPNM4057I	Security: IP address: [arg1] had [arg2] login failures, it will be blocked to access for [arg3] minutes.	Informational
FQXSPOS4000I	OS Watchdog response [arg1] by [arg2] .	Informational
FQXSPOS4001I	Watchdog [arg1] Screen Capture Occurred .	Informational
FQXSPOS4004I	Operating System status has changed to [arg1].	Informational
FQXSPOS4005I	Host Power-On password changed by user [arg1] from [arg2] at IP address [arg3].	Informational
FQXSPOS4006I	Host Power-On password cleared by user [arg1] from [arg2] at IP address [arg3].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPOS4007I	Host Admin password changed by user [arg1] from [arg2] at IP address [arg3].	Informational
FQXSPOS4008I	Host Admin password cleared by user [arg1] from [arg2] at IP address [arg3].	Informational
FQXSPOS4009I	OS Crash Video Captured.	Informational
FQXSPPP4000I	Attempting to [arg1] server [arg2] by user [arg3].	Informational
FQXSPPP4001I	Server Power Off Delay set to [arg1] by user [arg2].	Informational
FQXSPPP4002I	Server [arg1] scheduled for [arg2] at [arg3] by user [arg4].	Informational
FQXSPPP4003I	Server [arg1] scheduled for every [arg2] at [arg3] by user [arg4].	Informational
FQXSPPP4004I	Server [arg1] [arg2] cleared by user [arg3].	Informational
FQXSPPP4005I	The power cap value changed from [arg1] watts to [arg2] watts by user [arg3].	Informational
FQXSPPP4006I	The minimum power cap value changed from [arg1] watts to [arg2] watts.	Informational
FQXSPPP4007I	The maximum power cap value changed from [arg1] watts to [arg2] watts.	Informational
FQXSPPP4008I	The soft minimum power cap value changed from [arg1] watts to [arg2] watts.	Informational
FQXSPPP4011I	Power capping was activated by user [arg1].	Informational
FQXSPPP4012I	Power capping was deactivated by user [arg1].	Informational
FQXSPPP4013I	Static Power Savings mode has been turned on by user [arg1].	Informational
FQXSPPP4014I	Static Power Savings mode has been turned off by user [arg1].	Informational
FQXSPPP4015I	Dynamic Power Savings mode has been turned on by user [arg1].	Informational
FQXSPPP4016I	Dynamic Power Savings mode has been turned off by user [arg1].	Informational
FQXSPPP4017I	Power cap and external throttling occurred.	Informational
FQXSPPP4018I	External throttling occurred .	Informational
FQXSPPP4019I	Power cap throttling occurred.	Informational
FQXSPPP4020I	The measured power value has returned below the power cap value.	Informational
FQXSPPP4021I	The new minimum power cap value has returned below the power cap value.	Informational
FQXSPPP4022I	The server was restarted for an unknown reason.	Informational
FQXSPPP4023I	The server is restarted by chassis control command.	Informational
FQXSPPP4024I	The server was reset via push button.	Informational
FQXSPPP4025I	The server was powered-up via power push button.	Informational
FQXSPPP4026I	The server was restarted when the watchdog expired..	Informational
FQXSPPP4027I	The server was restarted for OEM reason.	Informational
FQXSPPP4028I	The server was automatically powered on because the power restore policy is set to always restore..	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPPP4029I	The server was automatically powered on because the power restore policy is set to restore previous power state..	Informational
FQXSPPP4030I	The server was reset via Platform Event Filter.	Informational
FQXSPPP4031I	The server was power-cycled via Platform Event Filter.	Informational
FQXSPPP4032I	The server was soft reset.	Informational
FQXSPPP4033I	The server was powered up via Real Time Clock (scheduled power on).	Informational
FQXSPPP4034I	The server was powered off for an unknown reason.	Informational
FQXSPPP4035I	The server was powered off by chassis control command.	Informational
FQXSPPP4036I	The server was powered off via push button.	Informational
FQXSPPP4037I	The server was powered off when the watchdog expired.	Informational
FQXSPPP4038I	The server stayed powered off because the power restore policy is set to always restore..	Informational
FQXSPPP4039I	The server stayed powered off because the power restore policy is set to restore previous power state..	Informational
FQXSPPP4040I	The server was powered off via Platform Event Filter.	Informational
FQXSPPP4041I	The server was powered off via Real Time Clock (scheduled power off).	Informational
FQXSPPP4042I	Management Controller [arg1] reset was initiated due to Power-On-Reset.	Informational
FQXSPPP4043I	Management Controller [arg1] reset was initiated by PRESET.	Informational
FQXSPPP4044I	Management Controller [arg1] reset was initiated by CMM.	Informational
FQXSPPP4045I	Management Controller [arg1] reset was initiated by XCC firmware.	Informational
FQXSPPP4046I	Remote power permission is [arg1].	Informational
FQXSPPP4047I	Management Controller [arg1] reset was initiated by user [arg2].	Informational
FQXSPPP4048I	Attempting to AC power cycle server [arg1] by user [arg2].	Informational
FQXSPPP4049I	Management Controller [arg1] reset was initiated by Front Panel.	Informational
FQXSPPP4050I	Management Controller [arg1] reset was initiated to activate PFR Firmware.	Informational
FQXSPPU0000I	[ProcessorElementName] in slot [SlotElementName] has been added.	Informational
FQXSPPU2000I	[ProcessorElementName] in slot [SlotElementName] has been removed.	Informational
FQXSPPU2001I	An Over-Temperature Condition has been removed on [ProcessorElementName].	Informational
FQXSPPU2002I	The Processor [ProcessorElementName] is no longer operating in a Degraded State.	Informational
FQXSPPW0001I	[PowerSupplyElementName] has been added to container [PhysicalPackageElementName].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPPW0005I	[PowerSupplyElementName] is operating in an Input State that is out of range.	Informational
FQXSPPW0008I	[SensorElementName] has been turned off.	Informational
FQXSPPW0009I	[PowerSupplyElementName] has been Power Cycled.	Informational
FQXSPPW2001I	[PowerSupplyElementName] has been removed from container [PhysicalPackageElementName].	Informational
FQXSPPW2002I	[PowerSupplyElementName] has returned to OK status.	Informational
FQXSPPW2003I	Failure no longer predicted on [PowerSupplyElementName].	Informational
FQXSPPW2006I	[PowerSupplyElementName] has returned to a Normal Input State.	Informational
FQXSPPW2007I	[PowerSupplyElementName] Configuration is OK.	Informational
FQXSPPW2008I	[PowerSupplyElementName] has been turned on.	Informational
FQXSPPW2018I	[PowerSupplyElementName] out-of-range has returned to a Normal Input State.	Informational
FQXSPPW2031I	Numeric sensor [NumericSensorElementName] going low (lower non-critical) has deasserted.	Informational
FQXSPPW2035I	Numeric sensor [NumericSensorElementName] going low (lower critical) has deasserted.	Informational
FQXSPPW2047I	Numeric sensor [NumericSensorElementName] going high (upper critical) has deasserted.	Informational
FQXSPPW2057I	Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.	Informational
FQXSPPW2061I	Sensor [SensorElementName] has transitioned to a less severe state from critical.	Informational
FQXSPPW2063I	Sensor [SensorElementName] has transitioned to a less severe state from critical.	Informational
FQXSPPW2101I	Redundancy Degraded for [RedundancySetElementName] has deasserted.	Informational
FQXSPPW2104I	Non-redundant:Sufficient Resources from Redundancy Degraded or Fully Redundant for [RedundancySetElementName] has deasserted.	Informational
FQXSPPW2110I	Non-redundant:Insufficient Resources for [RedundancySetElementName] has deasserted.	Informational
FQXSPPW4001I	PCIe Power Brake for [arg1] has been [arg2].	Informational
FQXSPSD0000I	The [StorageVolumeElementName] has been added.	Informational
FQXSPSD0001I	The [StorageVolumeElementName] Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has been added.	Informational
FQXSPSD0003I	Hot Spare enabled for [ComputerSystemElementName].	Informational
FQXSPSD0005I	Hot Spare enabled for drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).	Informational
FQXSPSD0007I	Rebuild in progress for Array in system [ComputerSystemElementName].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPSD0008I	Array rebuild in progress on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Informational
FQXSPSD2000I	The [StorageVolumeElementName] has been removed from unit [PhysicalPackageElementName].	Informational
FQXSPSD2001I	The [StorageVolumeElementName] has recovered from a fault.	Informational
FQXSPSD2002I	Failure no longer Predicted on [StorageVolumeElementName] for array [ComputerSystemElementName].	Informational
FQXSPSD2003I	Hot spare disabled for [ComputerSystemElementName].	Informational
FQXSPSD2005I	Critical Array [ComputerSystemElementName] has deasserted.	Informational
FQXSPSD2006I	Array in system [ComputerSystemElementName] has been restored.	Informational
FQXSPSD2007I	Rebuild completed for Array in system [ComputerSystemElementName].	Informational
FQXSPSD2008I	Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has recovered from a fault.	Informational
FQXSPSD2010I	Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has been removed.	Informational
FQXSPSD2011I	Failure no longer Predicted on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Informational
FQXSPSD2012I	Hot Spare disabled for drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).	Informational
FQXSPSD2013I	Array critical deasserted on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Informational
FQXSPSD2014I	Array restored on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Informational
FQXSPSD2015I	Array rebuild completed on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Informational
FQXSPSE2000I	The Chassis [PhysicalPackageElementName] was closed.	Informational
FQXSPSE4001I	Remote Login Successful. Login ID: [arg1] using [arg2] from [arg3] at IP address [arg4].	Informational
FQXSPSE4002I	Security: Userid: [arg1] using [arg2] had [arg3] login failures from WEB client at IP address [arg4].	Informational
FQXSPSE4003I	Security: Login ID: [arg1] had [arg2] login failures from CLI at [arg3].	Informational
FQXSPSE4004I	Remote access attempt failed. Invalid userid or password received. Userid is [arg1] from WEB browser at IP address [arg2].	Informational
FQXSPSE4005I	Remote access attempt failed. Invalid userid or password received. Userid is [arg1] from TELNET client at IP address [arg2].	Informational
FQXSPSE4007I	Security: Userid: [arg1] using [arg2] had [arg3] login failures from an SSH client at IP address [arg4].	Informational
FQXSPSE4008I	SNMPv1 [arg1] set by user [arg2]: Name=[arg3], AccessType=[arg4], Address=[arg5], .	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPSE4009I	LDAP Server configuration set by user [arg1]: SelectionMethod=[arg2], DomainName=[arg3], Server1=[arg4], Server2=[arg5], Server3=[arg6], Server4=[arg7].	Informational
FQXSPSE4010I	LDAP set by user [arg1]: RootDN=[arg2], UIDSearchAttribute=[arg3], BindingMethod=[arg4], EnhancedRBS=[arg5], TargetName=[arg6], GroupFilter=[arg7], GroupAttribute=[arg8], LoginAttribute=[arg9].	Informational
FQXSPSE4011I	Secure Web services (HTTPS) [arg1] by user [arg2].	Informational
FQXSPSE4012I	Secure CIM/XML(HTTPS) [arg1] by user [arg2].	Informational
FQXSPSE4013I	Secure LDAP [arg1] by user [arg2].	Informational
FQXSPSE4014I	SSH [arg1] by user [arg2].	Informational
FQXSPSE4015I	Global Login General Settings set by user [arg1]: AuthenticationMethod=[arg2], LockoutPeriod=[arg3], SessionTimeout=[arg4].	Informational
FQXSPSE4016I	Global Login Account Security set by user [arg1]: PasswordRequired=[arg2], PasswordExpirationPeriod=[arg3], MinimumPasswordReuseCycle=[arg4], MinimumPasswordLength=[arg5], MinimumPasswordChangeInterval=[arg6], MaxmumLoginFailures=[arg7], LockoutAfterMaxFailures=[arg8].	Informational
FQXSPSE4017I	User [arg1] created.	Informational
FQXSPSE4018I	User [arg1] removed.	Informational
FQXSPSE4019I	User [arg1] password modified.	Informational
FQXSPSE4020I	User [arg1] role set to [arg2].	Informational
FQXSPSE4021I	User [arg1] custom privileges set: [arg2][arg3][arg4][arg5][arg6][arg7][arg8][arg9].	Informational
FQXSPSE4022I	User [arg1] for SNMPv3 set: AuthenticationProtocol=[arg2], PrivacyProtocol=[arg3], AccessType=[arg4], HostforTraps=[arg5] by user [arg6] from [arg7] at IP address [arg8].	Informational
FQXSPSE4023I	SSH Client key added for user [arg1] by user [arg2] from [arg3] at IP address [arg4].	Informational
FQXSPSE4024I	SSH Client key imported for user [arg1] from [arg2] by user [arg3] from [arg4] at IP address [arg5].	Informational
FQXSPSE4025I	SSH Client key removed from user [arg1] by user [arg2] from [arg3] at IP address [arg4].	Informational
FQXSPSE4026I	Security: Userid: [arg1] had [arg2] login failures from a CIM client at IP address [arg3].	Informational
FQXSPSE4027I	Remote access attempt failed. Invalid userid or password received. Userid is [arg1] from a CIM client at IP address [arg2].	Informational
FQXSPSE4028I	Security: Userid: [arg1] had [arg2] login failures from IPMI client at IP address [arg3].	Informational
FQXSPSE4029I	Security: Userid: [arg1] had [arg2] login failures from SNMP client at IP address [arg3].	Informational
FQXSPSE4030I	Security: Userid: [arg1] had [arg2] login failures from IPMI serial client.	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPSE40311	Remote Login Successful. Login ID: [arg1] from [arg2] serial interface.	Informational
FQXSPSE40321	Login ID: [arg1] from [arg2] at IP address [arg3] has logged off.	Informational
FQXSPSE40331	Login ID: [arg1] from [arg2] at IP address [arg3] has been logged off.	Informational
FQXSPSE40341	User [arg1] has removed a certificate.	Informational
FQXSPSE40351	A certificate has been revoked .	Informational
FQXSPSE40361	The [arg1] certificate is expired and has been removed.	Informational
FQXSPSE40371	Crypto mode modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPSE40381	Minimum TLS level modified from [arg1] to [arg2] by user [arg3].	Informational
FQXSPSE40391	Temporary user account [arg1] is created by inband tool.	Informational
FQXSPSE40401	Temporary user account [arg1] expires.	Informational
FQXSPSE40411	Security: Userid: [arg1] had [arg2] login failures from a SFTP client at IP address [arg3].	Informational
FQXSPSE40421	The third-party password function [arg1] by user [arg2] from [arg3] at IP address [arg4].	Informational
FQXSPSE40431	Retrieving the third-party password [arg1] by user [arg2] from [arg3] at IP address [arg4].	Informational
FQXSPSE40441	User [arg1] third-party hashed password has been [arg2] by user [arg3] from [arg4] at IP address [arg5].	Informational
FQXSPSE40451	The Salt of user [arg1] third-party password has been [arg2] by user [arg3] from [arg4] at IP address [arg5].	Informational
FQXSPSE40461	The third-party password of the user [arg1] has been retrieved by user [arg2] from [arg3] at IP address [arg4].	Informational
FQXSPSE40471	Role [arg1] is [arg2] and assigned with custom privileges [arg3][arg4][arg5][arg6][arg7][arg8][arg9][arg10][arg11] by user [arg12] .	Informational
FQXSPSE40481	Role [arg1] is removed by user [arg2].	Informational
FQXSPSE40491	Role [arg1] is assigned to user [arg2] by user [arg3].	Informational
FQXSPSE40501	[arg1] sent IPMI command from [arg2], raw data: [arg3][arg4][arg5].	Informational
FQXSPSR20011	Sensor [SensorElementName] has deasserted the transition to non-recoverable from a less severe state.	Informational
FQXSPSS40001	Management Controller Test Alert Generated by [arg1].	Informational
FQXSPSS40011	Server General Settings set by user [arg1]: Name=[arg2], Contact=[arg3], Location=[arg4], Room=[arg5], RackID=[arg6], Rack U-position=[arg7], Address=[arg8].	Informational
FQXSPSS40021	License key for [arg1] added by user [arg2].	Informational
FQXSPSS40031	License key for [arg1] removed by user [arg2].	Informational
FQXSPSS40041	Test Call Home Generated by user [arg1].	Informational
FQXSPSS40051	Manual Call Home by user [arg1]: [arg2].	Informational
FQXSPSS40061	Call Home to [arg1] failed to complete: [arg2].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPSS4007I	The BMC functionality tier is changed from [arg1] to [arg2].	Informational
FQXSPSS4008I	The [arg1] setting has been changed to [arg2] by user [arg3].	Informational
FQXSPSS4009I	System enters LXPM maintenance mode.	Informational
FQXSPSS4010I	Test Audit Log generated by user [arg1].	Informational
FQXSPTR4000I	Management Controller [arg1] clock has been set from NTP server [arg2].	Informational
FQXSPTR4001I	Date and Time set by user [arg1]: Date=[arg2], Time=[arg3], DST Auto-adjust=[arg4], Timezone=[arg5].	Informational
FQXSPTR4002I	Synchronize time setting by user [arg1]: Mode=Sync with NTP Server, NTPServerHost1=[arg2]:[arg3],NTPServerHost2=[arg4]:[arg5], NTPServerHost3=[arg6]:[arg7],NTPServerHost4=[arg8]:[arg9], NTPUpdateFrequency=[arg10].	Informational
FQXSPTR4003I	Synchronize time setting by user [arg1]: Mode=Sync with server clock.	Informational
FQXSPUN0017I	Sensor [SensorElementName] has transitioned to normal state.	Informational
FQXSPUN0026I	Device [LogicalDeviceElementName] has been added.	Informational
FQXSPUN0048I	The RAID controller in PCI slot [arg1] in optimal status.	Informational
FQXSPUN2009I	Sensor [SensorElementName] has deasserted.	Informational
FQXSPUN2012I	Sensor [SensorElementName] has deasserted.	Informational
FQXSPUN2018I	Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.	Informational
FQXSPUN2019I	Sensor [SensorElementName] has transitioned to a less severe state from critical.	Informational
FQXSPUN2023I	Sensor [SensorElementName] has deasserted the transition to non-recoverable.	Informational
FQXSPUN2049I	The RAID controller in PCI slot [arg1] is no longer in warning status.	Informational
FQXSPUN2050I	The RAID controller in PCI slot [arg1] is no longer in critical status.	Informational
FQXSPUP0002I	A firmware or software change occurred on system [ComputerSystemElementName].	Informational
FQXSPUP4001I	Flash of [arg1] from [arg2] succeeded for user [arg3] .	Informational
FQXSPUP4002I	Flash of [arg1] from [arg2] failed for user [arg3].	Informational
FQXSPWD0000I	Watchdog Timer expired for [WatchdogElementName].	Informational
FQXSPWD0001I	Reboot of system [ComputerSystemElementName] initiated by watchdog [WatchdogElementName].	Informational
FQXSPWD0002I	Powering off system [ComputerSystemElementName] initiated by watchdog [WatchdogElementName].	Informational
FQXSPWD0003I	Power cycle of system [ComputerSystemElementName] initiated by watchdog [WatchdogElementName].	Informational
FQXSPWD0004I	Watchdog Timer interrupt occurred for [WatchdogElementName].	Informational

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPBR4001I	Running the backup Management Controller [arg1] main application.	Warning
FQXSPCA0007J	Numeric sensor [NumericSensorElementName] going high (upper non-critical) has asserted.	Warning
FQXSPCA0015J	Sensor [SensorElementName] has transitioned from normal to non-critical state.	Warning
FQXSPDM4002I	Device [arg1] VPD is not valid.	Warning
FQXSPEA0001J	Sensor [SensorElementName] has transitioned from normal to non-critical state.	Warning
FQXSPEA0003J	Link down is detected on port [arg1] of the PCIe device [arg2].	Warning
FQXSPIO0014J	Bus [SensorElementName] is operating in a degraded state.	Warning
FQXSPIO2000J	The connector [PhysicalConnectorElementName] has been disconnected.	Warning
FQXSPMA0010J	[PhysicalMemoryElementName] on Subsystem [MemoryElementName] Throttled.	Warning
FQXSPMA0011G	Memory Logging Limit Reached for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Warning
FQXSPMA0024G	Sensor [SensorElementName] has asserted.	Warning
FQXSPNM4010I	DHCP[[arg1]] failure, no IP address assigned.	Warning
FQXSPNM4032I	DHCPv6 failure, no IP address assigned.	Warning
FQXSPPP4009I	The measured power value exceeded the power cap value.	Warning
FQXSPPP4010I	The new minimum power cap value exceeded the power cap value.	Warning
FQXSPPU0002G	The Processor [ProcessorElementName] is operating in a Degraded State.	Warning
FQXSPPW0003G	Failure predicted on [PowerSupplyElementName].	Warning
FQXSPPW0006I	[PowerSupplyElementName] has lost input.	Warning
FQXSPPW0031J	Numeric sensor [NumericSensorElementName] going low (lower non-critical) has asserted.	Warning
FQXSPPW0057J	Sensor [SensorElementName] has transitioned from normal to non-critical state.	Warning
FQXSPPW0101J	Redundancy Degraded for [RedundancySetElementName] has asserted.	Warning
FQXSPPW0104J	Non-redundant:Sufficient Resources from Redundancy Degraded or Fully Redundant for [RedundancySetElementName] has asserted.	Warning
FQXSPSD0002G	Failure Predicted on [StorageVolumeElementName] for array [ComputerSystemElementName].	Warning
FQXSPSD0003G	Failure Predicted on drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).	Warning
FQXSPSE0000F	The Chassis [PhysicalPackageElementName] was opened.	Warning
FQXSPUN0009G	Sensor [SensorElementName] has asserted.	Warning

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPUN0018J	Sensor [SensorElementName] has transitioned from normal to non-critical state.	Warning
FQXSPBR4003I	Platform Watchdog Timer expired for [arg1].	Error
FQXSPBR4007I	Management Controller [arg1]: Configuration restoration from a file by user [arg2] failed to complete.	Error
FQXSPBR4008I	Management Controller [arg1]: Configuration restoration from a file by user [arg2] failed to start.	Error
FQXSPCA0002M	Numeric sensor [NumericSensorElementName] going low (lower critical) has asserted.	Error
FQXSPCA0009M	Numeric sensor [NumericSensorElementName] going high (upper critical) has asserted.	Error
FQXSPCA0011N	Numeric sensor [NumericSensorElementName] going high (upper non-recoverable) has asserted.	Error
FQXSPCA0017M	Sensor [SensorElementName] has transitioned to critical from a less severe state.	Error
FQXSPCA0019N	Sensor [SensorElementName] has transitioned to non-recoverable from a less severe state.	Error
FQXSPEA0002M	Sensor [SensorElementName] has transitioned to critical from a less severe state.	Error
FQXSPFW0000N	The System [ComputerSystemElementName] encountered a POST Error.	Error
FQXSPFW0002N	The System [ComputerSystemElementName] encountered a firmware hang.	Error
FQXSPIO0001L	The connector [PhysicalConnectorElementName] has encountered a configuration error.	Error
FQXSPIO0003N	A diagnostic interrupt has occurred on system [ComputerSystemElementName].	Error
FQXSPIO0004L	A bus timeout has occurred on bus [SensorElementName].	Error
FQXSPIO0006N	A software NMI has occurred on system [ComputerSystemElementName].	Error
FQXSPIO0007N	A PCI PERR has occurred on system [ComputerSystemElementName].	Error
FQXSPIO0008N	A PCI SERR has occurred on system [ComputerSystemElementName].	Error
FQXSPIO0011N	An Uncorrectable Error has occurred on [SensorElementName].	Error
FQXSPIO0013N	A Fatal Bus Error has occurred on bus [SensorElementName].	Error
FQXSPIO0015M	Fault in slot [PhysicalConnectorSystemElementName] on system [ComputerSystemElementName].	Error
FQXSPMA0002N	Configuration Error for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Error
FQXSPMA0007L	Scrub Failure for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Error

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPMA0008N	Uncorrectable error detected for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Error
FQXSPMA0012M	An Over-Temperature Condition has been detected on the [PhysicalMemoryElementName] on Subsystem [MemoryElementName].	Error
FQXSPOS4002I	Watchdog [arg1] Failed to Capture Screen.	Error
FQXSPOS4003I	Platform Watchdog Timer expired for [arg1].	Error
FQXSPOS4010I	OS Crash Video Capture Failed.	Error
FQXSPPU0001N	An Over-Temperature Condition has been detected on [ProcessorElementName].	Error
FQXSPPU0003N	[ProcessorElementName] has Failed with IERR.	Error
FQXSPPU0004M	[ProcessorElementName] has Failed with FRB1/BIST condition.	Error
FQXSPPU0009N	[ProcessorElementName] has a Configuration Mismatch.	Error
FQXSPPU0011N	An SM BIOS Uncorrectable CPU complex error for [ProcessorElementName] has asserted.	Error
FQXSPPW0002L	[PowerSupplyElementName] has Failed.	Error
FQXSPPW0007L	[PowerSupplyElementName] has a Configuration Mismatch.	Error
FQXSPPW0035M	Numeric sensor [NumericSensorElementName] going low (lower critical) has asserted.	Error
FQXSPPW0047M	Numeric sensor [NumericSensorElementName] going high (upper critical) has asserted.	Error
FQXSPPW0061M	Sensor [SensorElementName] has transitioned to critical from a less severe state.	Error
FQXSPPW0063M	Sensor [SensorElementName] has transitioned to critical from a less severe state.	Error
FQXSPPW0110M	Non-redundant:Insufficient Resources for [RedundancySetElementName] has asserted.	Error
FQXSPSD0001L	The [StorageVolumeElementName] has a fault.	Error
FQXSPSD0002L	Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has a fault.	Error
FQXSPSD0005L	Array [ComputerSystemElementName] is in critical condition.	Error
FQXSPSD0006L	Array [ComputerSystemElementName] has failed.	Error
FQXSPSD0007L	Array critical asserted on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Error
FQXSPSD0008L	Array failed on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).	Error
FQXSPSE4000I	Certificate Authority [arg1] has detected a [arg2] Certificate Error.	Error
FQXSPSE4006I	XCC detected an invalid SSL certificate in the Management Controller [arg1] .	Error
FQXSPSR0001N	Sensor [SensorElementName] has transitioned to non-recoverable from a less severe state.	Error

Table 2. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSPUN0019M	Sensor [SensorElementName] has transitioned to critical from a less severe state.	Error
FQXSPUN0023N	Sensor [SensorElementName] has transitioned to non-recoverable.	Error
FQXSPUP0007L	Invalid or Unsupported firmware or software was detected on system [ComputerSystemElementName].	Error
FQXSPUP4000I	Please ensure that the Management Controller [arg1] is flashed with the correct firmware. The Management Controller is unable to match its firmware to the server.	Error
FQXSPUP4003I	[arg1] firmware mismatch internal to system [arg2]. Please attempt to flash the [arg3] firmware.	Error
FQXSPUP4004I	XCC firmware mismatch between nodes/servers [arg1] and [arg2]. Please attempt to flash the XCC firmware to the same level on all nodes/servers.	Error
FQXSPUP4005I	FPGA firmware mismatch between nodes/servers [arg1] and [arg2]. Please attempt to flash the FPGA firmware to the same level on all nodes/servers.	Error

List of XClarity Controller events

This section lists all messages that can be sent from the XClarity Controller.

- **FQXSPBR4000I: Management Controller [arg1]: Configuration restored from a file by user [arg2].**

This message is for the use case where a user restores a Management Controller configuration from a file.

Severity: Info
 Serviceable: No
 Automatically notify Support: No
 Alert Category: none
 SNMP Trap ID:
 CIM Prefix: IMM CIM ID: 0027

User Action:

Information only; no action is required.

- **FQXSPBR4001I: Running the backup Management Controller [arg1] main application.**

This message is for the use case where a Management Controller has resorted to running the backup main application.

Severity: Warning
 Serviceable: No
 Automatically notify Support: No
 Alert Category: System - other
 SNMP Trap ID: 22
 CIM Prefix: IMM CIM ID: 0030

User Action:

Complete the following steps until the problem is solved:

1. Update the BMC firmware.

2. NOTE: Some cluster solutions require specific code levels or coordinated code updates. If the device is part of a cluster solution, verify that the latest level of code is supported for the cluster solution before you update the code.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPBR4002I: Management Controller [arg1] Reset was caused by restoring default values.**

This message is for the use case where a Management Controller has been reset due to a user restoring the configuration to default values.

Severity: Info
 Serviceable: No
 Automatically notify Support: No
 Alert Category: none
 SNMP Trap ID:
 CIM Prefix: IMM CIM ID: 0032

User Action:

Information only; no action is required.

- **FQXSPBR4003I: Platform Watchdog Timer expired for [arg1].**

This message is for the use case when an implementation has detected a Platform Watchdog Timer Expired

Severity: Error
 Serviceable: No
 Automatically notify Support: No
 Alert Category: System - OS Timeout
 SNMP Trap ID: 21
 CIM Prefix: IMM CIM ID: 0039

User Action:

Complete the following steps until the problem is solved:

1. Reconfigure the watchdog timer to a higher value.
2. Make sure that the BMC Ethernet-over-USB interface is enabled.
3. Reinstall the RNDIS or cdc_ether device driver for the operating system.
4. Disable the watchdog timer.
5. Check the integrity of the installed operating system.
6. If problem persists, collect Service Data log.
7. Contact Lenovo Support.

- **FQXSPBR4004I: Server timeouts set by user [arg1]: EnableOSWatchdog=[arg2], OSWatchdogTimeout=[arg3], EnableLoaderWatchdog=[arg4], LoaderTimeout=[arg5].**

A user configures Server Timeouts

Severity: Info
 Serviceable: No
 Automatically notify Support: No
 Alert Category: none
 SNMP Trap ID:
 CIM Prefix: IMM CIM ID: 0095

User Action:

Information only; no action is required.

- **FQXSPBR4005I: Management Controller [arg1]: Configuration saved to a file by user [arg2].**

A user saves a Management Controller configuration to a file.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0109

User Action:

Information only; no action is required.

- **FQXSPBR4006I: Management Controller [arg1]: Configuration restoration from a file by user [arg2] completed.**

This message is for the use case where a user restores a Management Controller configuration from a file and it completes.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0136

User Action:

Information only; no action is required.

- **FQXSPBR4007I: Management Controller [arg1]: Configuration restoration from a file by user [arg2] failed to complete.**

This message is for the use case where a user restores a Management Controller configuration from a file and the restoration fails to complete.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0137

User Action:

Complete the following steps until the problem is solved:

1. Retry the operation.
2. AC cycle the system.
3. If Problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPBR4008I: Management Controller [arg1]: Configuration restoration from a file by user [arg2] failed to start.**

This message is for the use case where a user restores a Management Controller configuration from a file and the restoration fails to start.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0138

User Action:

Complete the following steps until the problem is solved:

1. Check if password for encrypted backup config file is correct.
2. Retry the operation.
3. AC cycle the system.
4. If problem persists, collect Service Data log.
5. Contact Lenovo Support.

- **FQXSPCA0002M: Numeric sensor [NumericSensorElementName] going low (lower critical) has asserted.**

This message is for the use case when an implementation has detected a Lower Critical sensor going low has asserted.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Fan Failure
SNMP Trap ID: 11
CIM Prefix: PLAT CIM ID: 0480

User Action:

Complete the following steps:

1. Ensure fans are installed correctly.
2. If fan is installed with issue, please reinstall fan.
3. If the problem persists, visually inspect fans for physical damage, dust, or any other contamination. If yes, clean fans, and install fans.
4. If the problem still exist, then please contact Lenovo support.

- **FQXSPCA0007J: Numeric sensor [NumericSensorElementName] going high (upper non-critical) has asserted.**

This message is for the use case when an implementation has detected an Upper Non-critical sensor going high has asserted.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Temperature
SNMP Trap ID: 12
CIM Prefix: PLAT CIM ID: 0490

User Action:

Complete the following steps:

1. Check the event log of system management module and XClarity Controller for any fan or cooling-related issues or power-related issues.
2. Make sure that the airflow at the front and rear of the chassis is not obstructed and that fillers are in place, clean, and correctly installed.
3. Make sure that the room temperature is within operating specifications.

- **FQXSPCA0009M: Numeric sensor [NumericSensorElementName] going high (upper critical) has asserted.**

This message is for the use case when an implementation has detected an Upper Critical sensor going high has asserted.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0494

User Action:

Complete the following steps:

1. Ensure the room temperature is within server environmental specification to adjust the temperature.
2. If the problem issue still exist, check XCC Web GUI to check the temperature value is still higher than system spec.
3. Please contact Lenovo support.

- **FQXSPCA0011N: Numeric sensor [NumericSensorElementName] going high (upper non-recoverable) has asserted.**

This message is for the use case when an implementation has detected an Upper Non-recoverable sensor going high has asserted.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0498

User Action:

Complete the following steps:

1. Ensure the room temperature is within server environmental specification to adjust the temperature.
2. If the problem issue still exist, check XCC Web GUI to check the temperature value is still higher than system spec.
3. Please contact Lenovo support.

- **FQXSPCA0015J: Sensor [SensorElementName] has transitioned from normal to non-critical state.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-critical from normal.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Temperature

SNMP Trap ID: 12
CIM Prefix: PLAT CIM ID: 0520

User Action:

Complete the following steps:

1. Check the event log of xClarity Controller for any fan or cooling-related issues or power-related issues.
2. Make sure that the airflow is not obstructed and that fillers are in place and correctly installed.
3. Make sure that the room temperature is within operating specifications.

- **FQXSPCA0017M: Sensor [SensorElementName] has transitioned to critical from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to critical from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0522

User Action:

Complete the following steps:

1. Check the event log of XClarity Controller for any fan or cooling-related issues or power-related issues.
2. Make sure that the airflow at the front and rear of the chassis is not obstructed and that fillers are in place, clean, and correctly installed.
3. Make sure that the room temperature is within operating specifications.
4. Check M.2 module is in the correct slot location by referring to user manual.
5. If the problem still exist, please contact Lenovo support.

- **FQXSPCA0019N: Sensor [SensorElementName] has transitioned to non-recoverable from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-recoverable from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0524

User Action:

Complete the following steps:

1. Check the event log of XClarity Controller for any fan or cooling-related issues or power-related issues.
2. Make sure that the airflow at the front and rear of the chassis is not obstructed and that fillers are in place, clean, and correctly installed.
3. Make sure that the room temperature is within operating specifications.

- **FQXSPCA2002I: Numeric sensor [NumericSensorElementName] going low (lower critical) has deasserted.**

This message is for the use case when an implementation has detected a Lower Critical sensor going low has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Fan Failure
SNMP Trap ID: 11
CIM Prefix: PLAT CIM ID: 0481

User Action:

Information only; no action is required

- **FQXSPCA2007I: Numeric sensor [NumericSensorElementName] going high (upper non-critical) has deasserted.**

This message is for the use case when an implementation has detected an Upper Non-critical sensor going high has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Temperature
SNMP Trap ID: 12
CIM Prefix: PLAT CIM ID: 0491

User Action:

Information only; no action is required

- **FQXSPCA2009I: Numeric sensor [NumericSensorElementName] going high (upper critical) has deasserted.**

This message is for the use case when an implementation has detected an Upper Critical sensor going high has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0495

User Action:

Information only; no action is required

- **FQXSPCA2011I: Numeric sensor [NumericSensorElementName] going high (upper non-recoverable) has deasserted.**

This message is for the use case when an implementation has detected an Upper Non-recoverable sensor going high has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0

CIM Prefix: PLAT CIM ID: 0499

User Action:

Information only; no action is required

- **FQXSPCA2015I: Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.**

This message is for the use case when an implementation has detected that a Sensor has deasserted a transition to non-critical from normal.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Temperature
SNMP Trap ID: 12
CIM Prefix: PLAT CIM ID: 0521

User Action:

Information only; no action is required

- **FQXSPCA2017I: Sensor [SensorElementName] has transitioned to a less severe state from critical.**

This message is for the use case when an implementation has detected a Sensor transition to less severe from critical.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0523

User Action:

Information only; no action is required

- **FQXSPCA2019I: Sensor [SensorElementName] has deasserted the transition to non-recoverable from a less severe state.**

This message is for the use case when an implementation has detected that the Sensor transition to non-recoverable from less severe has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0525

User Action:

Information only; no action is required

- **FQXSPCN4000I: Serial Redirection set by user [arg1]: Mode=[arg2], BaudRate=[arg3], StopBits=[arg4], Parity=[arg5], SessionTerminateSequence=[arg6].**

A user configured the Serial Port mode

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0078

User Action:

Information only; no action is required.

- **FQXSPCN4001I: Remote Control session started by user [arg1] in [arg2] mode.**

Remote Control session started

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0128

User Action:

Information only; no action is required.

- **FQXSPCN4002I: User [arg1] has terminated an active console session.**

A user has terminated an active console session

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0145

User Action:

Information only; no action is required.

- **FQXSPCN4003I: Remote Control session started by user [arg1] in [arg2] mode has been closed.**

Remote Control session closed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0194

User Action:

Information only; no action is required.

- **FQXSPCR2001I: Sensor [SensorElementName] has deasserted the transition to non-recoverable from a less severe state.**

This message is for the use case when an implementation has detected that the Sensor transition to non-recoverable from less severe has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0525

User Action:

Information only; no action is required

- **FQXSPDM4000I: Inventory data changed for device [arg1], new device data hash=[arg2], new master data hash=[arg3] .**

Something has caused the physical inventory to change

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0072

User Action:

Information only; no action is required.

- **FQXSPDM4001I: Storage [arg1] has changed.**

This message is for the use case where an IP address for the Storage Management has changed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - BMC Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0139

User Action:

Information only; no action is required.

- **FQXSPDM4002I: Device [arg1] VPD is not valid.**

The VPD for a device is invalid

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0142

User Action:

Collect Service Data log and contact Lenovo Support.

- **FQXSPDM4003I: TKLM servers set by user [arg1]: TKLMServer1=[arg2] Port=[arg3], TKLMServer2=[arg4] Port=[arg5], TKLMServer3=[arg6] Port=[arg7], TKLMServer4=[arg8] Port=[arg9].**

A user configured the TKLM servers

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none

SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0146

User Action:

Information only; no action is required.

- **FQXSPDM4004I: TKLM servers device group set by user [arg1]: TKLMServerDeviceGroup=[arg2] .**

A user configured the TKLM device group

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0147

User Action:

Information only; no action is required.

- **FQXSPDM4005I: User [arg1] has generated a new encryption key pair and installed a self-signed certificate for the TKLM client.**

User generated a new encryption key pair and installed a self-signed certificate for the TKLM client

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0148

User Action:

Information only; no action is required.

- **FQXSPDM4006I: User [arg1] has generated a new encryption key and certificate signing request for the TKLM client.**

User generated a new encryption key and certificate signing request for the TKLM client

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0149

User Action:

Information only; no action is required.

- **FQXSPDM4007I: User [arg1] has imported a signed certificate for the TKLM client from [arg2].**

User imported a signed certificate for the TKLM client

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:

CIM Prefix: IMM CIM ID: 0150

User Action:

Information only; no action is required.

- **FQXSPDM4008I: User [arg1] has imported a server certificate for the TKLM server.**

User imported a server certificate for the TKLM Server

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0151

User Action:

Information only; no action is required.

- **FQXSPDM4009I: User [arg1] has [arg2] file [arg3] from [arg4].**

User has mounted/unmounted file from URL or server

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0162

User Action:

Information only; no action is required.

- **FQXSPEA0001J: Sensor [SensorElementName] has transitioned from normal to non-critical state.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-critical from normal.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0520

User Action:

Use Storcli, LSA, arconf, or Maxview to check if there is any warning or critical RAID event.

- **FQXSPEA0002M: Sensor [SensorElementName] has transitioned to critical from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to critical from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50

CIM Prefix: PLAT CIM ID: 0522

User Action:

Use Storcli, LSA, arconf, or Maxview to check if there is any warning or critical RAID event.

- **FQXSPEA0003J: Link down is detected on port [arg1] of the PCIe device [arg2].**

This message is for the use case when an implementation has detected a Link down of PCIe device.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0520

User Action:

Information only; no action is required.

- **FQXSPEA2001I: Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.**

This message is for the use case when an implementation has detected that a Sensor has deasserted a transition to non-critical from normal.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0521

User Action:

Use storcli or LSA to check if there is any warning or critical RAID event.

- **FQXSPEA2002I: Sensor [SensorElementName] has transitioned to a less severe state from critical.**

This message is for the use case when an implementation has detected a Sensor transition to less severe from critical.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0523

User Action:

Use Storcli, LSA, arconf, or Maxview to check if there is any warning or critical RAID event.

- **FQXSPEA2003I: Link up is detected on port [arg1] of the PCIe device [arg2].**

This message is for the use case when an implementation has detected that a link up of PCIe.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60

CIM Prefix: PLAT CIM ID: 0521

User Action:

Information only; no action is required

- **FQXSPEM4000I: The [arg1] on system [arg2] cleared by user [arg3].**

This message is for the use case where a Management Controller Event Log on a system is cleared by a user.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0020

User Action:

Information only; no action is required.

- **FQXSPEM4001I: The [arg1] on system [arg2] is 75% full.**

This message is for the use case where a Management Controller Event Log on a system is 75% full.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Event Log Fullness
SNMP Trap ID: 35
CIM Prefix: IMM CIM ID: 0037

User Action:

Information only; no action is required.

- **FQXSPEM4002I: The [arg1] on system [arg2] is 100% full.**

This message is for the use case where a Management Controller Event Log on a system is 100% full.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Event Log Fullness
SNMP Trap ID: 35
CIM Prefix: IMM CIM ID: 0038

User Action:

To avoid losing older log entries, save the log as a text file and clear the log.

- **FQXSPEM4003I: LED [arg1] state changed to [arg2] by [arg3].**

A user has modified the state of an LED

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0071

User Action:

Information only; no action is required.

- **FQXSPeM4004I: SNMP [arg1] enabled by user [arg2] .**

A user enabled SNMPv1 or SNMPv3 or Traps

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0073

User Action:

Information only; no action is required.

- **FQXSPeM4005I: SNMP [arg1] disabled by user [arg2] .**

A user disabled SNMPv1 or SNMPv3 or Traps

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0074

User Action:

Information only; no action is required.

- **FQXSPeM4006I: Alert Configuration Global Event Notification set by user [arg1]: RetryLimit=[arg2], RetryInterval=[arg3], EntryInterval=[arg4].**

A user changes the Global Event Notification settings.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0110

User Action:

Information only; no action is required.

- **FQXSPeM4007I: Alert Recipient Number [arg1] updated: Name=[arg2], DeliveryMethod=[arg3], Address=[arg4], IncludeLog=[arg5], Enabled=[arg6], EnabledAlerts=[arg7], AllowedFilters=[arg8] by user [arg9] from [arg10] at IP address [arg11].**

A user adds or updates an Alert Recipient

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0111

User Action:

Information only; no action is required.

- **FQXSPPEM4008I: SNMP Traps enabled by user [arg1]: EnabledAlerts=[arg2], AllowedFilters=[arg3] .**

A user enabled the SNMP Traps configuration

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0112

User Action:

Information only; no action is required.

- **FQXSPPEM4009I: The UEFI Definitions have been changed.**

UEFI Definitions change has been detected

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0152

User Action:

Information only; no action is required.

- **FQXSPPEM4010I: UEFI Reported: [arg1].**

UEFI audit event logged.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0161

User Action:

Information only; no action is required.

- **FQXSPPEM4011I: XCC failed to log previous event [arg1].**

XCC failed to log a previous event.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0196

User Action:

Information only; no action is required.

- **FQXSPEM4012I: User [arg1] made system [arg2] Encapsulation lite Mode.**

Encapsulation lite mode status change

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0201

User Action:

Information only; no action is required.

- **FQXSPEM4013I: Battery error was detected by RAID controller. The battery unit needs replacement.([arg1],[arg2],[arg3],[arg4],[arg5])**

Battery error was detected by RAID controller

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0202

User Action:

Information only; no action is required.

- **FQXSPEM4014I: The RAID controller has problem with the battery. Please contact technical support to resolve this issue.([arg1],[arg2],[arg3],[arg4],[arg5])**

The RAID controller has problem with the battery

Severity: Info
Serviceable: No
Automatically notify Support: Yes
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0203

User Action:

Information only; no action is required.

- **FQXSPEM4015I: The RAID controller detected unrecoverable error. The controller needs replacement.([arg1],[arg2],[arg3],[arg4],[arg5])**

The RAID controller detected unrecoverable error

Severity: Info
Serviceable: No
Automatically notify Support: Yes
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0204

User Action:

Information only; no action is required.

- **FQXSPeM4016I: The RAID controller detected one or more problems. Please contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])**

The RAID controller detected one or more problems

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0205

User Action:

Information only; no action is required.

- **FQXSPeM4017I: The RAID controller detected one or more possible configuration changes within the subsystem. Please check the drive LED status. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])**

The RAID controller detected one or more possible configuration changes within the subsystem

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0206

User Action:

Information only; no action is required.

- **FQXSPeM4018I: Enclosure/Chassis issue detected with one or more units. Please check the enclosure/chassis units to repair the problem.([arg1],[arg2],[arg3],[arg4],[arg5])**

Enclosure/Chassis issue detected with one or more units

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0207

User Action:

Information only; no action is required.

- **FQXSPeM4019I: Connectivity issue detected with the enclosure/chassis. Please check your cable configurations to repair the problem.([arg1],[arg2],[arg3],[arg4],[arg5])**

Connectivity issue detected with the enclosure/chassis

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0208

User Action:

Information only; no action is required.

- **FQXSPPEM4020I: Fan problem detected with the enclosure/chassis. Please check the enclosure/chassis unit fan for correct operation.([arg1],[arg2],[arg3],[arg4],[arg5])**

Fan problem detected with the enclosure/chassis

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0209

User Action:

Information only; no action is required.

- **FQXSPPEM4022I: Enclosure/Chassis power supply has problem. Please check the enclosure/chassis unit power supply for correct operation.([arg1],[arg2],[arg3],[arg4],[arg5])**

Enclosure/Chassis power supply has problem

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0210

User Action:

Information only; no action is required.

- **FQXSPPEM4023I: One or more virtual drive are in abnormal status that may cause unavailable virtual drive. Please check the event logs and if events are targeted to the same disk then replace the drive. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])**

One or more virtual drive are in abnormal status that may cause unavailable virtual drive

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0211

User Action:

Information only; no action is required.

- **FQXSPPEM4024I: The RAID controller detected one or more possible configuration problem within the subsystem. Please check the event logs and if events are targeted to the same disk then replace the drive. If necessary, contact technical support for additional assistance.([arg1],[arg2],[arg3],[arg4],[arg5])**

The RAID controller detected one or more possible configuration problem within the subsystem

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0212

User Action:

Information only; no action is required.

- **FQXSP4025I: One or more virtual drive have problem. Please contact technical support to resolve this issue.**([arg1],[arg2],[arg3],[arg4],[arg5])

One or more virtual drive have problem

Severity: Info
Serviceable: No
Automatically notify Support: Yes
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0213

User Action:

Information only; no action is required.

- **FQXSP4026I: Drive error was detected by RAID controller. Please contact technical support to resolve this issue.**([arg1],[arg2],[arg3],[arg4],[arg5])

Drive error was detected by RAID controller

Severity: Info
Serviceable: No
Automatically notify Support: Yes
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0214

User Action:

Information only; no action is required.

- **FQXSP4027I: Drive error was detected by RAID controller. Please check the event logs and if events are targeted to the same disk then replace the drive. If necessary, contact technical support for additional assistance.**([arg1],[arg2],[arg3],[arg4],[arg5])

Drive error was detected by RAID controller

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0215

User Action:

Information only; no action is required.

- **FQXSP4028I: The port [arg1] of PCIe device [arg2] at [arg3] has link [arg4].**

PCI device link

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0220

User Action:

Information only; no action is required.

- **FQXSPPEM4029I: All PCIe slots on [arg1] may not be functional based upon your current CPU population.**

PCIe not be functional

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0221

User Action:

Information only; no action is required.

- **FQXSPPEM4030I: A scheduled operation on the RAID controller has encountered an issue. Refer to RAID Logs under Server Management, Local Storage, for details.([arg1],[arg2],[arg3],[arg4],[arg5])**

The RAID controller has scheduled operation issue

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0223

User Action:

Information only; no action is required.

- **FQXSPFC4000I: The bare metal connection process has been started.**

Bare Metal Connection process has been started

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0143

User Action:

Information only; no action is required.

- **FQXSPFC4001I: The bare metal update application reports a status of [arg1].**

Bare Metal Update Application Status

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0144

User Action:

Information only; no action is required.

- **FQXSPFC4002I: System running in setup.**

System running in setup

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0193

User Action:

Information only; no action is required.

- **FQXSPFC4003I: UEFI deployment boot mode is enabled for NextBoot.**

UEFI deployment boot mode is enabled for NextBoot

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0197

User Action:

Information only; no action is required.

- **FQXSPFC4004I: UEFI deployment boot mode is enabled for NextAc.**

UEFI deployment boot mode is enabled for NextAC

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0198

User Action:

Information only; no action is required.

- **FQXSPFC4005I: UEFI deployment boot mode has been disabled.**

UEFI deployment boot mode has been disabled

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0199

User Action:

Information only; no action is required.

- **FQXSPFW0000N: The System [ComputerSystemElementName] encountered a POST Error.**

This message is for the use case when an implementation has detected a Post Error.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0184

User Action:

Complete the following steps:

1. Original UEFI settings are still present. If customer desires to continue using the original settings, select Save Settings.
2. If User did not intentionally trigger the reboots, check logs for probable cause. For example, if there is a battery fault event, follow the steps to resolve that event.
3. Undo recent system changes (settings or devices added). Verify that the system boots. Then, re-install options one at a time to locate the problem.
4. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this error. Update UEFI firmware if applicable.
5. Remove and re-install CMOS battery on system board for 30 seconds to clear CMOS contents. If it boots successfully, then restore system settings.
6. If problem persists, collect Service Data log.
7. Contact Lenovo Support.

- **FQXSPFW0002N: The System [ComputerSystemElementName] encountered a firmware hang.**

This message is for the use case when an implementation has detected a System Firmware Hang.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: System - Boot failure
SNMP Trap ID: 25
CIM Prefix: PLAT CIM ID: 0186

User Action:

Complete the following steps:

1. Original UEFI settings are still present. If customer desires to continue using the original settings, select Save Settings.
2. If User did not intentionally trigger the reboots, check logs for probable cause. For example, if there is a battery fault event, follow the steps to resolve that event.
3. Undo recent system changes (settings or devices added). Verify that the system boots. Then, re-install options one at a time to locate the problem.
4. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this error. Update UEFI firmware if applicable.
5. Remove and re-install CMOS battery on system board for 30 seconds to clear CMOS contents. If it boots successfully, then restore system settings.

6. If problem persists, collect Service Data log.
7. Contact Lenovo Support.

- **FQXSPIO0000I: The connector [PhysicalConnectorElementName] has been connected.**

This message is for the use case when an implementation has detected a Connector has been Connected.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0264

User Action:

Information only; no action is required

- **FQXSPIO0001L: The connector [PhysicalConnectorElementName] has encountered a configuration error.**

This message is for the use case when an implementation has detected an Interconnect Configuration Error.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0266

User Action:

Complete the following steps until the problem is solved:

1. Make sure USB cable to system board is securely connected.
2. Replace USB module if the problem still exist.

- **FQXSPIO0003N: A diagnostic interrupt has occurred on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a Front Panel NMI / Diagnostic Interrupt.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0222

User Action:

If the NMI button has not been pressed, complete the following steps:

1. Reboot the system.
2. If error still exist, then collect service log and contact Lenovo support.

- **FQXSPIO0004L: A bus timeout has occurred on bus [SensorElementName].**

This message is for the use case when an implementation has detected a Bus Timeout.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0224

User Action:

Complete the following steps:

1. Update the firmware (UEFI&XCC) to the latest level.
2. Please reseal the processor and reboot the server.
3. If the problem still exist, (service technician) please replace the system board.
4. If the problem still exist, contact Lenovo support.

- **FQXSPIO0006N: A software NMI has occurred on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a Software NMI.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0228

User Action:

Check the event log in system event log to resolve any issues related the NMI

- **FQXSPIO0007N: A PCI PERR has occurred on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a PCI PERR.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0232

User Action:

Complete the following steps to solve:

1. 1. Reseat the adapter or other slot.
2. 2. If the problem still exist then replace the adapter.
3. 3. If the problem still exist then contact local service.

- **FQXSPIO0008N: A PCI SERR has occurred on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a PCI SERR.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0234

User Action:

Complete the following steps to solve:

1. Reseat the adapter or other slot.
2. If the problem still exist then replace the adapter.
3. If the problem still exist then contact local service.

- **FQXSPIO0010I: A Correctable Bus Error has occurred on bus [SensorElementName].**

This message is for the use case when an implementation has detected a Bus Correctable Error.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0238

User Action:

Information only; please correct the error recorded in system log to resolve the error

- **FQXSPIO0011N: An Uncorrectable Error has occurred on [SensorElementName].**

This message is for the use case when an implementation has detected a Bus Uncorrectable Error.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0240

User Action:

Check <http://support.lenovo.com/> for TECH tips or firmware updates that might correct the error.

1. Make sure that all I/O expansion adapters have correct and matching levels of device drivers and firmware.
2. Check the event log of XClarity Controller for additional information about failing components.
3. If there are no entries related to the error in the event log, contact Lenovo support

- **FQXSPIO0013N: A Fatal Bus Error has occurred on bus [SensorElementName].**

This message is for the use case when an implementation has detected a Bus Fatal Error.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0244

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or firmware update for the system or adapter that applies to this error.
2. If problem persists, collect Service Data log.

3. Contact Lenovo Support.

- **FQXSPIO0014J: Bus [SensorElementName] is operating in a degraded state.**

This message is for the use case when an implementation has detected a Bus is Degraded.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0246

User Action:

Complete the following steps:

1. Reseat the adapter on other slot.
2. If the problem still exist then replace the adapter.
3. If the problem still exist, collect service log then contact local service.

- **FQXSPIO0015M: Fault in slot [PhysicalConnectorSystemElementName] on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a Fault in a slot.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0330

User Action:

Complete the following steps to fix the error:

1. Make sure that all I/O expansion adapters have correct and matching levels of device drivers and firmware.
2. Check the event log of XClarity Controller for additional information about failing components. Check <http://support.lenovo.com/> for TECH tips or firmware updates that might correct the error.
3. If there are no entries related to the error in the event log, contact Lenovo support

- **FQXSPIO2000J: The connector [PhysicalConnectorElementName] has been disconnected.**

This message is for the use case when an implementation has detected a Connector was Disconnected.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0265

User Action:

Ensure the cables are connected correctly

- **FQXSPIO2001I: The connector [PhysicalConnectorElementName] configuration error has been repaired.**

This message is for the use case when an implementation has detected an Interconnect Configuration was Repaired.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0267

User Action:

Information only; no action is required

- **FQXSPIO2003I: System [ComputerSystemElementName] has recovered from a diagnostic interrupt.**

This message is for the use case when an implementation has detected a recovery from a Front Panel NMI / Diagnostic Interrupt

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0223

User Action:

Information only; no action is required

- **FQXSPIO2004I: Bus [SensorElementName] has recovered from a bus timeout.**

This message is for the use case when an implementation has detected that a system has recovered from a Bus Timeout.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0225

User Action:

Information only; no action is required

- **FQXSPIO2006I: System [ComputerSystemElementName] has recovered from an NMI.**

This message is for the use case when an implementation has detected a Software NMI has been Recovered from.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0230

User Action:

Information only; no action is required

- **FQXSPIO2007I: A PCI PERR recovery has occurred on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a PCI PERR recovered.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0233

User Action:

Information only; no action is required

- **FQXSPIO2008I: A PCI SERR on system [ComputerSystemElementName] has deasserted.**

This message is for the use case when an implementation has detected a PCI SERR deassertion.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0235

User Action:

Information only; no action is required

- **FQXSPIO2010I: Bus [SensorElementName] has recovered from a Correctable Bus Error.**

This message is for the use case when an implementation has detected that a system has recovered from a Bus Correctable Error.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0239

User Action:

Information only; no action is required.

- **FQXSPMA0001I: Error Detected and Corrected for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected a Memory corrected error.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0124

User Action:

Information only; no action is required.

- **FQXSPMA0002N: Configuration Error for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected a Memory DIMM configuration error has been corrected.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Memory
SNMP Trap ID: 41
CIM Prefix: PLAT CIM ID: 0126

User Action:

Complete the following steps:

1. If the DIMM configuration was changed prior to this failure verify that the DIMMs are installed in the correct population sequence.
2. RESEAT the DIMM that failed POST memory test and the DIMMs on adjacent slots if populated. Boot to F1 setup and enable the DIMM. Reboot the system.
3. If the DIMMs have been upgraded just prior to the issue than update uEFI to the latest version.
4. If the problem persists, collect Service Data logs.
5. Contact Lenovo Support.

- **FQXSPMA0007L: Scrub Failure for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected a Memory Scrub failure.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Memory
SNMP Trap ID: 41
CIM Prefix: PLAT CIM ID: 0136

User Action:

Complete the following steps:

1. Ensure one or more DIMMs are installed in the server.
2. Resolve existing memory errors if they are present.
3. If no memory fault is recorded in the logs, verify that all DIMM connectors are enabled using the Setup utility or the OneCLI utility.
4. Reseat all DIMMs ensuring that DIMMs are installed in the correct population sequence, according to the service information for this product.
5. Clear CMOS memory on system board. Note that all firmware settings will revert to the defaults.
6. Reflash UEFI firmware.
7. If problem persists, collect Service Data log.
8. Contact Lenovo Support.

- **FQXSPMA0008N: Uncorrectable error detected for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected a Memory uncorrectable error.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Memory
SNMP Trap ID: 41
CIM Prefix: PLAT CIM ID: 0138

User Action:

Complete the following steps:

1. If the server has recently been installed, moved, serviced, or upgraded, verify that the DIMM is properly seated and visually verify that there is no foreign material in any DIMM connector on that memory channel. If either of these conditions is found, correct and retry with the same DIMM. (Note: The event Log might contain a recent FQXSFMA0011I event denoting detected change in DIMM population that could be related to this problem.)
2. If no problem is observed on the DIMM connectors or the problem persists, replace the DIMM identified by LightPath and/or event log entry.
3. If problem recurs on the same DIMM connector, replace the other DIMMs on the same memory channel.
4. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this memory error.
5. If problem recurs on the same DIMM connector, inspect connector for damage. If damage found or problem persists, collect Service Data log.
6. Contact Lenovo Support.

- **FQXSPMA0010J: [PhysicalMemoryElementName] on Subsystem [MemoryElementName] Throttled.**

This message is for the use case when an implementation has detected Memory has been Throttled.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0142

User Action:

Complete the following steps:

1. Check the event log of XClarity Controller for any fan or cooling related issues.
2. Make sure that the airflow at the front and rear of the chassis is not bstructed, and that fillers are in place, clean, and correctly installed.
3. Make sure that the room temperature is within operating specifications.
4. If the problem persists and there are no other DIMMs with the same problem, replace the DIMM.

- **FQXSPMA0011G: Memory Logging Limit Reached for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected that the Memory Logging Limit has been Reached.

Severity: Warning
Serviceable: Yes
Automatically notify Support: Yes

Alert Category: Warning - Memory
SNMP Trap ID: 43
CIM Prefix: PLAT CIM ID: 0144

User Action:

Complete the following steps:

1. If the server has recently been installed, moved, serviced, or upgraded, verify that the DIMM is properly seated and visually verify that there is no foreign material in any DIMM connector on that memory channel. If either of these conditions is found, correct and retry with the same DIMM. (Note: The event Log might contain a recent FQXSFMA0011I event denoting detected change in DIMM population that could be related to this problem.)
2. If no problem is observed on the DIMM connectors or the problem persists, replace the DIMM identified by LightPath and/or event log entry.
3. If problem recurs on the same DIMM connector, replace the other DIMMs on the same memory channel.
4. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this memory error.
5. If problem recurs on the same DIMM connector, inspect connector for damage. If damage found or problem persists, collect Service Data log.
6. Contact Lenovo Support.

- **FQXSPMA0012M: An Over-Temperature Condition has been detected on the [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected an Over Temperature Condition for Memory that has been Detected.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0146

User Action:

Complete the following steps until the problem is solved:

1. Check the event log of XClarity Controller (XCC) for any fan- or cooling-related issues.
2. Make sure that the airflow at the front and rear of the chassis is not obstructed and are in place, clean, and correctly installed.
3. Make sure that the room temperature is within operating specifications.
4. If the problem remains and no other DIMMs have the same indication, replace the DIMM.

- **FQXSPMA0022I: Memory sparing initiated for [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected that Memory double chip sparing has been initiated.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:

CIM Prefix: PLAT CIM ID: 0140

User Action:

Information only; no action is required.

- **FQXSPMA0024G: Sensor [SensorElementName] has asserted.**

This message is for the use case when an implementation has detected a Sensor has asserted.

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Memory
SNMP Trap ID: 43
CIM Prefix: PLAT CIM ID: 0508

User Action:

Complete the following steps:

1. If the DIMM configuration was changed prior to this failure verify that the DIMMs are installed in the correct population sequence.
2. RESEAT the DIMM that failed POST memory test and the DIMMs on adjacent slots if populated. Boot to F1 setup and enable the DIMM. Reboot the system.
3. If the DIMMs have been upgraded just prior to the issue than update uEFI to the latest version.
4. If the problem persists, collect Service Data logs.
5. Contact Lenovo Support.

- **FQXSPMA0025I: Sensor [SensorElementName] has asserted.**

This message is for the use case when an implementation has detected a Sensor has asserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0508

User Action:

Information only; no action is required

- **FQXSPMA2007I: Scrub Failure for [PhysicalMemoryElementName] on Subsystem [MemoryElementName] has recovered.**

This message is for the use case when an implementation has detected a Memory Scrub failure recovery.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Memory
SNMP Trap ID: 41
CIM Prefix: PLAT CIM ID: 0137

User Action:

Information only; no action is required

- **FQXSPMA2010I: [PhysicalMemoryElementName] on Subsystem [MemoryElementName] is no longer Throttled.**

This message is for the use case when an implementation has detected Memory is no longer Throttled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0143

User Action:

Information only; no action is required

- **FQXSPMA2012I: An Over-Temperature Condition has been removed on the [PhysicalMemoryElementName] on Subsystem [MemoryElementName].**

This message is for the use case when an implementation has detected an Over Temperature Condition for Memory that has been Removed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0147

User Action:

Information only; no action is required

- **FQXSPMA2024I: Sensor [SensorElementName] has deasserted.**

This message is for the use case when an implementation has detected a Sensor has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Memory
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0509

User Action:

Information only; no action is required

- **FQXSPNM4000I: Management Controller [arg1] Network Initialization Complete.**

This message is for the use case where a Management Controller network has completed initialization.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - BMC Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0001

User Action:

Information only; no action is required.

- **FQXSPNM4001: Ethernet Data Rate modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where a user modifies the Ethernet Port data rate.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0003

User Action:

Information only; no action is required.

- **FQXSPNM4002: Ethernet Duplex setting modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where A user modifies the Ethernet Port duplex setting.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0004

User Action:

Information only; no action is required.

- **FQXSPNM4003: Ethernet MTU setting modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where a user modifies the Ethernet Port MTU setting.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0005

User Action:

Information only; no action is required.

- **FQXSPNM4004: Ethernet locally administered MAC address modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where a user modifies the Ethernet Port MAC address setting.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0006

User Action:

Information only; no action is required.

- **FQXSPNM4005: Ethernet interface [arg1] by user [arg2].**

This message is for the use case where a user enables or disabled the ethernet interface.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0007

User Action:

Information only; no action is required.

- **FQXSPNM4006I: Hostname set to [arg1] by user [arg2].**

This message is for the use case where user modifies the Hostname of a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - BMC Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0008

User Action:

Information only; no action is required.

- **FQXSPNM4007I: IP address of network interface modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where user modifies the IP address of a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - BMC Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0009

User Action:

Information only; no action is required.

- **FQXSPNM4008I: IP subnet mask of network interface modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where a user modifies the IP subnet mask of a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0010

User Action:

Information only; no action is required.

- **FQXSPNM4009I: IP address of default gateway modified from [arg1] to [arg2] by user [arg3].**

This message is for the use case where a user modifies the default gateway IP address of a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0011

User Action:

Information only; no action is required.

- **FQXSPNM4010I: DHCP[[arg1]] failure, no IP address assigned.**

This message is for the use case where a DHCP server fails to assign an IP address to a Management Controller.

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0013

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the XCC/BMC management network cable is connected and the network ports is active.
2. Make sure that there is a DHCP server on the network that can assign an IP address to the XCC/BMC.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPNM4011I: ENET[[arg1]] DHCP-HSTN=[arg2], DN=[arg3], IP@[arg4], SN=[arg5], GW@[arg6], DNS1@[arg7] .**

This message is for the use case where a Management Controller IP address and configuration has been assigned by the DHCP server.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0022

User Action:

Information only; no action is required.

- **FQXSPNM4012I: ENET[[arg1]] IP-Cfg:HstName=[arg2], IP@[arg3] ,NetMsk=[arg4], GW@[arg5] .**

This message is for the use case where a Management Controller IP address and configuration has been assigned statically using user data.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none

SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0023

User Action:

Information only; no action is required.

- **FQXSPNM4013I: LAN: Ethernet[[arg1]] interface is no longer active.**

This message is for the use case where a Management Controller ethernet interface is no longer active.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0024

User Action:

Information only; no action is required.

- **FQXSPNM4014I: LAN: Ethernet[[arg1]] interface is now active.**

This message is for the use case where a Management Controller ethernet interface is now active.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0025

User Action:

Information only; no action is required.

- **FQXSPNM4015I: DHCP setting changed to [arg1] by user [arg2].**

This message is for the use case where a user changes the DHCP setting.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0026

User Action:

Information only; no action is required.

- **FQXSPNM4016I: Domain name set to [arg1] by user [arg2].**

Domain name set by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0043

User Action:

Information only; no action is required.

- **FQXSPNM4017I: Domain Source changed to [arg1] by user [arg2].**

Domain source changed by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0044

User Action:

Information only; no action is required.

- **FQXSPNM4018I: DDNS setting changed to [arg1] by user [arg2].**

DDNS setting changed by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0045

User Action:

Information only; no action is required.

- **FQXSPNM4019I: DDNS registration successful. The domain name is [arg1].**

DDNS registration and values

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0046

User Action:

Information only; no action is required.

- **FQXSPNM4020I: IPv6 enabled by user [arg1] .**

IPv6 protocol is enabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0047

User Action:

Information only; no action is required.

- **FQXSPNM4021I: IPv6 disabled by user [arg1] .**

IPv6 protocol is disabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0048

User Action:

Information only; no action is required.

- **FQXSPNM4022I: IPv6 static IP configuration enabled by user [arg1].**

IPv6 static address assignment method is enabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0049

User Action:

Information only; no action is required.

- **FQXSPNM4023I: IPv6 DHCP enabled by user [arg1].**

IPv6 DHCP assignment method is enabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0050

User Action:

Information only; no action is required.

- **FQXSPNM4024I: IPv6 stateless auto-configuration enabled by user [arg1].**

IPv6 statless auto-assignment method is enabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0051

User Action:

Information only; no action is required.

- **FQXSPNM4025I: IPv6 static IP configuration disabled by user [arg1].**

IPv6 static assignment method is disabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0052

User Action:

Information only; no action is required.

- **FQXSPNM4026I: IPv6 DHCP disabled by user [arg1].**

IPv6 DHCP assignment method is disabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0053

User Action:

Information only; no action is required.

- **FQXSPNM4027I: IPv6 stateless auto-configuration disabled by user [arg1].**

IPv6 statless auto-assignment method is disabled by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0054

User Action:

Information only; no action is required.

- **FQXSPNM4028I: ENET[[arg1]] IPv6-LinkLocal:HstName=[arg2], IP@=[arg3] ,Pref=[arg4] .**

IPv6 Link Local address is active

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0055

User Action:

Information only; no action is required.

- **FQXSPNM4029I: ENET[[arg1]] IPv6-Static:HstName=[arg2], IP@=[arg3] ,Pref=[arg4], GW@=[arg5] .**

IPv6 Static address is active

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0056

User Action:

Information only; no action is required.

- **FQXSPNM4030I: ENET[[arg1]] DHCPv6-HSTN=[arg2], DN=[arg3], IP@[arg4], Pref=[arg5], DNS1@[arg5].**

IPv6 DHCP-assigned address is active

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0057

User Action:

Information only; no action is required.

- **FQXSPNM4031I: IPv6 static address of network interface modified from [arg1] to [arg2] by user [arg3].**

A user modifies the IPv6 static address of a Management Controller

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0058

User Action:

Information only; no action is required.

- **FQXSPNM4032I: DHCPv6 failure, no IP address assigned.**

S DHCP6 server fails to assign an IP address to a Management Controller.

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0059

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the XCC/BMC management network cable is connected and the network ports is active.
2. Make sure that there is a DHCPv6 server on the network that can assign an IP address to the XCC/BMC.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPNM4033I: Telnet port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the telnet port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0061

User Action:

Information only; no action is required.

- **FQXSPNM4034I: SSH port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the SSH port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0062

User Action:

Information only; no action is required.

- **FQXSPNM4035I: Web-HTTP port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the Web HTTP port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0063

User Action:

Information only; no action is required.

- **FQXSPNM4036I: Web-HTTPS port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the Web HTTPS port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0064

User Action:

Information only; no action is required.

- **FQXSPNM4037I: CIM/XML HTTP port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the CIM HTTP port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0065

User Action:

Information only; no action is required.

- **FQXSPNM4038I: CIM/XML HTTPS port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the CIM HTTPS port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0066

User Action:

Information only; no action is required.

- **FQXSPNM4039I: SNMP Agent port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the SNMP Agent port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0067

User Action:

Information only; no action is required.

- **FQXSPNM4040I: SNMP Traps port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the SNMP Traps port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0068

User Action:

Information only; no action is required.

- **FQXSPNM4041I: Syslog port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the Syslog receiver port number

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0069

User Action:

Information only; no action is required.

- **FQXSPNM4042I: Remote Presence port number changed from [arg1] to [arg2] by user [arg3].**

A user has modified the Remote Presence port number

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0070

User Action:

Information only; no action is required.

- **FQXSPNM4043I: SMTP Server set by user [arg1] to [arg2]:[arg3].**

A user configured the SMTP server

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0086

User Action:

Information only; no action is required.

- **FQXSPNM4044I: Telnet [arg1] by user [arg2].**

A user enables or disables Telnet services

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0087

User Action:

Information only; no action is required.

- **FQXSPNM4045I: DNS servers set by user [arg1]: UseAdditionalServers=[arg2], PreferredDNStype=[arg3], IPv4Server1=[arg4], IPv4Server2=[arg5], IPv4Server3=[arg6], IPv6Server1=[arg7], IPv6Server2=[arg8], IPv6Server3=[arg9].**

A user configures the DNS servers

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none

SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0088

User Action:

Information only; no action is required.

- **FQXSPNM4046I: LAN over USB [arg1] by user [arg2].**

A user configured USB-LAN

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0089

User Action:

Information only; no action is required.

- **FQXSPNM4047I: LAN over USB Port Forwarding set by user [arg1]: ExternalPort=[arg2], USB-LAN port=[arg3].**

A user configured USB-LAN port forwarding

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0090

User Action:

Information only; no action is required.

- **FQXSPNM4048I: PXE boot requested by user [arg1].**

PXE boot requested

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0129

User Action:

Information only; no action is required.

- **FQXSPNM4049I: User [arg1] has initiated a TKLM Server Connection Test to check connectivity to server [arg2].**

User initiated a TKLM Server Connection test.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:

CIM Prefix: IMM CIM ID: 0159

User Action:

Information only; no action is required.

- **FQXSPNM4050I: User [arg1] has initiated an SMTP Server Connection Test.**

User initiated an SMTP Server Connection test.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0160

User Action:

Information only; no action is required.

- **FQXSPNM4051I: User [arg1] has set the SMTP Server reverse-path to [arg2].**

User set SMTP Server reverse-path address

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0163

User Action:

Information only; no action is required.

- **FQXSPNM4052I: DHCP specified hostname is set to [arg1] by user [arg2].**

DHCP specified hostname is set by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0216

User Action:

Information only; no action is required.

- **FQXSPNM4053I: DNS discovery of Lenovo XClarity Administrator has been [arg1] by user [arg2].**

DNS discovery of Lenovo XClarity Administrator

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0217

User Action:

Information only; no action is required.

- **FQXSPNM4054I: The hostname from DHCP is [arg1] by user [arg2].**

This message is for getting hostname from DHCP.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - IMM Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0244

User Action:

Information only; no action is required.

- **FQXSPNM4055I: The hostname from DHCP is invalid.**

This message is for hostname from DHCP is invalid.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - IMM Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0245

User Action:

Information only; no action is required.

- **FQXSPNM4056I: The NTP server address [arg1] is invalid.**

Report NTP server invalid

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - IMM Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0249

User Action:

Information only; no action is required.

- **FQXSPNM4057I: Security: IP address: [arg1] had [arg2] login failures, it will be blocked to access for [arg3] minutes.**

This message is for the use case where IP address blocking.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - IMM Network event
SNMP Trap ID: 37
CIM Prefix: IMM CIM ID: 0250

User Action:

Information only; no action is required.

- **FQXSPOS4000I: OS Watchdog response [arg1] by [arg2] .**

This message is for the use case where an OS Watchdog has been enabled or disabled by a user.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0012

User Action:

Information only; no action is required.

- **FQXSPOS4001I: Watchdog [arg1] Screen Capture Occurred .**

This message is for the use case where an operating system error has occurred and the screen was captured.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0028

User Action:

Complete the following steps until the problem is solved:

1. If there was no operating-system error:
2. Reconfigure the watchdog timer to a higher value.
3. Make sure that the BMC Ethernet-over-USB interface is enabled.
4. Reinstall the RNDIS or cdc_ether device driver for the operating system.
5. Disable the watchdog.
6. If there was an operating-system error, check the integrity of the installed operating system.

- **FQXSPOS4002I: Watchdog [arg1] Failed to Capture Screen.**

This message is for the use case where an operating system error has occurred and the screen capture failed.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0029

User Action:

Complete the following steps until the problem is solved:

1. Reconfigure the watchdog timer to a higher value.
2. Make sure that the BMC Ethernet over USB interface is enabled.
3. Reinstall the RNDIS or cdc_ether device driver for the operating system.
4. Disable the watchdog.
5. Check the integrity of the installed operating system.

6. If problem persists, collect Service Data log.
7. Contact Lenovo Support.

- **FQXSPOS4003I: Platform Watchdog Timer expired for [arg1].**

An implementation has detected an OS Loader Watchdog Timer Expired

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Loader timeout
SNMP Trap ID: 26
CIM Prefix: IMM CIM ID: 0060

User Action:

Complete the following steps until the problem is solved:

1. Reconfigure the watchdog timer to a higher value.
2. Make sure that the BMC Ethernet over USB interface is enabled.
3. Reinstall the RNDIS or cdc_ether device driver for the operating system.
4. Disable the watchdog.
5. If problem persists, collect Service Data log.
6. Contact Lenovo Support. Check the integrity of the installed operating system.

- **FQXSPOS4004I: Operating System status has changed to [arg1].**

Operating System status change

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0191

User Action:

Information only; no action is required.

- **FQXSPOS4005I: Host Power-On password changed by user [arg1] from [arg2] at IP address [arg3].**

This message is for the use case where Host Power-On password changed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0231

User Action:

Information only; no action is required.

- **FQXSPOS4006I: Host Power-On password cleared by user [arg1] from [arg2] at IP address [arg3].**

This message is for the use case where Host Power-On password cleared.

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0232

User Action:

Information only; no action is required.

- **FQXSPOS4007I: Host Admin password changed by user [arg1] from [arg2] at IP address [arg3].**

This message is for the use case where Host Admin password changed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0233

User Action:

Information only; no action is required.

- **FQXSPOS4008I: Host Admin password cleared by user [arg1] from [arg2] at IP address [arg3].**

This message is for the use case where Host Admin password cleared.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0234

User Action:

Information only; no action is required.

- **FQXSPOS4009I: OS Crash Video Captured.**

This message is for the use case where OS Crash Video Captured.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0235

User Action:

Information only; no action is required.

- **FQXSPOS4010I: OS Crash Video Capture Failed.**

This message is for the use case where OS Crash Video Capture Failed.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22

CIM Prefix: IMM CIM ID: 0236

User Action:

Complete the following steps until the problem is solved:

1. Check if the OS watchdog is enabled
2. Check if the crash video recording is enabled
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPPP4000I: Attempting to [arg1] server [arg2] by user [arg3].**

This message is for the use case where a user is using the Management Controller to perform a power function on the system.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0015

User Action:

Information only; no action is required.

- **FQXSPPP4001I: Server Power Off Delay set to [arg1] by user [arg2].**

A user configured the Server Power Off Delay

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0081

User Action:

Information only; no action is required.

- **FQXSPPP4002I: Server [arg1] scheduled for [arg2] at [arg3] by user [arg4].**

A user configured a Server Power action at a specific time

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0082

User Action:

Information only; no action is required.

- **FQXSPPP4003I: Server [arg1] scheduled for every [arg2] at [arg3] by user [arg4].**

A user configured a recurring Server Power Action

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0083

User Action:

Information only; no action is required.

- **FQXSPPP4004I: Server [arg1] [arg2] cleared by user [arg3].**

A user cleared a Server Power Action.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0084

User Action:

Information only; no action is required.

- **FQXSPPP4005I: The power cap value changed from [arg1] watts to [arg2] watts by user [arg3].**

Power Cap values changed by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0113

User Action:

Information only; no action is required.

- **FQXSPPP4006I: The minimum power cap value changed from [arg1] watts to [arg2] watts.**

Minimum Power Cap value changed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0114

User Action:

Information only; no action is required.

- **FQXSPPP4007I: The maximum power cap value changed from [arg1] watts to [arg2] watts.**

Maximum Power Cap value changed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:

CIM Prefix: IMM CIM ID: 0115

User Action:

Information only; no action is required.

- **FQXSPPP4008I: The soft minimum power cap value changed from [arg1] watts to [arg2] watts.**

Soft Minimum Power Cap value changed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0116

User Action:

Information only; no action is required.

- **FQXSPPP4009I: The measured power value exceeded the power cap value.**

Power exceeded cap

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: IMM CIM ID: 0117

User Action:

Information only; no action is required.

- **FQXSPPP4010I: The new minimum power cap value exceeded the power cap value.**

Minimum Power Cap exceeds Power Cap

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: IMM CIM ID: 0118

User Action:

Information only; no action is required.

- **FQXSPPP4011I: Power capping was activated by user [arg1].**

Power capping activated by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0119

User Action:

Information only; no action is required.

- **FQXSPPP4012I: Power capping was deactivated by user [arg1].**

Power capping deactivated by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0120

User Action:

Information only; no action is required.

- **FQXSPPP4013I: Static Power Savings mode has been turned on by user [arg1].**

Static Power Savings mode turned on by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0121

User Action:

Information only; no action is required.

- **FQXSPPP4014I: Static Power Savings mode has been turned off by user [arg1].**

Static Power Savings mode turned off by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0122

User Action:

Information only; no action is required.

- **FQXSPPP4015I: Dynamic Power Savings mode has been turned on by user [arg1].**

Dynamic Power Savings mode turned on by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0123

User Action:

Information only; no action is required.

- **FQXSPPP4016I: Dynamic Power Savings mode has been turned off by user [arg1].**

Dynamic Power Savings mode turned off by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0124

User Action:

Information only; no action is required.

- **FQXSPPP4017I: Power cap and external throttling occurred.**

Power cap and external throttling occurred

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0125

User Action:

Information only; no action is required.

- **FQXSPPP4018I: External throttling occurred .**

External throttling occurred

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0126

User Action:

Information only; no action is required.

- **FQXSPPP4019I: Power cap throttling occurred.**

Power cap throttling occurred

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0127

User Action:

Information only; no action is required.

- **FQXSPPP4020I: The measured power value has returned below the power cap value.**

Power exceeded cap recovered

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: IMM CIM ID: 0130

User Action:

Information only; no action is required.

- **FQXSPPP4021I: The new minimum power cap value has returned below the power cap value.**

Minimum Power Cap exceeds Power Cap recovered

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: IMM CIM ID: 0131

User Action:

Information only; no action is required.

- **FQXSPPP4022I: The server was restarted for an unknown reason.**

The server was restarted for an unknown reason

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0166

User Action:

Information only; no action is required.

- **FQXSPPP4023I: The server is restarted by chassis control command.**

Server is restarted by chassis control command

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0167

User Action:

Information only; no action is required.

- **FQXSPPP4024I: The server was reset via push button.**

Server was reset via push button

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22

CIM Prefix: IMM CIM ID: 0168

User Action:

Information only; no action is required.

- **FQXSPPP4025I: The server was powered-up via power push button.**

Server was power-up via power push button

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0169

User Action:

Information only; no action is required.

- **FQXSPPP4026I: The server was restarted when the watchdog expired..**

Server was restarted when the watchdog expired.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0170

User Action:

Information only; no action is required.

- **FQXSPPP4027I: The server was restarted for OEM reason.**

Server was restarted for OEM reason

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0171

User Action:

Information only; no action is required.

- **FQXSPPP4028I: The server was automatically powered on because the power restore policy is set to always restore..**

Server was automatically powered on because the power restore policy is set to always restore.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0172

User Action:

Information only; no action is required.

- **FQXSPPP4029I: The server was automatically powered on because the power restore policy is set to restore previous power state..**

Server was automatically powered on because the power restore policy is set to restore previous power state.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0173

User Action:

Information only; no action is required.

- **FQXSPPP4030I: The server was reset via Platform Event Filter.**

Server was reset via Platform Event Filter

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0174

User Action:

Information only; no action is required.

- **FQXSPPP4031I: The server was power-cycled via Platform Event Filter.**

Server was power-cycled via Platform Event Filter

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0175

User Action:

Information only; no action is required.

- **FQXSPPP4032I: The server was soft reset.**

Server was soft reset

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0176

User Action:

Information only; no action is required.

- **FQXSPPP4033I: The server was powered up via Real Time Clock (scheduled power on).**

Server was powered up via Real Time Clock (scheduled power on)

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0177

User Action:

Information only; no action is required.

- **FQXSPPP4034I: The server was powered off for an unknown reason.**

Server was powered off for an unknown reason

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0178

User Action:

Information only; no action is required.

- **FQXSPPP4035I: The server was powered off by chassis control command.**

Server was powered off by chassis control command

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0179

User Action:

Information only; no action is required.

- **FQXSPPP4036I: The server was powered off via push button.**

Server was powered off via push button

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0180

User Action:

Information only; no action is required.

- **FQXSPPP4037I: The server was powered off when the watchdog expired.**

Server was powered off when the watchdog expired.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0181

User Action:

Information only; no action is required.

- **FQXSPPP4038I: The server stayed powered off because the power restore policy is set to always restore..**

Server stayed powered off because the power restore policy is set to always restore.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0182

User Action:

Information only; no action is required.

- **FQXSPPP4039I: The server stayed powered off because the power restore policy is set to restore previous power state..**

Server stayed powered off because the power restore policy is set to restore previous power state.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0183

User Action:

Information only; no action is required.

- **FQXSPPP4040I: The server was powered off via Platform Event Filter.**

Server was power off via Platform Event Filter

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0184

User Action:

Information only; no action is required.

- **FQXSPPP4041I: The server was powered off via Real Time Clock (scheduled power off).**

Server was powered up via Real Time Clock (scheduled power off)

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0185

User Action:

Information only; no action is required.

- **FQXSPPP4042I: Management Controller [arg1] reset was initiated due to Power-On-Reset.**

Management Controller reset was initiated due to Power-On-Reset

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0186

User Action:

Information only; no action is required.

- **FQXSPPP4043I: Management Controller [arg1] reset was initiated by PRESET.**

Management Controller reset was initiated by PRESET

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0187

User Action:

Information only; no action is required.

- **FQXSPPP4044I: Management Controller [arg1] reset was initiated by CMM.**

Management Controller reset was initiated by CMM

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0188

User Action:

Information only; no action is required.

- **FQXSPPP4045I: Management Controller [arg1] reset was initiated by XCC firmware.**

Management Controller reset was initiated by XCC firmware

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0189

User Action:

Information only; no action is required.

- **FQXSPPP4047I: Management Controller [arg1] reset was initiated by user [arg2].**

This message is for the use case where a Management Controller reset is initiated by a user.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0021

User Action:

Information only; no action is required.

- **FQXSPPP4048I: Attempting to AC power cycle server [arg1] by user [arg2].**

AC power cycle server

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0227

User Action:

Information only; no action is required.

- **FQXSPPP4049I: Management Controller [arg1] reset was initiated by Front Panel.**

Management Controller reset was initiated by Front Panel

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0252

User Action:

Information only; no action is required.

- **FQXSPPP4050I: Management Controller [arg1] reset was initiated to activate PFR Firmware.**

Management Controller reset was initiated to activate PFR Firmware.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0253

User Action:

Information only; no action is required.

- **FQXSPPU0000I: [ProcessorElementName] in slot [SlotElementName] has been added.**

This message is for the use case when an implementation has detected a Processor has been Added.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0034

User Action:

Information only; no action is required.

- **FQXSPPU0001N: An Over-Temperature Condition has been detected on [ProcessorElementName].**

This message is for the use case when an implementation has detected an Over-Temperature Condition Detected for Processor.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0036

User Action:

Complete the following steps until the problem is solved:

1. Check the event log of XClarity Controller (XCC) for any fan- or cooling-related issues.
2. Make sure that the airflow at the front and rear of the chassis is not obstructed and that fillers are in place, clean, and correctly installed.
3. Make sure that the room temperature is within operating specifications.
4. Make sure that the microprocessor 1 heat sink is installed correctly and the thermal interface is correctly applied.
5. Once you finish the action above and can't solve issue, please contact Lenovo support.

- **FQXSPPU0002G: The Processor [ProcessorElementName] is operating in a Degraded State.**

This message is for the use case when an implementation has detected a Processor is running in the Degraded state.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - CPU
SNMP Trap ID: 42
CIM Prefix: PLAT CIM ID: 0038

User Action:

Complete the following steps:

1. Check the XCC event log for any fan, cooling or power related issues.
2. Make sure fan and power supply unit is installed correctly and clean.

3. Make sure that the airflow at the front and rear of the chassis is not obstructed
4. Make sure that the room temperature is in the range in the operating specifications.
5. If the problem still exist and XCC event is realted to power supply unit, please upgrade power supply unit with supported specification.
6. Once you finish the action above and can't solve issue, please contact Lenovo support.

- **FQXSPPU0003N: [ProcessorElementName] has Failed with IERR.**

This message is for the use case when an implementation has detected a Processor Failed - IERR Condition.

Severity: Error
 Serviceable: Yes
 Automatically notify Support: No
 Alert Category: Critical - CPU
 SNMP Trap ID: 40
 CIM Prefix: PLAT CIM ID: 0042

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or UEFI firmware update that applies to this Processor error.
2. Reboot system.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPPU0004M: [ProcessorElementName] has Failed with FRB1/BIST condition.**

This message is for the use case when an implementation has detected a Processor Failed - FRB1/BIST condition.

Severity: Error
 Serviceable: Yes
 Automatically notify Support: Yes
 Alert Category: Critical - CPU
 SNMP Trap ID: 40
 CIM Prefix: PLAT CIM ID: 0044

User Action:

Complete the following steps:

1. If the system board or firmware was just updated, check the Lenovo support site for an applicable service bulletin or firmware update that applies to this processor error.
2. If problem persists, collect Service Data log.
3. Contact Lenovo Support.

- **FQXSPPU0009N: [ProcessorElementName] has a Configuration Mismatch.**

This message is for the use case when an implementation has detected a Processor Configuration Mismatch has occurred.

Severity: Error
 Serviceable: Yes
 Automatically notify Support: No
 Alert Category: Critical - CPU
 SNMP Trap ID: 40

CIM Prefix: PLAT CIM ID: 0062

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this processor error.
2. If problem persists, collect Service Data log.
3. Contact Lenovo Support.

- **FQXSPPU0011N: An SM BIOS Uncorrectable CPU complex error for [ProcessorElementName] has asserted.**

This message is for the use case when an SM BIOS Uncorrectable CPU complex error has asserted.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - CPU
SNMP Trap ID: 40
CIM Prefix: PLAT CIM ID: 0816

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or UEFI firmware update that applies to this error.
2. Reboot system.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPPU2000I: [ProcessorElementName] in slot [SlotElementName] has been removed.**

This message is for the use case when an implementation has detected a Processor has been Removed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0035

User Action:

Information only; no action is required.

- **FQXSPPU2001I: An Over-Temperature Condition has been removed on [ProcessorElementName].**

This message is for the use case when an implementation has detected a Over-Temperature Condition has been Removed for Processor.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Temperature
SNMP Trap ID: 0
CIM Prefix: PLAT CIM ID: 0037

User Action:

Information only; no action is required

- **FQXSPPU2002I: The Processor [ProcessorElementName] is no longer operating in a Degraded State.**

This message is for the use case when an implementation has detected a Processor is no longer running in the Degraded state.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - CPU
SNMP Trap ID: 42
CIM Prefix: PLAT CIM ID: 0039

User Action:

Information only; no action is required

- **FQXSPPW0001I: [PowerSupplyElementName] has been added to container [PhysicalPackageElementName].**

This message is for the use case when an implementation has detected a Power Supply has been added.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0084

User Action:

Information only; no action is required

- **FQXSPPW0002L: [PowerSupplyElementName] has Failed.**

This message is for the use case when an implementation has detected a Power Supply has failed.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Power
SNMP Trap ID: 4
CIM Prefix: PLAT CIM ID: 0086

User Action:

Please check the event log in XClarity Controller (XCC) Web GUI to identify the power supply unit failure.

1. Check the system spec, and replace the power supply unit with another unit of the same wattage.

- **FQXSPPW0003G: Failure predicted on [PowerSupplyElementName].**

This message is for the use case when an implementation has detected a Power Supply failure is predicted.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: PLAT CIM ID: 0088

User Action:

Please check the event log in XClarity Controller (XCC) Web GUI to identify the power supply unit failure.

- **FQXSPPW0005I: [PowerSupplyElementName] is operating in an Input State that is out of range.**

This message is for the use case when an implementation has detected a Power Supply that has input out of range.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0098

User Action:

Information only; no action is required

- **FQXSPPW0006I: [PowerSupplyElementName] has lost input.**

This message is for the use case when an implementation has detected a Power Supply that has input that has been lost.

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0100

User Action:

Make sure power cables are connected correctly.

- **FQXSPPW0007L: [PowerSupplyElementName] has a Configuration Mismatch.**

This message is for the use case when an implementation has detected a Power Supply with a Configuration Error.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Power
SNMP Trap ID: 4
CIM Prefix: PLAT CIM ID: 0104

User Action:

Please check wattage consistency of PSU on XClarity Controller (XCC) Web GUI. If the PSUs are not of the same wattage, replace one to make the wattage of two PSUs consistent, and make sure the wattage is supported by the system.

- **FQXSPPW0008I: [SensorElementName] has been turned off.**

This message is for the use case when an implementation has detected a Power Unit that has been Disabled.

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: System - Power Off
SNMP Trap ID: 23
CIM Prefix: PLAT CIM ID: 0106

User Action:

Information only; no action is required

- **FQXSPPW0009I: [PowerSupplyElementName] has been Power Cycled.**

This message is for the use case when an implementation has detected a Power Unit that has been power cycled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0108

User Action:

Information only; no action is required

- **FQXSPPW0031J: Numeric sensor [NumericSensorElementName] going low (lower non-critical) has asserted.**

This message is for the use case when an implementation has detected a Lower Non-critical sensor going low has asserted.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Voltage
SNMP Trap ID: 13
CIM Prefix: PLAT CIM ID: 0476

User Action:

CMOS battery is recommended to replace with new one.

- **FQXSPPW0035M: Numeric sensor [NumericSensorElementName] going low (lower critical) has asserted.**

This message is for the use case when an implementation has detected a Lower Critical sensor going low has asserted.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Voltage
SNMP Trap ID: 1
CIM Prefix: PLAT CIM ID: 0480

User Action:

Complete the following steps:

1. If the specified sensor is Planar 3.3V or Planar 5V, (trained technician only)replace the system board.
2. If the specified sensor is Planar 12V, ensure PDB board is installed correctly and check the XClarity Controller event log for power-supply-related issues, and resolve those issues.
3. If the problem remains, replace (trained technician only)the PDB board or system board.

- **FQXSPW0047M: Numeric sensor [NumericSensorElementName] going high (upper critical) has asserted.**

This message is for the use case when an implementation has detected an Upper Critical sensor going high has asserted.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Voltage
SNMP Trap ID: 1
CIM Prefix: PLAT CIM ID: 0494

User Action:

Complete the following steps:

1. If the specified sensor is Planar 3.3V or Planar 5V, (trained technician only)replace the system board.
2. If the specified sensor is Planar 12V, ensure PDB board is installed correctly and check the XClarity Controller event log for power-supply-related issues, and resolve those issues.
3. If the problem remains, replace (trained technician only)the PDB or system board.

- **FQXSPW0057J: Sensor [SensorElementName] has transitioned from normal to non-critical state.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-critical from normal.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: PLAT CIM ID: 0520

User Action:

Please check event log in xClarity Controller web interface.

- **FQXSPW0061M: Sensor [SensorElementName] has transitioned to critical from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to critical from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Power
SNMP Trap ID: 4
CIM Prefix: PLAT CIM ID: 0522

User Action:

Complete the following steps:

1. Ensure the power supply units meet the system spec requirements in terms of wattage, efficiency level, and are among the list of supported models.
2. Check the event log in XClarity Controller (XCC) Web GUI for the detailed information to reseal/reinstall/upgrade the power supply units.
3. If the problem still exists, please contact Lenovo support.

- **FQXSPPW0063M: Sensor [SensorElementName] has transitioned to critical from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to critical from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Voltage
SNMP Trap ID: 1
CIM Prefix: PLAT CIM ID: 0522

User Action:

Complete the following steps until the problem is solved:

1. If the specified sensor is Planar 3.3V or Planar 5V, replace the system board (trained technician only).
2. If the specified sensor is Planar 12V, check XClarity Controller (XCC)event log for power-supply-related issues and resolve those issues. If the problem remains, replace the system board (trained technician only).
3. Contact local service provider. To locate a reseller authorized by Lenovo to provide warranty service, go to <http://www.ibm.com/partnerworld> and click Business Partner Locator.

- **FQXSPPW0101J: Redundancy Degraded for [RedundancySetElementName] has asserted.**

This message is for the use case when Redundancy Degraded has asserted.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Redundant Power Supply
SNMP Trap ID: 10
CIM Prefix: PLAT CIM ID: 0804

User Action:

Please ensure the PSU wattage and efficiency level are supported by the system, and the PSU is among the list of supported models.

- **FQXSPPW0104J: Non-redundant:Sufficient Resources from Redundancy Degraded or Fully Redundant for [RedundancySetElementName] has asserted.**

This message is for the use case when a Redundancy Set has transitioned from Redundancy Degraded or Fully Redundant to Non-redundant:Sufficient.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Redundant Power Supply
SNMP Trap ID: 10
CIM Prefix: PLAT CIM ID: 0806

User Action:

Please ensure the PSU wattage and efficiency level are supported by the system, and the PSU is among the list of supported models.

- **FQXSPPW0110M: Non-redundant:Insufficient Resources for [RedundancySetElementName] has asserted.**

This message is for the use case when a Redundancy Set has transitioned to Non-redundant:Insufficient Resources.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Redundant Power Supply
SNMP Trap ID: 9
CIM Prefix: PLAT CIM ID: 0810

User Action:

Complete the following steps until the problem is solved:

1. Check if the power supply unit is missing, failing or not installed properly. If so, re-install or replace it.
2. Check the power supply unit max rate and power capping policy. If the required power resource is not met, replace the power supply unit with another unit that meets the system requirements.

- **FQXSPW2001I: [PowerSupplyElementName] has been removed from container [PhysicalPackageElementName].**

This message is for the use case when an implementation has detected a Power Supply has been removed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0085

User Action:

Information only; no action is required

- **FQXSPW2002I: [PowerSupplyElementName] has returned to OK status.**

This message is for the use case when an implementation has detected a Power Supply return to normal operational status.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Power
SNMP Trap ID: 4
CIM Prefix: PLAT CIM ID: 0087

User Action:

Information only; no action is required

- **FQXSPW2003I: Failure no longer predicted on [PowerSupplyElementName].**

This message is for the use case when an implementation has detected a Power Supply failure is no longer predicted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: PLAT CIM ID: 0089

User Action:

Information only; no action is required

- **FQXSPPW2006I: [PowerSupplyElementName] has returned to a Normal Input State.**

This message is for the use case when an implementation has detected a Power Supply that has input that has returned to normal.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0099

User Action:

Information only; no action is required

- **FQXSPPW2007I: [PowerSupplyElementName] Configuration is OK.**

This message is for the use case when an implementation when a Power Supply configuration is OK.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Power
SNMP Trap ID: 4
CIM Prefix: PLAT CIM ID: 0105

User Action:

Information only; no action is required

- **FQXSPPW2008I: [PowerSupplyElementName] has been turned on.**

This message is for the use case when an implementation has detected a Power Unit that has been Enabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Power On
SNMP Trap ID: 24
CIM Prefix: PLAT CIM ID: 0107

User Action:

Information only; no action is required

- **FQXSPPW2018I: [PowerSupplyElementName] out-of-range has returned to a Normal Input State.**

This message is for the use case when an implementation has detected a Power Supply that has input that has returned to normal.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0099

User Action:

Information only; no action is required.

- **FQXSPW2031I: Numeric sensor [NumericSensorElementName] going low (lower non-critical) has deasserted.**

This message is for the use case when an implementation has detected a Lower Non-critical sensor going low has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Voltage
SNMP Trap ID: 13
CIM Prefix: PLAT CIM ID: 0477

User Action:

Information only; no action is required

- **FQXSPW2035I: Numeric sensor [NumericSensorElementName] going low (lower critical) has deasserted.**

This message is for the use case when an implementation has detected a Lower Critical sensor going low has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Voltage
SNMP Trap ID: 1
CIM Prefix: PLAT CIM ID: 0481

User Action:

Information only; no action is required

- **FQXSPW2047I: Numeric sensor [NumericSensorElementName] going high (upper critical) has deasserted.**

This message is for the use case when an implementation has detected an Upper Critical sensor going high has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Voltage
SNMP Trap ID: 1
CIM Prefix: PLAT CIM ID: 0495

User Action:

Information only; no action is required

- **FQXSPW2057I: Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.**

This message is for the use case when an implementation has detected that a Sensor has deasserted a transition to non-critical from normal.

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: Warning - Power
SNMP Trap ID: 164
CIM Prefix: PLAT CIM ID: 0521

User Action:

Information only; no action is required

- **FQXSPW2061I: Sensor [SensorElementName] has transitioned to a less severe state from critical.**

This message is for the use case when an implementation has detected a Sensor transition to less severe from critical.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Power
SNMP Trap ID: 4
CIM Prefix: PLAT CIM ID: 0523

User Action:

Information only; no action is required

- **FQXSPW2063I: Sensor [SensorElementName] has transitioned to a less severe state from critical.**

This message is for the use case when an implementation has detected a Sensor transition to less severe from critical.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Voltage
SNMP Trap ID: 1
CIM Prefix: PLAT CIM ID: 0523

User Action:

Information only; no action is required

- **FQXSPW2101I: Redundancy Degraded for [RedundancySetElementName] has deasserted.**

This message is for the use case when Redundancy Degraded has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Redundant Power Supply
SNMP Trap ID: 10
CIM Prefix: PLAT CIM ID: 0805

User Action:

Information only; no action is required.

- **FQXSPW2104I: Non-redundant:Sufficient Resources from Redundancy Degraded or Fully Redundant for [RedundancySetElementName] has deasserted.**

This message is for the use case when a Redundancy Set has transitioned from Non-redundant:Sufficient Resources.

Severity: Info

Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Redundant Power Supply
SNMP Trap ID: 10
CIM Prefix: PLAT CIM ID: 0807

User Action:

Information only; no action is required.

- **FQXSPPW2110I: Non-redundant:Insufficient Resources for [RedundancySetElementName] has deasserted.**

This message is for the use case when a Redundancy Set has transitioned from Non-redundant: Insufficient Resources.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Redundant Power Supply
SNMP Trap ID: 9
CIM Prefix: PLAT CIM ID: 0811

User Action:

Information only; no action is required.

- **FQXSPPW4001I: PCIe Power Brake for [arg1] has been [arg2].**

This message is for the use case where PCIe Power Brake.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0243

User Action:

Check if system have fan fail error, Raidlink CEM fail occurring or Ambient temperature over 35C, implement the "error" service action to recovery the system and reduce ambient temperature under 35C.

- **FQXSPSD0000I: The [StorageVolumeElementName] has been added.**

This message is for the use case when an implementation has detected a Drive has been Added.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0162

User Action:

Information only; no action is required

- **FQXSPSD0001I: The [StorageVolumeElementName] Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has been added.**

This message is for the use case when an implementation has detected a Drive has been Added.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0162

User Action:

Information only; no action is required

- **FQXSPSD0001L: The [StorageVolumeElementName] has a fault.**

This message is for the use case when an implementation has detected a Drive was Disabled due to fault.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0164

User Action:

Complete the following steps:

1. Check the Support Portal(<http://support.lenovo.com/>)for service bulletins and TECH tips and firmware update related to your drive.
2. Check for any other RAID-related error.
3. Replace the drive.

- **FQXSPSD0002G: Failure Predicted on [StorageVolumeElementName] for array [ComputerSystemElementName].**

This message is for the use case when an implementation has detected an Array Failure is Predicted.

Severity: Warning
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: System - Predicted Failure
SNMP Trap ID: 27
CIM Prefix: PLAT CIM ID: 0168

User Action:

Replace hard disk drive 0 at the next maintenance period.

- **FQXSPSD0002L: Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has a fault.**

This message is for the use case when an implementation has detected a Drive was Disabled due to fault.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0164

User Action:

Complete the following steps:

1. Check the Support Portal(<http://support.lenovo.com/>)for service bulletins and TECH tips and firmware update related to your drive.
2. Check for any other RAID-related error.
3. Replace the drive.

- **FQXSPSD0003G: Failure Predicted on drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).**

This message is for the use case when an implementation has detected an Array Failure is Predicted.

Severity: Warning
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: System - Predicted Failure
SNMP Trap ID: 27
CIM Prefix: PLAT CIM ID: 0168

User Action:

Replace hard disk drive 0 at the next maintenance period.

- **FQXSPSD0003I: Hot Spare enabled for [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a Hot Spare has been Enabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0170

User Action:

Information only; no action is required

- **FQXSPSD0005I: Hot Spare enabled for drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).**

This message is for the use case when an implementation has detected a Hot Spare has been Enabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0170

User Action:

Information only; no action is required

- **FQXSPSD0005L: Array [ComputerSystemElementName] is in critical condition.**

This message is for the use case when an implementation has detected that an Array is Critical.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0174

User Action:

Replace the hard disk drive that is indicated by a lit status LED.

- **FQXSPSD0006L: Array [ComputerSystemElementName] has failed.**

This message is for the use case when an implementation has detected that an Array Failed.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0176

User Action:

Complete the following steps:

1. Replace any hard disk drive that is indicated by a lit status LED.
2. Re-create the array.
3. Restore the data from a backup.

- **FQXSPSD0007I: Rebuild in progress for Array in system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected that an Array Rebuild is in Progress.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0178

User Action:

Information only; no action is required

- **FQXSPSD0007L: Array critical asserted on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected that an Array is Critical.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0174

User Action:

Replace the hard disk drive that is indicated by a lit status LED.

- **FQXSPSD0008I: Array rebuild in progress on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected that an Array Rebuild is in Progress.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other

SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0178

User Action:

Information only; no action is required

- **FQXSPSD0008L: Array failed on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected that an Array Failed.

Severity: Error
Serviceable: Yes
Automatically notify Support: Yes
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0176

User Action:

Complete the following steps:

1. Replace any hard disk drive that is indicated by a lit status LED.
2. Re-create the array.
3. Restore the data from a backup.

- **FQXSPSD2000I: The [StorageVolumeElementName] has been removed from unit [PhysicalPackageElementName].**

This message is for the use case when an implementation has detected a Drive has been Removed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0163

User Action:

Complete the following steps until the problem is solved:

1. If drive was intentionally removed, make sure that there is a filler in the drive bay.
2. Make sure that the drive is correctly seated.
3. If drive is correctly seated, replace the drive.

- **FQXSPSD2001I: The [StorageVolumeElementName] has recovered from a fault.**

This message is for the use case when an implementation has detected a Drive was Enabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0167

User Action:

Information only; no action is required

- **FQXSPSD2002I: Failure no longer Predicted on [StorageVolumeElementName] for array [ComputerSystemElementName].**

This message is for the use case when an implementation has detected an Array Failure is no longer Predicted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Predicted Failure
SNMP Trap ID: 27
CIM Prefix: PLAT CIM ID: 0169

User Action:

Information only; no action is required

- **FQXSPSD2003I: Hot spare disabled for [ComputerSystemElementName].**

This message is for the use case when an implementation has detected a Hot Spare has been Disabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0171

User Action:

Information only; no action is required

- **FQXSPSD2005I: Critical Array [ComputerSystemElementName] has deasserted.**

This message is for the use case when an implementation has detected that an Critical Array has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0175

User Action:

Information only; no action is required

- **FQXSPSD2006I: Array in system [ComputerSystemElementName] has been restored.**

This message is for the use case when an implementation has detected that a Failed Array has been Restored.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0177

User Action:

Information only; no action is required

- **FQXSPSD2007I: Rebuild completed for Array in system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected that an Array Rebuild has Completed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0179

User Action:

Information only; no action is required

- **FQXSPSD2008I: Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has recovered from a fault.**

This message is for the use case when an implementation has detected a Drive was Enabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0167

User Action:

Information only; no action is required

- **FQXSPSD2010I: Drive [arg1] in the enclosure/chassis(MTM-SN: [arg2]) has been removed.**

This message is for the use case when an implementation has detected a Drive has been Removed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: PLAT CIM ID: 0163

User Action:

Complete the following steps until the problem is solved:

1. If drive was intentionally removed, make sure that there is a filler in the drive bay.
2. Make sure that the drive is correctly seated.
3. If drive is correctly seated, replace the drive.

- **FQXSPSD2011I: Failure no longer Predicted on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected an Array Failure is no longer Predicted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Predicted Failure
SNMP Trap ID: 27
CIM Prefix: PLAT CIM ID: 0169

User Action:

Information only; no action is required

- **FQXSPSD2012I: Hot Spare disabled for drive [arg1] in the enclosure/chassis (MTM-SN: [arg2]).**

This message is for the use case when an implementation has detected a Hot Spare has been Disabled.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0171

User Action:

Information only; no action is required

- **FQXSPSD2013I: Array critical deasserted on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected that an Critical Array has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0175

User Action:

Information only; no action is required

- **FQXSPSD2014I: Array restored on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected that a Failed Array has been Restored.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0177

User Action:

Information only; no action is required

- **FQXSPSD2015I: Array rebuild completed on drive [arg1] in the enclosure/chassis (MTM-S/N: [arg2]).**

This message is for the use case when an implementation has detected that an Array Rebuild has Completed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other

SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0179

User Action:

Information only; no action is required

- **FQXSPSE0000F: The Chassis [PhysicalPackageName] was opened.**

This message is for the use case when the Chassis has been opened.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0004

User Action:

If the chassis is either opened or is not properly sealed, please ensure the chassis is installed properly. Ensure chassis intruder cable is connected correctly. (or no damaged)

- **FQXSPSE2000I: The Chassis [PhysicalPackageName] was closed.**

This message is for the use case when a Chassis has been closed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0005

User Action:

Information only; no action is required.

- **FQXSPSE4000I: Certificate Authority [arg1] has detected a [arg2] Certificate Error.**

This message is for the use case when there is an error with an SSL Server, SSL Client, or SSL Trusted CA Certificate.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0002

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the certificate that you are importing is correct and properly generated.
2. If problem persists, collect Service Data log.
3. Contact Lenovo Support.

- **FQXSPSE4001I: Remote Login Successful. Login ID: [arg1] using [arg2] from [arg3] at IP address [arg4].**

This message is for the use case where a user successfully logs in to a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0014

User Action:

Information only; no action is required.

- **FQXSPSE4002I: Security: Userid: [arg1] using [arg2] had [arg3] login failures from WEB client at IP address [arg4].**

This message is for the use case where a user has failed to log in to a Management Controller from a web browser.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0016

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the correct login ID and password are being used.
2. Have the system administrator reset the login ID or password.

- **FQXSPSE4003I: Security: Login ID: [arg1] had [arg2] login failures from CLI at [arg3].**

This message is for the use case where a user has failed to log in to a Management Controller from the Legacy CLI.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0017

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the correct login ID and password are being used.
2. Have the system administrator reset the login ID or password.

- **FQXSPSE4004I: Remote access attempt failed. Invalid userid or password received. Userid is [arg1] from WEB browser at IP address [arg2].**

This message is for the use case where a remote user has failed to establish a remote control session from a Web browser session.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0018

User Action:

Make sure that the correct login ID and password are being used.

- **FQXSPSE4005I: Remote access attempt failed. Invalid userid or password received. Userid is [arg1] from TELNET client at IP address [arg2].**

This message is for the use case where a user has failed to log in to a Management Controller from a telnet session.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0019

User Action:

Make sure that the correct login ID and password are being used.

- **FQXSPSE4006I: XCC detected an invalid SSL certificate in the Management Controller [arg1] .**

This message is for the use case where a Management Controller has detected invalid SSL data in the configuration data and is clearing the configuration data region and disabling the SSL.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0034

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the certificate that you are importing is correct and properly generated / certificate CSR is correct
2. If problem persists, collect Service Data log.
3. Contact Lenovo Support.

- **FQXSPSE4007I: Security: Userid: [arg1] using [arg2] had [arg3] login failures from an SSH client at IP address [arg4].**

This message is for the use case where a user has failed to log in to a Management Controller from SSH.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0041

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the correct login ID and password are being used.
2. Have the system administrator reset the login ID or password.

- **FQXSPSE4008I: SNMPv1 [arg1] set by user [arg2]: Name=[arg3], AccessType=[arg4], Address=[arg5], .**

A user changed the SNMP community string

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0075

User Action:

Information only; no action is required.

- **FQXSPSE4009I: LDAP Server configuration set by user [arg1]: SelectionMethod=[arg2], DomainName=[arg3], Server1=[arg4], Server2=[arg5], Server3=[arg6], Server4=[arg7].**

A user changed the LDAP server configuration

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0076

User Action:

Information only; no action is required.

- **FQXSPSE4010I: LDAP set by user [arg1]: RootDN=[arg2], UIDSearchAttribute=[arg3], BindingMethod=[arg4], EnhancedRBS=[arg5], TargetName=[arg6], GroupFilter=[arg7], GroupAttribute=[arg8], LoginAttribute=[arg9].**

A user configured an LDAP Miscellaneous setting

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0077

User Action:

Information only; no action is required.

- **FQXSPSE4011I: Secure Web services (HTTPS) [arg1] by user [arg2].**

A user enables or disables Secure web services

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0091

User Action:

Information only; no action is required.

- **FQXSPSE4012I: Secure CIM/XML(HTTPS) [arg1] by user [arg2].**

A user enables or disables Secure CIM/XML services

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0092

User Action:

Information only; no action is required.

- **FQXSPSE4013I: Secure LDAP [arg1] by user [arg2].**

A user enables or disables Secure LDAP services

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0093

User Action:

Information only; no action is required.

- **FQXSPSE4014I: SSH [arg1] by user [arg2].**

A user enables or disables SSH services

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0094

User Action:

Information only; no action is required.

- **FQXSPSE4015I: Global Login General Settings set by user [arg1]: AuthenticationMethod=[arg2], LockoutPeriod=[arg3], SessionTimeout=[arg4].**

A user changes the Global Login General Settings

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0098

User Action:

Information only; no action is required.

- **FQXSPSE4016I: Global Login Account Security set by user [arg1]: PasswordRequired=[arg2], PasswordExpirationPeriod=[arg3], MinimumPasswordReuseCycle=[arg4],**

**MinimumPasswordLength=[arg5], MinimumPasswordChangeInterval=[arg6],
MaxmumLoginFailures=[arg7], LockoutAfterMaxFailures=[arg8].**

A user changes the Global Login Account Security Settings to Legacy

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0099

User Action:

Information only; no action is required.

- **FQXSPSE4017I: User [arg1] created.**

A user account was created

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0100

User Action:

Information only; no action is required.

- **FQXSPSE4018I: User [arg1] removed.**

A user account was deleted

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0101

User Action:

Information only; no action is required.

- **FQXSPSE4019I: User [arg1] password modified.**

A user account was changed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0102

User Action:

Information only; no action is required.

- **FQXSPSE4020I: User [arg1] role set to [arg2].**

A user account role assigned

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0103

User Action:

Information only; no action is required.

- **FQXSPSE4021: User [arg1] custom privileges set: [arg2][arg3][arg4][arg5][arg6][arg7][arg8][arg9].**

User account privileges assigned

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0104

User Action:

Information only; no action is required.

- **FQXSPSE4022: User [arg1] for SNMPv3 set: AuthenticationProtocol=[arg2], PrivacyProtocol=[arg3], AccessType=[arg4], HostforTraps=[arg5] by user [arg6] from [arg7] at IP address [arg8].**

User account SNMPv3 settings changed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0105

User Action:

Information only; no action is required.

- **FQXSPSE4023: SSH Client key added for user [arg1] by user [arg2] from [arg3] at IP address [arg4].**

User locally defined an SSH Client key

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0106

User Action:

Information only; no action is required.

- **FQXSPSE4024: SSH Client key imported for user [arg1] from [arg2] by user [arg3] from [arg4] at IP address [arg5].**

User imported an SSH Client key

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0107

User Action:

Information only; no action is required.

- **FQXSPSE4025I: SSH Client key removed from user [arg1] by user [arg2] from [arg3] at IP address [arg4].**

User removed an SSH Client key

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0108

User Action:

Information only; no action is required.

- **FQXSPSE4026I: Security: Userid: [arg1] had [arg2] login failures from a CIM client at IP address [arg3].**

This message is for the use case where a user has failed to log in to a Management Controller from CIM.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0140

User Action:

Information only; no action is required.

- **FQXSPSE4027I: Remote access attempt failed. Invalid userid or password received. Userid is [arg1] from a CIM client at IP address [arg2].**

This message is for the use case where a remote user has failed to establish a remote control session from CIM.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0141

User Action:

Information only; no action is required.

- **FQXSPSE4028I: Security: Userid: [arg1] had [arg2] login failures from IPMI client at IP address [arg3].**

This message is for the use case where a user has failed to log in to a Management Controller from IPMI.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0153

User Action:

Information only; no action is required.

- **FQXSPSE4029I: Security: Userid: [arg1] had [arg2] login failures from SNMP client at IP address [arg3].**

This message is for the use case where a user has failed to access a Management Controller from SNMP.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0154

User Action:

Information only; no action is required.

- **FQXSPSE4030I: Security: Userid: [arg1] had [arg2] login failures from IPMI serial client.**

This message is for the use case where a user has failed to log in to a Management Controller from IPMI serial client

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0155

User Action:

Information only; no action is required.

- **FQXSPSE4031I: Remote Login Successful. Login ID: [arg1] from [arg2] serial interface.**

This message is for the use case where a user successfully logs in to a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0156

User Action:

Information only; no action is required.

- **FQXSPSE4032I: Login ID: [arg1] from [arg2] at IP address [arg3] has logged off.**

This message is for the use case where a user has logged off of a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0157

User Action:

Information only; no action is required.

- **FQXSPSE4033I: Login ID: [arg1] from [arg2] at IP address [arg3] has been logged off.**

This message is for the use case where a user has been logged off of a Management Controller.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0158

User Action:

Information only; no action is required.

- **FQXSPSE4034I: User [arg1] has removed a certificate.**

User removed certificate

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0164

User Action:

Information only; no action is required.

- **FQXSPSE4035I: A certificate has been revoked .**

A certificate has been revoked

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0165

User Action:

Information only; no action is required.

- **FQXSPSE4036I: The [arg1] certificate is expired and has been removed.**

Expired certificate has been removed

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0190

User Action:

Information only; no action is required.

- **FQXSPSE4037I: Crypto mode modified from [arg1] to [arg2] by user [arg3].**

Crypto mode modified

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0218

User Action:

Information only; no action is required.

- **FQXSPSE4038I: Minimum TLS level modified from [arg1] to [arg2] by user [arg3].**

Minimum TLS level modified

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0219

User Action:

Information only; no action is required.

- **FQXSPSE4039I: Temporary user account [arg1] is created by inband tool.**

Temporary user account create

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0228

User Action:

Information only; no action is required.

- **FQXSPSE4040I: Temporary user account [arg1] expires.**

Temporary user account expire

Severity: Info
Serviceable: No
Automatically notify Support: No

Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0229

User Action:

The user account you input has expired.

- **FQXSPSE4041I: Security: Userid: [arg1] had [arg2] login failures from a SFTP client at IP address [arg3].**

This message is for the use case where a user has failed to log in to a Management Controller from SFTP.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Remote Login
SNMP Trap ID: 30
CIM Prefix: IMM CIM ID: 0230

User Action:

Information only; no action is required.

- **FQXSPSE4042I: The third-party password function [arg1] by user [arg2] from [arg3] at IP address [arg4].**

This message is for the use case where a user successfully switch the third-party password function.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0238

User Action:

Information only; no action is required.

- **FQXSPSE4043I: Retrieving the third-party password [arg1] by user [arg2] from [arg3] at IP address [arg4].**

This message is for the use case where a user successfully switch the retrieving the third-party password.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0239

User Action:

Information only; no action is required.

- **FQXSPSE4044I: User [arg1] third-party hashed password has been [arg2] by user [arg3] from [arg4] at IP address [arg5].**

This message is for the use case where a user successfully manage the third-party hashed password.

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0240

User Action:

Information only; no action is required.

- **FQXSPSE4045I: The Salt of user [arg1] third-party password has been [arg2] by user [arg3] from [arg4] at IP address [arg5].**

This message is for the use case where a user successfully manage the third-party password salt.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0241

User Action:

Information only; no action is required.

- **FQXSPSE4046I: The third-party password of the user [arg1] has been retrieved by user [arg2] from [arg3] at IP address [arg4].**

This message is for the use case where a user successfully retrieving the third-party password.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0242

User Action:

Information only; no action is required.

- **FQXSPSE4047I: Role [arg1] is [arg2] and assigned with custom privileges [arg3][arg4][arg5][arg6] [arg7][arg8][arg9][arg10][arg11] by user [arg12] .**

Role create modify and assign

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0246

User Action:

Information only; no action is required.

- **FQXSPSE4048I: Role [arg1] is removed by user [arg2].**

Role is removed

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: none
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0247

User Action:

Information only; no action is required.

- **FQXSPSE4049I: Role [arg1] is assigned to user [arg2] by user [arg3].**

Role is assigned

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0248

User Action:

Information only; no action is required.

- **FQXSPSE4050I: [arg1] sent IPMI command from [arg2], raw data: [arg3][arg4][arg5].**

This message is for the use case where IPMI command to be sent.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0251

User Action:

Information only; no action is required.

- **FQXSPSR0001N: Sensor [SensorElementName] has transitioned to non-recoverable from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-recoverable from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0524

User Action:

Using XCC web or LSA or Storcli to check the status of every virtual disk on your system, resolve the problem on the problematic virtual disk(s).

- **FQXSPSR2001I: Sensor [SensorElementName] has deasserted the transition to non-recoverable from a less severe state.**

This message is for the use case when an implementation has detected that the Sensor transition to non-recoverable from less severe has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Hard Disk drive
SNMP Trap ID: 5
CIM Prefix: PLAT CIM ID: 0525

User Action:

Information only; no action is required

- **FQXSPSS4000I: Management Controller Test Alert Generated by [arg1].**

This message is for the use case where a user has generated a Test Alert.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0040

User Action:

Information only; no action is required.

- **FQXSPSS4001I: Server General Settings set by user [arg1]: Name=[arg2], Contact=[arg3], Location=[arg4], Room=[arg5], RackID=[arg6], Rack U-position=[arg7], Address=[arg8].**

A user configured the Location setting

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0080

User Action:

Information only; no action is required.

- **FQXSPSS4002I: License key for [arg1] added by user [arg2].**

A user installs License Key

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0096

User Action:

Information only; no action is required.

- **FQXSPSS4003I: License key for [arg1] removed by user [arg2].**

A user removes a License Key

Severity: Info
Serviceable: No

Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0097

User Action:

Information only; no action is required.

- **FQXSPSS4004I: Test Call Home Generated by user [arg1].**

Test Call Home generated by user.

Severity: Info
Serviceable: No
Automatically notify Support: Yes
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0134

User Action:

Information only; no action is required.

- **FQXSPSS4005I: Manual Call Home by user [arg1]: [arg2].**

Manual Call Home by user.

Severity: Info
Serviceable: No
Automatically notify Support: Yes
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0135

User Action:

Information only; no action is required.

- **FQXSPSS4006I: Call Home to [arg1] failed to complete: [arg2].**

Call Home failed to complete.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0195

User Action:

Information only; no action is required.

- **FQXSPSS4007I: The BMC functionality tier is changed from [arg1] to [arg2].**

Tier Change

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22

CIM Prefix: IMM CIM ID: 0222

User Action:

Information only; no action is required.

- **FQXSPSS4008I: The [arg1] setting has been changed to [arg2] by user [arg3].**

The setting has been changed by user

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0225

User Action:

Information only; no action is required.

- **FQXSPSS4009I: System enters LXPM maintenance mode.**

The system enters maintenance mode

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0226

User Action:

Information only; no action is required.

- **FQXSPSS4010I: Test Audit Log generated by user [arg1].**

This message is for the use case where OS Crash Video Capture Failed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0237

User Action:

Information only; no action is required.

- **FQXSPTR4000I: Management Controller [arg1] clock has been set from NTP server [arg2].**

This message is for the use case where a Management Controller clock has been set from the Network Time Protocol server.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0033

User Action:

Complete the following steps until the problem is solved:

1. Make sure that the certificate that you are importing is correct.
2. Try to import the certificate again.

- **FQXSPTR4001I: Date and Time set by user [arg1]: Date=[arg2], Time=[arg3], DST Auto-adjust=[arg4], Timezone=[arg5].**

A user configured the Date and Time settings

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0079

User Action:

Information only; no action is required.

- **FQXSPTR4002I: Synchronize time setting by user [arg1]: Mode=Sync with NTP Server, NTPServerHost1=[arg2]:[arg3],NTPServerHost2=[arg4]:[arg5],NTPServerHost3=[arg6]:[arg7], NTPServerHost4=[arg8]:[arg9],NTPUpdateFrequency=[arg10].**

A user configured the Date and Time synchronize settings

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0085

User Action:

Information only; no action is required.

- **FQXSPTR4003I: Synchronize time setting by user [arg1]: Mode=Sync with server clock.**

A user configured the Date and Time synchronize settings

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0224

User Action:

Information only; no action is required.

- **FQXSPUN0009G: Sensor [SensorElementName] has asserted.**

This message is for the use case when an implementation has detected a Sensor has asserted.

Severity: Warning
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other

SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0508

User Action:

Reboot the system. If the problem still exist, press F1 or use LXPM to do XCC FW update.

- **FQXSPUN0017I: Sensor [SensorElementName] has transitioned to normal state.**

This message is for the use case when an implementation has detected a Sensor transition to the normal state.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0518

User Action:

Information only; no action is required

- **FQXSPUN0018J: Sensor [SensorElementName] has transitioned from normal to non-critical state.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-critical from normal.

Severity: Warning
Serviceable: Yes
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0520

User Action:

Please check event log of XClarity Controller to investigate the identified device for enhancement.

- **FQXSPUN0019M: Sensor [SensorElementName] has transitioned to critical from a less severe state.**

This message is for the use case when an implementation has detected a Sensor transitioned to critical from less severe.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0522

User Action:

Complete the following steps:

1. Please check XCC web GUI to see the identified error.
2. Check system event log to fix the error.
3. If the problem still exist, please contact local service.

- **FQXSPUN0023N: Sensor [SensorElementName] has transitioned to non-recoverable.**

This message is for the use case when an implementation has detected a Sensor transitioned to non-recoverable.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0530

User Action:

Complete the following steps:

1. Check the Lenovo support site for an applicable service bulletin or firmware update that applies to this error.
2. Reboot the system.
3. If the error continues, replace the system-board assembly (see hardware maintenance manual).

- **FQXSPUN0026I: Device [LogicalDeviceElementName] has been added.**

This message is for the use case when an implementation has detected a Device was inserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0536

User Action:

Information only; no action is required

- **FQXSPUN0048I: The RAID controller in PCI slot [arg1] in optimal status.**

This message is for the use case when an implementation has detected a Sensor transition to the normal state.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0518

User Action:

Information only; no action is required

- **FQXSPUN2009I: Sensor [SensorElementName] has deasserted.**

This message is for the use case when an implementation has detected a Sensor has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0509

User Action:

Information only; no action is required

- **FQXSPUN2012: Sensor [SensorElementName] has deasserted.**

This message is for the use case when an implementation has detected a Sensor has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0509

User Action:

Information only; no action is required

- **FQXSPUN2018: Sensor [SensorElementName] has deasserted the transition from normal to non-critical state.**

This message is for the use case when an implementation has detected that a Sensor has deasserted a transition to non-critical from normal.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0521

User Action:

Information only; no action is required

- **FQXSPUN2019: Sensor [SensorElementName] has transitioned to a less severe state from critical.**

This message is for the use case when an implementation has detected a Sensor transition to less severe from critical.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0523

User Action:

Information only; no action is required

- **FQXSPUN2023: Sensor [SensorElementName] has deasserted the transition to non-recoverable.**

This message is for the use case when an implementation has detected that the Sensor transition to non-recoverable has deasserted.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0531

User Action:

Information only; no action is required

- **FQXSPUN2049I: The RAID controller in PCI slot [arg1] is no longer in warning status.**

This message is for the use case when an implementation has detected that a Sensor has deasserted a transition to non-critical from normal.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Warning - Other
SNMP Trap ID: 60
CIM Prefix: PLAT CIM ID: 0521

User Action:

Information only; no action is required

- **FQXSPUN2050I: The RAID controller in PCI slot [arg1] is no longer in critical status.**

This message is for the use case when an implementation has detected a Sensor transition to less severe from critical.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50
CIM Prefix: PLAT CIM ID: 0523

User Action:

Information only; no action is required

- **FQXSPUP0002I: A firmware or software change occurred on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected that the Firmware or Software Changed.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0438

User Action:

Information only; no action is required

- **FQXSPUP0007L: Invalid or Unsupported firmware or software was detected on system [ComputerSystemElementName].**

This message is for the use case when an implementation has detected an Invalid/Unsupported Firmware/Software Version.

Severity: Error
Serviceable: Yes
Automatically notify Support: No
Alert Category: Critical - Other
SNMP Trap ID: 50

CIM Prefix: PLAT CIM ID: 0446

User Action:

Reflash or update XCC firmware

- **FQXSPUP4000I: Please ensure that the Management Controller [arg1] is flashed with the correct firmware. The Management Controller is unable to match its firmware to the server.**

This message is for the use case where a Management Controller firmware version does not match the server.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0031

User Action:

Complete the following steps until the problem is solved:

1. Update the BMC firmware.
2. NOTE: Some cluster solutions require specific code levels or coordinated code updates. If the device is part of a cluster solution, verify that the latest level of code is supported for the cluster solution before you update the code.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPUP4001I: Flash of [arg1] from [arg2] succeeded for user [arg3] .**

This message is for the use case where a user has successfully flashed the firmware component (MC Main Application, MC Boot ROM, BIOS, Diagnostics, System Power Backplane, Remote Expansion Enclosure Power Backplane, Integrated System Management).

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: none
SNMP Trap ID:
CIM Prefix: IMM CIM ID: 0035

User Action:

Information only; no action is required.

- **FQXSPUP4002I: Flash of [arg1] from [arg2] failed for user [arg3].**

This message is for the use case where a user has not flashed the firmware component from the interface and IP address due to a failure.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0036

User Action:

Information only; no action is required.

- **FQXSPUP4003I: [arg1] firmware mismatch internal to system [arg2]. Please attempt to flash the [arg3] firmware.**

This message is for the use case where a specific type of firmware mismatch has been detected.

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0042

User Action:

Complete the following steps until the problem is solved:

1. AC cycle the system.
2. Reflash XCC/BMC firmware to the latest version.
3. NOTE: Some cluster solutions require specific code levels or coordinated code updates. If the device is part of a cluster solution, verify that the latest level of code is supported for the cluster solution before you update the code.
4. If problem persists, collect Service Data log.
5. Contact Lenovo Support.

- **FQXSPUP4004I: XCC firmware mismatch between nodes/servers [arg1] and [arg2]. Please attempt to flash the XCC firmware to the same level on all nodes/servers.**

A mismatch of XCC firmware has been detected between nodes/servers

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22
CIM Prefix: IMM CIM ID: 0132

User Action:

Complete the following steps until the problem is solved:

1. Reflash XCC/BMC firmware to the latest version on all servers.
2. NOTE: Some cluster solutions require specific code levels or coordinated code updates. If the device is part of a cluster solution, verify that the latest level of code is supported for the cluster solution before you update the code.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPUP4005I: FPGA firmware mismatch between nodes/servers [arg1] and [arg2]. Please attempt to flash the FPGA firmware to the same level on all nodes/servers.**

A mismatch of FPGA firmware has been detected between nodes/servers

Severity: Error
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID: 22

CIM Prefix: IMM CIM ID: 0133

User Action:

Complete the following steps until the problem is solved:

1. Reflash XCC/BMC firmware to the latest version on all servers.
2. NOTE: Some cluster solutions require specific code levels or coordinated code updates. If the device is part of a cluster solution, verify that the latest level of code is supported for the cluster solution before you update the code.
3. If problem persists, collect Service Data log.
4. Contact Lenovo Support.

- **FQXSPWD0000I: Watchdog Timer expired for [WatchdogElementName].**

This message is for the use case when an implementation has detected a Watchdog Timer Expired.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0368

User Action:

Information only; no action is required

- **FQXSPWD0001I: Reboot of system [ComputerSystemElementName] initiated by watchdog [WatchdogElementName].**

This message is for the use case when an implementation has detected a Reboot by a Watchdog occurred.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0370

User Action:

Information only; no action is required

- **FQXSPWD0002I: Powering off system [ComputerSystemElementName] initiated by watchdog [WatchdogElementName].**

This message is for the use case when an implementation has detected a Poweroff by Watchdog has occurred.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0372

User Action:

Information only; no action is required

- **FQXSPWD0003I: Power cycle of system [ComputerSystemElementName] initiated by watchdog [WatchdogElementName].**

This message is for the use case when an implementation has detected a Power Cycle by Watchdog occurred.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0374

User Action:

Information only; no action is required

- **FQXSPWD0004I: Watchdog Timer interrupt occurred for [WatchdogElementName].**

This message is for the use case when an implementation has detected a Watchdog Timer interrupt occurred.

Severity: Info
Serviceable: No
Automatically notify Support: No
Alert Category: System - Other
SNMP Trap ID:
CIM Prefix: PLAT CIM ID: 0376

User Action:

Information only; no action is required

Chapter 3. UEFI events

UEFI error messages can be generated when the server starts up (POST) or while the server is running. UEFI error messages are logged in the Lenovo XClarity Controller event log in the server.

For each event code, the following fields are displayed:

Event identifier

An identifier that uniquely identifies an event.

Event description

The logged message string that appears for an event.

Explanation

Provides additional information to explain why the event occurred.

Severity

An indication of the level of concern for the condition. The severity is abbreviated in the event log to the first character. The following severities can be displayed:

- **Informational.** The event was recorded for audit purposes, usually a user action or a change of states that is normal behavior.
- **Warning.** The event is not as severe as an error, but if possible, the condition should be corrected before it becomes an error. It might also be a condition that requires additional monitoring or maintenance.
- **Error.** The event is a failure or critical condition that impairs service or an expected function.

User Action

Indicates what actions you should perform to solve the event. Perform the steps listed in this section in the order shown until the problem is solved. If you cannot solve the problem after performing all steps, contact Lenovo Support.

UEFI events organized by severity

The following table lists all UEFI events, organized by severity (Information, Error, and Warning).

Table 3. Events organized by severity

Event ID	Message String	Severity
FQXSFMA0001I	DIMM [arg1] Disable has been recovered. [arg2]	Informational
FQXSFMA0002I	The uncorrectable memory error state has been cleared.	Informational
FQXSFMA0006I	[arg1] DIMM [arg2] has been detected, the DIMM serial number is [arg3].	Informational
FQXSFMA0007I	[arg1] DIMM number [arg2] has been replaced. [arg3]	Informational
FQXSFMA0008I	DIMM [arg1] POST memory test failure has been recovered. [arg2]	Informational
FQXSFMA0011I	Memory population change detected. [arg1]	Informational
FQXSFP0020I	The UEFI firmware image capsule signature is invalid.	Informational
FQXSFP0021I	The TPM physical presence state has been cleared.	Informational

Table 3. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSFP0023I	Secure Boot Image Verification Failure has been cleared as no failure in this round boot.	Informational
FQXSFP04034I	TPM Firmware recovery is finished, rebooting system to take effect.	Informational
FQXSFP04038I	TPM Firmware recovery successful.	Informational
FQXSFP04041I	TPM Firmware update is in progress. Please DO NOT power off or reset system.	Informational
FQXSFP04042I	TPM Firmware update is finished, rebooting system to take effect.	Informational
FQXSFP04044I	The current TPM firmware version could not support TPM version toggling.	Informational
FQXSFP04046I	TPM Firmware will be updated from TPM1.2 to TPM2.0.	Informational
FQXSFP04047I	TPM Firmware will be updated from TPM2.0 to TPM1.2.	Informational
FQXSFP04049I	TPM Firmware update successful.	Informational
FQXSFP04059I	User requested to skip freezing lock of AHCI-attached SATA drives. System UEFI accepted the request and will execute prior to OS boot.	Informational
FQXSFP04060I	Skipped freezing lock of AHCI-attached SATA drives.	Informational
FQXSFP04061I	Restored default locking behavior of AHCI-attached SATA drives.	Informational
FQXSFP04080I	Host Power-On password has been changed.	Informational
FQXSFP04081I	Host Power-On password has been cleared.	Informational
FQXSFP04082I	Host Admin password has been changed.	Informational
FQXSFP04083I	Host Admin password has been cleared.	Informational
FQXSFP04084I	Host boot order has been changed.	Informational
FQXSFP04085I	Host WOL boot order has been changed.	Informational
FQXSFSM0007I	The XCC System Event log (SEL) is full.	Informational
FQXSFSR0002I	[arg1] GPT corruption recovered, DiskGUID: [arg2]	Informational
FQXSFD0001G	DRIVER HEALTH PROTOCOL: Missing Configuration. Requires Change Settings From F1.	Warning
FQXSFD0002M	DRIVER HEALTH PROTOCOL: Reports 'Failed' Status Controller.	Warning
FQXSFD0003I	DRIVER HEALTH PROTOCOL: Reports 'Reboot' Required Controller.	Warning
FQXSFD0005M	DRIVER HEALTH PROTOCOL: Disconnect Controller Failed. Requires 'Reboot'.	Warning
FQXSFD0006M	DRIVER HEALTH PROTOCOL: Reports Invalid Health Status Driver.	Warning
FQXSFD0007G	Security Key Lifecycle Manager (SKLM) IPMI Error.	Warning
FQXSFP0021G	Hardware physical presence is in asserted state.	Warning
FQXSFP0022G	The TPM configuration is not locked.	Warning
FQXSFP0023G	Secure Boot Image Verification Failure Warning.	Warning
FQXSFP04033F	TPM Firmware recovery is in progress. Please DO NOT power off or reset system.	Warning

Table 3. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSFPU4035M	TPM Firmware recovery failed. TPM chip may be damaged.	Warning
FQXSFPU4040M	TPM selftest has failed.	Warning
FQXSFPU4043G	TPM Firmware update aborted. System is rebooting...	Warning
FQXSFPU4045G	Physical Presence is not asserted, abort TPM Firmware upgrade.	Warning
FQXSFPU4050G	Failed to update TPM Firmware.	Warning
FQXSFPU4051G	Undefined TPM_TCM_POLICY found	Warning
FQXSFPU4052G	TPM_TCM_POLICY is not locked	Warning
FQXSFPU4053G	System TPM_TCM_POLICY does not match the planar.	Warning
FQXSFPU4054G	TPM/TCM card logical binding has failed.	Warning
FQXSFPW0001L	CMOS has been cleared.	Warning
FQXSFSM0002N	Boot Permission denied by Management Module: System Halted.	Warning
FQXSFSM0003N	Timed Out waiting on boot permission from Management Module: System Halted.	Warning
FQXSFSM0004M	An XCC communication failure has occurred.	Warning
FQXSFSR0001M	[arg1] GPT corruption detected, DiskGUID: [arg2]	Warning
FQXSFSR0003G	The number of boot attempts has been exceeded. No bootable device found.	Warning
FQXSFTTR0001L	An invalid date and time have been detected.	Warning
FQXSFD0004M	DRIVER HEALTH PROTOCOL: Reports 'System Shutdown' Required Controller.	Error
FQXSFIO0011M	A PCIe parity error has occurred on Bus [arg1] Device [arg2] Function [arg3]. The Vendor ID for the device is [arg4] and the Device ID is [arg5]. The Physical slot number is [arg6].	Error
FQXSFIO0012M	A PCIe system error has occurred on Bus [arg1] Device [arg2] Function [arg3]. The Vendor ID for the device is [arg4] and the Device ID is [arg5]. The Physical slot number is [arg6].	Error
FQXSFMA0001M	DIMM [arg1] has been disabled due to an error detected during POST. [arg2]	Error
FQXSFMA0002M	An uncorrectable memory error has been detected on DIMM [arg1] at address [arg2]. [arg3]	Error
FQXSFMA0003K	A memory mismatch has been detected. Please verify that the memory configuration is valid. [arg1]	Error
FQXSFMA0004N	No system memory has been detected. [arg1]	Error
FQXSFMA0005N	Memory is present within the system but could not be configured. Please verify that the memory configuration is valid. [arg1]	Error
FQXSFMA0008M	DIMM [arg1] has failed the POST memory test. [arg2]	Error
FQXSFMA0027K	Invalid memory configuration (Unsupported DIMM Population) detected. Please verify memory configuration is valid.[arg1]	Error

Table 3. Events organized by severity (continued)

Event ID	Message String	Severity
FQXSFMA0029L	The [arg1] PFA Threshold limit has been exceeded on DIMM [arg2]. [arg3]	Error
FQXSFP0016N	A processor within the system has failed the BIST.	Error
FQXSFP0017G	A processor microcode update failed.	Error
FQXSFP0018N	CATERR(IERR) has asserted on processor [arg1].	Error
FQXSFP0019N	An uncorrectable error has been detected on processor [arg1].	Error
FQXSFP0030N	A firmware fault has been detected in the UEFI image.	Error
FQXSFP0031N	The number of POST attempts has reached the value configured in F1 setup. The system has booted with default UEFI settings. User specified settings have been preserved and will be used on subsequent boots unless modified before rebooting.	Error
FQXSFP0034L	The TPM could not be initialized properly.	Error
FQXSFP04056M	TPM/TCM card is changed, need install back the original TCM/TPM card which shipped with the system.	Error
FQXSFSM0008M	Boot permission timeout detected.	Error

List of UEFI events

This section lists all messages that can be sent from UEFI.

- **FQXSFDD0001G: DRIVER HEALTH PROTOCOL: Missing Configuration. Requires Change Settings From F1.**

Severity: Warning

User Action:

Complete the following steps:

1. Go to F1 Setup > System Settings > Settings > Driver Health Status List and find a driver/controller reporting Configuration Required status.
2. Search for the driver menu from System Settings and change settings appropriately.
3. Save settings and restart the system.
4. If the problem persists, collect Service Data logs.
5. Contact Lenovo Support.

- **FQXSFDD0002M: DRIVER HEALTH PROTOCOL: Reports 'Failed' Status Controller.**

Severity: Warning

User Action:

Complete the following steps:

1. Reboot the system.
2. Reflash the adapter firmware.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFDD0003I: DRIVER HEALTH PROTOCOL: Reports 'Reboot' Required Controller.**

Severity: Warning

User Action:

Complete the following steps:

 1. No action required - system will reboot at the end of POST.
 2. Reflash the adapter firmware.
 3. If the problem persists, collect Service Data logs.
 4. Contact Lenovo Support.
- **FQXSFDD0004M: DRIVER HEALTH PROTOCOL: Reports 'System Shutdown' Required Controller.**

Severity: Fatal

User Action:

Complete the following steps:

 1. Reboot the system.
 2. Reflash the adapter firmware.
 3. If the problem persists, collect Service Data logs.
 4. Contact Lenovo Support.
- **FQXSFDD0005M: DRIVER HEALTH PROTOCOL: Disconnect Controller Failed. Requires 'Reboot'.**

Severity: Warning

User Action:

Complete the following steps:

 1. Reboot the system to reconnect the controller.
 2. Reflash the adapter firmware.
 3. If the problem persists, collect Service Data logs.
 4. Contact Lenovo Support.
- **FQXSFDD0006M: DRIVER HEALTH PROTOCOL: Reports Invalid Health Status Driver.**

Severity: Warning

User Action:

Complete the following steps:

 1. Reboot the system.
 2. Reflash the adapter firmware.
 3. If the problem persists, collect Service Data logs.
 4. Contact Lenovo Support.
- **FQXSFDD0007G: Security Key Lifecycle Manager (SKLM) IPMI Error.**

Severity: Warning

User Action:

Complete the following steps:

 1. Check Lenovo support site for an applicable service bulletin or UEFI firmware update that applies to this error.
 2. A/C cycle the system.

3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFI00011M: A PCIe parity error has occurred on Bus [arg1] Device [arg2] Function [arg3]. The Vendor ID for the device is [arg4] and the Device ID is [arg5]. The Physical slot number is [arg6].**

Severity: Error

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable device driver, firmware update, version of service information for this product or other information that applies to this error. Load new device driver and any required firmware updates.
2. If this node and/or any attached cables were recently installed, moved, serviced or upgraded.
 - a. Reseat Adapter and any attached cables.
 - b. Reload Device Driver.
 - c. If device is not recognized, reconfiguring slot to Gen1 or Gen2 may be required. Gen1/Gen2 settings can be configured via F1 Setup -> System Settings -> Devices and I/O Ports ->PCIe Gen1/Gen2/Gen3 Speed Selection, or the OneCLI utility.
 - d. If a PCIe error has also been reported on a second slot within the same node, please ensure steps a, b, and c above are also performed for that adapter before proceeding.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFI00012M: A PCIe system error has occurred on Bus [arg1] Device [arg2] Function [arg3]. The Vendor ID for the device is [arg4] and the Device ID is [arg5]. The Physical slot number is [arg6].**

Severity: Error

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable device driver, firmware update, version of service information for this product or other information that applies to this error. Load new device driver and any required firmware updates.
2. If this device and/or any attached cables were recently installed, moved, serviced or upgraded.
 - a. Reseat Adapter and any attached cables.
 - b. Reload Device Driver.
 - c. If device is not recognized, reconfiguring slot to Gen1 or Gen2 may be required. Gen1/Gen2 settings can be configured via F1 Setup -> System Settings -> Devices and I/O Ports ->PCIe Gen1/Gen2/Gen3 Speed Selection, or the OneCLI utility.
 - d. If a PCIe error has also been reported on a second slot within the same node, please ensure steps a, b, and c above are also performed for that adapter before proceeding.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFMA0001I: DIMM [arg1] Disable has been recovered. [arg2]**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFMA0001M: DIMM [arg1] has been disabled due to an error detected during POST. [arg2]**

Severity: Error

User Action:

Complete the following steps:

1. Reseat the affected DIMM (Note: The event Log might contain a recent FQXSFMA0011I event denoting detected change in DIMM population that could be related to this problem.)
2. Boot to F1 setup and enable the DIMM (For AMD, do not need to enable DIMM in Setup). Reboot the system.
3. Update UEFI firmware to the latest version.
4. If the problem persists, collect Service Data logs.
5. Contact Lenovo Support.

- **FQXSFMA0002I: The uncorrectable memory error state has been cleared.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFMA0002M: An uncorrectable memory error has been detected on DIMM [arg1] at address [arg2]. [arg3]**

Severity: Error

User Action:

Complete the following steps:

1. Reseat the affected DIMM (Note: The event Log might contain a recent FQXSFMA0011I event denoting detected change in DIMM population that could be related to this problem.)
2. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this memory error.
3. If problem recurs collect Service Data log.
4. Contact Lenovo Support.

- **FQXSFMA0003K: A memory mismatch has been detected. Please verify that the memory configuration is valid. [arg1]**

Severity: Error

User Action:

Complete the following steps:

1. Boot to uEFI F1 screen and check if any memory DIMM is disabled. Memory could be disabled due to previous uncorrectable Errors or uEFI memory test/training errors.
2. Verify that the DIMMs are installed in the correct population sequence.
3. Update UEFI firmware to the latest version.
4. If the problem persists, collect Service Data logs
5. Contact Lenovo Support.

- **FQXSFMA0004N: No system memory has been detected. [arg1]**

Severity: Error

User Action:

Complete the following steps:

1. Ensure one or more supported DIMMs are installed in the correct population sequence.
 2. If the system has light-path then check for any lit DIMM-connector LEDs, and if found, reseal those DIMMs. Alternatively (i.e. if light path is not available) the same can be accomplished using XCC GUI.
 3. Swap DIMMs between slots when more than one DIMM is available in the system.
 4. If the DIMMs have been upgraded just prior to the issue than update uEFI using alternate or minimal configuration.
 5. If the problem persists, collect Service Data logs.
 6. Contact Lenovo Support.
- **FQXSFMA0005N: Memory is present within the system but could not be configured. Please verify that the memory configuration is valid. [arg1]**

Severity: Error

User Action:

Complete the following steps:

1. Ensure one or more DIMMs are installed in the server.
 2. Resolve existing memory errors if they are present.
 3. If no memory fault is recorded in the logs and no DIMM connector error LEDs are lit, verify that all DIMM connectors are enabled using the Setup utility or the OneCLI utility.
 4. Reseat all DIMMs ensuring that DIMMs are installed in the correct population sequence, according to the service information for this product.
 5. Clear CMOS memory. Note that all firmware settings will revert to the defaults.
 6. Reflash UEFI firmware.
 7. If the problem persists, collect Service Data logs.
 8. Contact Lenovo Support.
- **FQXSFMA0006I: [arg1] DIMM [arg2] has been detected, the DIMM serial number is [arg3].**

Severity: Info

User Action:

Complete the following steps:

1. If this information event is logged in the XCC event log, the server does not have qualified memory installed.
 2. The memory installed may not be covered under warranty.
 3. Without qualified memory, speeds supported above industry standards will not be enabled.
 4. Please contact your Local Sales Representative or Authorized Business Partner to order qualified memory to replace the unqualified DIMM(s).
 5. After you install qualified memory and power up the server, check to ensure this informational event is not logged again.
- **FQXSFMA0007I: [arg1] DIMM number [arg2] has been replaced. [arg3]**

Severity: Info

User Action:

Complete the following steps:

1. If this information event is logged in the XCC event log, the server does not have qualified memory installed.

2. The memory installed may not be covered under warranty.
3. Without qualified memory, speeds supported above industry standards will not be enabled.
4. Please contact your Local Sales Representative or Authorized Business Partner to order qualified memory to replace the unqualified DIMM(s).
5. After you install qualified memory and power up the server, check to ensure this informational event is not logged again.

- **FQXSFMA0008I: DIMM [arg1] POST memory test failure has been recovered. [arg2]**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFMA0008M: DIMM [arg1] has failed the POST memory test. [arg2]**

Severity: Error

User Action:

Complete the following steps:

1. If the DIMM configuration was changed prior to this failure verify that the DIMMs are installed in the correct population sequence.
2. RESEAT the DIMM that failed POST memory test and the DIMMs on adjacent slots if populated. Boot to F1 setup and enable the DIMM. Reboot the system.
3. If the DIMMs have been upgraded just prior to the issue than update uEFI to the latest version.
4. If the problem persists, collect Service Data logs.
5. Contact Lenovo Support.

- **FQXSFMA0011I: Memory population change detected. [arg1]**

Severity: Info

User Action:

Complete the following steps:

1. If you have added or removed DIMMs to the system, and no additional errors were detected, then please ignore this message.
2. Check system event log for uncorrected DIMM failures and replace those DIMMs.

- **FQXSFMA0027K: Invalid memory configuration (Unsupported DIMM Population) detected. Please verify memory configuration is valid.[arg1]**

Severity: Error

User Action:

Complete the following steps:

1. This event could follow an uncorrectable memory error or failed memory test. Check the log and resolve that event first. DIMMs disabled by other errors or actions could cause this event.
2. Ensure that the DIMM are populated in the correct sequence, according to the service information for this product.
3. If DIMMs are present and properly installed, check for any lit DIMM connector error LEDs, and if found, reseal those DIMMs, then check logs for memory diagnostic codes.
4. Reset UEFI to default settings.
5. If problem persists, update UEFI firmware.

6. If the problem persists, collect Service Data logs.
7. Contact Lenovo Support.

- **FQXSFMA0029L: The [arg1] PFA Threshold limit has been exceeded on DIMM [arg2]. [arg3]**

Severity: Error

User Action:

Complete the following steps:

1. Reseat the affected DIMM (Note: The event Log might contain a recent FQXSFMA0011I event denoting detected change in DIMM population that could be related to this problem.)
2. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this memory error.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFPU0016N: A processor within the system has failed the BIST.**

Severity: Error

User Action:

Complete the following steps:

1. If the processor or firmware was just updated, check the Lenovo support site for an applicable service bulletin or firmware update that applies to this processor error.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFPU0017G: A processor microcode update failed.**

Severity: Error

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this Processor error.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFPU0018N: CATERR(IERR) has asserted on processor [arg1].**

Severity: Error

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or UEFI firmware update that applies to this Processor error.
2. Reboot the system.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFPU0019N: An uncorrectable error has been detected on processor [arg1].**

Severity: Error

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or UEFI firmware update that applies to this error.
2. Reboot the system.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFP0020I: The UEFI firmware image capsule signature is invalid.**

Severity: Info

User Action:

Complete the following steps:

1. Reboot the system. Reflash UEFI image.
2. If error does not persist no additional recovery action is required.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFP0021G: Hardware physical presence is in asserted state.**

Severity: Warning

User Action:

Complete the following steps:

1. Complete any administrative tasks requiring the TPM physical presence switch to be in the "ON" position.
2. Restore the physical presence switch to the "OFF" position and reboot the system.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFP0021I: The TPM physical presence state has been cleared.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP0022G: The TPM configuration is not locked.**

Severity: Warning

User Action:

Complete the following steps:

1. Reboot the system.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFP0023G: Secure Boot Image Verification Failure Warning.**

Severity: Warning

User Action:

Complete the following steps:

1. It's a security warning message when user want to boot from an unauthorized UEFI image or OS while Secure Boot is enabled and Secure Boot Mode is in User Mode. If customer does not want to boot any unauthorized UEFI image or OS, please remove that bootable device.
 2. If customer does want to boot this unauthorized UEFI image or OS, there're two ways to allow system boot from this unauthorized image, the first is to disable Secure Boot, the second is to enroll the unauthorized image into DB(Authorized Signature Database).
 - a. Disable Secure Boot: assert Physical Presence and then change Secure Boot Setting to Disable (in F1 Setup -> System Settings -> Security -> Security Boot Configuration -> Security Boot Setting).
 - b. Enroll the unauthorized UEFI Image. assert the Physical Presence and then change Secure Boot Policy to Custom Policy (in Setup -> System Settings -> Security -> Security Boot Configuration -> Security Boot Policy), then enter into "Security Boot Custom Policy" Menu, press the "Enroll Efi Image" button, select the unauthorized UEFI Image in the popup box. (NOTE: There're two ways to assert Physical Presence. 1) switch Physical Presence Jumper to ON ; 2) If the Physical Presence Policy has been set to enabled (F1 Setup -> System Settings -> Security -> Physical Presence Policy Configuration), user is allowed to assert remote Physical Presence via IPMI tool.)
 3. If the problem persists, collect Service Data logs.
 4. Contact Lenovo Support.
- **FQXSFP0023I: Secure Boot Image Verification Failure has been cleared as no failure in this round boot.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP0030N: A firmware fault has been detected in the UEFI image.**

Severity: Error

User Action:

Complete the following steps:

1. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this error.
2. Reflash UEFI image.
3. Undo recent system changes (settings or devices added). Verify that the system boots. Then, re-install options one at a time to locate the problem.
4. If problem persists, save customer's UEFI configurations, then remove and re-install CMOS battery for 30 seconds to clear CMOS contents. If it boots successfully, then restore system settings.
5. If the problem persists, collect Service Data logs.
6. Contact Lenovo Support.

- **FQXSFP0031N: The number of POST attempts has reached the value configured in F1 setup.The system has booted with default UEFI settings. User specified settings have been preserved and will be used on subsequent boots unless modified before rebooting.**

Severity: Error

User Action:

Complete the following steps:

1. Original UEFI settings are still present. If customer desires to continue using the original settings, select Save Settings.

2. If User did not intentionally trigger the reboots, check logs for probable cause. For example, if there is a battery fault event, follow the steps to resolve that event.
3. Undo recent system changes (settings or devices added). Verify that the system boots. Then, re-install options one at a time to locate the problem.
4. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this error. Update UEFI firmware if applicable.
5. Save customer's UEFI configurations, then remove and re-install CMOS battery for 30 seconds to clear CMOS contents. If it boots successfully, then restore system settings.
6. If the problem persists, collect Service Data logs.
7. Contact Lenovo Support.

- **FQXSFP0034L: The TPM could not be initialized properly.**

Severity: Error

User Action:

Complete the following steps:

1. Reboot the system. Reflash UEFI image.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFP04033F: TPM Firmware recovery is in progress. Please DO NOT power off or reset system.**

Severity: Warning

User Action:

Information only; no action is required.

Note: The system will not respond to power off signal (FQXSFP04034I) while TPM firmware recovery in progress.

- **FQXSFP04034I: TPM Firmware recovery is finished, rebooting system to take effect.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP04035M: TPM Firmware recovery failed. TPM chip may be damaged.**

Severity: Warning

User Action:

Complete the following steps:

1. Reboot the system.
2. If the error recurs TPM related features will not work.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFP04038I: TPM Firmware recovery successful.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4040M: TPM selftest has failed.**
 - Severity: Warning
 - User Action:
 - Complete the following steps:
 1. Reboot the system.
 2. If the error recurs TPM related features will not work.
 3. If the problem persists, collect Service Data logs.
 4. Contact Lenovo Support.
- **FQXSFP4041I: TPM Firmware update is in progress. Please DO NOT power off or reset system.**
 - Severity: Info
 - User Action:
 - Information only; no action is required.
- **FQXSFP4042I: TPM Firmware update is finished, rebooting system to take effect.**
 - Severity: Info
 - User Action:
 - Information only; no action is required.
- **FQXSFP4043G: TPM Firmware update aborted. System is rebooting...**
 - Severity: Warning
 - User Action:
 - Information only; no action is required.
- **FQXSFP4044I: The current TPM firmware version could not support TPM version toggling.**
 - Severity: Info
 - User Action:
 - Information only; no action is required.
- **FQXSFP4045G: Physical Presence is not asserted, abort TPM Firmware upgrade.**
 - Severity: Warning
 - User Action:
 - Information only; no action is required.
- **FQXSFP4046I: TPM Firmware will be updated from TPM1.2 to TPM2.0.**
 - Severity: Info
 - User Action:
 - Information only; no action is required.
- **FQXSFP4047I: TPM Firmware will be updated from TPM2.0 to TPM1.2.**
 - Severity: Info
 - User Action:
 - Information only; no action is required.
- **FQXSFP4049I: TPM Firmware update successful.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4050G: Failed to update TPM Firmware.**

Severity: Warning

User Action:

Information only; no action is required.

- **FQXSFP4051G: Undefined TPM_TCM_POLICY found**

Severity: Warning

User Action:

Complete the following steps:

1. Reboot the system.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFP4052G: TPM_TCM_POLICY is not locked**

Severity: Warning

User Action:

Complete the following steps:

1. Reboot the system.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFP4053G: System TPM_TCM_POLICY does not match the planar.**

Severity: Warning

User Action:

Complete the following steps:

1. Remove any newly added TPM/TCM card from the planar or re-install the original TPM/TCM card that shipped with the system.
2. Reboot the system.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFP4054G: TPM/TCM card logical binding has failed.**

Severity: Warning

User Action:

Complete the following steps:

1. Reboot the system.
2. If the problem persists, collect Service Data logs.
3. Contact Lenovo Support.

- **FQXSFP4056M: TPM/TCM card is changed, need install back the original TCM/TPM card which shipped with the system.**

Severity: Error

User Action:

Complete the following steps:

1. Re-install the original TCM/TPM card that shipped with the system.
2. Reboot the system.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFP4059I: User requested to skip freezing lock of AHCI-attached SATA drives. System UEFI accepted the request and will execute prior to OS boot.**

Severity: Info

User Action:

Complete the following steps:

1. Change SystemOobCustom.SkipAhciFreezeLock from Disable to Enable using OneCLI tool.
2. Reboot the system into OS.

- **FQXSFP4060I: Skipped freezing lock of AHCI-attached SATA drives.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4061I: Restored default locking behavior of AHCI-attached SATA drives.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4080I: Host Power-On password has been changed.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4081I: Host Power-On password has been cleared.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4082I: Host Admin password has been changed.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFP4083I: Host Admin password has been cleared.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFPW0084I: Host boot order has been changed.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFPW0085I: Host WOL boot order has been changed.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFPW0001L: CMOS has been cleared.**

Severity: Warning

User Action:

Complete the following steps:

1. If the CMOS clear was user initiated this event can be safely ignored and no further action is required.
2. If the system was recently installed, moved, or serviced, make sure the battery is properly seated.
3. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this error.
4. If the problem persists, collect Service Data logs.
5. Contact Lenovo Support.

- **FQXSFSM0002N: Boot Permission denied by Management Module: System Halted.**

Severity: Warning

User Action:

Complete the following steps:

1. Check XCC logs.
2. Review power policies and system configuration settings in the XCC GUI.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFSM0003N: Timed Out waiting on boot permission from Management Module: System Halted.**

Severity: Warning

User Action:

Complete the following steps:

1. Check XCC logs.
2. Review power policies and system configuration settings in the XCC GUI.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFSM0004M: An XCC communication failure has occurred.**

Severity: Warning

User Action:

Complete the following steps:

1. AC cycle the system.
2. Make sure XCC and UEFI FW are operating with same compatible level.
3. Check Lenovo support site for an applicable service bulletin or firmware update that applies to this error.
4. Reflash XCC Firmware.
5. If the problem persists, collect Service Data logs.
6. Contact Lenovo Support.

- **FQXSFSM0007I: The XCC System Event log (SEL) is full.**

Severity: Info

User Action:

Complete the following steps:

1. Use BMC Web Interface to clear event logs.
2. If BMC communication is unavailable, use F1 Setup to access System Event Logs Menu and Choose Clear BMC System Event Logs and Restart Server.

- **FQXSFSM0008M: Boot permission timeout detected.**

Severity: Error

User Action:

Complete the following steps:

1. Review XCC logs for communication errors and resolve.
2. AC cycle the system.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

- **FQXSFSR0001M: [arg1] GPT corruption detected, DiskGUID: [arg2]**

Severity: Warning

User Action:

Complete the following steps:

1. Remove all the external drive during POST to avoid this event false triggered.
2. Check the XCC event log, if this event has a follow up recovery event log, means GTP corruption has been recovered successfully, then ignore this event message and do not perform the remaining steps.
3. Back up the data disk.
4. Press F1 Setup->SystemSettings->Recovery->Disk GPT Recovery and set to "Automatic."
5. Save settings and restart the system.
6. Boot to F1 setup; system automatically tries to recover the GPT during the POST.
7. Restart the system.
8. Re-format the LUN or disk and re-install the OS.
9. If the problem persists, collect Service Data logs.
10. Contact Lenovo Support.

- **FQXSFSR0002I: [arg1] GPT corruption recovered, DiskGUID: [arg2]**

Severity: Info

User Action:

Information only; no action is required.

- **FQXSFSR0003G: The number of boot attempts has been exceeded. No bootable device found.**

Severity: Warning

User Action:

Complete the following steps:

1. Remove AC power from the system.
2. Connect at least one bootable device to the system.
3. Connect AC power to the system.
4. Power on system and retry.
5. If the problem persists, collect Service Data logs.
6. Contact Lenovo Support.

- **FQXSFTTR0001L: An invalid date and time have been detected.**

Severity: Warning

User Action:

Complete the following steps:

1. Check the XCC event logs. This event should immediately precede an FQXSFPW0001L error. Resolve that event or any other battery related errors.
2. Use F1 Setup to reset date and time.
3. If the problem persists, collect Service Data logs.
4. Contact Lenovo Support.

Chapter 4. XClarity Provisioning Manager events

The following events can be generated by the Lenovo XClarity Provisioning Manager.

For each event code, the following fields are displayed:

Event identifier

An identifier that uniquely identifies an event.

Event description

The logged message string that appears for an event.

Explanation

Provides additional information to explain why the event occurred.

Severity

An indication of the level of concern for the condition. The severity is abbreviated in the event log to the first character. The following severities can be displayed:

- **Informational.** The event was recorded for audit purposes, usually a user action or a change of states that is normal behavior.
- **Warning.** The event is not as severe as an error, but if possible, the condition should be corrected before it becomes an error. It might also be a condition that requires additional monitoring or maintenance.
- **Error.** The event is a failure or critical condition that impairs service or an expected function.

User Action

Indicates what actions you should perform to solve the event. Perform the steps listed in this section in the order shown until the problem is solved. If you cannot solve the problem after performing all steps, contact Lenovo Support.

LXPM events organized by severity

The following table lists all LXPM events, organized by severity (Information, Error, and Warning).

Table 4. Events organized by severity

Event ID	Message String	Severity
FQXPMCL0005I	Start to install OS.	Informational
FQXPMCL0006I	Export raid config successfully.	Informational
FQXPMCL0007I	Import raid config successfully.	Informational
FQXPMCL0008I	Export uefi settings successfully.	Informational
FQXPMCL0009I	Import uefi settings successfully.	Informational
FQXPMCL0010I	Export bmc settings successfully.	Informational
FQXPMCL0011I	Import bmc settings successfully.	Informational
FQXPMEM0002I	LXPM firmware image found. Starting LXPM	Informational
FQXPMEM0003I	LXPM has exited. Control returned to UEFI	Informational

Table 4. Events organized by severity (continued)

Event ID	Message String	Severity
FQXPMEM0004I	Launching diagnostic program	Informational
FQXPMEM0005I	boot diagnostic program success	Informational
FQXPMER0002I	Clearing RAID configuration and internal storage	Informational
FQXPMER0003I	RAID configuration cleared successfully	Informational
FQXPMER0004I	Internal storage drives erased successfully	Informational
FQXPMER0005I	All system logs cleared successfully	Informational
FQXPMER0006I	UEFI factory default settings loaded successfully	Informational
FQXPMER0007I	BMC factory default settings loaded successfully	Informational
FQXPMNM0002I	Set BMC network parameters to new values.	Informational
FQXPMOS0028I	[arg1] OS installed	Informational
FQXPMSR0012I	Change disk drives' state successfully.	Informational
FQXPMSR0022I	Create new virtual disk successfully.	Informational
FQXPMSR0032I	Removed existing virtual disk successfully.	Informational
FQXPMUP0101I	Start to update LXPM	Informational
FQXPMUP0102I	Start to update window driver	Informational
FQXPMUP0103I	Start to update linux driver	Informational
FQXPMUP0104I	Start to update UEFI	Informational
FQXPMUP0105I	Start to update BMC	Informational
FQXPMUP0106I	Successfully updated the firmware	Informational
FQXPMVD0003I	Update VPD data successfully.	Informational
FQXPMCL0001K	Bootx64.efi is not found. Failed to Boot OS.	Warning
FQXPMCL0002K	Failed to read Deployment Manager Signature from USB.	Warning
FQXPMCL0003K	BMC communication failed: DRIVER Mount Failure.	Warning
FQXPMCL0004K	BMC communication succeeded. Volume Name MISMATCHED.	Warning
FQXPMCL0005K	Current System Boot Mode is Legacy. OS Clone only support UEFI Mode.	Warning
FQXPMCL0006K	Failed to export raid config.	Warning
FQXPMCL0007K	Failed to import raid config.	Warning
FQXPMCL0008K	Failed to export uefi settings.	Warning
FQXPMCL0009K	Failed to import uefi settings.	Warning
FQXPMCL0010K	Failed to export bmc settings.	Warning
FQXPMCL0011K	Failed import bmc settings.	Warning
FQXPMNM0001G	Failed to set new BMC network parameters.	Warning
FQXPMOS0001K	Bootx64.efi is not found. Failed to Boot OS.	Warning

Table 4. Events organized by severity (continued)

Event ID	Message String	Severity
FQXPMOS0002K	Failed to read Deployment Manager Signature from USB.	Warning
FQXPMOS0003K	Failed to copy Windows boot files to target	Warning
FQXPMOS0004K	BMC Communication Failed: EMMC2USB Mount Failure.	Warning
FQXPMOS0005K	BMC communication failed: DRIVER Mount Failure.	Warning
FQXPMOS0006K	BMC communication succeeded. Volume Name MISMATCHED.	Warning
FQXPMOS0007K	Failed to read License RTF file.	Warning
FQXPMOS0008K	Please make sure the Ethernet cable has been plugged into your computer and your network settings are correct.	Warning
FQXPMOS0009K	Current System Boot Mode is Legacy. LXPM OS installation only support UEFI Mode.	Warning
FQXPMSR0001K	Found unsupported RAID adapter.	Warning
FQXPMSR0011K	Failed to change disk drives' state.	Warning
FQXPMSR0021L	Failed to create new virtual disk.	Warning
FQXPMSR0031L	Failed to remove existing virtual disk	Warning
FQXPMUP0001K	The system configuration does not meet the prerequisite	Warning
FQXPMUP0002K	The selected packages are not compatible	Warning
FQXPMUP0003K	Unable to obtain the minimum level of UEFI	Warning
FQXPMUP0004K	Unable to obtain the installed version of UEFI	Warning
FQXPMUP0005K	Unable to obtain the installed version of BMC	Warning
FQXPMUP0006K	Unable to obtain the installed version of LXPM	Warning
FQXPMUP0007K	Unable to obtain the installed version of linux driver	Warning
FQXPMUP0008K	Unable to obtain the installed version of windows driver	Warning
FQXPMVD0001H	Failed to get VPD data.	Warning
FQXPMVD0002H	Failed to update the VPD data.	Warning
FQXPMVD0011K	Failed to get the TPM/TPM card/TCM policy status	Warning
FQXPMVD0012K	Failed to set the TPM/TPM card/TCM policy	Warning
FQXPMEM0001M	Unable to locate LXPM firmware image	Error
FQXPMEM0006M	Unable to locate diagnostic firmware image	Error
FQXPMEM0007M	Diagnostic image cannot be launched as "Console Redirection" is enabled	Error
FQXPMEM0008M	Diagnostic image cannot be launched as the image may be corrupt	Error
FQXPMER0002M	Failed to clear RAID configuration	Error
FQXPMER0003M	Failed to erase internal storage drives	Error
FQXPMER0004M	Failed to clear system logs	Error
FQXPMER0005M	Failed to load UEFI factory default settings	Error

Table 4. Events organized by severity (continued)

Event ID	Message String	Severity
FQXPMER0006M	Failed to load XCC factory default settings	Error
FQXPMSD0001M	HDD Test was interrupted by the host with a hardware or software reset	Error
FQXPMSD0002M	A fatal error or unknown test error occurred while the device was executing its self-test	Error
FQXPMSD0003M	self-test completed having a test element that failed and the test element that failed is not known.	Error
FQXPMSD0004M	self-test completed having the electrical element of the test failed.	Error
FQXPMSD0005M	self-test completed having the servo (and/or seek) test element of the test failed.	Error
FQXPMSD0006M	self-test completed having the read element of the test failed.	Error
FQXPMSD0007M	Hard Drive(s) not found	Error
FQXPMSD0008M	UEFI is not ready for LXPM to send command to test hard drive.	Error
FQXPMSD0009M	Device error is occurred when LXPM send command to test hard drive.	Error
FQXPMSD0010M	uEFI is timeout while LXPM send command to test hard drive.	Error
FQXPMSD0011M	The hard drive is not supported by uEFI while LXPM send command to test hard drive.	Error
FQXPMUP0201M	BMC communication failed: EMMC2USB mount failure. Failed to update the firmware	Error
FQXPMUP0202M	Transfer the update package error. Failed to update the firmware	Error
FQXPMUP0203M	BMC communication failed: EMMC2USB unmount failure. Failed to update the firmware	Error
FQXPMUP0204M	BMC communication failed: Execute the update cmd failure. Failed to update the firmware	Error
FQXPMUP0205M	BMC communication failed: Get the update status failure. Failed to update the firmware	Error
FQXPMUP0206M	The level of the update package is too old. Failed to update the firmware.	Error
FQXPMUP0207M	The update package is invalid. Failed to update the firmware.	Error
FQXPMUP0208M	Failed to execute reboot BMC command	Error

List of XClarity Provisioning Manager events

This section lists all messages that can be sent from the Lenovo XClarity Provisioning Manager.

- **FQXPMCL0001K: Bootx64.efi is not found. Failed to Boot OS.**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. If the problem persists, reflash BMC firmware.

3. Reboot system and retry OS booting.
4. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

5. If the problem persists, please contact technical support.

- **FQXPMCL0002K: Failed to read Deployment Manager Signature from USB.**

Severity: Warning

User Action:

1. Ensure proper operation of the virtual USB connection.
2. Restart BMC via BMC setting under uEFI setup on LXPM left panel. Restart BMC via supported method and reboot the system.
3. Reflash BMC firmware.
4. Clone the image over and retry the operation.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMCL0003K: BMC communication failed: DRIVER Mount Failure.**

Severity: Warning

User Action:

1. Ensure proper operation of the virtual USB connection.
2. Restart BMC via supported method and reboot the system.
3. Reflash BMC firmware.
4. Clone the image over and retry the operation.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMCL0004K: BMC communication succeeded. Volume Name MISMATCHED.**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Clone the image over and retry the operation.
4. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

5. If the problem persists, please contact technical support.

- **FQXPMCL0005I: Start to install OS.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0005K: Current System Boot Mode is Legacy. OS Clone only support UEFI Mode.**

Severity: Warning

User Action:

1. Change Boot mode to UEFI mode (UEFI Setup -> Boot Manager -> Boot Modes -> System Boot Mode and select UEFI Mode.)
2. Clone the image over and retry the operation.

- **FQXPMCL0006I: Export raid config successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0006K: Failed to export raid config.**

Severity: Warning

User Action:

1. Check the following Lenovo support site for information on supported RAID adapters. <http://www.lenovo.com/us/en/serverproven/index.shtml>
2. Ensure RAID adapter, LXPM, and UEFI firmware are at the latest levels.
3. Ensure the state of the RAID adapter and disk drives are normal.
4. Verify proper physical connection of the disk drive, SAS expander (if applicable) and RAID adapter.
5. Reboot the machine and retry the export of the RAID configuration.
6. If the problem persists, please contact technical support.

- **FQXPMCL0007I: Import raid config successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0007K: Failed to import raid config.**

Severity: Warning

User Action:

1. Check the following Lenovo support site for information on supported RAID adapters. <http://www.lenovo.com/us/en/serverproven/index.shtml>
2. Ensure RAID adapter, LXPM, and UEFI firmware are at the latest levels.
3. Ensure the state of RAID adapter and disk drives are healthy.
4. Ensure good physical connection between the disk drives and RAID adapter.
5. Ensure the platform and RAID config is identical to original configuration.

6. Reboot the machine and retry the import of the RAID configuration.
7. If the problem persists, please contact technical support.

- **FQXPMCL0008I: Export uefi settings successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0008K: Failed to export uefi settings.**

Severity: Warning

User Action:

1. Ensure proper connection to USB/network drive and retry to export uEFI setting.
2. Reboot and try the uEFI setting export again.
3. Reflash UEFI firmware.
4. If the problem persists, please contact technical support.

- **FQXPMCL0009I: Import uefi settings successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0009K: Failed to import uefi settings.**

Severity: Warning

User Action:

1. Ensure proper connection to USB/network drive and retry the uEFI setting import.
2. Ensure that same system model type to import the uEFI setting and UEFI version should be the same.
3. Reboot and try to import a new clone of the UEFI settings.
4. Reflash UEFI firmware.
5. If the problem persists, please contact technical support.

- **FQXPMCL0010I: Export bmc settings successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0010K: Failed to export bmc settings.**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Perform AC reset.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. Retry the export of BMC setting.
4. If the problem persists, please contact technical support.

- **FQXPMCL0011I: Import bmc settings successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMCL0011K: Failed import bmc settings.**

Severity: Warning

User Action:

1. Ensure BMC version is the same between source and target.
2. Restart BMC via supported method and reboot the system.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. Retry the import of BMC setting.
5. If the problem persists, please contact technical support.

- **FQXPMEM0001M: Unable to locate LXPM firmware image**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash the LXPM.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMEM0002I: LXPM firmware image found. Starting LXPM**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMEM0003I: LXPM has exited. Control returned to UEFI**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMEM0004I: Launching diagnostic program**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMEM0005I: boot diagnostic program success**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMEM0006M: Unable to locate diagnostic firmware image**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. If the problem persists, please contact technical support.

- **FQXPMEM0007M: Diagnostic image cannot be launched as "Console Redirection" is enabled**

Severity: Error

User Action:

1. Disable "Configure Console Redirection" in UEFI Setup by following below steps: - Go to F1 Setup -> System Settings -> Devices and I/O Ports-> Console Redirection Settings -> - Select "Console Redirection" - Change the setting to "Disable" and save - Next reboot the system.
2. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. If the problem persists, please contact technical support.

- **FQXPMEM0008M: Diagnostic image cannot be launched as the image may be corrupt**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. Reflash the LXPM.
4. If the problem persists, please contact technical support.

- **FQXPMER0002I: Clearing RAID configuration and internal storage**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMER0002M: Failed to clear RAID configuration**

Severity: Error

User Action:

1. Restart the system and retry the operation again.
2. If the problem persists, contact technical support.

- **FQXPMER0003I: RAID configuration cleared successfully**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMER0003M: Failed to erase internal storage drives**

Severity: Error

User Action:

1. Ensure the proper connection of hard drives, backplane, and related cables.
2. Check if security function is enabled for the hard disk drives, if yes, disable that and retry the operation.
3. Ensure device firmware is at the latest level.
4. Restart the system and retry the operation again.
5. If the problem persists, contact technical support.

- **FQXPMER0004I: Internal storage drives erased successfully**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMER0004M: Failed to clear system logs**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Retry this operation again.
3. If the problem persists, contact technical support.

- **FQXPMER0005I: All system logs cleared successfully**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMER0005M: Failed to load UEFI factory default settings**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Retry this operation again.

3. If the problem persists, contact technical support.

- **FQXPMER0006I: UEFI factory default settings loaded successfully**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMER0006M: Failed to load XCC factory default settings**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Retry this operation again.
3. If the problem persists, perform AC power cycle. (wait several seconds between AC power is off and on)
4. Retry this operation again.
5. If the problem persists, contact technical support.

- **FQXPMER0007I: BMC factory default settings loaded successfully**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMNM0001G: Failed to set new BMC network parameters.**

Severity: Warning

User Action:

1. Ensure input parameters are valid.
2. Wait for one minute and retry the setting.
3. Restart BMC via supported method and reboot the system.
4. Retry the setting change.
5. Use UEFI setup to change parameters (optional).

- **FQXPMNM0002I: Set BMC network parameters to new values.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMOS0001K: Bootx64.efi is not found. Failed to Boot OS.**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Reboot system and retry OS booting.
4. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

5. If the problem persists, please contact technical support.

- **FQXPMOS0002K: Failed to read Deployment Manager Signature from USB.**

Severity: Warning

User Action:

1. Ensure proper operation of the virtual USB connection.
2. Restart BMC via supported method and reboot the system.
3. If the problem persists, reflash BMC firmware.
4. Retry OS deployment.
5. If the problem persists, perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMOS0003K: Failed to copy Windows boot files to target**

Severity: Warning

User Action:

1. Ensure proper operation of the virtual USB connection.
2. Restart BMC via supported method and reboot the system.
3. Reflash BMC firmware.
4. Retry OS deployment.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMOS0004K: BMC Communication Failed: EMMC2USB Mount Failure.**

Severity: Warning

User Action:

1. Ensure proper operation of the virtual USB connection.
2. Restart BMC via supported method and reboot the system.
3. Reflash BMC firmware.
4. Retry OS deployment.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMOS0005K: BMC communication failed: DRIVER Mount Failure.**

Severity: Warning

User Action:

1. Ensure proper operation of the virtual USB connection.
2. Restart BMC via supported method and reboot the system.
3. Reflash BMC firmware.
4. Retry OS deployment.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMOS0006K: BMC communication succeeded. Volume Name MISMATCHED.**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. If the problem persists, reflash BMC firmware.
3. Retry OS deployment.
4. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

5. If the problem persists, please contact technical support.

- **FQXPMOS0007K: Failed to read License RTF file.**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. If the problem persists, reflash BMC firmware.
3. Use another OS media (USB DVD or USB key).
4. Retry OS deployment.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, please contact technical support.

- **FQXPMOS0008K: Please make sure the Ethernet cable has been plugged into your computer and your network settings are correct.**

Severity: Warning

User Action:

1. Ensure proper operation of SMB/CIFS and NFS communications (make sure the Ethernet cable has been plugged and network settings are correct.).
2. Make sure the OS version and folder path are correct.
3. Retry CIFS and NFS installation.
4. If the problem persists, please contact technical support.

- **FQXPMOS0009K: Current System Boot Mode is Legacy. LXPM OS installation only support UEFI Mode.**

Severity: Warning

User Action:

1. Change boot mode to UEFI mode
2. Retry OS deployment.

- **FQXPMOS0028I: [arg1] OS installed**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMSD0001M: HDD Test was interrupted by the host with a hardware or software reset**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Retry the test.
4. If the problem persists, please contact technical support.

- **FQXPMSD0002M: A fatal error or unknown test error occurred while the device was executing its self-test**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Retry the test.
4. If the problem persists, please contact technical support.

- **FQXPMSD0003M: self-test completed having a test element that failed and the test element that failed is not known.**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Retry the test.
4. If the problem persists, please contact technical support.

- **FQXPMSD0004M: self-test completed having the electrical element of the test failed.**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Retry the test.
4. If the problem persists, please contact technical support.

- **FQXPMSD0005M: self-test completed having the servo (and/or seek) test element of the test failed.**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Retry the test.
4. If the problem persists, please contact technical support.

- **FQXPMSD0006M: self-test completed having the read element of the test failed.**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Retry the test.
4. If the problem persists, please contact technical support.

- **FQXPMSD0007M: Hard Drive(s) not found**

Severity: Error

User Action:

1. Remove A/C from the server and reseal all drives, backplanes, RAID adapters, expanders (if any), and cables.
2. Ensure device firmware is at the latest level.
3. Verify that the same Error is present in BMC or OneCLI inventory log.
4. Retry the test.
5. If the problem persists, please contact technical support.

- **FQXPMSD0008M: UEFI is not ready for LXPM to send command to test hard drive.**

Severity: Error

User Action:

1. Reboot system and run the test again.
2. If this message is still reported, please run the latest version of SMART tool on OS which is open source tool and could be downloaded from website to check hard drive status.
3. If the problem persists, please contact technical support.

- **FQXPMSD0009M: Device error is occurred when LXPM send command to test hard drive.**

Severity: Error

User Action:

1. Reboot system and run the test again later.
2. If this message is still reported, please run the latest version of SMART tool on OS which is open source tool and could be downloaded from website to check hard drive status.
3. If the problem persists, please contact technical support.

- **FQXPMSD0010M: uEFI is timeout while LXPM send command to test hard drive.**

Severity: Error

User Action:

1. Reboot system and run the test again later.
2. If this message is still reported, please run the latest version of SMART tool on OS which is open source tool and could be downloaded from website to check hard drive status.
3. If the problem persists, please contact technical support.

- **FQXPMSD0011M: The hard drive is not supported by uEFI while LXPM send command to test hard drive.**

Severity: Error

User Action:

1. Please check hard drive specification to see if the hard drive support ATA self-test feature.
2. If the problem persists, please contact technical support.

- **FQXPMSR0001K: Found unsupported RAID adapter.**

Severity: Warning

User Action:

1. Check the following Lenovo support site for information on supported RAID adapters. <http://www.lenovo.com/us/en/serverproven/index.shtml>
2. Ensure RAID adapter, LXPM, and UEFI firmware are at the latest levels.
3. If the problem persists, please contact technical support.

- **FQXPMSR0011K: Failed to change disk drives' state.**

Severity: Warning

User Action:

1. Ensure LXPM and RAID adapter firmware are at the latest levels.
2. Ensure the state of the RAID adapter and disk drives are both healthy.
3. Verify proper physical connection of the disk drive, SAS expander (if applicable) and RAID adapter.
4. Ensure the operation to the special drive is legal or logical. (For example, you cannot change Unconfigured BAD to Online status)
5. Reboot the machine and retry to change disk drives' state.
6. If the problem persists, please contact technical support.

- **FQXPMSR0012I: Change disk drives' state successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMSR0021L: Failed to create new virtual disk.**

Severity: Warning

User Action:

1. Ensure LXPM and RAID adapter firmware are at the latest levels.
2. Ensure the state of RAID adapter and disk drives are both healthy.
3. Verify proper physical connection of the disk drive, SAS expander (if applicable)and RAID adapter.
4. Ensure the drive status is correct (Unconfigured Good).
5. Reboot the machine and retry to create new virtual disk.
6. If the problem persists, please contact technical support.

- **FQXPMSR0022I: Create new virtual disk successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMSR0031L: Failed to remove existing virtual disk**

Severity: Warning

User Action:

1. Ensure LXPM and RAID adapter firmware are at the latest levels.
2. Ensure the state of RAID adapter and disk drives are both healthy.
3. Verify proper physical connection of the disk drive, SAS expander (if applicable)and RAID adapter.
4. Reboot the machine and retry to remove the existing virtual disk.
5. If the problem persists, please contact technical support.

- **FQXPMSR0032I: Removed existing virtual disk successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0001K: The system configuration does not meet the prerequisite**

Severity: Warning

User Action:

1. Follow prompts to update the firmware and retry the update.
2. If the problem persists, please contact technical support.

- **FQXPMUP0002K: The selected packages are not compatible**

Severity: Warning

User Action:

1. Follow prompts to update each individual firmware package.

2. If the problem persists, please contact technical support.

- **FQXPMUP0003K: Unable to obtain the minimum level of UEFI**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMUP0004K: Unable to obtain the installed version of UEFI**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMUP0005K: Unable to obtain the installed version of BMC**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMUP0006K: Unable to obtain the installed version of LXPM**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMUP0007K: Unable to obtain the installed version of linux driver**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. If the problem persists, please contact technical support.

- **FQXPMUP0008K: Unable to obtain the installed version of windows driver**

Severity: Warning

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMUP0101I: Start to update LXPM**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0102I: Start to update window driver**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0103I: Start to update linux driver**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0104I: Start to update UEFI**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0105I: Start to update BMC**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0106I: Successfully updated the firmware**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMUP0201M: BMC communication failed: EMMC2USB mount failure. Failed to update the firmware**

Severity: Error

User Action:

1. Restart BMC via supported method and BMC setting via uEFI setup or "Restart Management Controller" in BMC web UI. Then, reboot the system.
2. If the problem persists, reflash the BMC firmware.
3. If the problem persists, perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
5. If the problem persists, please contact technical support.

- **FQXPMUP0202M: Transfer the update package error. Failed to update the firmware**

Severity: Error

User Action:

1. Ensure the update package is not corrupt undamaged and then retry the update.
2. Ensure proper connection to USB/network drive and retry the update.
3. Restart BMC via supported method and BMC setting via uEFI setup or "Restart Management Controller" in BMC web UI. Then, reboot the system.
4. If the problem persists, reflash the BMC firmware.
5. If the problem persists, perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
7. If the problem persists, please contact technical support.

- **FQXPMUP0203M: BMC communication failed: EMMC2USB unmount failure. Failed to update the firmware**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash the BMC firmware
3. If the problem persists, perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
5. If the problem persists, please contact technical support.

- **FQXPMUP0204M: BMC communication failed: Execute the update cmd failure. Failed to update the firmware**

Severity: Error

User Action:

1. Restart BMC via supported method.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
5. If the problem persists, please contact technical support.

- **FQXPMUP0205M: BMC communication failed: Get the update status failure. Failed to update the firmware**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
5. If the problem persists, please contact technical support.

- **FQXPMUP0206M: The level of the update package is too old. Failed to update the firmware.**

Severity: Error

User Action:

1. Follow prompts to select a newer version of the update package and retry the update.
2. Restart BMC via supported method and reboot the system.
3. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
5. If the problem persists, please contact technical support.

- **FQXPMUP0207M: The update package is invalid. Failed to update the firmware.**

Severity: Error

User Action:

1. Ensure the update package is not corrupt and retry the update.
2. Ensure proper connection to USB/network drive and retry the update.
3. Restart BMC via supported method and BMC setting via uEFI setup or "Restart Management Controller" in BMC web UI. Then, reboot the system.
4. Reflash the BMC firmware.
5. Perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

6. If the problem persists, try a different Lenovo tool to perform the update (eg. XClarity Administrator, XClarity Controller, or XClarity Essential OneCLI).
7. If the problem persists, please contact technical support.

- **FQXPMUP0208M: Failed to execute reboot BMC command**

Severity: Error

User Action:

1. Restart BMC via supported method and reboot the system.
2. Reflash BMC firmware.
3. If the problem persists, perform AC reset or virtual reseal.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

4. If the problem persists, please contact technical support.

- **FQXPMVD0001H: Failed to get VPD data.**

Severity: Warning

User Action:

1. Press "Back" button and press "Update VPD..." button again.
2. Perform AC reset or virtual reseal if step 1 failed.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. If the problem persists, please contact technical support.

- **FQXPMVD0002H: Failed to update the VPD data.**

Severity: Warning

User Action:

1. Press "Update" button on VPD update page.
2. Perform AC reset or virtual reseal if step 1 failed.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. If the problem persists, please contact technical support.

- **FQXPMVD0003I: Update VPD data successfully.**

Severity: Info

User Action:

Information only; no action is required.

- **FQXPMVD0011K: Failed to get the TPM/TPM card/TCM policy status**

Severity: Warning

User Action:

1. Press "Back" button and press "Update VPD..." button again.
2. Perform AC reset or virtual reseal if step 1 failed.

Note: When performing AC reset, after powering off AC, wait several seconds before powering on AC. After AC power is restored, power on the host system.

3. If the problem persists, please contact technical support.

- **FQXPMVD0012K: Failed to set the TPM/TPM card/TCM policy**

Severity: Warning

User Action:

1. Press "Apply" button on VPD update page.
2. Reboot the system if step 1 failed.
3. If the problem persists, please contact technical support.

Appendix A. Getting help and technical assistance

If you need help, service, or technical assistance or just want more information about Lenovo products, you will find a wide variety of sources available from Lenovo to assist you.

On the World Wide Web, up-to-date information about Lenovo systems, optional devices, services, and support are available at:

<http://datacentersupport.lenovo.com>

Note: IBM is Lenovo's preferred service provider for ThinkSystem.

Before you call

Before you call, there are several steps that you can take to try and solve the problem yourself. If you decide that you do need to call for assistance, gather the information that will be needed by the service technician to more quickly resolve your problem.

Attempt to resolve the problem yourself

You can solve many problems without outside assistance by following the troubleshooting procedures that Lenovo provides in the online help or in the Lenovo product documentation. The Lenovo product documentation also describes the diagnostic tests that you can perform. The documentation for most systems, operating systems, and programs contains troubleshooting procedures and explanations of error messages and error codes. If you suspect a software problem, see the documentation for the operating system or program.

You can find the product documentation for your ThinkSystem products at the following location:

<http://thinksystem.lenovofiles.com/help/index.jsp>

You can take these steps to try to solve the problem yourself:

- Check all cables to make sure that they are connected.
- Check the power switches to make sure that the system and any optional devices are turned on.
- Check for updated software, firmware, and operating-system device drivers for your Lenovo product. The Lenovo Warranty terms and conditions state that you, the owner of the Lenovo product, are responsible for maintaining and updating all software and firmware for the product (unless it is covered by an additional maintenance contract). Your service technician will request that you upgrade your software and firmware if the problem has a documented solution within a software upgrade.
- If you have installed new hardware or software in your environment, check <https://static.lenovo.com/us/en/serverproven/index.shtml> to make sure that the hardware and software is supported by your product.
- Go to <http://datacentersupport.lenovo.com> and check for information to help you solve the problem.
 - Check the Lenovo forums at https://forums.lenovo.com/t5/Datacenter-Systems/ct-p/sv_eq to see if someone else has encountered a similar problem.

You can solve many problems without outside assistance by following the troubleshooting procedures that Lenovo provides in the online help or in the Lenovo product documentation. The Lenovo product documentation also describes the diagnostic tests that you can perform. The documentation for most systems, operating systems, and programs contains troubleshooting procedures and explanations of error messages and error codes. If you suspect a software problem, see the documentation for the operating system or program.

Gathering information needed to call Support

If you believe that you require warranty service for your Lenovo product, the service technicians will be able to assist you more efficiently if you prepare before you call. You can also see <http://datacentersupport.lenovo.com/warrantylookup> for more information about your product warranty.

Gather the following information to provide to the service technician. This data will help the service technician quickly provide a solution to your problem and ensure that you receive the level of service for which you might have contracted.

- Hardware and Software Maintenance agreement contract numbers, if applicable
- Machine type number (Lenovo 4-digit machine identifier)
- Model number
- Serial number
- Current system UEFI and firmware levels
- Other pertinent information such as error messages and logs

As an alternative to calling Lenovo Support, you can go to <https://support.lenovo.com/servicerequest> to submit an Electronic Service Request. Submitting an Electronic Service Request will start the process of determining a solution to your problem by making the pertinent information available to the service technicians. The Lenovo service technicians can start working on your solution as soon as you have completed and submitted an Electronic Service Request.

Collecting service data

To clearly identify the root cause of a server issue or at the request of Lenovo Support, you might need collect service data that can be used for further analysis. Service data includes information such as event logs and hardware inventory.

Service data can be collected through the following tools:

- **Lenovo XClarity Provisioning Manager**

Use the Collect Service Data function of Lenovo XClarity Provisioning Manager to collect system service data. You can collect existing system log data or run a new diagnostic to collect new data.

- **Lenovo XClarity Controller**

You can use the Lenovo XClarity Controller web interface or the CLI to collect service data for the server. The file can be saved and sent to Lenovo Support.

- For more information about using the web interface to collect service data, see the “Downloading service data” section in the XCC documentation version compatible with your server at https://sysmgt.lenovofiles.com/help/topic/lxcc_frontend/lxcc_overview.html.
- For more information about using the CLI to collect service data, see the “ffdc command” section in the XCC documentation version compatible with your server at https://sysmgt.lenovofiles.com/help/topic/lxcc_frontend/lxcc_overview.html.

- **Lenovo XClarity Administrator**

Lenovo XClarity Administrator can be set up to collect and send diagnostic files automatically to Lenovo Support when certain serviceable events occur in Lenovo XClarity Administrator and the managed endpoints. You can choose to send diagnostic files to Lenovo Support using Call Home or to another service provider using SFTP. You can also manually collect diagnostic files, open a problem record, and send diagnostic files to the Lenovo Support Center.

You can find more information about setting up automatic problem notification within the Lenovo XClarity Administrator at http://sysmgt.lenovofiles.com/help/topic/com.lenovo.lxca.doc/admin_setupcallhome.html.

- **Lenovo XClarity Essentials OneCLI**

Lenovo XClarity Essentials OneCLI has inventory application to collect service data. It can run both in-band and out-of-band. When running in-band within the host operating system on the server, OneCLI can collect information about the operating system, such as the operating system event log, in addition to the hardware service data.

To obtain service data, you can run the **getinfor** command. For more information about running the **getinfor**, see http://sysmgt.lenovofiles.com/help/topic/toolstr_cli_lenovo/onecli_r_getinfor_command.html.

Contacting Support

You can contact Support to obtain help for your issue.

You can receive hardware service through a Lenovo Authorized Service Provider. To locate a service provider authorized by Lenovo to provide warranty service, go to <https://datacentersupport.lenovo.com/serviceprovider> and use filter searching for different countries. For Lenovo support telephone numbers, see <https://datacentersupport.lenovo.com/supportphonenumberlist> for your region support details.

Index

C

collecting service data 178
creating a personalized support web page 177
custom support web page 177

E

error codes and messages
 UEFI 133, 153
error messages,
 UEFI 133, 153
events, UEFI 133, 153

G

Getting help 177

H

hardware service and support telephone numbers 179

help 177

S

service and support
 before you call 177
 hardware 179
 software 179
service data 178
software service and support telephone numbers 179
support web page, custom 177

T

telephone numbers 179

U

UEFI error messages 133, 153
UEFI events 133, 153

Lenovo