

Product Line
PA-RACK

Type
RM-PA-T6

Supported Models **PALO ALTO NETWORKS
PA410**

DIMENSIONS 1.3U/2U

COLOR RAL 9005 Black

PRODUCT DIMENSIONS 57 x 482 x 217 mm

(height x width x depth) 2.24 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Remove the four rubber feet from the bottom of the Palo Alto appliance.
2. Remove the bolts situated on the bottom of the appliance.
3. Place your Palo Alto device on the rack with the connectors facing the front.
4. Fix the appliance with the four provided bolts from the bottom of the rack.
5. To install the power supply, put the zip ties through the designated holes, place the power supply on the rack between the zip ties and tighten firmly.
6. Secure the cable with the zip tie on the rack (detail 1) and tie the excess length of the power cable down with a zip tie.
7. Place your PA-Rack in your 19 inch rack.
8. Place the Rackmount.IT front plate **BELOW** the rack mount kit. Together they are 2U high.



Detail 1

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	PA-Rack
1	Rackmount.IT front plate
3	Zip ties
4	Bolts M3x35mm



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 1 - 10-08-2022

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT