

PDL Reference Guide for the Xerox® PrimeLink® C9265/C9275/C9281 Printer Series

Customer Tip

© 2024 Xerox Corporation. All rights reserved. Xerox® and PrimeLink® are trademarks of Xerox Corporation in the United States and/or other countries. BR40941

Other company trademarks are also acknowledged.

Document Version: 1.0 (December 2024).

Overview

This document enables a user to access the extended features of the Xerox® PrimeLink® C9265/C9275/C9281 Printer Series in environments that do not have a custom driver.

Note: Some of the commands and syntax used in this document requires some familiarity with either PostScript (PS) or Printer Command Language (PCL).

This document provides the Printer Description Language (PDL) commands and syntax for each feature. The following items are also included:

- A PostScript table that describes the PostScript features the Xerox® PrimeLink® C9265/ C9275/ C9281 Printer Series supports and the syntax to use the feature.
- A PCL table that describes the PCL features the Xerox PrimeLink® C9265/ C9275/ C9281 Printer Series supports and the syntax to use the feature.

This document is not intended to be a complete PS or PCL reference manual. It is a guide for using the PS and PCL commands with PrimeLink.

Refer to these additional reference materials PostScript Language Reference Manual, Third Edition, ISBN 0-201-38922-8, PCL5 Printer Language Technical Reference Manual, Hewlett-Packard Manual and Printer Job Language Technical Reference Manual, Hewlett-Packard Manual.

Using this Guide

Search the Feature Table to determine whether the feature you wish to use is supported.

- Verify that the platform supports the feature. For example, the PrimeLink must have the Finisher option installed to use stapling commands.
- Following across the table to find the syntax listed for the PDL examples shown. Read the Dependencies/Caveats section.

Contents

- Overview..... 3**
- Using this Guide 3**
- PCL 5**
- PCL/PJL Implementation 6**
- PCL/PJL Feature Dependencies/Caveats 11**
- PJL Template 11**
- Sample PJL Headers 12**
- PCL Font List 14**
- PostScript Fonts..... 17**
- Additional Information 18**

PCL

The Xerox® PrimeLink® C9265/ C9275/ C9281 Printer Series supports PCL5e and PCL XL emulations that enable the features listed in the following table.

| FEATURE | DESCRIPTION |
|---|---|
| Job Name | Job Name |
| Custom Paper Size | This command specifies the custom designated media size. |
| Media Size | This command specifies the size of media on which to print the job. |
| Media Source | This command specifies the tray to supply the job's media. |
| Output Location | Indicates the output bin where the print job is sent. |
| Quantity | Use this command to specify the number of collated sets of a document. |
| Stapling | This command indicates use and location of staple(s). |
| Punch | This command indicates hole punches for a print job on a device with hole punch capability. |
| Folding | This command indicates to fold the print job. |
| Booklet | This command enables you to print documents as small booklets. The pages are reordered sequentially and are oriented so that when they are folded, the paging is correct. |
| Resolution | This command sets the resolution value. |
| Bits Per Pixel | This command sets the color depth value. |
| Copies | Use this command to specify the number of uncollated sets of a document in a print job. |
| Simplex | Deliver one-sided output |
| Duplex | Deliver two-sided output |
| Orientation | Landscape or Portrait |
| Job Mode | Opening Command, Required for all files |
| Force Short Edge Feeding | The Values indicate the feed edge to use. |
| Job Type (Secure Print / Proof Print / Box Print) | You can specify Confidential (Secure) Print or Proof Print |
| Job Based Accounting | This command is used to pass accounting codes to a printer enabled for Job Based Accounting. |
| Delay Print | Delays printing a job until the time specified by the command. |
| Banner Sheet | Turns on/off the banner sheet that prints at the beginning of every job. |

PCL/PJL Implementation

The following table contains the PCL feature commands and the syntax required to use the feature.

| ELEMENT | DESCRIPTION | VALUES |
|-------------------|---|--|
| Job Name | @PJL SET JOBNAME = "jobname-string" | Where jobname-string is a maximum of 32 characters Exclude ["](22H) character |
| Custom Paper Size | Not in PJL command. You have to specify by PCL: <ESC>&l101A | Width of Custom Paper is specified by <ESC>&f#l where # = decipoints for (100 - 330) mm. Length of Custom Paper is specified by <ESC>&f#J where # = decipoints for (148 - 488) mm. For instance: 4.25-inch x 5.5-inch will give <ESC>&f3060l3960J by 4.25-inch x 720 decipoints/inch = 3060 and 5.5-inch x 720 decipoints/inch = 3960. |
| Media Size | @PJL SET PAPER = <i>value</i> | Where <i>value</i> is one of the following: A6 = A6 (105 x 148mm) A5 = A5 (148 x 210mm) † A4 = A4 (210 x 297mm) A3 = A3 (297 x 420mm) JISB6 = B6 (128 x 182mm) JISB5 = B5 (182 x 257mm) JISB4 = B4 (257 x 364mm) STATEMENT = Statement (5.5 x 8.5") † EXECUTIVE = Executive (7.25 x 10.5") † 8X10 = 8 x 10" LETTER = Letter (8.5 x 11") SPANISH = 215 x 315mm JISEXEC = 8.5 x 13" LEGAL = Legal (8.5 x 14") 11X15 = 11 x 15" LEDGER = Tabloid (11 x 17") A4COVER = A4 Cover (223 x 297mm) LETTERCOVER = 9 x 11" SPECIALA4 = 226x310mm DT_SPECIALA3 = 310x432mm 12X18 = Oversized Tabloid (12 x 18") † SA3 = SRA3 (320 x 450mm) † 126X192 = 12.6x19.2(320x487.7mm) 13X18 = 13x18(330.2x457.2mm) † 13X19 = 13x19(330.2x482.6mm) ROC16K = 16K (194 x 267mm) † ROC8K = 8K (267 x 388mm) 16KAIGCO = 16K (195 x 270mm) † 8KAIGCO = 8K (270 x 390mm) JPOST = Postcard (100 x 148mm) JPOSTD = Postcard (148 x 200mm) POSTCARD = Postcard (4 x 6") 50X70 = 5 x 7" TYOUKEI3 = Envelope (120 x 235mm) |

| | | |
|--------------|-------------------------------------|--|
| | | <p>KAKUGATA2 = Envelope (240 x 332mm) COM10 = No. 10 Envelope (4.1 x 9.5") C4 KAKUGATA20 = Envelope (229 x 324mm) C5 = C5 Envelope (162 x 229mm) KAKUGATA6 = Envelope (162 x 229mm)</p> |
| | <ESC>&l <i>int</i> A | <p>Where <i>value</i> is one of the following: 24 = A6 (105 x 148mm) 25 = A5 (148 x 210mm) † 26 = A4 (210 x 297mm) 27 = A3 (297 x 420mm) 44 = B6 (128 x 182mm) 45 = B5 (182 x 257mm) 46 = B4 (257 x 364mm) 41 = Statement (5.5 x 8.5") † 1 = Executive (7.25 x 10.5") † 208 = 8 x 10" 2 = Letter (8.5 x 11") 43 = 215 x 315mm 18 = 8.5 x 13" 3 = Legal (8.5 x 14") 217 = 11 x 15" 6 = Tabloid (11 x 17") 200 = A4 Cover (223 x 297mm) 201 = 9 x 11" 224 = 226x310mm 225 = 310x432mm 213 = Oversized Tabloid (12 x 18") 197 = SRA3 (320 x 450mm) 219 = 16K (194 x 267mm) † 220 = 8K (267 x 388mm) 71 = Postcard (100 x 148mm) 72 = Postcard (148 x 200mm) 216 = Postcard (4 x 6") 204 = 5 x 7" 218 = Envelope (120 x 235mm) 81 = No. 10 Envelope (4.1 x 9.5") 91 = C5 Envelope (162 x 229mm)</p> |
| Media Source | @PJL SET MEDIASOURCE = <i>value</i> | <p>Where <i>value</i> is one of the following: TRAY1: Feed from paper tray1 TRAY2: Tray2 TRAY3: Tray3 TRAY4: Tray4 TRAY5: Tray5 (Bypass) TRAY6: Tray6 TRAY7: Tray7</p> |
| | <ESC>&l <i>int</i> H | <p>Where <i>int</i> is one of the following: 0: Feed paper from default tray 4: Tray1 1: Tray2 5: Tray3 8: Tray4 20: Auto 2 or 3: Tray5 (Bypass) 22: Tray6 23: Tray7 39: T1(Interposer)</p> |

| | | |
|-----------------|---|--|
| Output Location | @PJL SET OUTBIN = <i>value</i> | Where <i>value</i> is one of the following: UPPER: Main tray (Hewlett-Packard compatible) MAINTRAY: Main tray MAINTRAY3: finisher top tray OUTBIN101: Finisher tray BOOKLETTRAY: booklet tray FOLDERTRAY: folder tray |
| | <ESC>&l <i>int</i> G | Where <i>int</i> is one of the following: 0: Automatic Selection 1: Main tray 4: finisher top tray 6: Finisher tray 41: Stacker tray |
| Stapling | @PJL SET STAPLE = <i>value</i> | Where <i>value</i> is one of the following: TOPDUAL TOPLEFT BOTTOMDUAL BOTTOMLEFT BOTTOMRIGHT LEFTDUAL RIGHTDUAL SADDLE NONE |
| Punch | @PJL SET PUNCH = <i>value1</i> | Where <i>value1</i> is one of the following: TOP RIGHT LEFT BOTTOM NONE |
| | @PJL SET JOBATTR = "@PNHN = <i>value2</i> " | Where <i>value2</i> is one of the following: TWO: 2 holes THREE: 3 holes FOUR: 4 holes |
| Folding | @PJL SET JOBATTR = "@FOLD = <i>value1</i> " | Where <i>value1</i> is one of the following: BIFOLDINSIDE: Bi-Folding (single page) Print Inside BIFOLDOUTSIDE : Bi-Folding (single page) Print Outside BIFOLDMULTIOUTSIDE : Bi-Folding (multi page) The "Collated" feature needs to be enabled for the booklet functions to work. LETTERCFOLDINSIDE : C Fold Print Inside LETTERCFOLDOUTSIDE : C Fold Print Outside LETTERZFOLDINSIDE : Z Tri Fold Print Inside LETTERZFOLDOUTSIDE : Z Tri Fold Print Outside ZFOLDLEFT : Z Fold Half Sheet Left Bind |

| | | |
|----------------|---|---|
| | | ZFOLDRIGHT : Z Fold Half Sheet Right Bind |
| Booklet | <p>@PJL SET JOBATTR = "@BKLT = <i>value1</i>"</p> <p>@PJL SET JOBATTR = "@BKSG = <i>value2</i>"</p> <p>@PJL SET JOBATTR = "@BKDN = <i>int1</i>"</p> <p>@PJL SET JOBATTR = "@BKTP = <i>int2</i>"</p> | <p>Where <i>value1</i> is one of the following:</p> <p>NONEDIVIDE: Compile a booklet as long as the number of sheets does not exceed the limit.</p> <p>AUTODIVIDE: Divide sheets into sets automatically in case of exceeding the limit number of sheets.</p> <p>MANUALDIVIDE: Divide sheets based on the specified limit manually.</p> <p>OFF: Do not compile a booklet</p> <p>Where <i>value2</i> is one of the following:</p> <p>RIGHT: Right to left page order binding LEFT: Left to right page order binding</p> <p>Where <i>int1</i> is: 1-9999: Booklet dividing number for each set.</p> <p>Where <i>int2</i> is: 1-9999 : Booklet total pages of document</p> |
| Quantity | @PJL SET QTY = <i>int</i> | <p>Where <i>int</i> is: 1-999 (If you use this parameter, it also indicate use collate mode automatically.)</p> |
| Resolution | @PJL SET RESOLUTION = <i>value</i> | <p>Where <i>value</i> is one of the following: 600 1200</p> |
| Bits Per Pixel | @PJL SET BITSPERPIXEL = <i>value</i> | <p>Where <i>value</i> is one of the following: 1: 1 bit per pixel (per plane)</p> |
| Copies | @PJL SET COPIES = <i>int</i> | <p>Where <i>int</i> is: 1-999 (This parameter used for uncollated mode.)</p> |
| | <ESC>&l <i>int</i> X | <p>Where <i>int</i> is: 1-999</p> |
| Simplex | @PJL SET SIMPLEX = <i>value1</i> | <p>Where <i>value1</i> is one of the following: OFF: simplex</p> |
| | <ESC>&l <i>int</i> S | <p>Where <i>int</i> is one of the following: 0: simplex</p> |
| Duplex | @PJL SET DUPLEX = <i>value1</i> | <p>Where <i>value1</i> is one of the following: ON: duplex</p> |
| | @PJL SET BINDING = <i>value2</i> | <p>Where <i>value2</i> is one of the following: LONGEDGE SHORTEDGE (<i>value2</i> is used combined with <i>value1</i>=ON)</p> |
| | <ESC>&l <i>int</i> S | <p>Where <i>int</i> is one of the following: 1: Duplex Long Edge Binding 2: Duplex Short Edge Binding</p> |
| Orientation | @PJL SET ORIENTATION = <i>value</i> | <p>Where <i>value</i> is one of the following: PORTRAIT LANDSCAPE</p> |

| | | |
|---------------------------------|--|--|
| | <ESC>&l <i>int</i> O | Where <i>int</i> is one of the following: 0: Portrait 1: Landscape 2: Reverse Portrait 3: Reverse Landscape |
| Force short edge feeding | @PJL SET PAPERDIRECTION = <i>value</i> | Where <i>value</i> is one of the following: SEF: Short Edge Feed LEF: Long Edge Feed |
| Job Mode | @PJL JOB MODE = <i>value</i> | Where <i>value</i> is one of the following: PRINTER: for Printer |
| Job Type (Secure Print / Proof) | @PJL SET HOLD = <i>value1</i> @PJL SET HOLDKEY = " <i>string</i> " | Where <i>value1</i> is one of the following: PROOF: proof print STORE: confidential print (secure print) The HOLDKEY variable acts as a password without encryption to protect a held job. <i>string</i> is a maximum of 16 character (legal value 20H-FFH) as password without encryption. The default value is "". When "" (empty string) is specified, no password is required. |
| Job Based Accounting & Auditron | @PJL SET JOBATTR = "@JOAU = <i>string1</i> " @PJL SET JOBATTR = "@JOAP = <i>string2</i> " @PJL SET JOBATTR = "@DAID = <i>string3</i> " | Where <i>string1</i> is a maximum of 32 character (legal value: 20H-7EH) as job owner (Capital character & small character is distinguished) Where <i>string2</i> is a maximum of 12 character (legal value: 20H-7EH) as password without encryption. It can be null (zero length string) Where <i>string3</i> is a maximum of 32 character (legal value 20H-7EH) as account ID. It can be null (zero length string) |
| Delay Print | @PJL SET JOBATTR = "@PRTM = <i>YYYY:MM:DD:hh:mm</i> " | <i>YYYY:MM:DD:hh:mm</i> <i>YYYY</i> : year (AD 2000~2099) <i>MM</i> : month (1~12) <i>DD</i> : day (1~31) <i>hh</i> : hour (0~23) <i>mm</i> : minute (0~59) |
| Banner Sheet | @PJL SET JOBATTR = "@BANR= <i>value</i> " | Where <i>value</i> is one of the following: START: start sheet DEVICE: depend on device setting OFF: no banner sheet |

PCL/PJL Feature Dependencies/Caveats

- All PJL commands must be in the first 2,500 bytes of the job.
- To combine printer escape commands (not including PJL commands):
 - The first two characters after the <esc> MUST be the same.
 - All alpha characters MUST be lowercase, except the final terminating character.
 - The commands are read left to right. Combine commands in the order you wish them to execute.
 - For example, combine print 5 copies (<ESC>&|5X) and use letter size (<ESC>&|2A) as <ESC>&|5x2A.
- In case of duplicate commands, the last one requested takes precedence.
- The @PJL SET COPIES takes precedence over the PCL Escape Command (<ESC>& | int X>) to set copies. In general, a PJL command takes precedence over a PCL command.

PJL Template

This section illustrates a standard PJL template that is used to access general print features as well as product specific features. This template lists each feature and the syntax, both PCL commands and PJL, required to use these features.

Section 1 (Opening Command, Required for all files)

```
<ESC>%-12345X@PJL JOB MODE=PRINTER
```

Section 2 (PJL Set Commands)

```
@PJL SET RESOLUTION=600  
@PJL SET COPIES=1
```

Section 3 (PCL Code used to invoke PCL Language)

```
@PJL ENTER LANGUAGE=PCL
```

Section 4 (PCL Data Stream or ASCII Document inserted here for Options such as selection Different Fonts, Simplex, Duplex, etc.)

```
*****
```

Section 5 (Closing Command, Required at end of Document)

```
<ESC>%-12345X@PJL EOJ
```

Sample PJI Headers

This section contains examples of these commands in use.

Example 1 Simple Print

```
<ESC>%-12345X@PJI JOB MODE=PRINTER<CR><LF>  
@PJI COMMENT Beginning PCL Job<CR><LF>  
@PJI SET OUTBIN=MAINTRAY<CR><LF>  
@PJI SET QTY=1<CR><LF>  
@PJI SET RESOLUTION=600<CR><LF>  
@PJI SET JOBATTR="@JOAU=Nagaoka" <CR><LF>
```

Example 2 Finishing Options (Stapling)

```
<ESC>%-12345X@PJI JOB MODE=PRINTER<CR><LF>  
@PJI SET OUTBIN=OUTBIN101<CR><LF>  
@PJI SET FINISH=ON<CR><LF>  
@PJI SET STAPLE=TOPLEFT<CR><LF>
```

Example 3 Finishing Options (Punch)

```
<ESC>%-12345X@PJI JOB MODE=PRINTER<CR><LF>  
@PJI SET OUTBIN=OUTPIN101<CR><LF>  
@PJI SET FINISH=ON<CR><LF>  
@PJI SET PUNCH=LEFT<CR><LF>  
@PJI SET JOBATTR="@PNHN=TWO" <CR><LF>
```

Example 4 Finishing Options (Saddle stapling and folding) - Example of division in every 5 sheets.

```
<ESC>%-12345X@PJI JOB MODE=PRINTER<CR><LF>  
@PJI SET OUTBIN=BOOKLETTRAY<CR><LF>  
@PJI SET FINISH=ON<CR><LF>  
@PJI SET STAPLE=SADDLE<CR><LF>  
@PJI SET JOBATTR="@FOLD=BIFOLDMULTIOUTSIDE" <CR><LF>  
@PJI SET JOBATTR="@BKLT=MANUALDIVIDE" <CR><LF>  
@PJI SET JOBATTR="@BKSG=LEFT" <CR><LF>  
@PJI SET JOBATTR="@BKDN=5" <CR><LF>
```

Example 5 Finishing Options (Bi-Folding(multi page))

It is an example of division in every 5 sheets.

```
<ESC>%-12345X@PJI JOB MODE=PRINTER<CR><LF>  
@PJI SET OUTBIN=BOOKLETTRAY<CR><LF>  
@PJI SET FINISH=NONE<CR><LF>  
@PJI SET STAPLE=NONE <CR><LF>  
@PJI SET JOBATTR="@FOLD=BIFOLDMULTIOUTSIDE" <CR><LF>  
@PJI SET JOBATTR="@BKLT=MANUALDIVIDE" <CR><LF>  
@PJI SET JOBATTR="@BKSG=LEFT" <CR><LF>
```

```
@PJL SET JOBATTR="@BKDN=5"<CR><LF>
@PJL SET QTY=1<CR><LF>
```

Example 6 Finishing Options (Bi-Folding(single page))

```
<ESC>%-12345X@PJL JOB MODE=PRINTER<CR><LF>
@PJL SET OUTBIN=BOOKLETTRAY<CR><LF>
@PJL SET FINISH=NONE<CR><LF>
@PJL SET STAPLE=NONE <CR><LF>
@PJL SET JOBATTR="@FOLD=BIFOLDINSIDE"<CR><LF>
@PJL SET JOBATTR="@BKSG=LEFT"<CR><LF>
```

Example 7 Proof Print

```
<ESC>%-12345X@PJL JOB MODE=PRINTER<CR><LF>
@PJL SET HOLD=PROOF <CR><LF>
@PJL SET USERNAME="John" <CR><LF>
@PJL SET JOBNAME="Job1" <CR><LF>
```

Example 8 Confidential (Secure) Print without encryption

Password: 1234

```
<ESC>%-12345X@PJL JOB MODE=PRINTER<CR><LF>
@PJL SET HOLD=STORE <CR><LF>
@PJL SET HOLDKEY="1234"<CR><LF>
@PJL SET USERNAME="John" <CR><LF>
@PJL SET JOBNAME="Job1" <CR><LF>
```

Example 9 Banner Sheet

banner : start sheet

```
@PJL SET JOBATTR="@BANR=START"<CR><LF>
@PJL SET JOBATTR="@BCMT=Banner
CommentString"<CR><LF>
```

Example 10 Job Based Accounting & Auditor

userID:Patricia, Password: none, accountID: none

```
<ESC>%-12345X@PJL JOB MODE=PRINTER<CR><LF>
@PJL SET JOBATTR="@JOAU=Patricia"<CR><LF>
@PJL SET JOBATTR="@JOAP="<CR><LF>
@PJL SET JOBATTR="@DAID="<CR><LF>
```

PCL Font List

The following PCL fonts are resident on the device. The commands in the table reference a 12-point font. If you wish to use any other point size, change the 12v within the PCL Escape Command to the desired size (.25 – 999.75).

The commands listed use the default symbol set, Roman-8. To change the symbol set, you include the alternate symbol set after the first <ESC> and before the second <ESC>. Use the line printer examples as a reference.

| FONT | NAME | ESCAPE |
|------|----------------------|-----------------------------|
| 1 | Albertus Medium | <esc><esc>(s1p12v0s1b4362T |
| 2 | Albertus Extra Bold | <esc><esc>(s1p12v0s4b4362T |
| 3 | Antique Olive | <esc><esc>(s1p12v0s0b4168T |
| 4 | Antique Olive Bold | <esc><esc>(s1p12v0s3b4168T |
| 5 | Antique Olive Italic | <esc><esc>(s1p12v1s0b4168T |
| 6 | Arial | <esc><esc>(s1p12v0s0b16602T |
| 7 | Arial Bold | <esc><esc>(s1p12v0s3b16602T |
| 8 | Arial Italic | <esc><esc>(s1p12v1s0b16602T |
| 9 | Arial Bold Italic | <esc><esc>(s1p12v1s3b16602T |
| 10 | CG Times | <esc><esc>(s1p12v0s0b4101T |
| 11 | CG Times Bold | <esc><esc>(s1p12v0s3b4101T |
| 12 | CG Times Italic | <esc><esc>(s1p12v1s0b4101T |
| 13 | CG Times Bold Italic | <esc><esc>(s1p12v1s3b4101T |
| 14 | CG Omega | <esc><esc>(s1p12v0s0b4113T |
| 15 | CG Omega Bold | <esc><esc>(s1p12v0s3b4113T |
| 16 | CG Omega Italic | <esc><esc>(s1p12v1s0b4113T |
| 17 | CG Omega Bold Italic | <esc><esc>(s1p12v1s3b4113T |
| 18 | Clarendon Condensed | <esc><esc>(s1p12v4s3b4140T |
| 19 | Coronet | <esc><esc>(s1p12v1s0b4116T |
| 20 | Courier | <esc><esc>(s1p12v0s0b4099T |
| 21 | Courier Bold | <esc><esc>(s1p12v0s3b4099T |
| 22 | Courier Italic | <esc><esc>(s1p12v1s0b4099T |
| 23 | Courier Bold Italic | <esc><esc>(s1p12v1s3b4099T |

| | | |
|----|---------------------------------|------------------------------------|
| 24 | Garamond Antiqua | <esc><esc>(s1p12v0s0b4197T |
| 25 | Garamond Halbfett | <esc><esc>(s1p12v0s3b4197T |
| 26 | Garamond Kursiv | <esc><esc>(s1p12v1s0b4197T |
| 27 | Garamond Kursiv Halbfett | <esc><esc>(s1p12v1s1b4197T |
| 28 | Line Printer (Roman- 8) | <esc>(8U<esc>(s0p16.67h8.5v0s0b0T |
| 29 | Line Printer (Latin-1) | <esc>(0U<esc>(s0p16.67h8.5v0s0b0T |
| 30 | Line Printer (PC-8) | <esc>(10U<esc>(s0p16.67h8.5v0s0b0T |
| 31 | Line Printer (PC-8 D/N) | <esc>(11U<esc>(s0p16.67h8.5v0s0b0T |
| 32 | Line Printer (PC-850) | <esc>(12U<esc>(s0p16.67h8.5v0s0b0T |
| 33 | Line Printer (Legal) | <esc>(1U<esc>(s0p16.67h8.5v0s0b0T |
| 34 | Marigold | <esc><esc>(s1p12v0s0b4297T |
| 35 | Times New | <esc><esc>(s1p12v0s0b16901T |
| 36 | Times New Bold | <esc><esc>(s1p12v0s3b16901T |
| 37 | Times New Italic | <esc><esc>(s1p12v1s0b16901T |
| 38 | Times New Bold Italic | <esc><esc>(s1p12v1s3b16901T |
| 39 | Symbol | <esc>(19M<esc>(s1p12v0s0b16686T |
| 40 | Wingdings | <esc>(579L<esc>(s1p12v0s1b31402T |
| 41 | Univers Bold | <esc><esc>(s1p12v0s3b4148T |
| 42 | Univers Bold Italic | <esc><esc>(s1p12v1s3b4148T |
| 43 | Univers Bold Condensed | <esc><esc>(s1p12v4s3b4148T |
| 44 | Univers Bold Condensed Italic | <esc><esc>(s1p12v5s3b4148T |
| 45 | Univers Medium | <esc><esc>(s1p12v0s0b4148T |
| 46 | Univers Medium Italic | <esc><esc>(s1p12v1s0b4148T |
| 47 | Univers Medium Condensed | <esc><esc>(s1p12v4s0b4148T |
| 48 | Univers Medium Condensed Italic | <esc><esc>(s1p12v5s0b4148T |
| 49 | Letter Gothic | <esc><esc>(s1p12h0s0b4102T |
| 50 | Letter Gothic Italic | <esc><esc>(s1p12h1s0b4102T |
| 51 | Letter Gothic Bold | <esc><esc>(s1p12h0s3b4102T |
| 52 | Times Roman | <esc><esc>(s1p12h0s3b4102T |
| 53 | Times Italic | <esc><esc>(s1p12h0s3b4102T |
| 54 | Times Bold | <esc><esc>(s1p12h0s3b4102T |
| 55 | Times Bold Italic | <esc><esc>(s1p12h0s3b4102T |
| 56 | Helvetica | <esc><esc>(s1p12v0s0b24580T |

| | | |
|----|------------------------------------|---------------------------------|
| 57 | Helvetica Oblique | <esc><esc>(s1p12v1s0b24580T |
| 58 | Helvetica Bold | <esc><esc>(s1p12v0s3b24580T |
| 59 | Helvetica Bold Oblique | <esc><esc>(s1p12v1s3b24580T |
| 60 | CourierPS | <esc><esc>(s0p12h0s0b24579T |
| 61 | CourierPS Oblique | <esc><esc>(s0p12h1s0b24579T |
| 62 | CourierPS Bold | <esc><esc>(s0p12h0s3b24579T |
| 63 | CourierPS Bold Oblique | <esc><esc>(s0p12h1s3b24579T |
| 64 | SymbolPS | <esc>(19M<esc>(s1p12v0s0b45358T |
| 65 | Palatino Roman | <esc><esc>(s1p12v0s0b24591T |
| 66 | Palatino Italic | <esc><esc>(s1p12v0s0b24591T |
| 67 | Palatino Bold | <esc><esc>(s1p12v0s0b24591T |
| 68 | Palatino Bold Italic | <esc><esc>(s1p12v0s0b24591T |
| 69 | ITC Bookman Light | <esc><esc>(s1p12v0s-3b24623T |
| 70 | ITC Bookman Light Italic | <esc><esc>(s1p12v1s-3b24623T |
| 71 | ITC Bookman Demi | <esc><esc>(s1p12v0s2b24623T |
| 72 | ITC Bookman Demi Italic | <esc><esc>(s1p12v1s2b24623T |
| 73 | Helvetica Narrow | <esc><esc>(s1p12v4s0b24580T |
| 74 | Helvetica Narrow Oblique | <esc><esc>(s1p12v5s0b24580T |
| 75 | Helvetica Narrow Bold | <esc><esc>(s1p12v4s3b24580T |
| 76 | Helvetica Narrow Bold Oblique | <esc><esc>(s1p12v5s3b24580T |
| 77 | New Century Schoolbook Roman | <esc><esc>(s1p12v0s0b24703T |
| 78 | New Century Schoolbook Italic | <esc><esc>(s1p12v1s0b24703T |
| 79 | New Century Schoolbook Bold | <esc><esc>(s1p12v0s3b24703T |
| 80 | New Century Schoolbook Bold Italic | <esc><esc>(s1p12v1s3b24703T |
| 81 | ITC Avant Garde Book | <esc><esc>(s1p12v0s0b24607T |
| 82 | ITC Avant Garde Book Oblique | <esc><esc>(s1p12v1s0b24607T |
| 83 | ITC Avant Garde Demi | <esc><esc>(s1p12v0s2b24607T |
| 84 | ITC Avant Garde Demi Oblique | <esc><esc>(s1p12v1s2b24607T |
| 85 | ITC Zapf Chancery Medium Italic | <esc><esc>(s1p12v1s0b45099T |
| 86 | ITC Zapf Dingbats | <esc><esc>(s1p12v0s0b45101T |

PostScript Fonts

The following PostScript fonts are resident with Adobe interpreter.

| | |
|-------------------------------------|------------------------------------|
| Albertus | Helvetica |
| Albertus Italic | Helvetica Oblique |
| Albertus Light | Helvetica Bold |
| Antique Olive Roman | Helvetica Bold Oblique |
| Antique Olive Italic | Helvetica Narrow |
| Antique Olive Bold | Helvetica Narrow Oblique |
| Antique Olive Compact | Helvetica Narrow Bold |
| Apple Chancery | Helvetica Narrow Bold Oblique |
| Arial | Helvetica Condensed |
| Arial Italic | Helvetica Condensed Oblique |
| Arial Bold | Helvetica Condensed Bold |
| Arial Bold Italic | Helvetica Condensed Bold Oblique |
| ITC Avant Garde Gothic Book | Hoefler Text |
| ITC Avant Garde Gothic Book Oblique | Hoefler Text Italic |
| ITC Avant Garde Gothic Demi | Hoefler Text Black |
| ITC Avant Garde Gothic Demi Oblique | Hoefler Text Black Italic |
| Bodoni Roman | Hoefler Ornaments |
| Bodoni Italic | Joanna |
| Bodoni Bold | Joanna Italic |
| Bodoni Bold Italic | Joanna Bold |
| Bodoni Poster | Joanna Bold Italic |
| Bodoni Poster Compressed | Letter Gothic |
| ITC Bookman Light | Letter Gothic Slanted |
| ITC Bookman Light Italic | Letter Gothic Bold |
| ITC Bookman Demi | Letter Gothic Bold Slanted |
| ITC Bookman Demi Italic | ITC Lubalin Graph Book |
| Carta | ITC Lubalin Graph Book Oblique |
| Chicago | ITC Lubalin Graph Demi |
| Clarendon Roman | ITC Lubalin Graph Demi Oblique |
| Clarendon Bold | Marigold |
| Clarendon Light | Monaco |
| Cooper Black | ITC Mona Lisa Recut |
| Cooper Black Italic | New Century Schoolbook Roman |
| Copperplate Gothic 32BC | New Century Schoolbook Italic |
| Copperplate Gothic 33BC | New Century Schoolbook Bold |
| Coronet | New Century Schoolbook Bold Italic |
| Courier | NewYork |
| Courier Oblique | OCR-B Letterpress M |
| Courier Bold | Optima Roman |
| Courier Bold Oblique | Optima Italic |
| Eurostile Medium | Optima Bold |
| Eurostile Bold | Optima Bold Italic |
| Eurostile Extended No. 2 | Oxford |
| Eurostile Bold Extended No. 2 | Palatino Roman |
| Geneva | Palatino Italic |
| Gill Sans | Palatino Bold |
| Gill Sans Italic | Palatino Bold Italic |
| Gill Sans Bold | Stempel Garamond Roman |
| Gill Sans Bold Italic | Stempel Garamond Italic |
| Gill Sans Light | Stempel Garamond Bold |

Gill Sans Light Italic
Gill Sans Extra Bold
Gill Sans Condensed
Gill Sans Condensed Bold
Goudy Oldstyle
Goudy Oldstyle Italic
Goudy Bold
Goudy Bold Italic
Goudy Extra Bold
Times New Roman Bold
Times New Roman Bold Italic
Univers 45 Light
Univers 45 Light Oblique
Univers 55
Univers 55 Oblique
Univers 65 Bold
Univers 65 Bold Oblique
Univers 57 Condensed
Univers 57 Condensed Oblique

Stempel Garamond Bold Italic
Symbol
Tekton Regular
Times Roman
Times Italic
Times Bold
Times Bold Italic
Times New Roman
Times New Roman Italic
Univers 67 Condensed Bold
Univers 67 Condensed Bold Oblique
Univers 53 Extended
Univers 53 Extended Oblique
Univers 63 Extended Bold
Univers 63 Extended Bold Oblique
Wingdings
ITC Zapf Chancery Medium Italic
ITC Zapf Dingbat

Additional Information

You can reach Xerox Customer Support at <http://www.xerox.com> or by calling Xerox Support in your country.

Xerox Support welcomes feedback on all documentation – send feedback via email to:
USA.DSSC.Doc.Feedback@xerox.com