

# Statement of Volatility – Dell U2724DE Monitor

**⚠ CAUTION:** A CAUTION indicates either potential damage to hardware or erasure of data and tells you how to avoid the problem.

The Dell U2724DE Monitor contains both volatile and non-volatile components. Volatile components erase their data immediately after power is removed from the component. Non-volatile components continue to retain their data even after power is removed from the component. The following Non-volatile components are present on the Dell U2724DE Monitor system board.

**Table 1. List of Non-Volatile Components on System Board**

Description	Reference Designator	Volatility Description	User Accessible for external data	Remedial Action (action necessary to erase data)
Serial Flash ROM MX25L6433FM2J-08Q	U303	Non-volatile Flash memory, 64 MB. To store scaler firmware.	No	Part place on Interface Board, it has hardware/software write protected.
EEPROM M24128-BRMN6TP	U302	Non-volatile memory, 128 KB. To store scaler firmware.	No	Part place on Interface Board, it has hardware/software write protected.
EEPROM M24C02-RMN6TP	U1203	Non-volatile memory, 2 KB. To store HDMI EDID, data.	No	Part place on Interface Board, it has hardware/software write protected.
Serial Flash ROM W25X40CLSNIG	U1904	Non-volatile Flash memory, 4 MB. To store USB3.0 firmware.	No	Part place on Interface Board, it has hardware/software write protected.
Serial Flash ROM XM25QH40BJGT	U1909	Non-volatile Flash memory, 4 MB. To store USB3.0 firmware.	No	Part place on Interface Board, it has hardware/software write protected.
Serial Flash ROM MX25V20066M1102	U2902	Non-volatile Flash memory, 2 MB. To store USB2.0 firmware.	No	Part place on TBT Board, it has hardware/software write protected.
Serial Flash ROM W25Q80DVSNIG	U3103	Non-volatile Flash memory, 8 MB. To store PD firmware.	No	Part place on TBT Board, it has hardware/software write protected.
Serial Flash ROM MX25V80066M1102	U3104	Non-volatile Flash memory, 8 MB. To store PD firmware.	No	Part place on TBT Board, it has hardware/software write protected.
Serial Flash ROM MX25V16066M2102	U2601	Non-volatile Flash memory, 16 MB. To	No	Part place on TBT Board, it has

		store Goshen ridge firmware.		hardware/software write protected.
--	--	---------------------------------	--	---------------------------------------

- △ CAUTION: All other components on the system board lose data if power is removed from the system. Primary power loss (unplugging the power cord and removing the battery) destroys all user data on the memory (DDR3, 1067 MHz). Secondary power loss (removing the on-board coin-cell battery) destroys system data on the system configuration and time-of-day information.