

VGA with Audio over Cat5 Extender, Receiver, USB-Powered, Up to 300-ft.

MODEL NUMBER: **B132-100A-SR**



Description

Tripp Lite's B132-100A-SR VGA with Audio over Cat5 Extender Receiver Unit is designed to work with Tripp Lite's [B132-002A-2](#) and [B132-004A-2](#) VGA with Audio over Cat5 Extender / Splitter Transmitter Units. Unlike the [B132-100A](#) Receiver Unit (which supports distances up to 1,000-ft.), or the B132-100A-MR (which supports distances up to 750-ft.) the B132-100A-SR is a cost effective solution for distances up to 300-ft. It extends a 1440 x 900 video and audio signal up to 150-ft. from the source, or a 1024 x 768 video and audio signal up to 300-ft. Power is supplied via the included USB Micro-B cable, with no external power supply required. Connect the included Micro-B cable between the Receiver and a USB port on a computer, monitor, or USB wall charger, such as the Tripp Lite [UAC-1B](#). It also features equalization and gain controls to adjust the video image. Audio connections are made with standard [3.5mm stereo cables](#) (not included). Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases.

Features

- Works with a [B132-002A-2](#) or [B132-004A-2](#) Transmitter Unit to extend a VGA video and audio signal up to 300-ft. from the source
- Extends a 1440 x 900 video and audio signal up to 150-ft, or a 1024 x 768 video and audio signal up to 300-ft.
- 24AWG, Solid Wire Cat5e/6 cable (such as Tripp Lite's [N202-Series](#) Cat6 cables) is required to achieve maximum distance and resolution
- Power is supplied via the included USB Micro-B cable; no external power supply required
- Features built-in equalization and gain controls to adjust the video image
- All operating systems supported
- Plug and play; no software or drivers required
- HDCP and EDID compliant
- Ideal for digital signage installations for retail, schools, churches, etc.
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

Specifications

Highlights

- Works with a [B132-002A-2](#) or [B132-004A-2](#) Transmitter Unit to extend a VGA video and audio signal up to 300-ft. from the source
- Extends a 1440 x 900 video and audio signal up to 150-ft, or a 1024 x 768 video and audio signal up to 300-ft.
- Power is supplied via the included USB Micro-B cable; no external power supplies required
- Plug and play, no software or drivers required
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases.

Package Includes

- B132-100A-SR
- USB Micro-B cable
- Screwdriver for EQ/Gain adjustment
- Owner's Manual

OVERVIEW	
Chromebook Compatible	No
Display Style	Splitter
Model Type	VGA
Cable Types	CAT5/CAT5E
CONNECTIONS	
Connector A	HD15 (MALE)
Connector B	3.5MM (FEMALE)
Connector C	RJ45 (FEMALE)
CERTIFICATIONS	
Approvals	CE, FCC, RoHS, REACH
WARRANTY	
Product Warranty Period (Worldwide)	1-year limited warranty

© 2015 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.