



# AC-360-Z V2 Quickstart Guide

Thank You for Purchasing the **Ultimate Zoom Room Microphone.**



*To begin, make sure the following items are included in the box:*

- 5V Power Supply
- Mounting Pads
- USB-C to USB-C Cable
- Right Angle USB-C Cable
- USB-C to USB-A Cable
- Right Angle USB-C to USB-A Cable

*To use the AC-360-Z V2 as a single main unit on your table or desk:*

1. Pick your desired **RIGHT ANGLE USB** cable.
2. Use the OUT port on the microphone and connect to your computer.
3. On your Zoom Room controller, navigate to the settings menu, and select "MXL AC-360Z V2 (1)" as your microphone source.

*To use the AC-360-Z V2 as a single main unit **FIXED** to your table or desk:*

1. Pick your desired **STRAIGHT USB** cable.
2. Use the OUT port on the microphone, drop through hole on table or mounting surface.
3. Unscrew removable rubber feet and apply included mounting pads to bottom of unit.
4. Connect the AC-360-Z V2 to your computer.
5. On your Zoom Room controller, navigate to the settings menu, and select "MXL AC-360Z V2 (1)" as your microphone source.

- You do **NOT** need to use the 5V Power Supply when only using a single unit.
- Each connected AC-360-Z V2 will display as 4 microphone devices in your computer's settings.

For Customer Service and Support, Call MXL Tech Support at (800) 800-6608





**Please Note:**



# AC-360-Z V2





## To use the AC-360-Z V2 as an extension unit on your table or desk:

1. Pick the **RIGHT ANGLE USB-C to RIGHT ANGLE USB-C** cable.
2. Use the OUT port on the microphone and connect to the EXT port on your main unit.
3. Connect the provided power supply to the extension unit.
4. Your Zoom Room controller will display, "MXL AC360V2 (2)" as an available microphone source. Tap  , followed by the "Update to 2 Microphones" option. [See more](#)
5. [OPTIONAL] Repeat for a 3rd unit.
6. Your Zoom Room controller will display, "MXL AC360V2 (3)" as an available microphone source. Tap  , followed by the "Update to 3 Microphones" option. [See more](#)

- Each extension unit will require the 5V Power Supply.
- Daisy chain each extension microphone point to point.
- Each connected AC-360-Z V2 will display as 4 microphone devices in your computer's settings.

# Extension Unit Installation Guide

## To use the AC-360-Z V2 as an extension unit **FIXED** to your table or desk:

1. Pick your desired **STRAIGHT USB-C to STRAIGHT USB-C** cable
2. Use the OUT port on the microphone, drop through hole on table or mounting surface, connect to EXT port on your main unit.
3. Connect the provided power supply to the extension unit.
4. Unscrew removable rubber feet and apply included mounting pads to bottom of unit.
5. Your Zoom Room controller will display, "MXL AC360V2 (2)" as an available microphone source. Tap  , followed by the "Update to 2 Microphones" option. [See more](#)
6. [OPTIONAL] Repeat for a 3rd unit.
7. Your Zoom Room controller will display, "MXL AC360V2 (3)" as an available microphone source. Tap  , followed by the "Update to 3 Microphones" option. [See more](#)

CONNECTED AC-360-Z V2s	COMPUTER INPUTS SHOWN	ZOOM ROOM CONTROLLER MIC INPUTS SHOWN
1	4	1
2	8	2
3	12	3



Please Note: