

## 70x15mm Replacement Ball Bearing Computer Case Fan w/ TX3 Connector

**Product ID:** FAN7X15TX3



This versatile 70mm fan is an ideal replacement fan for keeping your computer running cool. The fan can be powered through a TX3 connection, and features a dual ball bearing design that ensures reliable cooling and longer fan lifespan.

The fan can be used to replace the fan component of some CPU coolers or mounted to the side panel of a computer case and features a tachometer pin on the TX3 motherboard connector that provides the host system with fan operating status information.

### Certifications, Reports and Compatibility

#### Applications

- Replace a noisy or failed computer case fan
- Install into a computer to increase air flow and cooling

#### Features

- Dual ball bearing design
- 3-pin connector with tachometer wire

---

#### Hardware

Warranty

2 Years

Fan Bearing Type	Ball Bearing
------------------	--------------

---

**Performance**

Air Flow Rate	29.58 CFM
Noise Level	< 34 dBA
MTBF	50,000 Hours
Fan RPM	3500

---

**Connector(s)**

Connector Type(s)	Fan (3 pin, TX3)
-------------------	------------------

---

**Power**

Input Voltage	12V DC
Input Current	26 mA
Power Consumption (In Watts)	3.12W

---

**Environmental**

Operating Temperature	-10C to 70C (14F to 158F)
Storage Temperature	-40C to 75C (-40F to 167F)
Humidity	0~65% RH

---


**Physical Characteristics**

Color	Black
Material	Plastic
Product Length	2.8 in [70 mm]
Product Width	0.6 in [15 mm]
Product Height	2.8 in [70 mm]
Weight of Product	1.8 oz [50 g]

---

**Packaging Information**

Package Length	5.6 in [14.3 cm]
Package Width	3.8 in [96 mm]



Package Height 1.3 in [32 mm]

Shipping (Package) Weight 2.6 oz [75 g]

---

**What's in the Box**

Included in Package 7cm Case Fan  
Mounting Screws

---

***\*Product appearance and specifications are subject to change without notice.***

