



#### Product Overview:

Made for permanent installations, the LA-116 flexible dipole antenna can be mounted on a wall, inside a drop ceiling, or anywhere that requires discreet placement and extended range. Configured for use with our 72 MHz transmitters and receivers, the LA-116 is 203 cm (80 in.) in length and flexible to fit any space or venue where it is needed.

#### Highlights:

- Flexible for many different applications
- For use with 72 MHz products
- Easy to install
- Transmission range of up to 244 m (800 ft.)

#### Includes:

One (1) LA-116 Coaxial Dipole Remote Antenna (72 MHz)

| Product Specification: Coaxial Dipole Remote Antenna (72 MHz) |  |
|---|--|
| RF  |  |
| Frequency Range   | 72.0250 - 75.9500 MHz  |
| Typical Range   | Range up to 244 m / 800 ft.  |
| Physical  |  |
| Material  | Polyethylene Insulation, PVC Jacket, tinned copper conductor, tinned copper braided shield |
| Shipping Weight   | 0.5 kg (1.0 lb)  |
| Diameter  | 4.88 mm (0.19 in.)   |
| Cable Length  | 7.62 m (25 ft.)  |
| Cable Type  | RG-58 50 Ohm Coaxial   |
| Weight  | 0.38 kg (13.40 oz.)  |