

NDA-U-PSU0 PSU, 24VAC, for NDA-7100PEN/PENF









- ► Aluminum enclosure rated to IP66 and NEMA 4X to prevent dust and water ingress
- ► IK10 impact rating ensures enclosure integrity

Bosch offers a series of stand-alone power supply units that provide VAC power to AUTODOME 7100i cameras for applications without PoE. Each unit has a cover door that provides IP66/NEMA 4X ingress protection and meets power and electrical safety requirements in extreme environmental conditions. The unique design and the IK10 rating protect the power supply units from vandalism and tampering events.

These units can be mounted directly to a wall or other flat surface. Optional pole and corner mounting accessories are also available, allowing you to tailor your AUTODOME installation to your specific requirements. Multiple cable gland/conduit entry points protect cables and simplify installation. The NDA-U-PSU0 does not have a transformer (for direct 24 VAC power input).

Regulatory information

For a full list of all related certifications/standards, refer to the Product Test Reports, available on the online catalog, on the Documents tab of the product page for your device. If the document is unavailable on the product page, contact your sales representative.

Electromagnetic Compatibility (EMC)

Complies with FCC Part 15, ICES-003 Issue 7 (for Canada only), and CE regulations, including latest versions of: EN 50130-4: 2011 EN 55032: 2015 + a11: 2020 (Class A)

EN 61000-3-2: 2014
EN 61000-3-3: 2013
FCC 47 Part 15 B


RoHS


Complies with EN IEC 63000:2018

Product Safety

Complies with EN, IEC and UL Standards
62368-1: 2014

Installation/configuration notes





Parts	inc	uc	ed

Quantity	Component
1	NDA-U-PSU0 power supply box
1	Quick installation guide
1	Safety and security information manual

Technical specifications

Model	Input	Output Rating	Input Fuses	Output F	uses
				Camera	Heater
NDA-U-PSU0	24 VAC, 50/60 Hz	24 V @ 96 VA	5.0 A	2.0 A	3.15 A

Mechanical

Certifications	UL, CE, Plenum Rated
Dimensions (W x H x D), all models ²	170.0 x 216.4 x 105.0 mm (6.69 x 8.52 x 4.13 in.)
Construction Material	Cast Aluminum
Standard Color	White (RAL9003)
Standard Finish	Powder coated, sand finish
2. Dimensions for power supplies include the cover.	

Environmental

Operating Temperature	-60°C to 55°C (-76°F to 131°F)
Humidity	0% to 100%, condensing
Environmental Protection	IP66, IK 10 (IEC 62262), NEMA 4X

Ordering information

NDA-U-PSU0 PSU, 24VAC, for NDA-7100PEN/PENF Power supply unit without transformer, 24 VAC, IK10 Order number NDA-U-PSU0 | F.01U.411.639

Accessories

NDA-U-PMAL Pole mount adapter large Universal pole mount adapter, white; large Order number NDA-U-PMAL | F.01U.324.944

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com

Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Tell: +49 (0)89 6290 0 Fax:+49 (0)89 6290 1020 de.securitysystems@bosch.com www.boschsecurity.com North America: Bosch Security Systems, LLC 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 onlinehelp@us.bosch.com www.boschsecurity.com Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2809
www.boschsecurity.com/xc/en/contact/

www.boschsecurity.com

NDA-U-CMT Corner mount adapter

Universal corner mount, white Order number NDA-U-CMT | F.01U.324.946

NDA-7100-PEN Pendant arm for AUTODOME 7100i

Pendant arm mount for AUTODOME 7100i and AUTODOME 7100i IR cameras

Order number NDA-7100-PEN | F.01U.389.329

Pendant arm with direct fiber connection for

NDA-7100-PENF Pendant arm fiber AUTODOME 7100i

AUTODOME 7100i and AUTODOME 7100i IR cameras Order number NDA-7100-PENF | F.01U.395.439