

# HyperX QuadCast 2 - USB Microphone (Black) (872V1AA)



## The New Standard.

The HyperX QuadCast 2 refines everything that made the original such a favorite amongst gamers, streamers, and content creators around the world. All the fan-favorite features are still here: the iconic stunning lighting, the tap-to-mute sensor, 4 selectable polar patterns, the 3.5mm headphone jack, and included shock mount and desktop stand but now with a range of innovative additions packaged in a new sleek, full aluminum silhouette. QuadCast 2 features upgraded



### Hi-Res Studio-Quality Recording

The QuadCast 2 will help take your recordings to the next level by capturing more sound detail and allowing the subtleties of your voice to shine through.

### Tap-to-Mute Sensor

Simply tap the top of the QuadCast 2 to prevent audio accidents and quickly mute the microphone.

### Intuitive On-Board Controls

The multifunction knob lets you quickly and easily adjust your microphone gain, playback volume, monitoring volume, and switch between 4 polar patterns.

## Specifications

<b>Weight</b>	Weight (Microphone) 335 g; (Shock mount and stand) 137 g; (Microphone stand) 273 g; Total Weight (with cable) 819 g.
<b>Weight</b>	Weight (Microphone) 11.8 oz; (Shock mount and stand) 4.8 oz; (Microphone stand) 9.6 oz; Total Weight (with cable) 28.8 oz.
<b>UPC number</b>	197497651058
<b>Manufacturer Warranty</b>	2 year
<b>What's in the box</b>	HyperX QuadCast 2 USB Microphone, 3m USB-C to USB-C cable, USB-C to USB-A adapter, Quick Start Guide.

## Top Recommended Displays, Accessories and Services

No Top Recommended Displays, Accessories and Services

## Messaging Footnotes

[1] Universal shock mount must be able to accommodate 55mm mic diameter and not obstruct multifunction knob.

## Technical Specifications Footnotes

No Technical Specifications Footnotes

---

© Copyright 2024 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

