

# Projector Control Command Reference Manual

## Projector Control Command Reference Manual Appendixes

This is the supplemental document to the principal. Please refer to the principal about detailed information including precautions.

### No.BDT140014

#### Revision History

| Revision | Date          | Description                 | Reference | Supported models                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|----------|---------------|-----------------------------|-----------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 29.0     | July 18, 2023 | Added the supported models. | 8.0       | NP4100 / NP4100W<br>NP-M430WL / NP-M380HL<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /<br>NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /<br>NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /<br>NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /<br>NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X<br>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P627UL / NP-P547UL<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X<br>NP-P605UL / NP-P525UL / NP-P525WL<br>NP-P506QL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PA1705UL / NP-PA1505UL<br>NP-PA1004UL / NP-PA804UL<br>NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PE506UL / NP-PE506WL<br>NP-PE456USL / NP-PE456WSL<br>NP-PE401H<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br>NP-PV800UL / NP-PV730UL / NP-PV710UL<br>NP-PV710UL+<br>NP-PX2201UL<br>NP-PX2000UL<br>NP-PX1005QL<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /<br>NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |

|      |              |                             |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|------|--------------|-----------------------------|-----|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 28.0 | May 30, 2023 | Added the supported models. | 8.0 | NP4100 / NP4100W<br>NP-M430WL / NP-M380HL<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /<br>NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /<br>NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /<br>NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /<br>NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br><i>NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X</i><br><i>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X</i><br>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P627UL / NP-P547UL<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X<br>NP-P605UL / NP-P525UL / NP-P525WL<br>NP-P506QL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PA1004UL / NP-PA804UL<br>NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PE506UL / NP-PE506WL<br>NP-PE456USL / NP-PE456WSL<br>NP-PE401H<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br><i>NP-PV800UL / NP-PV730UL / NP-PV710UL</i><br>NP-PV710UL+<br>NP-PX2201UL<br>NP-PX2000UL<br>NP-PX1005QL<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /<br>NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |
|------|--------------|-----------------------------|-----|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

|      |                       |                                                                                                                |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|------|-----------------------|----------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 27.0 | 2023/1/6<br>2022/7/21 | Added the supported models.<br>Added SILENT to 097-8. ECO<br>MODE REQUEST and 098-8.<br>ECO MODE SET commands. | 8.0<br><br>NP4100 / NP4100W<br>NP-M430WL / NP-M380HL<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /<br>NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /<br>NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /<br>NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /<br>NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br><i>NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X</i><br><i>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X</i><br>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br><i>NP-P627UL / NP-P547UL</i><br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X<br>NP-P605UL / NP-P525UL / NP-P525WL<br>NP-P506QL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PA1004UL / NP-PA804UL<br>NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PE506UL / NP-PE506WL<br>NP-PE456USL / NP-PE456WSL<br>NP-PE401H<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br><i>NP-PV710UL+</i><br>NP-PX2201UL<br>NP-PX2000UL<br>NP-PX1005QL<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /<br>NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |
|      |                       |                                                                                                                |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |

|      |               |                                                                      |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
|------|---------------|----------------------------------------------------------------------|-----|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 26.0 | July 21, 2022 | Added the supported models.                                          | 8.0 | NP-P605UL / NP-P525UL / NP-P525WL<br>NP-P506QL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PA1004UL / NP-PA804UL<br>NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PE506UL / NP-PE506WL<br><i>NP-PE456USL / NP-PE456WSL</i><br>NP-PE401H<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br>NP-PX2201UL<br>NP-PX2000UL<br>NP-PX1005QL<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /<br>NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| 25.0 | June 29, 2022 | Added the supported models.<br>Fixed incorrect order of some models. | 8.0 | NP4100 / NP4100W<br><i>NP-M430WL / NP-M380HL</i><br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /<br>NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /<br>NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /<br>NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /<br>NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br><i>NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X</i><br><i>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X</i><br>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X<br>NP-P605UL / NP-P525UL / NP-P525WL<br>NP-P506QL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PA1004UL / NP-PA804UL<br>NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PE506UL / NP-PE506WL<br>NP-PE401H<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br><i>NP-PX2201UL</i><br>NP-PX2000UL<br>NP-PX1005QL |

|      |                |                             |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|------|----------------|-----------------------------|-----|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|      |                |                             |     | NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 24.0 | March 22, 2022 | Added the supported models. | 7.1 | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br><i>NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X</i><br><i>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X</i><br>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br>NP-P605UL / NP-P525UL / NP-P525WL<br>NP-P506QL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE506UL / NP-PE506WL<br>NP-PE401H<br>NP-PA1004UL / NP-PA804UL<br>NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br>NP-PX2000UL<br>NP-PX1005QL<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |
|      |                |                             |     | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |

|      |                  |                                                                                                                                                                                                                                                     |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|------|------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 23.0 | January 11, 2022 | <p>Added the supported models.</p> <p>Corrected the error.<br/>"Input terminal"</p> <p>Added the supporting model name of NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X / NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X / NP-MC342X / NP-MC302X</p> | 7.1 | <p><del>NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X</del><br/><del>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X</del></p> <p>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br/>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br/>NP-MC342X / NP-MC302X</p> <p>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br/>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br/>NP-ME360X / NP-ME310X / NP-ME270X</p> <p>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br/>NP-P603X / NP-P523X / NP-PE523X<br/>NP-P605UL / NP-P525UL / NP-P525WL<br/>NP-P506QL<br/>NP-P502HL / NP-P502WL<br/>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br/>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br/>NP-P420X / NP-P350X / NP-P350W<br/>NP-PE401H</p> <p>NP-PA1004UL / NP-PA804UL<br/>NP-PA803UL / NP-PA703UL / NP-PA653UL<br/>NP-PA803U / NP-PA723U / NP-PA653U /<br/>NP-PA853W / NP-PA703W / NP-PA903X<br/>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br/>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br/>NP-PA721X / NP-PA621X<br/>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br/>NP-PH3501QL / NP-PH2601QL<br/>NP-PH1400U<br/>NP-PH1202HL / NP-PH1002HL<br/>NP-PH1000U<br/>NP-PX2000UL<br/>NP-PX1005QL<br/>NP-PX1004UL<br/>NP-PX803UL<br/>NP-PX750U / NP-PX700W / NP-PX800X<br/>NP-PX651X / NP-PX581W<br/>NP-PX620X / NP-PX550W<br/>NP-PX602UL / NP-PX602WL<br/>NP-U321H<br/>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br/>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br/>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br/>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br/>NP-V311W / NP-V281W / NP-V311X<br/>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /<br/>NP-V230 / NP-V260R<br/>NP-VE303X / NP-VE303<br/>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p> |
| 22.0 | January 26, 2021 | Added the supported models.                                                                                                                                                                                                                         | 7.1 | <p>NP4100 / NP4100W<br/>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /<br/>NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /<br/>NP-M260XS / NP-M300WS / NP-M260WS</p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /<br/>NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /<br/>NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br/>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br/>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br/>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br/><del>NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X</del><br/><del>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X</del><br/><del>NP-MC342X / NP-MC302X</del></p> <p>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br/>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br/>NP-ME360X / NP-ME310X / NP-ME270X</p> <p>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br/>NP-P603X / NP-P523X / NP-PE523X<br/>NP-P605UL / NP-P525UL / NP-P525WL<br/>NP-P506QL<br/>NP-P502HL / NP-P502WL<br/>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br/>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br/>NP-P420X / NP-P350X / NP-P350W<br/>NP-PE401H</p> <p>NP-PA1004UL / NP-PA804UL<br/>NP-PA803UL / NP-PA703UL / NP-PA653UL<br/>NP-PA803U / NP-PA723U / NP-PA653U /<br/>NP-PA853W / NP-PA703W / NP-PA903X<br/>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br/>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br/>NP-PA721X / NP-PA621X<br/>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br/>NP-PH3501QL / NP-PH2601QL<br/>NP-PH1400U<br/>NP-PH1202HL / NP-PH1002HL<br/>NP-PH1000U</p>                                                                                                                                                                  |

|      |                  |                             |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|------|------------------|-----------------------------|-----|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|      |                  |                             |     | <p>NP-PX2000UL<br/> NP-PX1005QL<br/> NP-PX1004UL<br/> NP-PX803UL<br/> NP-PX750U / NP-PX700W / NP-PX800X<br/> NP-PX651X / NP-PX581W<br/> NP-PX620X / NP-PX550W<br/> NP-PX602UL / NP-PX602WL<br/> NP-U321H<br/> NP-U300X / NP-U250X / NP-U310W / NP-U260W<br/> NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br/> NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br/> NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br/> NP-V311W / NP-V281W / NP-V311X<br/> NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br/> NP-VE303X / NP-VE303<br/> NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| 21.0 | October 26, 2020 | Added the supported models. | 7.1 | <p>NP4100 / NP4100W<br/> NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br/> NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br/> NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br/> NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br/> NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br/> NP-ME360X / NP-ME310X / NP-ME270X<br/> NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br/> NP-P605UL / NP-P525UL / NP-P525WL<br/> NP-P506QL<br/> NP-P502HL / NP-P502WL<br/> NP-P502H / NP-P502W / NP-P452H / NP-P452W<br/> NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br/> NP-P420X / NP-P350X / NP-P350W<br/> NP-PE401H<br/> NP-PA1004UL / NP-PA804UL<br/> NP-PA803UL / NP-PA703UL / NP-PA653UL<br/> NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br/> NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br/> NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br/> NP-PH3501QL / NP-PH2601QL<br/> NP-PH1400U<br/> NP-PH1202HL / NP-PH1002HL<br/> NP-PH1000U<br/> NP-PX2000UL<br/> NP-PX1005QL<br/> NP-PX1004UL<br/> NP-PX803UL<br/> NP-PX750U / NP-PX700W / NP-PX800X<br/> NP-PX651X / NP-PX581W<br/> NP-PX620X / NP-PX550W<br/> NP-PX602UL / NP-PX602WL<br/> NP-U321H<br/> NP-U300X / NP-U250X / NP-U310W / NP-U260W<br/> NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br/> NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br/> NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br/> NP-V311W / NP-V281W / NP-V311X<br/> NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br/> NP-VE303X / NP-VE303<br/> NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p> |
|      |                  |                             |     | <p>NP4100 / NP4100W<br/> NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br/> NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br/> NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br/> NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br/> NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br/> NP-ME360X / NP-ME310X / NP-ME270X</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |

|      |                    |                                                                                                                                              |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|------|--------------------|----------------------------------------------------------------------------------------------------------------------------------------------|-----|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 20.0 | April 16, 2020     | <p>Added the supported models.</p> <p>Corrected the error.<br/>"Input terminal"<br/>Modified Model name from NP-PH1005QL to NP-PX1005QL.</p> | 7.1 | <p>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br/>NP-P605UL / NP-P525UL / NP-P525WL<br/>NP-P502HL / NP-P502WL<br/>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br/>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br/>NP-P420X / NP-P350X / NP-P350W<br/>NP-PE401H<br/><i>NP-PA1004UL / NP-PA804UL</i><br/>NP-PA803UL / NP-PA653UL<br/>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br/>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br/>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br/>NP-PH3501QL / NP-PH2601QL<br/>NP-PH1400U<br/>NP-PH1202HL / NP-PH1002HL<br/>NP-PH1000U<br/><i>NP-PX2000UL</i><br/>NP-PX1005QL<br/>NP-PX1004UL<br/>NP-PX803UL<br/>NP-PX750U / NP-PX700W / NP-PX800X<br/>NP-PX651X / NP-PX581W<br/>NP-PX620X / NP-PX550W<br/>NP-PX602UL / NP-PX602WL<br/>NP-U321H<br/>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br/>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br/>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br/>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br/>NP-V311W / NP-V281W / NP-V311X<br/>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br/>NP-VE303X / NP-VE303<br/>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| 19.0 | September 30, 2019 | Added the supported models.                                                                                                                  | 7.0 | <p>NP4100 / NP4100W<br/>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br/>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br/>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br/>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br/>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br/>NP-ME360X / NP-ME310X / NP-ME270X<br/>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br/><i>NP-P605UL</i> / NP-P525UL / NP-P525WL<br/>NP-P502HL / NP-P502WL<br/>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br/>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br/>NP-P420X / NP-P350X / NP-P350W<br/>NP-PE401H<br/>NP-PA803UL / NP-PA653UL<br/>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br/>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br/>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br/>NP-PH3501QL / NP-PH2601QL<br/>NP-PH1400U<br/>NP-PH1202HL / NP-PH1002HL<br/>NP-PH1000U<br/>NP-PX1005QL<br/>NP-PX1004UL<br/>NP-PX803UL<br/>NP-PX750U / NP-PX700W / NP-PX800X<br/>NP-PX651X / NP-PX581W<br/>NP-PX620X / NP-PX550W<br/>NP-PX602UL / NP-PX602WL<br/>NP-U321H<br/>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br/>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br/>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br/>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br/>NP-V311W / NP-V281W / NP-V311X</p> |



|      |                |                             |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|------|----------------|-----------------------------|-----|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|      |                |                             |     | NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 18.0 | April 24, 2019 | Added the supported models. | 7.0 | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br>NP-P525UL / NP-P525WL<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE401H<br>NP-PA803UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br><i>NP-PX1005QL</i><br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |
| 17.0 | March 27, 2019 | Added the supported models. | 7.0 | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br><i>NP-P525UL / NP-P525WL</i><br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE401H<br>NP-PA803UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |

|      |                  |                                                                                                                                                                                                                                                                       |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|------|------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|      |                  |                                                                                                                                                                                                                                                                       |     | NP-PH1000U<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| 16.0 | July 6, 2018     | Added the supported models.<br><br>Corrected the error.<br>"3. Supported Command List"<br>NP-PA803UL / NP-PA653UL<br>does NOT support the following command.<br>037-3. FILTER USAGE<br>INFORMATION REQUEST                                                            | 7.0 | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE401H<br>NP-PA803UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH3501QL / NP-PH2601QL<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br>NP-PX1004UL<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |
| 15.1 | January 17, 2018 | Corrected the error.<br>■ Selection signal type<br>078-3. INPUT STATUS<br>REQUEST<br>305-3. BASIC INFORMATION<br>REQUEST<br>Model name : NP-PA803UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>Input terminal : HDBaseT | 6.1 | Same as Revision 15.0.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|      |                  |                                                                                                                                                                                                                                                                       |     | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |

|      |                   |                               |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|------|-------------------|-------------------------------|-----|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 15.0 | November 10, 2017 | Added the supported models.   | 6.1 | NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE401H<br><i>NP-PA803UL / NP-PA653UL</i><br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br><i>NP-PX1004UL</i><br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                                                                                                                                                                                      |
| 14.0 | July 3, 2017      | Added the supported models.   | 6.1 | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS<br>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X<br>NP-ME360X / NP-ME310X / NP-ME270X<br><i>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X</i><br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE401H<br>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH1400U<br>NP-PH1202HL / NP-PH1002HL<br>NP-PH1000U<br>NP-PX803UL<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX651X / NP-PX581W<br>NP-PX620X / NP-PX550W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-VE303X / NP-VE303<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |
| 13.1 | May 15, 2017      | Updated the Reference number. | 6.1 | Same as Revision 13.0.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |

|      |                  |                                                                                                                                                                                                |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|------|------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 13.0 | January 11, 2017 | <p>Added the supported models.</p> <p>Added the following commands in sheet "3. Supported Command List".</p> <p>051. LENS MUTE ON (SHUTTER CLOSE)</p> <p>052. LENS MUTE OFF (SHUTTER OPEN)</p> | 6.0 | <p>NP4100 / NP4100W</p> <p>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p> <p>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X</p> <p>NP-ME360X / NP-ME310X / NP-ME270X</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</p> <p>NP-P420X / NP-P350X / NP-P350W</p> <p>NP-PE401H</p> <p><i>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X</i></p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</p> <p>NP-PH1400U</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PH1000U</p> <p>NP-PX803UL</p> <p>NP-PX750U / NP-PX700W / NP-PX800X</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX620X / NP-PX550W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p>NP-U300X / NP-U250X / NP-U310W / NP-U260W</p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p>NP-V311W / NP-V281W / NP-V311X</p> <p>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R</p> <p>NP-VE303X / NP-VE303</p> <p>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p> |
| 12.0 | October 25, 2016 | Added the supported models.                                                                                                                                                                    | 5.0 | <p>NP4100 / NP4100W</p> <p>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p> <p><i>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X</i></p> <p>NP-ME360X / NP-ME310X / NP-ME270X</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</p> <p>NP-P420X / NP-P350X / NP-P350W</p> <p>NP-PE401H</p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</p> <p>NP-PH1400U</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PH1000U</p> <p>NP-PX803UL</p> <p>NP-PX750U / NP-PX700W / NP-PX800X</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX620X / NP-PX550W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p>NP-U300X / NP-U250X / NP-U310W / NP-U260W</p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p>NP-V311W / NP-V281W / NP-V311X</p> <p>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R</p> <p>NP-VE303X / NP-VE303</p> <p>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>                                                                              |
|      |                  |                                                                                                                                                                                                |     | NP4100 / NP4100W                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |

|      |                   |                                                                                                                                                                                             |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|------|-------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 11.0 | February 29, 2016 | <p>Added the supported models.</p> <p>Corrected [Aspect] sheet. ("WIDE ZOOM" is enabled by the WXGA model, and "LETTERBOX" is enabled by a XGA model about M403 / M402 / UM351 Series.)</p> | 5.0 | <p>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p> <p>NP-ME360X / NP-ME310X / NP-ME270X</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</p> <p>NP-P420X / NP-P350X / NP-P350W</p> <p>NP-PE401H</p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</p> <p>NP-PH1400U</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PH1000U</p> <p>NP-PX803UL</p> <p>NP-PX750U / NP-PX700W / NP-PX800X</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX620X / NP-PX550W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p>NP-U300X / NP-U250X / NP-U310W / NP-U260W</p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p>NP-V311W / NP-V281W / NP-V311X</p> <p>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R</p> <p><del>NP-VE303X / NP-VE303</del></p> <p>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>                                                                                                                                                                             |
| 10.0 | February 17, 2016 | <p>Added the supported models.<br/>(Added the models supported at Revision1.0)</p>                                                                                                          | 5.0 | <p><del>NP4100 / NP4100W</del></p> <p><del>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</del></p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p><del>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</del></p> <p><del>NP-ME360X / NP-ME310X / NP-ME270X</del></p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p><del>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</del></p> <p><del>NP-P420X / NP-P350X / NP-P350W</del></p> <p><del>NP-PE401H</del></p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p><del>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</del></p> <p><del>NP-PH1400U</del></p> <p>NP-PH1202HL / NP-PH1002HL</p> <p><del>NP-PH1000U</del></p> <p>NP-PX803UL</p> <p><del>NP-PX750U / NP-PX700W / NP-PX800X</del></p> <p>NP-PX651X / NP-PX581W</p> <p><del>NP-PX620X / NP-PX550W</del></p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p><del>NP-U300X / NP-U250X / NP-U310W / NP-U260W</del></p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p><del>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</del></p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p><del>NP-V311W / NP-V281W / NP-V311X</del></p> <p><del>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R</del></p> <p><del>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</del></p> |
| 9.0  | January 6, 2016   | Added the Copyright on all pages.                                                                                                                                                           | 5.0 | Same as Revision 8.0.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |

|     |                    |                                                                                                                                               |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|-----|--------------------|-----------------------------------------------------------------------------------------------------------------------------------------------|-----|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 8.0 | December 21, 2015  | Added the supported models.                                                                                                                   | 4.0 | NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PH1202HL / NP-PH1002HL<br>NP-PX651X / NP-PX581W<br>NP-PX602UL / NP-PX602WL<br>NP-PX803UL<br>NP-U321H<br>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H |
| 7.0 | December 11, 2015  | Added the supported models.                                                                                                                   | 4.0 | NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-P502HL / NP-P502WL<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PH1202HL / NP-PH1002HL<br>NP-PX651X / NP-PX581W<br>NP-PX602UL / NP-PX602WL<br>NP-PX803UL<br>NP-U321H<br>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                              |
| 6.0 | September 28, 2015 | Added the supported models.                                                                                                                   | 3.0 | NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-P502HL / NP-P502WL<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PH1202HL / NP-PH1002HL<br>NP-PX651X / NP-PX581W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                            |
| 5.0 | August 7, 2015     | Added the supported models.                                                                                                                   | 3.0 | NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PH1202HL / NP-PH1002HL<br>NP-PX651X / NP-PX581W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                     |
| 4.0 | August 3, 2015     | Added the supported models.<br>Corrected [3. Supported Command List] sheet.<br>(NP-U321H : "024. ONSCREEN MUTE ON" command is not supported.) | 3.0 | NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X<br>NP-PH1202HL / NP-PH1002HL<br>NP-PX651X / NP-PX581W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W<br>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                     |
| 3.0 | June 16, 2015      | Added the supported command.                                                                                                                  | 3.0 | Same as Revision 2.0.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |

|     |                 |                                                                |     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|-----|-----------------|----------------------------------------------------------------|-----|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 2.0 | May 29, 2015    | Changed the supported models.<br>Added the supported commands. | 2.0 | NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PH1202HL / NP-PH1002HL<br>NP-PX651X / NP-PX581W<br>NP-PX602UL / NP-PX602WL<br>NP-U321H<br>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 1.0 | August 22, 2014 | First version                                                  | 1.0 | NP4100 / NP4100W<br>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X /<br>NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS<br>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /<br>NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS<br>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W<br>NP-ME360X / NP-ME310X / NP-ME270X<br>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X<br>NP-P420X / NP-P350X / NP-P350W<br>NP-PE401H<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /<br>NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X<br>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U<br>NP-PH1400U<br>NP-PH1000U<br>NP-PX750U / NP-PX700W / NP-PX800X<br>NP-PX620X / NP-PX550W<br>NP-U300X / NP-U250X / NP-U310W / NP-U260W<br>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W<br>NP-V311W / NP-V281W / NP-V311X<br>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /<br>NP-V230 / NP-V260R<br>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280 |

## Contents

---

|                                                       |    |
|-------------------------------------------------------|----|
| <b>1. Connecting an External Device</b>               | 17 |
| <b>2. Standby Mode setting for receiving commands</b> | 18 |
| <b>3. Supported Command List</b>                      | 19 |
| <b>4. Supplementary Information by Command</b>        |    |
| Input terminal                                        | 25 |
| [018. INPUT SW CHANGE]                                |    |
| Aspect                                                | 29 |
| [030-12. ASPECT ADJUST]                               |    |
| Eco mode                                              | 31 |
| [097-8. ECO MODE REQUEST]                             |    |
| [098-8. ECO MODE SET]                                 |    |
| Base model type                                       | 32 |
| [078-1. SETTING REQUEST]                              |    |
| [305-1. BASE MODEL TYPE REQUEST]                      |    |
| Selection signal type                                 | 37 |
| [078-3. INPUT STATUS REQUEST]                         |    |
| [305-3. BASIC INFORMATION REQUEST]                    |    |
| Sub input                                             | 43 |
| [097-198. PIP/PICTURE BY PICTURE REQUEST]             |    |
| [098-198. PIP/PICTURE BY PICTURE SET]                 |    |
| Audio Select                                          | 45 |
| [319-10. AUDIO SELECT SET]                            |    |



# 1. Connecting an External Device

<Conventions>  
 ○ : Supported  
 — : Not supported

## ■ Projector

| Model name                                                                                                                                                                        | Serial port |         |          |          |           | LAN port | Wireless LAN unit |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|---------|----------|----------|-----------|----------|-------------------|
|                                                                                                                                                                                   | 4800bps     | 9600bps | 19200bps | 38400bps | 115200bps |          |                   |
| NP4100 / NP4100W                                                                                                                                                                  | ○           | ○       | ○        | ○        | —         | ○        | —                 |
| NP-M430WL / NP-M380HL                                                                                                                                                             | —           | —       | —        | ○        | —         | —        | —                 |
| NP-M420X / NP-M420XV<br>NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                         | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                              | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                                 | ○           | ○       | ○        | —        | —         | —        | —                 |
| NP-P627UL / NP-P547UL                                                                                                                                                             | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X                                                                                         | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-P506QL                                                                                                                                                                         | —           | ○       | —        | —        | —         | ○        | —                 |
| NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                         | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                                    | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          | ○           | ○       | ○        | ○        | ○         | ○        | ○                 |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                     | ○           | ○       | ○        | ○        | ○         | ○        | ○                 |
| NP-PE506UL / NP-PE506WL                                                                                                                                                           | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-PE501X                                                                                                                                                                         | ○           | ○       | ○        | ○        | —         | —        | —                 |
| NP-PE456USL / NP-PE456WSL                                                                                                                                                         | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-PE401H                                                                                                                                                                         | —           | —       | —        | ○        | —         | ○        | —                 |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PH1400U                                                                                                                                                                        | ○           | ○       | ○        | ○        | ○         | ○        | ○                 |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PH1000U                                                                                                                                                                        | ○           | ○       | ○        | ○        | ○         | ○        | ○                 |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              | ○           | ○       | ○        | ○        | —         | ○        | —                 |
| NP-PV710UL+                                                                                                                                                                       | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PX2201UL                                                                                                                                                                       | —           | ○       | —        | —        | —         | ○        | —                 |
| NP-PX2000UL                                                                                                                                                                       | —           | ○       | —        | —        | —         | ○        | —                 |
| NP-PX1005QL                                                                                                                                                                       | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PX1004UL<br>NP-PX803UL                                                                                                                                                         | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                                 | ○           | ○       | ○        | ○        | ○         | ○        | ○                 |
| NP-PX651X / NP-PX581W                                                                                                                                                             | —           | ○       | ○        | ○        | —         | ○        | —                 |
| NP-PX620X / NP-PX550W                                                                                                                                                             | ○           | ○       | ○        | ○        | —         | ○        | —                 |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           | ○           | ○       | ○        | ○        | ○         | ○        | —                 |
| NP-U321H                                                                                                                                                                          | —           | —       | —        | ○        | —         | ○        | —                 |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                         | —           | —       | —        | ○        | —         | ○        | —                 |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X<br>NP-UM352W                                                                                                                        | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                     | ○           | ○       | ○        | ○        | —         | ○        | ○                 |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              | —           | —       | —        | ○        | —         | ○        | —                 |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                                    | ○           | ○       | ○        | ○        | —         | ○        | —                 |
| NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                         | ○           | ○       | ○        | ○        | —         | ○        | —                 |
| NP-V230X / NP-V260 / NP-V230 / NP-V260R                                                                                                                                           | ○           | ○       | ○        | ○        | —         | —        | —                 |
| NP-VE303X / NP-VE303                                                                                                                                                              | —           | —       | —        | ○        | —         | —        | —                 |
| NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                       | ○           | ○       | ○        | ○        | —         | —        | —                 |

## 2. Standby Mode setting for receiving commands

The Standby Mode setting that can receive commands is different depending on the model.  
Please see the table below.

**Target command: "015. POWER ON"**

### ■ Projector

| Model name                                                                                                                                                                        | Setting of the Standby Mode           |                                      |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------|--------------------------------------|
|                                                                                                                                                                                   | When connected using a serial cable   | When connected using via a wired LAN |
| NP4100 / NP4100W                                                                                                                                                                  | Normal                                | Normal                               |
| NP-M430WL / NP-M380HL                                                                                                                                                             | Active, Eco                           |                                      |
| NP-M420X / NP-M420XV<br>NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                         | NORMAL, POWER-SAVING                  | NORMAL                               |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                              | NORMAL, POWER-SAVING                  | NORMAL                               |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-ME401W / NP-ME361W / NP-ME311W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                                 | NORMAL, POWER-SAVING                  |                                      |
| NP-P627UL / NP-P547UL                                                                                                                                                             | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X                                                                                         | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-P506QL                                                                                                                                                                         | Normal, Network standby, HDBaseT      | Network standby, HDBaseT             |
| NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                         | NORMAL, POWER-SAVING, NETWORK STANDBY | NORMAL, NETWORK STANDBY              |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                                    | NORMAL, POWER-SAVING                  | NORMAL                               |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         | OFF, ON                               | OFF, ON                              |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          | OFF, ON                               | OFF, ON                              |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  | NORMAL, SLEEP                         | NORMAL, SLEEP                        |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          | NORMAL, HTBaseT STANDBY               | HTBaseT STANDBY                      |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                     | NORMAL, POWER-SAVING, NETWORK STANDBY | NORMAL, NETWORK STANDBY              |
| NP-PE506UL / NP-PE506WL                                                                                                                                                           | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-PE501X                                                                                                                                                                         | NORMAL, POWER-SAVING                  |                                      |
| NP-PE456USL / NP-PE456WSL                                                                                                                                                         | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-PE401H                                                                                                                                                                         | NORMAL                                | NORMAL                               |
| NP-PH1400U                                                                                                                                                                        | NORMAL, POWER-SAVING, NETWORK STANDBY | NORMAL, NETWORK STANDBY              |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-PH1000U                                                                                                                                                                        | NORMAL, POWER-SAVING, NETWORK STANDBY | NORMAL, NETWORK STANDBY              |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              | NORMAL, NETWORK STANDBY, SLEEP        | NETWORK STANDBY, SLEEP               |
| NP-PV710UL+                                                                                                                                                                       | OFF, ON                               | OFF, ON                              |
| ※ NP-PX2201UL                                                                                                                                                                     | STANDBY POWER ON                      | STANDBY POWER ON                     |
| ※ NP-PX2000UL                                                                                                                                                                     | STANDBY POWER ON                      | STANDBY POWER ON                     |
| NP-PX1005QL                                                                                                                                                                       | NORMAL, SLEEP                         | NORMAL, SLEEP                        |
| NP-PX1004UL<br>NP-PX803UL                                                                                                                                                         | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                                 | NORMAL, POWER-SAVING, NETWORK STANDBY | NORMAL, NETWORK STANDBY              |
| NP-PX651X / NP-PX581W                                                                                                                                                             | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-PX620X / NP-PX550W                                                                                                                                                             | Normal                                | Normal                               |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-U321H                                                                                                                                                                          | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                         | Normal                                | Normal                               |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X<br>NP-UM352W                                                                                                                        | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                     | NORMAL, POWER-SAVING                  | NORMAL                               |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              | NORMAL, NETWORK STANDBY               | NETWORK STANDBY                      |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                                    | NORMAL, POWER-SAVING                  | NORMAL                               |
| NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                         | NORMAL, POWER-SAVING                  | NORMAL                               |
| NP-V230X / NP-V260 / NP-V230 / NP-V260R                                                                                                                                           | NORMAL, POWER-SAVING                  |                                      |
| NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                       | NORMAL, POWER-SAVING                  |                                      |

※ The following models use a different menu item name.

・ NP-PX2000UL/ NP-PX2201UL: STANDBY POWER

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 — : Not supported

#### ■ Projector

| Command                                   | NP4100<br>NP4100W<br>(firmware<br>version<br>1.02 or later) | NP-M430WL<br>NP-M380HL | NP-M420X<br>NP-M350X<br>NP-M300X<br>NP-M260X<br>NP-M230X<br>NP-M300W<br>NP-M260W | NP-M420XV | NP-M403X<br>NP-M363X<br>NP-M323X<br>NP-M283X<br>NP-M403W<br>NP-M363W<br>NP-M323W<br>NP-M333XS<br>NP-M353WS<br>NP-M303WS<br>NP-M403H<br>NP-M323H<br>NP-M353HS<br>NP-M323HS<br>NP-M303HS | NP-M402W<br>NP-M362W<br>NP-M402X<br>NP-M362X<br>NP-M322X<br>NP-M282X<br>NP-M322W<br>NP-M352WS<br>NP-M302WS<br>NP-M332XS | NP-M361X<br>NP-M311X<br>NP-M271X<br>NP-M311W<br>NP-M271W | NP-ME403U<br>NP-ME423W<br>NP-ME363W<br>NP-ME453X<br>NP-MC423W<br>NP-MC393W<br>NP-MC453X<br>NP-MC363X | NP-ME382U<br>NP-ME342U<br>NP-ME372W<br>NP-ME402X<br>NP-MC382W<br>NP-MC332W<br>NP-MC422X<br>NP-MC372X<br>NP-MC342X<br>NP-MC302X |
|-------------------------------------------|-------------------------------------------------------------|------------------------|----------------------------------------------------------------------------------|-----------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------|------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|
| 009. ERROR STATUS REQUEST                 | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 015. POWER ON                             | ○                                                           | ○                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 016. POWER OFF                            | ○                                                           | ○                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 018. INPUT SW CHANGE                      | ○                                                           | ○                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 020. PICTURE MUTE ON                      | ○                                                           | ○                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 021. PICTURE MUTE OFF                     | ○                                                           | ○                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 022. SOUND MUTE ON                        | ○                                                           | ○                      | ○                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 023. SOUND MUTE OFF                       | ○                                                           | ○                      | ○                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 024. ONSCREEN MUTE ON                     | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | —                                                                                                    | ○                                                                                                                              |
| 025. ONSCREEN MUTE OFF                    | ○                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 030-1. PICTURE ADJUST                     | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 030-2. VOLUME ADJUST                      | ○                                                           | —                      | ○                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 030-12. ASPECT ADJUST                     | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 030-15. OTHER ADJUST                      | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 037. INFORMATION REQUEST                  | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 037-3. FILTER USAGE INFORMATION REQUEST   | —                                                           | —                      | ○                                                                                | ○         | —                                                                                                                                                                                      | —                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 037-4. LAMP INFORMATION REQUEST 3         | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 037-6. CARBON SAVINGS INFORMATION REQUEST | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 050. REMOTE KEY CODE                      | —                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 051. LENS MUTE ON (SHUTTER CLOSE)         | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 052. LENS MUTE OFF (SHUTTER OPEN)         | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053. LENS CONTROL                         | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-1. LENS CONTROL REQUEST               | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-2. LENS CONTROL 2                     | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-3. LENS MEMORY CONTROL                | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-4. REFERENCE LENS MEMORY CONTROL      | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-5. LENS MEMORY OPTION REQUEST         | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-6. LENS MEMORY OPTION SET             | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-7. LENS INFORMATION REQUEST           | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-10. LENS PROFILE SET                  | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 053-11. LENS PROFILE REQUEST              | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 060-1. GAIN PARAMETER REQUEST 3           | ○                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 078-1. SETTING REQUEST                    | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 078-2. RUNNING STATUS REQUEST             | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 078-3. INPUT STATUS REQUEST               | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 078-4. MUTE STATUS REQUEST                | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 078-5. MODEL NAME REQUEST                 | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 078-6. COVER STATUS REQUEST               | —                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | —                                                                                                    | —                                                                                                                              |
| 079. FREEZE CONTROL                       | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 084. INFORMATION STRING REQUEST           | —                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 097-8. ECO MODE REQUEST                   | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 097-45. LAN PROJECTOR NAME REQUEST        | —                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 097-155. LAN MAC ADDRESS STATUS REQUEST2  | —                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | —                                                                                                    | ○                                                                                                                              |
| 097-198. PIP/PICTURE BY PICTURE REQUEST   | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 097-243-1. EDGE BLENDING MODE REQUEST     | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 098-8. ECO MODE SET                       | —                                                           | —                      | —                                                                                | —         | ○                                                                                                                                                                                      | ○                                                                                                                       | —                                                        | ○                                                                                                    | ○                                                                                                                              |
| 098-45. LAN PROJECTOR NAME SET            | —                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | —                                                                                                    | ○                                                                                                                              |
| 098-198. PIP/PICTURE BY PICTURE SET       | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 098-243-1. EDGE BLENDING MODE SET         | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |
| 305-1. BASE MODEL TYPE REQUEST            | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 305-2. SERIAL NUMBER REQUEST              | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 305-3. BASIC INFORMATION REQUEST          | ○                                                           | —                      | ○                                                                                | ○         | ○                                                                                                                                                                                      | ○                                                                                                                       | ○                                                        | ○                                                                                                    | ○                                                                                                                              |
| 319-10. AUDIO SELECT SET                  | —                                                           | —                      | —                                                                                | —         | —                                                                                                                                                                                      | —                                                                                                                       | —                                                        | —                                                                                                    | —                                                                                                                              |

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 — : Not supported

#### ■ Projector

| Command                                   | NP-M350XS<br>NP-M300XS<br>NP-M260XS<br>NP-M300WS<br>NP-M260WS | NP-ME401W<br>NP-ME361W<br>NP-ME331W<br>NP-ME301W<br>NP-ME401X<br>NP-ME361X<br>NP-ME331X<br>NP-ME301X | NP-ME360X<br>NP-ME310X<br>NP-ME270X | NP-P627UL<br>NP-P547UL | NP-P654U<br>NP-P474U<br>NP-P554W<br>NP-P474W<br>NP-P604X<br>NP-P603X<br>NP-P523X<br>NP-PE523X | NP-P605UL<br>NP-P525UL<br>NP-P525WL | NP-P506QL | NP-P502HL<br>NP-P502WL<br>NP-P502H<br>NP-P502W<br>NP-P452H<br>NP-P452W | NP-P501X<br>NP-P451X<br>NP-P451W<br>NP-P401W |
|-------------------------------------------|---------------------------------------------------------------|------------------------------------------------------------------------------------------------------|-------------------------------------|------------------------|-----------------------------------------------------------------------------------------------|-------------------------------------|-----------|------------------------------------------------------------------------|----------------------------------------------|
| 009. ERROR STATUS REQUEST                 | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 015. POWER ON                             | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 016. POWER OFF                            | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 018. INPUT SW CHANGE                      | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 020. PICTURE MUTE ON                      | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 021. PICTURE MUTE OFF                     | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 022. SOUND MUTE ON                        | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 023. SOUND MUTE OFF                       | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 024. ONSCREEN MUTE ON                     | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 025. ONSCREEN MUTE OFF                    | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | ○         | ○                                                                      | —                                            |
| 030-1. PICTURE ADJUST                     | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 030-2. VOLUME ADJUST                      | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 030-12. ASPECT ADJUST                     | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 030-15. OTHER ADJUST                      | —                                                             | —                                                                                                    | —                                   | ○                      | —                                                                                             | ○                                   | ○         | —                                                                      | —                                            |
| 037. INFORMATION REQUEST                  | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 037-3. FILTER USAGE INFORMATION REQUEST   | ○                                                             | ○                                                                                                    | ○                                   | —                      | ○                                                                                             | —                                   | —         | —                                                                      | ○                                            |
| 037-4. LAMP INFORMATION REQUEST 3         | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 037-6. CARBON SAVINGS INFORMATION REQUEST | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | —         | ○                                                                      | —                                            |
| 050. REMOTE KEY CODE                      | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 051. LENS MUTE ON (SHUTTER CLOSE)         | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 052. LENS MUTE OFF (SHUTTER OPEN)         | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053. LENS CONTROL                         | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-1. LENS CONTROL REQUEST               | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-2. LENS CONTROL 2                     | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-3. LENS MEMORY CONTROL                | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-4. REFERENCE LENS MEMORY CONTROL      | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-5. LENS MEMORY OPTION REQUEST         | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-6. LENS MEMORY OPTION SET             | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-7. LENS INFORMATION REQUEST           | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-10. LENS PROFILE SET                  | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 053-11. LENS PROFILE REQUEST              | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 060-1. GAIN PARAMETER REQUEST 3           | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | —                                                                      | —                                            |
| 078-1. SETTING REQUEST                    | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 078-2. RUNNING STATUS REQUEST             | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 078-3. INPUT STATUS REQUEST               | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 078-4. MUTE STATUS REQUEST                | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 078-5. MODEL NAME REQUEST                 | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 078-6. COVER STATUS REQUEST               | —                                                             | —                                                                                                    | —                                   | ○                      | —                                                                                             | ○                                   | —         | —                                                                      | ○                                            |
| 079. FREEZE CONTROL                       | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 084. INFORMATION STRING REQUEST           | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | —         | ○                                                                      | ○                                            |
| 097-8. ECO MODE REQUEST                   | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 097-45. LAN PROJECTOR NAME REQUEST        | ○                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 097-155. LAN MAC ADDRESS STATUS REQUEST2  | ○                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 097-198. PIP/PICTURE BY PICTURE REQUEST   | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | ○                                   | —         | —                                                                      | —                                            |
| 097-243-1. EDGE BLENDING MODE REQUEST     | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 098-8. ECO MODE SET                       | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | —                                            |
| 098-45. LAN PROJECTOR NAME SET            | ○                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○                                   | —         | ○                                                                      | ○                                            |
| 098-198. PIP/PICTURE BY PICTURE SET       | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | ○                                   | —         | —                                                                      | —                                            |
| 098-243-1. EDGE BLENDING MODE SET         | —                                                             | —                                                                                                    | —                                   | —                      | —                                                                                             | —                                   | —         | —                                                                      | —                                            |
| 305-1. BASE MODEL TYPE REQUEST            | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 305-2. SERIAL NUMBER REQUEST              | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 305-3. BASIC INFORMATION REQUEST          | ○                                                             | ○                                                                                                    | ○                                   | ○                      | ○                                                                                             | ○                                   | ○         | ○                                                                      | ○                                            |
| 319-10. AUDIO SELECT SET                  | —                                                             | ○                                                                                                    | —                                   | ○                      | ○                                                                                             | ○(Ver. 2.00 or later)               | —         | ○                                                                      | —                                            |

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 — : Not supported

#### ■ Projector

| Command                                   | NP-P420X<br>NP-P350X<br>NP-P350W | NP-PA1705UL<br>NP-PA1505UL | NP-PA1004UL<br>NP-PA804UL | NP-PA803UL<br>NP-PA703UL<br>NP-PA653UL | NP-PA803U<br>NP-PA723U<br>NP-PA653U<br>NP-PA853W<br>NP-PA703W<br>NP-PA903X | NP-PA622U<br>NP-PA522U<br>NP-PA672W<br>NP-PA572W<br>NP-PA722X<br>NP-PA622X<br>NP-PA621U<br>NP-PA521U<br>NP-PA671W<br>NP-PA571W<br>NP-PA721X<br>NP-PA621X | NP-PA600X<br>NP-PA500X<br>NP-PA550W<br>NP-PA500U | NP-PE506UL<br>NP-PE506WL | NP-PE501X |
|-------------------------------------------|----------------------------------|----------------------------|---------------------------|----------------------------------------|----------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------|--------------------------|-----------|
| 009. ERROR STATUS REQUEST                 | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 015. POWER ON                             | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 016. POWER OFF                            | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 018. INPUT SW CHANGE                      | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 020. PICTURE MUTE ON                      | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 021. PICTURE MUTE OFF                     | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 022. SOUND MUTE ON                        | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 023. SOUND MUTE OFF                       | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 024. ONSCREEN MUTE ON                     | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 025. ONSCREEN MUTE OFF                    | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | —         |
| 030-1. PICTURE ADJUST                     | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 030-2. VOLUME ADJUST                      | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 030-12. ASPECT ADJUST                     | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 030-15. OTHER ADJUST                      | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 037. INFORMATION REQUEST                  | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | ○                        | —         |
| 037-3. FILTER USAGE INFORMATION REQUEST   | ○                                | —                          | —                         | —                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 037-4. LAMP INFORMATION REQUEST 3         | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 037-6. CARBON SAVINGS INFORMATION REQUEST | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 050. REMOTE KEY CODE                      | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 051. LENS MUTE ON (SHUTTER CLOSE)         | —                                | ○                          | ○                         | —                                      | —                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 052. LENS MUTE OFF (SHUTTER OPEN)         | —                                | ○                          | ○                         | —                                      | —                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053. LENS CONTROL                         | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-1. LENS CONTROL REQUEST               | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-2. LENS CONTROL 2                     | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-3. LENS MEMORY CONTROL                | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-4. REFERENCE LENS MEMORY CONTROL      | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-5. LENS MEMORY OPTION REQUEST         | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-6. LENS MEMORY OPTION SET             | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-7. LENS INFORMATION REQUEST           | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-10. LENS PROFILE SET                  | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 053-11. LENS PROFILE REQUEST              | —                                | ○                          | ○                         | ○                                      | ○                                                                          | —                                                                                                                                                        | —                                                | —                        | —         |
| 060-1. GAIN PARAMETER REQUEST 3           | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | —         |
| 078-1. SETTING REQUEST                    | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | ○                        | —         |
| 078-2. RUNNING STATUS REQUEST             | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | ○                        | —         |
| 078-3. INPUT STATUS REQUEST               | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 078-4. MUTE STATUS REQUEST                | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 078-5. MODEL NAME REQUEST                 | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | ○                        | —         |
| 078-6. COVER STATUS REQUEST               | ○                                | —                          | —                         | —                                      | —                                                                          | —                                                                                                                                                        | —                                                | —                        | ○         |
| 079. FREEZE CONTROL                       | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 084. INFORMATION STRING REQUEST           | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 097-8. ECO MODE REQUEST                   | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 097-45. LAN PROJECTOR NAME REQUEST        | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 097-155. LAN MAC ADDRESS STATUS REQUEST2  | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 097-198. PIP/PICTURE BY PICTURE REQUEST   | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 097-243-1. EDGE BLENDING MODE REQUEST     | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 098-8. ECO MODE SET                       | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 098-45. LAN PROJECTOR NAME SET            | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | —                        | ○         |
| 098-198. PIP/PICTURE BY PICTURE SET       | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 098-243-1. EDGE BLENDING MODE SET         | —                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |
| 305-1. BASE MODEL TYPE REQUEST            | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 305-2. SERIAL NUMBER REQUEST              | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 305-3. BASIC INFORMATION REQUEST          | ○                                | ○                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | ○                                                | ○                        | ○         |
| 319-10. AUDIO SELECT SET                  | —                                | —                          | ○                         | ○                                      | ○                                                                          | ○                                                                                                                                                        | —                                                | —                        | —         |

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 — : Not supported

#### ■ Projector

| Command                                   | NP-PE456USL<br>NP-PE456WSL | NP-PE401H | NP-PH3501QL<br>NP-PH2601QL | NP-PH1400U | NP-PH1202HL<br>NP-PH1002HL | NP-PH1000U | NP-PV800UL<br>NP-PV730UL<br>NP-PV710UL | NP-PV710UL+ | NP-PX2201UL |
|-------------------------------------------|----------------------------|-----------|----------------------------|------------|----------------------------|------------|----------------------------------------|-------------|-------------|
| 009. ERROR STATUS REQUEST                 | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 015. POWER ON                             | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 016. POWER OFF                            | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 018. INPUT SW CHANGE                      | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 020. PICTURE MUTE ON                      | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 021. PICTURE MUTE OFF                     | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 022. SOUND MUTE ON                        | —                          | ○         | —                          | —          | —                          | —          | ○                                      | ○           | —           |
| 023. SOUND MUTE OFF                       | —                          | ○         | —                          | —          | —                          | —          | ○                                      | ○           | —           |
| 024. ONSCREEN MUTE ON                     | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 025. ONSCREEN MUTE OFF                    | —                          | —         | ○                          | ○          | ○                          | ○          | —                                      | ○           | ○           |
| 030-1. PICTURE ADJUST                     | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 030-2. VOLUME ADJUST                      | —                          | ○         | —                          | —          | —                          | —          | ○                                      | ○           | —           |
| 030-12. ASPECT ADJUST                     | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 030-15. OTHER ADJUST                      | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 037. INFORMATION REQUEST                  | ○                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 037-3. FILTER USAGE INFORMATION REQUEST   | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | —           |
| 037-4. LAMP INFORMATION REQUEST 3         | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 037-6. CARBON SAVINGS INFORMATION REQUEST | —                          | —         | —                          | —          | ○                          | —          | ○                                      | ○           | —           |
| 050. REMOTE KEY CODE                      | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 051. LENS MUTE ON (SHUTTER CLOSE)         | —                          | —         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 052. LENS MUTE OFF (SHUTTER OPEN)         | —                          | —         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 053. LENS CONTROL                         | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 053-1. LENS CONTROL REQUEST               | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | —           |
| 053-2. LENS CONTROL 2                     | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | —           |
| 053-3. LENS MEMORY CONTROL                | —                          | —         | ○                          | —          | ○                          | —          | —                                      | ○           | ○           |
| 053-4. REFERENCE LENS MEMORY CONTROL      | —                          | —         | ○                          | —          | ○                          | —          | —                                      | ○           | ○           |
| 053-5. LENS MEMORY OPTION REQUEST         | —                          | —         | ○                          | —          | ○                          | —          | —                                      | ○           | —           |
| 053-6. LENS MEMORY OPTION SET             | —                          | —         | ○                          | —          | ○                          | —          | —                                      | ○           | —           |
| 053-7. LENS INFORMATION REQUEST           | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | —           |
| 053-10. LENS PROFILE SET                  | —                          | —         | ○                          | —          | ○                          | —          | —                                      | ○           | ○           |
| 053-11. LENS PROFILE REQUEST              | —                          | —         | ○                          | —          | ○                          | —          | —                                      | ○           | ○           |
| 060-1. GAIN PARAMETER REQUEST 3           | —                          | —         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 078-1. SETTING REQUEST                    | ○                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 078-2. RUNNING STATUS REQUEST             | ○                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 078-3. INPUT STATUS REQUEST               | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 078-4. MUTE STATUS REQUEST                | —                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 078-5. MODEL NAME REQUEST                 | ○                          | —         | ○                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 078-6. COVER STATUS REQUEST               | —                          | —         | —                          | ○          | ○                          | ○          | —                                      | —           | —           |
| 079. FREEZE CONTROL                       | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 084. INFORMATION STRING REQUEST           | —                          | —         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | —           |
| 097-8. ECO MODE REQUEST                   | —                          | ○         | —                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 097-45. LAN PROJECTOR NAME REQUEST        | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 097-155. LAN MAC ADDRESS STATUS REQUEST2  | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 097-198. PIP/PICTURE BY PICTURE REQUEST   | —                          | —         | ○                          | —          | ○                          | —          | —                                      | —           | —           |
| 097-243-1. EDGE BLENDING MODE REQUEST     | —                          | —         | ○                          | —          | ○                          | —          | —                                      | —           | ○           |
| 098-8. ECO MODE SET                       | —                          | —         | —                          | —          | ○                          | —          | ○                                      | ○           | ○           |
| 098-45. LAN PROJECTOR NAME SET            | —                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 098-198. PIP/PICTURE BY PICTURE SET       | —                          | —         | ○                          | —          | ○                          | —          | —                                      | —           | —           |
| 098-243-1. EDGE BLENDING MODE SET         | —                          | —         | ○                          | —          | ○                          | —          | —                                      | —           | ○           |
| 305-1. BASE MODEL TYPE REQUEST            | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 305-2. SERIAL NUMBER REQUEST              | ○                          | —         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 305-3. BASIC INFORMATION REQUEST          | ○                          | ○         | ○                          | ○          | ○                          | ○          | ○                                      | ○           | ○           |
| 319-10. AUDIO SELECT SET                  | —                          | —         | —                          | —          | —                          | —          | —                                      | —           | —           |

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 — : Not supported

#### ■ Projector

| Command                                   | NP-PX2000UL | NP-PX1005QL | NP-PX1004UL<br>NP-PX803UL | NP-PX750U<br>NP-PX700W<br>NP-PX800X | NP-PX651X<br>NP-PX581W | NP-PX620X<br>NP-PX550W | NP-PX602UL<br>NP-PX602WL | NP-U321H | NP-U300X<br>NP-U250X<br>NP-U310W<br>NP-U260W |
|-------------------------------------------|-------------|-------------|---------------------------|-------------------------------------|------------------------|------------------------|--------------------------|----------|----------------------------------------------|
| 009. ERROR STATUS REQUEST                 | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 015. POWER ON                             | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 016. POWER OFF                            | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 018. INPUT SW CHANGE                      | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 020. PICTURE MUTE ON                      | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 021. PICTURE MUTE OFF                     | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 022. SOUND MUTE ON                        | —           | —           | —                         | —                                   | —                      | ○                      | —                        | ○        | ○                                            |
| 023. SOUND MUTE OFF                       | —           | —           | —                         | —                                   | —                      | ○                      | —                        | ○        | ○                                            |
| 024. ONSCREEN MUTE ON                     | ○           | ○           | ○                         | ○                                   | —                      | ○                      | ○                        | —        | ○                                            |
| 025. ONSCREEN MUTE OFF                    | ○           | ○           | ○                         | ○                                   | —                      | ○                      | ○                        | —        | —                                            |
| 030-1. PICTURE ADJUST                     | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 030-2. VOLUME ADJUST                      | —           | —           | —                         | —                                   | —                      | ○                      | —                        | ○        | ○                                            |
| 030-12. ASPECT ADJUST                     | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 030-15. OTHER ADJUST                      | ○           | ○           | ○                         | —                                   | —                      | —                      | ○                        | —        | —                                            |
| 037. INFORMATION REQUEST                  | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 037-3. FILTER USAGE INFORMATION REQUEST   | —           | —           | —                         | ○                                   | ○                      | —                      | —                        | ○        | ○                                            |
| 037-4. LAMP INFORMATION REQUEST 3         | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 037-6. CARBON SAVINGS INFORMATION REQUEST | —           | ○           | ○                         | —                                   | —                      | —                      | ○                        | —        | —                                            |
| 050. REMOTE KEY CODE                      | ○           | ○           | ○                         | ○                                   | ○                      | —                      | ○                        | ○        | ○                                            |
| 051. LENS MUTE ON (SHUTTER CLOSE)         | ○           | ○           | ○                         | ○                                   | —                      | —                      | ○                        | —        | —                                            |
| 052. LENS MUTE OFF (SHUTTER OPEN)         | ○           | ○           | ○                         | ○                                   | —                      | —                      | ○                        | —        | —                                            |
| 053. LENS CONTROL                         | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | —        | —                                            |
| 053-1. LENS CONTROL REQUEST               | —           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-2. LENS CONTROL 2                     | —           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-3. LENS MEMORY CONTROL                | ○           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-4. REFERENCE LENS MEMORY CONTROL      | ○           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-5. LENS MEMORY OPTION REQUEST         | —           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-6. LENS MEMORY OPTION SET             | —           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-7. LENS INFORMATION REQUEST           | —           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-10. LENS PROFILE SET                  | ○           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 053-11. LENS PROFILE REQUEST              | ○           | ○           | ○                         | —                                   | —                      | —                      | —                        | —        | —                                            |
| 060-1. GAIN PARAMETER REQUEST 3           | ○           | ○           | ○                         | ○                                   | —                      | ○                      | ○                        | —        | —                                            |
| 078-1. SETTING REQUEST                    | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 078-2. RUNNING STATUS REQUEST             | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 078-3. INPUT STATUS REQUEST               | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 078-4. MUTE STATUS REQUEST                | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 078-5. MODEL NAME REQUEST                 | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 078-6. COVER STATUS REQUEST               | —           | —           | ○                         | ○                                   | —                      | —                      | ○                        | —        | —                                            |
| 079. FREEZE CONTROL                       | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 084. INFORMATION STRING REQUEST           | —           | ○           | ○                         | ○                                   | —                      | —                      | ○                        | —        | —                                            |
| 097-8. ECO MODE REQUEST                   | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 097-45. LAN PROJECTOR NAME REQUEST        | ○           | ○           | ○                         | ○                                   | —                      | —                      | ○                        | ○        | ○                                            |
| 097-155. LAN MAC ADDRESS STATUS REQUEST2  | ○           | ○           | ○                         | ○                                   | ○                      | —                      | ○                        | ○        | ○                                            |
| 097-198. PIP/PICTURE BY PICTURE REQUEST   | —           | ○           | ○                         | —                                   | —                      | —                      | ○                        | —        | —                                            |
| 097-243-1. EDGE BLENDING MODE REQUEST     | ○           | ○           | ○                         | —                                   | —                      | —                      | ○                        | —        | —                                            |
| 098-8. ECO MODE SET                       | ○           | ○           | ○                         | —                                   | ○                      | —                      | ○                        | ○        | —                                            |
| 098-45. LAN PROJECTOR NAME SET            | ○           | ○           | ○                         | ○                                   | —                      | —                      | ○                        | ○        | ○                                            |
| 098-198. PIP/PICTURE BY PICTURE SET       | —           | ○           | ○                         | —                                   | —                      | —                      | ○                        | —        | —                                            |
| 098-243-1. EDGE BLENDING MODE SET         | ○           | ○           | ○                         | —                                   | —                      | —                      | ○                        | —        | —                                            |
| 305-1. BASE MODEL TYPE REQUEST            | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 305-2. SERIAL NUMBER REQUEST              | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | —                                            |
| 305-3. BASIC INFORMATION REQUEST          | ○           | ○           | ○                         | ○                                   | ○                      | ○                      | ○                        | ○        | ○                                            |
| 319-10. AUDIO SELECT SET                  | —           | —           | —                         | —                                   | —                      | —                      | —                        | —        | —                                            |

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 — : Not supported

#### ■ Projector

| Command                                   | NP-UM351W<br>NP-UM301W<br>NP-UM361X<br>NP-UM301X<br>NP-UM352W | NP-UM330X<br>NP-UM280X<br>NP-UM330W<br>NP-UM280W | NP-V332X<br>NP-V332W<br>NP-V302X<br>NP-V302W<br>NP-V302H | NP-V311W<br>NP-V281W<br>NP-V311X | NP-V300X<br>NP-V260X<br>NP-V300W<br>NP-V260W | NP-V230X<br>NP-V260<br>NP-V230<br>NP-V260R | NP-VE303X<br>NP-VE303 | NP-VE281X<br>NP-VE280X<br>NP-VE281<br>NP-VE280 |
|-------------------------------------------|---------------------------------------------------------------|--------------------------------------------------|----------------------------------------------------------|----------------------------------|----------------------------------------------|--------------------------------------------|-----------------------|------------------------------------------------|
| 009. ERROR STATUS REQUEST                 | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 015. POWER ON                             | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 016. POWER OFF                            | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 018. INPUT SW CHANGE                      | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 020. PICTURE MUTE ON                      | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 021. PICTURE MUTE OFF                     | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 022. SOUND MUTE ON                        | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 023. SOUND MUTE OFF                       | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 024. ONSCREEN MUTE ON                     | ○                                                             | ○                                                | —                                                        | ○                                | ○                                            | ○                                          | —                     | ○                                              |
| 025. ONSCREEN MUTE OFF                    | —                                                             | —                                                | —                                                        | ○                                | ○                                            | ○                                          | —                     | ○                                              |
| 030-1. PICTURE ADJUST                     | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 030-2. VOLUME ADJUST                      | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 030-12. ASPECT ADJUST                     | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 030-15. OTHER ADJUST                      | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 037. INFORMATION REQUEST                  | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 037-3. FILTER USAGE INFORMATION REQUEST   | ○                                                             | ○                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 037-4. LAMP INFORMATION REQUEST 3         | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 037-6. CARBON SAVINGS INFORMATION REQUEST | ○                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 050. REMOTE KEY CODE                      | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 051. LENS MUTE ON (SHUTTER CLOSE)         | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 052. LENS MUTE OFF (SHUTTER OPEN)         | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053. LENS CONTROL                         | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-1. LENS CONTROL REQUEST               | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-2. LENS CONTROL 2                     | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-3. LENS MEMORY CONTROL                | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-4. REFERENCE LENS MEMORY CONTROL      | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-5. LENS MEMORY OPTION REQUEST         | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-6. LENS MEMORY OPTION SET             | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-7. LENS INFORMATION REQUEST           | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-10. LENS PROFILE SET                  | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 053-11. LENS PROFILE REQUEST              | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 060-1. GAIN PARAMETER REQUEST 3           | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 078-1. SETTING REQUEST                    | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 078-2. RUNNING STATUS REQUEST             | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 078-3. INPUT STATUS REQUEST               | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 078-4. MUTE STATUS REQUEST                | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 078-5. MODEL NAME REQUEST                 | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 078-6. COVER STATUS REQUEST               | ○                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 079. FREEZE CONTROL                       | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 084. INFORMATION STRING REQUEST           | ○                                                             | ○                                                | —                                                        | —                                | —                                            | —                                          | —                     | ○                                              |
| 097-8. ECO MODE REQUEST                   | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 097-45. LAN PROJECTOR NAME REQUEST        | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | —                                          | ○                     | —                                              |
| 097-155. LAN MAC ADDRESS STATUS REQUEST2  | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | —                                          | —                     | —                                              |
| 097-198. PIP/PICTURE BY PICTURE REQUEST   | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 097-243-1. EDGE BLENDING MODE REQUEST     | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 098-8. ECO MODE SET                       | ○                                                             | —                                                | ○                                                        | —                                | —                                            | —                                          | ○                     | —                                              |
| 098-45. LAN PROJECTOR NAME SET            | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | —                                          | ○                     | —                                              |
| 098-198. PIP/PICTURE BY PICTURE SET       | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 098-243-1. EDGE BLENDING MODE SET         | —                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | —                     | —                                              |
| 305-1. BASE MODEL TYPE REQUEST            | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 305-2. SERIAL NUMBER REQUEST              | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 305-3. BASIC INFORMATION REQUEST          | ○                                                             | ○                                                | ○                                                        | ○                                | ○                                            | ○                                          | ○                     | ○                                              |
| 319-10. AUDIO SELECT SET                  | ○                                                             | —                                                | —                                                        | —                                | —                                            | —                                          | ○                     | —                                              |



#### 4. Supplementary Information by Command

##### 018. INPUT SW CHANGE

###### ■Input terminal

|                                                                                                                                                                                   | Input Terminal |           |           |     |       |         |         |          |           |  |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|-----------|-----------|-----|-------|---------|---------|----------|-----------|--|
| Model name                                                                                                                                                                        | COMPUTER       | COMPUTER2 | COMPUTER3 | BNC | VIDEO | BNC(CV) | S-VIDEO | BNC(Y/C) | Component |  |
| NP4100 / NP4100W                                                                                                                                                                  | 01h            | 02h       | 1Ah       | —   | 06h   | —       | 0Bh     | —        | 10h       |  |
| NP-M430WL / NP-M380HL                                                                                                                                                             | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-M420X / NP-M420XV<br>NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                         | 01h            | 02h       | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                              | 01h            | 02h       | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                                 | 01h            | 02h       | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-P627UL / NP-P547UL                                                                                                                                                             | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                                   | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-P506QL                                                                                                                                                                         | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                         | 01h            | —         | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                                    | 01h            | 02h       | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         | —              | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          | 01h            | —         | —         | 02h | —     | 06h     | —       | 0Bh      | —         |  |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          | 01h            | —         | —         | 02h | —     | 06h     | —       | 0Bh      | —         |  |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                     | 01h            | 02h       | 03h       | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PE506UL / NP-PE506WL                                                                                                                                                           | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PE501X                                                                                                                                                                         | 01h            | —         | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PE456USL / NP-PE456WSL                                                                                                                                                         | 01h            | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PE401H                                                                                                                                                                         | 01h            | —         | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         | —              | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PH1400U                                                                                                                                                                        | 01h            | 02h       | 03h       | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         | 01h            | —         | —         | 02h | —     | 06h     | —       | 0Bh      | —         |  |
| NP-PH1000U                                                                                                                                                                        | 01h            | 02h       | 03h       | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              | —              | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PV710UL+                                                                                                                                                                       | —              | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PX2201UL                                                                                                                                                                       | 01h            | —         | —         | 02h | —     | —       | —       | —        | —         |  |
| NP-PX2000UL                                                                                                                                                                       | 01h            | —         | —         | 02h | —     | —       | —       | —        | —         |  |
| NP-PX1005QL                                                                                                                                                                       | —              | —         | —         | —   | —     | —       | —       | —        | —         |  |
| NP-PX1004UL<br>NP-PX803UL                                                                                                                                                         | 01h            | —         | —         | 02h | —     | 06h     | —       | 0Bh      | —         |  |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                                 | 01h            | 02h       | 03h       | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-PX651X / NP-PX581W                                                                                                                                                             | 01h            | 02h       | 9Ch       | —   | 06h   | —       | 0Bh     | —        | 10h       |  |
| NP-PX620X / NP-PX550W                                                                                                                                                             | 01h            | 02h       | 1Ah       | —   | 06h   | —       | 0Bh     | —        | 10h       |  |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           | 01h            | —         | —         | 02h | —     | 06h     | —       | 0Bh      | —         |  |
| NP-U321H                                                                                                                                                                          | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                         | 01h            | 02h       | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-UM352W                                                                                                                                                                         | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                     | 01h            | —         | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                                    | 01h            | 02h       | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                         | 01h            | 02h       | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-V230X / NP-V260 / NP-V230                                                                                                                                                      | 01h            | —         | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-V260R                                                                                                                                                                          | 01h            | —         | —         | —   | 06h   | —       | 0Bh     | —        | —         |  |
| NP-VE303X / NP-VE303                                                                                                                                                              | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-VE281X / NP-VE281                                                                                                                                                              | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |
| NP-VE280X / NP-VE280                                                                                                                                                              | 01h            | —         | —         | —   | 06h   | —       | —       | —        | —         |  |

#### 4. Supplementary Information by Command

##### 018. INPUT SW CHANGE

##### ■Input terminal

| Model name                                                                                                                                                                        | Input terminal |       |             |              |      |            |       |        |       |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|-------|-------------|--------------|------|------------|-------|--------|-------|
|                                                                                                                                                                                   | HDMI           | HDMI2 | DisplayPort | DisplayPort2 | SLOT | STEREO DVI | DVI-D | VIEWER | USB-A |
| NP4100 / NP4100W                                                                                                                                                                  | —              | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-M430WL / NP-M380HL                                                                                                                                                             | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-M420X / NP-M420XV<br>NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                         | 1Ah            | —     | —           | —            | —    | —          | —     | 1Fh    | —     |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                              | 1Ah            | —     | —           | —            | —    | —          | —     | 1Fh    | —     |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    | 1Ah            | 1Bh   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                                 | —              | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-P627UL / NP-P547UL                                                                                                                                                             | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                                   | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-P564U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-P506QL                                                                                                                                                                         | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                         | 1Ah            | 1Bh   | —           | —            | —    | —          | —     | 1Fh    | —     |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                                    | 1Ah            | —     | —           | —            | —    | —          | —     | 1Fh    | —     |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          | A1h            | A2h   | A6h         | —            | —    | —          | —     | —      | —     |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  | A1h            | A2h   | A6h         | —            | —    | —          | —     | —      | —     |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          | A1h            | A2h   | A6h         | —            | —    | —          | —     | —      | —     |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          | A1h            | A2h   | A6h         | —            | —    | —          | —     | —      | 1Fh   |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                     | 1Ah            | —     | 1Bh         | —            | —    | —          | —     | 1Fh    | —     |
| NP-PE506UL / NP-PE506WL                                                                                                                                                           | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-PE501X                                                                                                                                                                         | 1Ah            | 1Bh   | —           | —            | —    | —          | —     | —      | —     |
| NP-PE456USL / NP-PE456WSL                                                                                                                                                         | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-PE401H                                                                                                                                                                         | 1Ah            | 1Bh   | —           | —            | —    | —          | —     | —      | —     |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         | A1h            | A2h   | A6h         | A7h          | ABh  | —          | —     | —      | —     |
| NP-PH1400U                                                                                                                                                                        | 1Ah            | —     | 1Bh         | —            | 1Ch  | 2Eh        | —     | 1Fh    | —     |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         | A1h            | —     | A6h         | —            | ABh  | —          | —     | —      | —     |
| NP-PH1000U                                                                                                                                                                        | 1Ah            | —     | 1Bh         | —            | 1Ch  | —          | —     | 1Fh    | —     |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-PV710UL+                                                                                                                                                                       | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-PX2201UL                                                                                                                                                                       | A1h            | A2h   | A6h         | —            | —    | —          | 9Ch   | —      | —     |
| NP-PX2000UL                                                                                                                                                                       | A1h            | A2h   | A6h         | —            | —    | —          | 9Ch   | —      | —     |
| NP-PX1005QL                                                                                                                                                                       | A1h            | A2h   | A6h         | A7h          | ABh  | —          | —     | —      | —     |
| NP-PX1004UL<br>NP-PX803UL                                                                                                                                                         | A1h            | —     | A6h         | —            | ABh  | —          | —     | —      | —     |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                                 | 1Ah            | —     | 1Bh         | —            | 1Ch  | —          | —     | 1Fh    | —     |
| NP-PX651X / NP-PX581W                                                                                                                                                             | A1h            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-PX620X / NP-PX550W                                                                                                                                                             | —              | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           | A1h            | —     | A6h         | —            | ABh  | —          | —     | —      | —     |
| NP-U321H                                                                                                                                                                          | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                         | 1Ah            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-UM352W                                                                                                                                                                         | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     | A1h            | A2h   | —           | —            | —    | —          | —     | —      | 1Fh   |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                     | 1Ah            | 1Bh   | —           | —            | —    | —          | —     | 1Fh    | —     |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              | A1h            | A2h   | —           | —            | —    | —          | —     | —      | —     |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                                    | 1Ah            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                         | 1Ah            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-V230X / NP-V260 / NP-V230                                                                                                                                                      | —              | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-V260R                                                                                                                                                                          | 1Ah            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-VE303X / NP-VE303                                                                                                                                                              | A1h            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-VE281X / NP-VE281                                                                                                                                                              | 1Ah            | —     | —           | —            | —    | —          | —     | —      | —     |
| NP-VE280X / NP-VE280                                                                                                                                                              | —              | —     | —           | —            | —    | —          | —     | —      | —     |

#### 4. Supplementary Information by Command

##### 018. INPUT SW CHANGE

###### ■Input terminal

|                                                                                                                                                                                   | Input Terminal |     |          |         |     |      |      |      |             |  |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|-----|----------|---------|-----|------|------|------|-------------|--|
| Model name                                                                                                                                                                        | NETWORK        | LAN | ETHERNET | HDBaseT | SDI | SDI2 | SDI3 | SDI4 | USB DISPLAY |  |
| NP4100 / NP4100W                                                                                                                                                                  | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-M430WL / NP-M380HL                                                                                                                                                             | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-M420X / NP-M420XV<br>NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                         | 20h            | —   | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                              | 20h            | —   | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           | —              | 20h | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                                 | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-P627UL / NP-P547UL                                                                                                                                                             | —              | 20h | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                                   | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 | —              | 20h | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-P506QL                                                                                                                                                                         | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-P502HL / NP-P502WL<br>NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                         | 20h            | —   | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                                    | 20h            | —   | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         | —              | —   | —        | BFh     | C4h | —    | —    | —    | —           |  |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          | —              | —   | —        | 20h     | —   | —    | —    | —    | —           |  |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          | —              | —   | 20h      | —       | —   | —    | —    | —    | —           |  |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                     | 20h            | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PE506UL / NP-PE506WL                                                                                                                                                           | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PE501X                                                                                                                                                                         | —              | —   | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-PE456USL / NP-PE456WSL                                                                                                                                                         | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PE401H                                                                                                                                                                         | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         | —              | —   | —        | BFh     | C4h | C5h  | C6h  | C7h  | —           |  |
| NP-PH1400U                                                                                                                                                                        | 20h            | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         | —              | —   | —        | 20h     | —   | —    | —    | —    | —           |  |
| NP-PH1000U                                                                                                                                                                        | 20h            | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-PV710UL+                                                                                                                                                                       | —              | —   | —        | BFh     | —   | —    | —    | —    | —           |  |
| NP-PX2201UL                                                                                                                                                                       | —              | —   | —        | —       | C4h | —    | —    | —    | —           |  |
| NP-PX2000UL                                                                                                                                                                       | —              | —   | —        | —       | C4h | —    | —    | —    | —           |  |
| NP-PX1005QL                                                                                                                                                                       | —              | —   | —        | BFh     | C4h | C5h  | C6h  | C7h  | —           |  |
| NP-PX1004UL<br>NP-PX803UL                                                                                                                                                         | —              | —   | —        | 20h     | —   | —    | —    | —    | —           |  |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                                 | 20h            | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PX651X / NP-PX581W                                                                                                                                                             | —              | —   | —        | 20h     | —   | —    | —    | —    | —           |  |
| NP-PX620X / NP-PX550W                                                                                                                                                             | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           | —              | —   | —        | 20h     | —   | —    | —    | —    | —           |  |
| NP-U321H                                                                                                                                                                          | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                         | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-UM352W                                                                                                                                                                         | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     | —              | 20h | —        | —       | —   | —    | —    | —    | —           |  |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                     | 20h            | —   | —        | —       | —   | —    | —    | —    | 22h         |  |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                                    | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                         | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-V230X / NP-V260 / NP-V230                                                                                                                                                      | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-V260R                                                                                                                                                                          | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-VE303X / NP-VE303                                                                                                                                                              | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-VE281X / NP-VE281                                                                                                                                                              | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |
| NP-VE280X / NP-VE280                                                                                                                                                              | —              | —   | —        | —       | —   | —    | —    | —    | —           |  |

#### 4. Supplementary Information by Command

##### 018. INPUT SW CHANGE

###### ■Input terminal

| Model name                                                                                                                                                               | Input Terminal |      |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|------|
|                                                                                                                                                                          | USB-B          | APPS |
| NP4100 / NP4100W                                                                                                                                                         | —              | —    |
| NP-M430WL / NP-M380HL                                                                                                                                                    | —              | —    |
| NP-M420X / NP-M420XV                                                                                                                                                     | —              | —    |
| NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS                                              | —              | —    |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS | 22h            | —    |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS                                                           | 22h            | —    |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                     | —              | —    |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X                                                                                                                            | —              | —    |
| NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                                                            | —              | —    |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X                                                                                                                            | —              | —    |
| NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X                                                                                                                            | —              | —    |
| NP-MC342X / NP-MC302X                                                                                                                                                    | —              | —    |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                            | 22h            | —    |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                        | —              | —    |
| NP-P627UL / NP-P547UL                                                                                                                                                    | —              | —    |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                          | —              | —    |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                     | —              | —    |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                        | —              | —    |
| NP-P506QL                                                                                                                                                                | —              | —    |
| NP-P502HL / NP-P502WL                                                                                                                                                    | —              | 23h  |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                | —              | —    |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                | —              | —    |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                           | —              | —    |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                | —              | —    |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                 | —              | —    |
| NP-PA803UL / NP-PA703UL / NP-PA653UL                                                                                                                                     | —              | —    |
| NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X                                                                                                    | —              | —    |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X                                                                                                    | —              | —    |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X                                                                                                    | —              | —    |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                            | —              | —    |
| NP-PE506UL / NP-PE506WL                                                                                                                                                  | —              | —    |
| NP-PE501X                                                                                                                                                                | —              | —    |
| NP-PE456USL / NP-PE456WSL                                                                                                                                                | —              | —    |
| NP-PE401H                                                                                                                                                                | —              | —    |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                | —              | —    |
| NP-PH1400U                                                                                                                                                               | —              | —    |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                | —              | —    |
| NP-PH1000U                                                                                                                                                               | —              | —    |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                     | —              | —    |
| NP-PV710UL+                                                                                                                                                              | —              | —    |
| NP-PX2201UL                                                                                                                                                              | —              | —    |
| NP-PX2000UL                                                                                                                                                              | —              | —    |
| NP-PX1005QL                                                                                                                                                              | —              | —    |
| NP-PX1004UL                                                                                                                                                              | —              | —    |
| NP-PX803UL                                                                                                                                                               | —              | —    |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                        | —              | —    |
| NP-PX651X / NP-PX581W                                                                                                                                                    | —              | —    |
| NP-PX620X / NP-PX550W                                                                                                                                                    | —              | —    |
| NP-PX602UL / NP-PX602WL                                                                                                                                                  | —              | —    |
| NP-U321H                                                                                                                                                                 | —              | —    |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                | —              | —    |
| NP-UM352W                                                                                                                                                                | 22h            | 23h  |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                            | 22h            | —    |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                            | —              | —    |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                     | —              | —    |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                           | —              | —    |
| NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                | —              | —    |
| NP-V230X / NP-V260 / NP-V230                                                                                                                                             | —              | —    |
| NP-V260R                                                                                                                                                                 | —              | —    |
| NP-VE303X / NP-VE303                                                                                                                                                     | —              | —    |
| NP-VE281X / NP-VE281                                                                                                                                                     | —              | —    |
| NP-VE280X / NP-VE280                                                                                                                                                     | —              | —    |

## 4. Supplementary Information by Command

### 030-12. ASPECT ADJUST

#### ■ Aspect

| Model name                                                                                                                                                                                                            | DATA01        |                       |             |      |        |        |      |       |      |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------|-----------------------|-------------|------|--------|--------|------|-------|------|
|                                                                                                                                                                                                                       | 00h           | 01h                   | 02h         |      | 03h    | 04h    | 05h  | 06h   |      |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS                                              | AUTO          | WIDE ZOOM (XGA Model) | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS                                                                                                        | AUTO          | WIDE ZOOM (XGA Model) | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X / NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X / NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X / NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X / NP-MC342X / NP-MC302X | Normal        | Wide                  | Full        |      | 4:3    | —      | —    | —     |      |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                                                         | AUTO          | WIDE ZOOM (XGA Model) | CHINEMA     | 16:9 | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-P627UL / NP-P547UL                                                                                                                                                                                                 | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X                                                                                                                                | AUTO          | WIDE ZOOM (XGA Model) | CHINEMA     | 16:9 | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                                                     | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-P506QL                                                                                                                                                                                                             | AUTO (FILL)   | —                     | 16:9        |      | —      | 4:3    | —    | —     |      |
| NP-P502HL / NP-P502WL / NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                                     | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                                                             | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | FULL  |      |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                                                              | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | FULL  |      |
| NP-PA803UL / NP-PA703UL / NP-PA653UL / NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X                                                                                                          | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | FULL  |      |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X                                                                                                                                                 | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | ZOOM  | FULL |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X                                                                                                                                                 | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | ZOOM  | FULL |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                                                             | 4:3           | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | FULL  |      |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                                                             | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | ZOOM  | FULL |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                                                                  | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-PV710UL+                                                                                                                                                                                                           | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | FULL  |      |
| NP-PX2201UL                                                                                                                                                                                                           | —             | —                     | 16:9        |      | —      | 4:3    | —    | 16:10 |      |
| NP-PX2000UL                                                                                                                                                                                                           | —             | —                     | 16:9        |      | —      | 4:3    | —    | 16:10 |      |
| NP-PX1005QL                                                                                                                                                                                                           | 4:3           | —                     | WIDE SCREEN | 16:9 | —      | —      | —    | FULL  |      |
| NP-PX1004UL / NP-PX803UL                                                                                                                                                                                              | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | ZOOM  | FULL |
| NP-PX651X / NP-PX581W                                                                                                                                                                                                 | 4:3           | —                     | 16:9        |      | 1.85:1 | 2.35:1 | Auto | 16:10 |      |
| NP-PX602UL / NP-PX602WL                                                                                                                                                                                               | 4:3 (WINDOWS) | LETTER BOX            | WIDE SCREEN | 16:9 | —      | —      | —    | ZOOM  | FULL |
| NP-U321H                                                                                                                                                                                                              | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-UM301X / NP-UM361X / NP-UM301W / NP-UM351W / NP-UM352W                                                                                                                                                             | AUTO          | WIDE ZOOM (XGA Model) | CHINEMA     | 16:9 | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                                                                  | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |
| NP-VE303X / NP-VE303                                                                                                                                                                                                  | AUTO          | —                     | 16:9        |      | NATIVE | 4:3    | 15:9 | 16:10 |      |

## 4. Supplementary Information by Command

### 030-12. ASPECT ADJUST

#### ■ Aspect

| Model name                                                                                                                                                                                                            | DATA01                  | 07h | 08h | 0Bh   | 0Ch  | 0Dh    | 0Eh  | 0Fh    | 10h  | 11h    | 12h |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------|-----|-----|-------|------|--------|------|--------|------|--------|-----|
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS                                              | LETTER BOX (WXGA Model) | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS                                                                                                        | LETTER BOX (WXGA Model) | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X / NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X / NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X / NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X / NP-MC342X / NP-MC302X | LETTERBOX (WXGA Model)  | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                                                         | LETTERBOX (WXGA Model)  | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-P627UL / NP-P547UL                                                                                                                                                                                                 | LETTER BOX              | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X                                                                                                                                | LETTERBOX (WXGA Model)  | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                                                     | LETTER BOX              | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-P506QL                                                                                                                                                                                                             | LETTER BOX              | —   | —   | —     | —    | —      | —    | —      | —    | 2.35:1 | —   |
| NP-P502HL / NP-P502WL / NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                                     | LETTER BOX              | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                                                             | ZOOM                    | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | NORMAL | —    | —      | —   |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                                                              | ZOOM                    | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | NORMAL | —    | —      | —   |
| NP-PA803UL / NP-PA703UL / NP-PA653UL / NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X                                                                                                          | ZOOM                    | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | NORMAL | —    | —      | —   |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X                                                                                                                                                 | —                       | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | —      | —    | —      | —   |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X                                                                                                                                                 | —                       | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | —      | —    | —      | —   |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                                                             | ZOOM                    | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | NORMAL | —    | —      | —   |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                                                             | —                       | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | —      | —    | —      | —   |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                                                                  | LETTER BOX              | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-PV710UL+                                                                                                                                                                                                           | ZOOM                    | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | NORMAL | —    | —      | —   |
| NP-PX2201UL                                                                                                                                                                                                           | LETTER BOX              | —   | 5:4 | —     | —    | NATIVE | AUTO | —      | 1.88 | 2.35   | —   |
| NP-PX2000UL                                                                                                                                                                                                           | LETTER BOX              | —   | 5:4 | —     | —    | NATIVE | AUTO | —      | 1.88 | 2.35   | —   |
| NP-PX1005QL                                                                                                                                                                                                           | ZOOM                    | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | NORMAL | —    | —      | —   |
| NP-PX1004UL / NP-PX803UL                                                                                                                                                                                              | —                       | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | —      | —    | —      | —   |
| NP-PX651X / NP-PX581W                                                                                                                                                                                                 | —                       | —   | 5:4 | 16:10 | —    | Native | Auto | —      | —    | —      | —   |
| NP-PX602UL / NP-PX602WL                                                                                                                                                                                               | —                       | —   | 5:4 | 16:10 | 15:9 | NATIVE | AUTO | —      | —    | —      | —   |
| NP-U321H                                                                                                                                                                                                              | —                       | 5:4 | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-UM301X / NP-UM361X / NP-UM301W / NP-UM351W / NP-UM352W                                                                                                                                                             | LETTERBOX (WXGA Model)  | —   | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                                                                  | —                       | 5:4 | —   | —     | —    | —      | —    | —      | —    | —      | —   |
| NP-VE303X / NP-VE303                                                                                                                                                                                                  | —                       | 5:4 | —   | —     | —    | —      | —    | —      | —    | —      | —   |

## 4. Supplementary Information by Command

### 097-8. ECO MODE REQUEST 098-8. ECO MODE SET

#### ■Eco mode

| Model name                                                                                                                                                                        | DATA01 |          |        |      |           |       |        |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|----------|--------|------|-----------|-------|--------|
|                                                                                                                                                                                   | 00h    | 01h      | 02h    | 03h  | 04h       | 05h   | 06h    |
| * NP4100 / NP4100W                                                                                                                                                                | Normal | Eco      | —      | —    | —         | —     | —      |
| NP-M420X / NP-M420XV<br>NP-M350X / NP-M230X / NP-M300W / NP-M260W /<br>NP-M350XS / NP-M300XS / NP-M300WS / NP-M260WS                                                              | OFF    | AUTO ECO | ECO1   | —    | —         | —     | —      |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-M300X / NP-M260X / NP-M260XS                                                                                                                                                   | OFF    | AUTO ECO | ECO1   | ECO2 | —         | —     | —      |
| NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                              | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    | NORMAL | —        | ECO1   | ECO2 | —         | BOOST | —      |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                                 | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-P627UL / NP-P547UL                                                                                                                                                             | OFF    | —        | —      | ECO  | LONG LIFE | —     | —      |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /<br>NP-P603X / NP-P523X / NP-PE523X                                                                                         | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 | OFF    | —        | —      | ECO  | LONG LIFE | —     | —      |
| NP-P506QL                                                                                                                                                                         | NORMAL | ECO      | —      | —    | —         | —     | —      |
| NP-P502HL / NP-P502WL                                                                                                                                                             | OFF    | ECO1     | ECO2   | —    | —         | —     | —      |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                         | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X                                                                                                                             | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-P420X / NP-P350X / NP-P350W                                                                                                                                                    | OFF    | AUTO ECO | ECO1   | —    | —         | —     | —      |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         | NORMAL | —        | —      | —    | LONG LIFE | —     | SILENT |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          | NORMAL | —        | ECO1   | ECO2 | —         | BOOST | —      |
| NP-PA803UL / NP-PA703UL / NP-PA653UL                                                                                                                                              | NORMAL | —        | ECO1   | ECO2 | LONG LIFE | —     | —      |
| NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                                                          | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                     | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PE401H                                                                                                                                                                         | OFF    | ECO      | —      | —    | —         | —     | —      |
| NP-PH1400U                                                                                                                                                                        | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         | NORMAL | —        | ECO1   | ECO2 | LONG LIFE | —     | —      |
| NP-PH1000U                                                                                                                                                                        | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              | NORMAL | —        | —      | —    | LONG LIFE | —     | SILENT |
| NP-PV710UL+                                                                                                                                                                       | NORMAL | —        | —      | —    | LONG LIFE | —     | SILENT |
| NP-PX2201UL                                                                                                                                                                       | NORMAL | —        | ECO    | —    | —         | —     | —      |
| NP-PX2000UL                                                                                                                                                                       | NORMAL | —        | ECO    | —    | —         | BOOST | —      |
| NP-PX1005QL                                                                                                                                                                       | NORMAL | —        | ECO1   | ECO2 | —         | —     | —      |
| NP-PX1004UL<br>NP-PX803UL                                                                                                                                                         | NORMAL | —        | ECO1   | ECO2 | —         | —     | —      |
| NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                                 | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-PX651X / NP-PX581W                                                                                                                                                             | NORMAL | ECO      | —      | —    | —         | —     | —      |
| * NP-PX620X / NP-PX550W                                                                                                                                                           | Normal | Eco      | —      | —    | —         | —     | —      |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           | NORMAL | —        | ECO1   | ECO2 | —         | —     | —      |
| NP-U321H                                                                                                                                                                          | OFF    | ECO      | —      | —    | —         | —     | —      |
| NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                         | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X<br>NP-UM352W                                                                                                                        | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                     | OFF    | AUTO ECO | NORMAL | ECO  | —         | —     | —      |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              | OFF    | ECO      | —      | —    | —         | —     | —      |
| NP-V311W / NP-V281W / NP-V311X                                                                                                                                                    | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-V300X / NP-V260X / NP-V230X / NP-V260 / NP-V230 / NP-V260R<br>NP-V300W / NP-V260W                                                                                              | OFF    | ON       | —      | —    | —         | —     | —      |
| NP-VE303X / NP-VE303                                                                                                                                                              | OFF    | ECO      | —      | —    | —         | —     | —      |
| NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280                                                                                                                                       | OFF    | ON       | —      | —    | —         | —     | —      |

\* The following models use a different menu item name.

- NP4100 / NP4100W : Lamp Mode
- NP-PX620X / NP-PX550W : Lamp Mode

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

| Model name  |                                | 078-1. SETTING REQUEST |        |        |
|-------------|--------------------------------|------------------------|--------|--------|
|             |                                | DATA01                 | DATA02 | DATA03 |
|             | 305-1. BASE MODEL TYPE REQUEST |                        |        |        |
|             | DATA01                         | DATA02                 | DATA12 | DATA13 |
| * NP4100    | 03h                            | 08h                    | 00h    | 10h    |
| * NP4100W   | 03h                            | 08h                    | 01h    | 10h    |
| * NP-M230X  | FFh                            | 13h                    | 09h    | 10h    |
| * NP-M260W  | FFh                            | 13h                    | 06h    | 10h    |
| * NP-M260WS | FFh                            | 13h                    | 08h    | 10h    |
| * NP-M260X  | FFh                            | 13h                    | 05h    | 10h    |
| * NP-M260XS | FFh                            | 13h                    | 07h    | 10h    |
| * NP-M271W  | FFh                            | 13h                    | 04h    | 13h    |
| * NP-M271X  | FFh                            | 13h                    | 02h    | 13h    |
| NP-M282X    | FFh                            | 22h                    | 03h    | 10h    |
| NP-M283X    | FFh                            | 22h                    | 03h    | 12h    |
| * NP-M300W  | FFh                            | 13h                    | 02h    | 10h    |
| * NP-M300WS | FFh                            | 13h                    | 04h    | 10h    |
| * NP-M300X  | FFh                            | 13h                    | 01h    | 10h    |
| * NP-M300XS | FFh                            | 13h                    | 03h    | 10h    |
| NP-M302WS   | FFh                            | 22h                    | 09h    | 10h    |
| NP-M303HS   | FFh                            | 22H                    | 04H    | 11H    |
| NP-M303WS   | FFh                            | 22h                    | 09h    | 12h    |
| * NP-M311W  | FFh                            | 13h                    | 01h    | 13h    |
| * NP-M311X  | FFh                            | 13h                    | 03h    | 13h    |
| NP-M322H    | FFh                            | 22h                    | 01h    | 11h    |
| NP-M322W    | FFh                            | 22h                    | 06h    | 10h    |
| NP-M322X    | FFh                            | 22h                    | 02h    | 10h    |
| NP-M323H    | FFh                            | 22h                    | 0Bh    | 12h    |
| NP-M323HS   | FFh                            | 22H                    | 03H    | 11H    |
| NP-M323W    | FFh                            | 22h                    | 06h    | 12h    |
| NP-M323X    | FFh                            | 22h                    | 02h    | 12h    |
| NP-M332XS   | FFh                            | 22h                    | 07h    | 10h    |
| NP-M333XS   | FFh                            | 22h                    | 07h    | 12h    |
| * NP-M350X  | FFh                            | 13h                    | 00h    | 10h    |
| * NP-M350XS | FFh                            | 13h                    | 0Ch    | 10h    |
| NP-M352WS   | FFh                            | 22h                    | 08h    | 10h    |
| NP-M353HS   | FFh                            | 22H                    | 02H    | 11H    |
| NP-M353WS   | FFh                            | 22h                    | 08h    | 12h    |
| * NP-M361X  | FFh                            | 13h                    | 00h    | 13h    |
| NP-M362W    | FFh                            | 22h                    | 05h    | 10h    |
| NP-M362X    | FFh                            | 22h                    | 01h    | 10h    |
| NP-M363W    | FFh                            | 22h                    | 05h    | 12h    |
| NP-M363X    | FFh                            | 22h                    | 01h    | 12h    |
| NP-M402H    | FFh                            | 22h                    | 00h    | 11h    |



## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

| Model name  |                                | 078-1. SETTING REQUEST |        |        |
|-------------|--------------------------------|------------------------|--------|--------|
|             |                                | DATA01                 | DATA02 | DATA03 |
|             | 305-1. BASE MODEL TYPE REQUEST |                        |        |        |
|             | DATA01                         | DATA02                 | DATA12 | DATA13 |
| NP-M402W    | FFh                            | 22h                    | 04h    | 10h    |
| NP-M402X    | FFh                            | 22h                    | 00h    | 10h    |
| NP-M403H    | FFh                            | 22h                    | 0Ah    | 12h    |
| NP-M403W    | FFh                            | 22h                    | 04h    | 12h    |
| NP-M403X    | FFh                            | 22h                    | 00h    | 12h    |
| * NP-M420X  | FFh                            | 13h                    | 0Ah    | 10h    |
| * NP-M420XV | FFh                            | 13h                    | 0Bh    | 10h    |
| NP-MC302X   | FFh                            | 32H                    | 1Ch    | 11h    |
| NP-MC332W   | FFh                            | 32H                    | 06h    | 11h    |
| NP-MC342X   | FFh                            | 32H                    | 07h    | 11h    |
| NP-MC363X   | FFh                            | 37h                    | 0Bh    | 10h    |
| NP-MC372X   | FFh                            | 32H                    | 04h    | 11h    |
| NP-MC382W   | FFh                            | 32H                    | 05h    | 11h    |
| NP-MC393W   | FFh                            | 37h                    | 09h    | 10h    |
| NP-MC422X   | FFh                            | 32H                    | 1Bh    | 11h    |
| NP-MC423W   | FFh                            | 37h                    | 08h    | 10h    |
| NP-MC453X   | FFh                            | 37h                    | 0Ah    | 10h    |
| * NP-ME270X | FFh                            | 10h                    | 02h    | 13h    |
| NP-ME301W   | FFh                            | 20H                    | 05H    | 14H    |
| NP-ME301X   | FFh                            | 20H                    | 04H    | 14H    |
| * NP-ME310X | FFh                            | 10h                    | 01h    | 13h    |
| NP-ME331W   | FFh                            | 20H                    | 03H    | 14H    |
| NP-ME331X   | FFh                            | 20H                    | 02H    | 14H    |
| NP-ME342U   | FFh                            | 32H                    | 01h    | 11h    |
| * NP-ME360X | FFh                            | 10h                    | 00h    | 13h    |
| NP-ME361W   | FFh                            | 20H                    | 01H    | 14H    |
| NP-ME361X   | FFh                            | 20H                    | 00H    | 14H    |
| NP-ME372W   | FFh                            | 32H                    | 02h    | 11h    |
| NP-ME382U   | FFh                            | 32H                    | 00h    | 11h    |
| NP-ME383W   | FFh                            | 37h                    | 02h    | 10h    |
| NP-ME402X   | FFh                            | 32H                    | 03h    | 11h    |
| NP-ME403U   | FFh                            | 37h                    | 00h    | 10h    |
| NP-ME423W   | FFh                            | 37h                    | 01h    | 10h    |
| NP-ME453X   | FFh                            | 37h                    | 03h    | 10h    |
| * NP-P350W  | FFh                            | 13h                    | 02h    | 11h    |
| * NP-P350X  | FFh                            | 13h                    | 01h    | 11h    |
| * NP-P401W  | FFh                            | 20h                    | 03h    | 10h    |
| * NP-P420X  | FFh                            | 13h                    | 00h    | 11h    |
| * NP-P451W  | FFh                            | 20h                    | 02h    | 10h    |
| * NP-P451X  | FFh                            | 20h                    | 01h    | 10h    |

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

| Model name  |                                | 078-1. SETTING REQUEST |        |        |
|-------------|--------------------------------|------------------------|--------|--------|
|             |                                | DATA01                 | DATA02 | DATA03 |
|             | 305-1. BASE MODEL TYPE REQUEST |                        |        |        |
|             | DATA01                         | DATA02                 | DATA12 | DATA13 |
| NP-P452H    | FFh                            | 22H                    | 02H    | 14H    |
| NP-P452W    | FFh                            | 22H                    | 03H    | 14H    |
| NP-P474U    | FFh                            | 20H                    | 0AH    | 15H    |
| NP-P474W    | FFh                            | 20H                    | 01H    | 15H    |
| * NP-P501X  | FFh                            | 20h                    | 00h    | 10h    |
| NP-P502H    | FFh                            | 22H                    | 00H    | 14H    |
| NP-P502HL   | FFh                            | 22h                    | 00h    | 13h    |
| NP-P502W    | FFh                            | 22H                    | 01H    | 14H    |
| NP-P502WL   | FFh                            | 22h                    | 01h    | 13h    |
| NP-P506QL   | FFh                            | 33H                    | 00H    | 10H    |
| NP-P523X    | FFh                            | 20H                    | 04H    | 15H    |
| NP-P525UL   | FFh                            | 32H                    | 00H    | 10H    |
| NP-P525WL   | FFh                            | 32h                    | 01h    | 10h    |
| NP-P547UL   | FFh                            | 40H                    | 01H    | 10H    |
| NP-P554U    | FFh                            | 20H                    | 09H    | 15H    |
| NP-P554W    | FFh                            | 20H                    | 00H    | 15H    |
| NP-P603X    | FFh                            | 20H                    | 03H    | 15H    |
| NP-P604X    | FFh                            | 20H                    | 02H    | 15H    |
| NP-P605UL   | FFh                            | 32H                    | 02H    | 10H    |
| NP-P627UL   | FFh                            | 40H                    | 00H    | 10H    |
| NP-PA1004UL | FFh                            | 34h                    | 00h    | 10h    |
| NP-PA1505UL | FFh                            | 42h                    | 01h    | 10h    |
| NP-PA1705UL | FFh                            | 42h                    | 00h    | 10h    |
| * NP-PA500U | FFh                            | 15h                    | 03h    | 10h    |
| * NP-PA500X | FFh                            | 15h                    | 01h    | 10h    |
| NP-PA521U   | FFh                            | 21h                    | 01h    | 10h    |
| NP-PA522U   | FFh                            | 21h                    | 01h    | 11h    |
| * NP-PA550W | FFh                            | 15h                    | 02h    | 10h    |
| NP-PA571W   | FFh                            | 21h                    | 03h    | 10h    |
| NP-PA572W   | FFh                            | 21h                    | 03h    | 11h    |
| * NP-PA600X | FFh                            | 15h                    | 00h    | 10h    |
| NP-PA621U   | FFh                            | 21h                    | 00h    | 10h    |
| NP-PA621X   | FFh                            | 21h                    | 05h    | 10h    |
| NP-PA622U   | FFh                            | 21h                    | 00h    | 11h    |
| NP-PA622X   | FFh                            | 21h                    | 05h    | 11h    |
| NP-PA653U   | FFh                            | 2Eh                    | 02h    | 10h    |
| NP-PA653UL  | FFh                            | 2Eh                    | 00h    | 11h    |
| NP-PA671W   | FFh                            | 21h                    | 02h    | 10h    |
| NP-PA672W   | FFh                            | 21h                    | 02h    | 11h    |
| NP-PA703UL  | FFh                            | 2Eh                    | 02h    | 11h    |
| NP-PA703W   | FFh                            | 2Eh                    | 05h    | 10h    |
| NP-PA721X   | FFh                            | 21h                    | 04h    | 10h    |
| NP-PA722X   | FFh                            | 21h                    | 04h    | 11h    |

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

| Model name   |                                | 078-1. SETTING REQUEST |        |        |
|--------------|--------------------------------|------------------------|--------|--------|
|              |                                | DATA01                 | DATA02 | DATA03 |
|              | 305-1. BASE MODEL TYPE REQUEST |                        |        |        |
|              | DATA01                         | DATA02                 | DATA12 | DATA13 |
| NP-PA723U    | FFh                            | 2Eh                    | 01h    | 10h    |
| NP-PA803U    | FFh                            | 2Eh                    | 00h    | 10h    |
| NP-PA803UL   | FFh                            | 2Eh                    | 01h    | 11h    |
| NP-PA804UL   | FFh                            | 34h                    | 01H    | 10H    |
| NP-PA853W    | FFh                            | 2Eh                    | 03h    | 10h    |
| NP-PA903X    | FFh                            | 2Eh                    | 06h    | 10h    |
| * NP-PE401H  | FFh                            | 14h                    | 00h    | 11h    |
| NP-PE456USL  | FFh                            | 37h                    | 08h    | 11h    |
| NP-PE456WSL  | FFh                            | 37h                    | 0Ah    | 11h    |
| * NP-PE501X  | FFh                            | 20h                    | 04h    | 10h    |
| NP-PE506UL   | FFh                            | 37h                    | 00h    | 11h    |
| NP-PE506WL   | FFh                            | 37h                    | 01h    | 11h    |
| NP-PE523X    | FFh                            | 20H                    | 05H    | 15H    |
| * NP-PH1000U | FFh                            | 19h                    | 00h    | 10h    |
| NP-PH1002HL  | FFh                            | 26h                    | 01h    | 10h    |
| NP-PH1202HL  | FFh                            | 26h                    | 00h    | 10h    |
| * NP-PH1400U | FFh                            | 19h                    | 00h    | 11h    |
| NP-PH2601QL  | FFh                            | 30h                    | 01h    | 10h    |
| NP-PH3501QL  | FFh                            | 30h                    | 00h    | 10h    |
| NP-PV710UL+  | FFh                            | 38h                    | 02h    | 10h    |
| NP-PV710UL   | FFh                            | 41h                    | 02h    | 10h    |
| NP-PV730UL   | FFh                            | 41h                    | 01h    | 10h    |
| NP-PV800UL   | FFh                            | 41h                    | 00h    | 10h    |
| NP-PX1004UL  | FFh                            | 2Fh                    | 00h    | 10h    |
| NP-PX1005QL  | FFh                            | 31h                    | 00h    | 10h    |
| NP-PX2000UL  | FFh                            | 35h                    | 00h    | 10h    |
| NP-PX2201UL  | FFh                            | 35h                    | 00h    | 11h    |
| * NP-PX550W  | 03h                            | 08h                    | 01h    | 11h    |
| NP-PX581W    | FFh                            | 27h                    | 01h    | 10h    |
| NP-PX602UL   | FFh                            | 25h                    | 00h    | 10h    |
| NP-PX602WL   | FFh                            | 25h                    | 01h    | 10h    |
| * NP-PX620X  | 03h                            | 08h                    | 00h    | 11h    |
| NP-PX651X    | FFh                            | 27h                    | 00h    | 10h    |
| * NP-PX700W  | FFh                            | 17h                    | 01h    | 10h    |
| * NP-PX750U  | FFh                            | 17h                    | 00h    | 10h    |
| * NP-PX800X  | FFh                            | 17h                    | 02h    | 10h    |
| NP-PX803UL   | FFh                            | 2Ch                    | 00h    | 10h    |
| * NP-U250X   | FFh                            | 14h                    | 01h    | 10h    |
| * NP-U260W   | FFh                            | 14h                    | 03h    | 10h    |
| * NP-U300X   | FFh                            | 14h                    | 02h    | 10h    |
| * NP-U310W   | FFh                            | 14h                    | 04h    | 10h    |
| NP-U321H     | FFh                            | 28h                    | 00h    | 10h    |
| * NP-UM280W  | FFh                            | 13h                    | 02h    | 12h    |
| * NP-UM280X  | FFh                            | 13h                    | 01h    | 12h    |
| NP-UM301W    | FFh                            | 20h                    | 02h    | 11h    |
| NP-UM301X    | FFh                            | 20h                    | 00h    | 11h    |

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

| Model name  |                                | 078-1. SETTING REQUEST |        |        |
|-------------|--------------------------------|------------------------|--------|--------|
|             |                                | DATA01                 | DATA02 | DATA03 |
|             | 305-1. BASE MODEL TYPE REQUEST |                        |        |        |
|             | DATA01                         | DATA02                 | DATA12 | DATA13 |
| * NP-UM330W | FFh                            | 13h                    | 03h    | 12h    |
| * NP-UM330X | FFh                            | 13h                    | 00h    | 12h    |
| NP-UM351W   | FFh                            | 20h                    | 03h    | 11h    |
| NP-UM352W   | FFh                            | 20h                    | 04h    | 11h    |
| NP-UM361X   | FFh                            | 20h                    | 01h    | 11h    |
| * NP-V230   | FFh                            | 16h                    | 04h    | 10h    |
| * NP-V230X  | FFh                            | 16h                    | 02h    | 10h    |
| * NP-V260   | FFh                            | 16h                    | 03h    | 10h    |
| * NP-V260R  | FFh                            | 16h                    | 07h    | 10h    |
| * NP-V260W  | FFh                            | 16h                    | 06h    | 10h    |
| * NP-V260X  | FFh                            | 16h                    | 01h    | 10h    |
| * NP-V281W  | FFh                            | 16h                    | 09h    | 10h    |
| * NP-V300W  | FFh                            | 16h                    | 05h    | 10h    |
| * NP-V300X  | FFh                            | 16h                    | 00h    | 10h    |
| NP-V302H    | FFh                            | 2Ah                    | 04h    | 10h    |
| NP-V302W    | FFh                            | 2Ah                    | 03h    | 10h    |
| NP-V302X    | FFh                            | 2Ah                    | 02h    | 10h    |
| * NP-V311W  | FFh                            | 16h                    | 08h    | 10h    |
| * NP-V311X  | FFh                            | 16h                    | 0Ah    | 10h    |
| NP-V332W    | FFh                            | 2Ah                    | 01h    | 10h    |
| NP-V332X    | FFh                            | 2Ah                    | 00h    | 10h    |
| * NP-VE280  | FFh                            | 16h                    | 05h    | 11h    |
| * NP-VE280X | FFh                            | 16h                    | 02h    | 11h    |
| * NP-VE281  | FFh                            | 16h                    | 04h    | 11h    |
| * NP-VE281X | FFh                            | 16h                    | 01h    | 11h    |
| NP-VE303    | FFh                            | 2Bh                    | 01h    | 10h    |
| NP-VE303X   | FFh                            | 2Bh                    | 00h    | 10h    |

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION REQUEST",  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

| Model name                                                                                                                                                               | DATA03 | 01h       | 01h     | 01h      | 01h          | 01h    |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|-----------|---------|----------|--------------|--------|
|                                                                                                                                                                          | DATA04 | 01h       | 02h     | 03h      | 06h          | 07h    |
| * NP4100 / NP4100W                                                                                                                                                       |        | Computer1 | Video   | S—Video  | Computer3    | —      |
| NP-M420X / NP-M420XV                                                                                                                                                     |        |           |         |          |              |        |
| * NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS                                            |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS                                                           |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| * NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                   |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X / NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                            |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X / NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X / NP-MC342X / NP-MC302X                                                    |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                            |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| * NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                      |        | COMPUTER1 | VIDEO   | —        | —            | —      |
| NP-P627UL / NP-P547UL                                                                                                                                                    |        | COMPUTER  | —       | —        | —            | USB-A  |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                          |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                     |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                        |        | COMPUTER  | —       | —        | —            | USB-A  |
| NP-P506QL                                                                                                                                                                |        | COMPUTER  | —       | —        | —            | —      |
| NP-P502HL / NP-P502WL                                                                                                                                                    |        | COMPUTER  | VIDEO   | —        | —            | —      |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                |        | COMPUTER  | VIDEO   | —        | —            | —      |
| * NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                              |        | COMPUTER  | VIDEO   | S—VIDEO  | HDMI1        | VIEWER |
| * NP-P420X / NP-P350X / NP-P350W                                                                                                                                         |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                |        | —         | —       | —        | —            | —      |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                 |        | COMPUTER  | —       | —        | —            | —      |
| NP-PA803UL / NP-PA703UL / NP-PA653UL / NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X                                                             |        | COMPUTER  | —       | —        | —            | —      |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X                                                                                                    |        | COMPUTER  | BNC(CV) | BNC(Y/C) | —            | —      |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X                                                                                                    |        | COMPUTER  | BNC(CV) | BNC(Y/C) | —            | USB-A  |
| * NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                          |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| * NP-PE506UL / NP-PE506WL                                                                                                                                                |        | COMPUTER  | —       | —        | —            | USB-A  |
| * NP-PE501X                                                                                                                                                              |        | COMPUTER  | VIDEO   | S—VIDEO  | HDMI1        | —      |
| * NP-PE456USL / NP-PE456WSL                                                                                                                                              |        | COMPUTER  | —       | —        | —            | USB-A  |
| * NP-PE401H                                                                                                                                                              |        | COMPUTER  | VIDEO   | S—VIDEO  | HDMI1        | —      |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                |        | —         | —       | —        | —            | —      |
| * NP-PH1400U                                                                                                                                                             |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                |        | COMPUTER  | BNC(CV) | BNC(Y/C) | —            | —      |
| * NP-PH1000U                                                                                                                                                             |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                     |        | —         | —       | —        | —            | —      |
| NP-PV710UL+                                                                                                                                                              |        | —         | —       | —        | —            | —      |
| NP-PX2201UL                                                                                                                                                              |        | COMPUTER  | —       | —        | —            | —      |
| NP-PX2000UL                                                                                                                                                              |        | COMPUTER  | —       | —        | —            | —      |
| NP-PX1005QL                                                                                                                                                              |        | —         | —       | —        | —            | —      |
| NP-PX1004UL                                                                                                                                                              |        | COMPUTER  | BNC(CV) | BNC(Y/C) | —            | —      |
| NP-PX803UL                                                                                                                                                               |        | —         | —       | —        | —            | —      |
| * NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                      |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | VIEWER |
| NP-PX651X / NP-PX581W                                                                                                                                                    |        | Computer1 | Video   | S-Video  | Component    | —      |
| * NP-PX620X / NP-PX550W                                                                                                                                                  |        | Computer1 | Video   | S—Video  | Computer3    | —      |
| NP-PX602UL / NP-PX602WL                                                                                                                                                  |        | COMPUTER  | BNC(CV) | BNC(Y/C) | —            | —      |
| NP-U321H                                                                                                                                                                 |        | COMPUTER  | VIDEO   | —        | HDMI1(078-3) | —      |
| * NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                              |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | —      |
| NP-UM352W                                                                                                                                                                |        | COMPUTER  | VIDEO   | —        | —            | —      |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                            |        | COMPUTER  | VIDEO   | —        | —            | USB-A  |
| * NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                          |        | COMPUTER  | VIDEO   | S—VIDEO  | HDMI1        | VIEWER |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                     |        | COMPUTER  | VIDEO   | —        | HDMI1(078-3) | —      |
| * NP-V311W / NP-V281W / NP-V311X                                                                                                                                         |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | —      |
| * NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                              |        | COMPUTER1 | VIDEO   | S—VIDEO  | HDMI         | —      |
| * NP-V230X / NP-V260 / NP-V230                                                                                                                                           |        | COMPUTER  | VIDEO   | S—VIDEO  | —            | —      |
| * NP-V260R                                                                                                                                                               |        | COMPUTER  | VIDEO   | S—VIDEO  | HDMI         | —      |
| NP-VE303X / NP-VE303                                                                                                                                                     |        | COMPUTER  | VIDEO   | —        | —            | —      |
| * NP-VE281X / NP-VE281                                                                                                                                                   |        | COMPUTER  | VIDEO   | —        | HDMI         | —      |
| * NP-VE280X / NP-VE280                                                                                                                                                   |        | COMPUTER  | VIDEO   | —        | —            | —      |

Supplement for "305-3. BASIC INFORMATION REQUEST"

| Parameter | Model name              | Description                               |
|-----------|-------------------------|-------------------------------------------|
| DATA04    | Selection signal type 2 | NP-U300X / NP-U250X / NP-U310W / NP-U260W |
| DATA07    | Sound mute              | NP-M420XV                                 |
| DATA09    | Freeze status           | NP4100 / NP4100W / NP-PX620X / NP-PX550W  |
|           |                         | If there is no signal, FFh is returned.   |
|           |                         | FFh is returned.                          |
|           |                         | Not supported (00h is always returned).   |

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

| Model name                                                                                                                                                                        | DATA03     | 01h | 01h   | 01h          | 01h          |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|-----|-------|--------------|--------------|
|                                                                                                                                                                                   | DATA04     | 0Ah | 20h   | 21h          | 22h          |
| * NP4100 / NP4100W                                                                                                                                                                |            | —   | —     | —            | —            |
| NP-M420X / NP-M420XV                                                                                                                                                              |            | —   | —     | —            | —            |
| * NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                                               |            | —   | —     | —            | —            |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS |            | —   | —     | HDMI1        | —            |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              |            | —   | —     | HDMI1        | —            |
| * NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                            |            | —   | —     | —            | —            |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    |            | —   | —     | HDMI1        | —            |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           |            | —   | —     | HDMI1        | —            |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  |            | —   | —     | HDMI1        | —            |
| * NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                               |            | —   | —     | —            | —            |
| NP-P627UL / NP-P547UL                                                                                                                                                             |            | —   | —     | HDMI1        | —            |
| NP-P603X / NP-P523X / NP-P523X                                                                                                                                                    |            | —   | —     | HDMI1        | —            |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              |            | —   | —     | HDMI1        | —            |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 |            | —   | —     | HDMI1        | —            |
| NP-P506QL                                                                                                                                                                         |            | —   | —     | HDMI1        | —            |
| NP-P502HL / NP-P502WL                                                                                                                                                             |            | —   | —     | HDMI1        | —            |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                         |            | —   | —     | HDMI1        | —            |
| * NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                       |            | —   | —     | —            | —            |
| * NP-P420X / NP-P350X / NP-P350W                                                                                                                                                  |            | —   | —     | —            | —            |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         |            | —   | —     | HDMI1        | —            |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          |            | —   | —     | HDMI1        | DiaplayPort  |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  |            | —   | —     | HDMI1        | DiaplayPort  |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          |            | —   | —     | HDMI1        | DiaplayPort  |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          |            | —   | —     | HDMI1        | DiaplayPort  |
| * NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                   |            | —   | —     | —            | —            |
| * NP-PE506UL / NP-PE506WL                                                                                                                                                         |            | —   | —     | HDMI1        | —            |
| * NP-PE501X                                                                                                                                                                       |            | —   | —     | —            | —            |
| * NP-PE456USL / NP-PE456WSL                                                                                                                                                       |            | —   | —     | HDMI1        | —            |
| * NP-PE401H                                                                                                                                                                       |            | —   | —     | —            | —            |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         |            | —   | —     | HDMI1        | DiaplayPort1 |
| * NP-PH1400U                                                                                                                                                                      | STEREO DVI | —   | —     | —            | —            |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         |            | —   | —     | HDMI         | DiaplayPort  |
| * NP-PH1000U                                                                                                                                                                      |            | —   | —     | —            | —            |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              |            | —   | —     | HDMI1        | —            |
| NP-PV710UL+                                                                                                                                                                       |            | —   | —     | HDMI1        | —            |
| NP-PX2201UL                                                                                                                                                                       |            | —   | DVI-D | HDMI1        | DiaplayPort  |
| NP-PX2000UL                                                                                                                                                                       |            | —   | DVI-D | HDMI1        | DiaplayPort  |
| NP-PX1005QL                                                                                                                                                                       |            | —   | —     | HDMI1        | DiaplayPort1 |
| NP-PX1004UL                                                                                                                                                                       |            | —   | —     | HDMI         | DiaplayPort  |
| NP-PX803UL                                                                                                                                                                        |            | —   | —     | HDMI         | DiaplayPort  |
| * NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                               |            | —   | —     | —            | —            |
| NP-PX651X / NP-PX581W                                                                                                                                                             |            | —   | —     | —            | Computer3    |
| * NP-PX620X / NP-PX550W                                                                                                                                                           |            | —   | —     | —            | —            |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           |            | —   | —     | HDMI         | DiaplayPort  |
| NP-U321H                                                                                                                                                                          |            | —   | —     | HDMI1(305-3) | —            |
| * NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                       |            | —   | —     | —            | —            |
| NP-UM352W                                                                                                                                                                         |            | —   | —     | HDMI1        | —            |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     |            | —   | —     | HDMI1        | —            |
| * NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                   |            | —   | —     | —            | —            |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              |            | —   | —     | HDMI1(305-3) | —            |
| * NP-V311W / NP-V281W / NP-V311X                                                                                                                                                  |            | —   | —     | —            | —            |
| * NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                       |            | —   | —     | —            | —            |
| * NP-V230X / NP-V260 / NP-V230                                                                                                                                                    |            | —   | —     | —            | —            |
| * NP-V260R                                                                                                                                                                        |            | —   | —     | —            | —            |
| NP-VE303X / NP-VE303                                                                                                                                                              |            | —   | —     | HDMI         | —            |
| * NP-VE281X / NP-VE281                                                                                                                                                            |            | —   | —     | —            | —            |
| * NP-VE280X / NP-VE280                                                                                                                                                            |            | —   | —     | —            | —            |

Supplement for "305-3. BASIC INFORMATION REQUEST"

| Parameter                      | Model name                                   |
|--------------------------------|----------------------------------------------|
| DATA04 Selection signal type 2 | NP-U300X / NP-U250X /<br>NP-U310W / NP-U260W |
| DATA07 Sound mute              | NP-M420XV                                    |
| DATA09 Freeze status           | NP4100 / NP4100W /<br>NP-PX620X / NP-PX550W  |

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

| Model name                                                                                                                                                               | DATA03 | 01h  | 01h     | 01h  | 02h       |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|------|---------|------|-----------|
|                                                                                                                                                                          | DATA04 | 23h  | 27h     | 28h  | 01h       |
| * NP4100 / NP4100W                                                                                                                                                       |        | —    | —       | —    | Computer2 |
| NP-M420X / NP-M420XV                                                                                                                                                     |        |      |         |      |           |
| * NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS                                            |        | —    | —       | —    | COMPUTER2 |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS |        | —    | —       | —    | —         |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS                                                           |        | —    | —       | —    | —         |
| * NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                   |        | —    | —       | —    | COMPUTER2 |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X / NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                            |        | —    | —       | —    | —         |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X / NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X / NP-MC342X / NP-MC302X                                                    |        | —    | —       | —    | —         |
| NP-ME401W / NP-ME361W / NP-ME31W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                             |        | —    | —       | —    | —         |
| * NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                      |        | —    | —       | —    | COMPUTER2 |
| NP-P627UL / NP-P547UL                                                                                                                                                    |        | —    | HDBaseT | —    | —         |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                          |        | —    | —       | —    | —         |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                     |        | —    | HDBaseT | —    | —         |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                        |        | —    | HDBaseT | —    | —         |
| NP-P506QL                                                                                                                                                                |        | —    | HDBaseT | —    | —         |
| NP-P502HL / NP-P502WL                                                                                                                                                    |        | —    | HDBaseT | —    | —         |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                |        | —    | —       | —    | —         |
| * NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                              |        | —    | —       | —    | —         |
| * NP-P420X / NP-P350X / NP-P350W                                                                                                                                         |        | —    | —       | —    | COMPUTER2 |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                |        | —    | HDBaseT | SDI  | —         |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                 |        | —    | HDBaseT | —    | —         |
| NP-PA803UL / NP-PA703UL / NP-PA653UL / NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X                                                             |        | —    | HDBaseT | —    | —         |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X                                                                                                    |        | —    | —       | —    | BNC       |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X                                                                                                    |        | —    | —       | —    | BNC       |
| * NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                          |        | —    | —       | —    | COMPUTER2 |
| * NP-PE506UL / NP-PE506WL                                                                                                                                                |        | —    | —       | —    | —         |
| * NP-PE501X                                                                                                                                                              |        | —    | —       | —    | —         |
| * NP-PE456USL / NP-PE456WSL                                                                                                                                              |        | —    | —       | —    | —         |
| * NP-PE401H                                                                                                                                                              |        | —    | —       | —    | —         |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                |        | SLOT | HDBaseT | SDI1 | —         |
| * NP-PH1400U                                                                                                                                                             |        | —    | —       | —    | COMPUTER2 |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                |        | SLOT | —       | —    | BNC       |
| * NP-PH1000U                                                                                                                                                             |        | —    | —       | —    | COMPUTER2 |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                     |        | —    | HDBaseT | —    | —         |
| NP-PV710UL+                                                                                                                                                              |        | —    | HDBaseT | —    | —         |
| NP-PX2201UL                                                                                                                                                              |        | —    | HDBaseT | SDI  | BNC       |
| NP-PX2000UL                                                                                                                                                              |        | —    | HDBaseT | SDI  | BNC       |
| NP-PX1005QL                                                                                                                                                              |        | SLOT | HDBaseT | SDI1 | —         |
| NP-PX1004UL                                                                                                                                                              |        | SLOT | HDBaseT | —    | BNC       |
| NP-PX803UL                                                                                                                                                               |        |      |         |      |           |
| * NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                      |        | —    | —       | —    | COMPUTER2 |
| NP-PX651X / NP-PX581W                                                                                                                                                    |        | HDMI | —       | —    | —         |
| * NP-PX620X / NP-PX550W                                                                                                                                                  |        | —    | —       | —    | Computer2 |
| NP-PX602UL / NP-PX602WL                                                                                                                                                  |        | SLOT | —       | —    | BNC       |
| NP-U321H                                                                                                                                                                 |        | —    | —       | —    | —         |
| * NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                              |        | —    | —       | —    | COMPUTER2 |
| NP-UM352W                                                                                                                                                                |        | —    | —       | —    | —         |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                            |        | —    | —       | —    | —         |
| * NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                          |        | —    | —       | —    | —         |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                     |        | —    | —       | —    | —         |
| * NP-V311W / NP-V281W / NP-V311X                                                                                                                                         |        | —    | —       | —    | COMPUTER2 |
| * NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                              |        | —    | —       | —    | COMPUTER2 |
| * NP-V230X / NP-V260 / NP-V230                                                                                                                                           |        | —    | —       | —    | —         |
| * NP-V260R                                                                                                                                                               |        | —    | —       | —    | —         |
| NP-VE303X / NP-VE303                                                                                                                                                     |        | —    | —       | —    | —         |
| * NP-VE281X / NP-VE281                                                                                                                                                   |        | —    | —       | —    | —         |
| * NP-VE280X / NP-VE280                                                                                                                                                   |        | —    | —       | —    | —         |

Supplement for "305-3. BASIC INFORMATION REQUEST"

| Parameter                      | Model name                                |
|--------------------------------|-------------------------------------------|
| DATA04 Selection signal type 2 | NP-U300X / NP-U250X / NP-U310W / NP-U260W |
| DATA07 Sound mute              | NP-M420XV                                 |
| DATA09 Freeze status           | NP4100 / NP4100W / NP-PX620X / NP-PX550W  |

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

| Model name                                                                                                                                                                        | DATA03 | 02h          | 02h      | 02h          | 02h          |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|--------------|----------|--------------|--------------|
|                                                                                                                                                                                   | DATA04 | 06h          | 07h      | 21h          | 22h          |
| * NP4100 / NP4100W                                                                                                                                                                |        | —            | —        | —            | —            |
| NP-M420X / NP-M420XV                                                                                                                                                              |        |              |          |              |              |
| * NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                                               |        | —            | NETWORK  | —            | —            |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS |        | —            | LAN      | HDMI2        | —            |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              |        | —            | LAN      | HDMI2        | —            |
| * NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                            |        | —            | NETWORK  | —            | —            |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    |        | —            | LAN      | HDMI2        | —            |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           |        | —            | LAN      | HDMI2        | —            |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  |        | —            | LAN      | HDMI2        | —            |
| * NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                               |        | —            | —        | —            | —            |
| NP-P627UL / NP-P547UL                                                                                                                                                             |        | —            | LAN      | HDMI2        | —            |
| NP-P603X / NP-P523X / NP-P523X                                                                                                                                                    |        | —            | —        | HDMI2        | —            |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              |        | —            | —        | HDMI2        | —            |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 |        | —            | LAN      | HDMI2        | —            |
| NP-P506QL                                                                                                                                                                         |        | —            | —        | HDMI2        | —            |
| NP-P502HL / NP-P502WL                                                                                                                                                             |        | —            | —        | HDMI2        | —            |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                         |        | —            | —        | HDMI2        | —            |
| * NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                       |        | HDMI2        | NETWORK  | —            | —            |
| * NP-P420X / NP-P350X / NP-P350W                                                                                                                                                  |        | —            | NETWORK  | —            | —            |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         |        | —            | —        | HDMI2        | —            |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          |        | —            | —        | HDMI2        | —            |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  |        | —            | —        | HDMI2        | —            |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          |        | —            | HDBaseT  | HDMI2        | —            |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          |        | —            | ETHERNET | HDMI2        | —            |
| * NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                   |        | DisplayPort  | NETWORK  | —            | —            |
| * NP-PE506UL / NP-PE506WL                                                                                                                                                         |        | —            | LAN      | HDMI2        | —            |
| * NP-PE501X                                                                                                                                                                       |        | HDMI2        | —        | —            | —            |
| * NP-PE456USL / NP-PE456WSL                                                                                                                                                       |        | —            | LAN      | HDMI2        | —            |
| * NP-PE401H                                                                                                                                                                       |        | HDMI2        | —        | —            | —            |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         |        | —            | —        | HDMI2        | DiaplayPort2 |
| * NP-PH1400U                                                                                                                                                                      |        | DisplayPort  | NETWORK  | —            | —            |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         |        | —            | HDBaseT  | —            | —            |
| * NP-PH1000U                                                                                                                                                                      |        | DisplayPort  | NETWORK  | —            | —            |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              |        | —            | —        | HDMI2        | —            |
| NP-PV710UL+                                                                                                                                                                       |        | —            | —        | HDMI2        | —            |
| NP-PX2201UL                                                                                                                                                                       |        | —            | —        | HDMI2        | —            |
| NP-PX2000UL                                                                                                                                                                       |        | —            | —        | HDMI2        | —            |
| NP-PX1005QL                                                                                                                                                                       |        | —            | —        | HDMI2        | DiaplayPort2 |
| NP-PX1004UL                                                                                                                                                                       |        | —            | —        | —            | —            |
| NP-PX803UL                                                                                                                                                                        |        | —            | —        | —            | —            |
| * NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                               |        | DisplayPort  | NETWORK  | —            | —            |
| NP-PX651X / NP-PX581W                                                                                                                                                             |        | Computer2    | —        | HDBaseT      | —            |
| * NP-PX620X / NP-PX550W                                                                                                                                                           |        | —            | —        | —            | —            |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           |        | —            | HDBaseT  | —            | —            |
| NP-U321H                                                                                                                                                                          |        | HDMI2(078-3) | —        | HDMI2(305-3) | —            |
| * NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                       |        | —            | —        | —            | —            |
| NP-UM352W                                                                                                                                                                         |        | —            | —        | HDMI2        | —            |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     |        | —            | LAN      | HDMI2        | —            |
| * NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                   |        | HDMI2        | NETWORK  | —            | —            |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              |        | HDMI2(078-3) | —        | HDMI2(305-3) | —            |
| * NP-V311W / NP-V281W / NP-V311X                                                                                                                                                  |        | —            | —        | —            | —            |
| * NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                       |        | —            | —        | —            | —            |
| * NP-V230X / NP-V260 / NP-V230                                                                                                                                                    |        | —            | —        | —            | —            |
| * NP-V260R                                                                                                                                                                        |        | —            | —        | —            | —            |
| NP-VE303X / NP-VE303                                                                                                                                                              |        | —            | —        | —            | —            |
| * NP-VE281X / NP-VE281                                                                                                                                                            |        | —            | —        | —            | —            |
| * NP-VE280X / NP-VE280                                                                                                                                                            |        | —            | —        | —            | —            |

Supplement for "305-3. BASIC INFORMATION REQUEST"

| Parameter                      | Model name                                   |
|--------------------------------|----------------------------------------------|
| DATA04 Selection signal type 2 | NP-U300X / NP-U250X /<br>NP-U310W / NP-U260W |
| DATA07 Sound mute              | NP-M420XV                                    |
| DATA09 Freeze status           | NP4100 / NP4100W /<br>NP-PX620X / NP-PX550W  |



#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

| Model name                                                                                                                                                                        | DATA03 | 02h  | 03h       | 03h       | 03h  |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|------|-----------|-----------|------|
|                                                                                                                                                                                   | DATA04 | 28h  | 01h       | 04h       | 06h  |
| * NP4100 / NP4100W                                                                                                                                                                |        | —    | —         | Component | —    |
| NP-M420X / NP-M420XV                                                                                                                                                              |        |      |           |           |      |
| * NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                                               |        | —    | —         | —         | —    |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS |        | —    | —         | —         | —    |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              |        | —    | —         | —         | —    |
| * NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                            |        | —    | —         | —         | —    |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    |        | —    | —         | —         | —    |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           |        | —    | —         | —         | —    |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  |        | —    | —         | —         | —    |
| * NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                               |        | —    | —         | —         | —    |
| NP-P627UL / NP-P547UL                                                                                                                                                             |        | —    | —         | —         | —    |
| NP-P603X / NP-P523X / NP-P523X                                                                                                                                                    |        | —    | —         | —         | —    |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              |        | —    | —         | —         | —    |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 |        | —    | —         | —         | —    |
| NP-P506QL                                                                                                                                                                         |        | —    | —         | —         | —    |
| NP-P502HL / NP-P502WL                                                                                                                                                             |        | —    | —         | —         | —    |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                         |        | —    | —         | —         | —    |
| * NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                       |        | —    | —         | —         | —    |
| * NP-P420X / NP-P350X / NP-P350W                                                                                                                                                  |        | —    | —         | —         | —    |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         |        | —    | —         | —         | —    |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          |        | —    | —         | —         | —    |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  |        | —    | —         | —         | —    |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          |        | —    | —         | —         | —    |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          |        | —    | —         | —         | —    |
| * NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                   |        | —    | COMPUTER3 | —         | —    |
| * NP-PE506UL / NP-PE506WL                                                                                                                                                         |        | —    | —         | —         | —    |
| * NP-PE501X                                                                                                                                                                       |        | —    | —         | —         | —    |
| * NP-PE456USL / NP-PE456WSL                                                                                                                                                       |        | —    | —         | —         | —    |
| * NP-PE401H                                                                                                                                                                       |        | —    | —         | —         | —    |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         |        | SDI2 | —         | —         | —    |
| * NP-PH1400U                                                                                                                                                                      |        | —    | COMPUTER3 | —         | SLOT |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         |        | —    | —         | —         | —    |
| * NP-PH1000U                                                                                                                                                                      |        | —    | COMPUTER3 | —         | SLOT |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              |        | —    | —         | —         | —    |
| NP-PV710UL+                                                                                                                                                                       |        | —    | —         | —         | —    |
| NP-PX2201UL                                                                                                                                                                       |        | —    | —         | —         | —    |
| NP-PX2000UL                                                                                                                                                                       |        | —    | —         | —         | —    |
| NP-PX1005QL                                                                                                                                                                       |        | SDI2 | —         | —         | —    |
| NP-PX1004UL                                                                                                                                                                       |        | —    | —         | —         | —    |
| NP-PX803UL                                                                                                                                                                        |        | —    | —         | —         | —    |
| * NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                               |        | —    | COMPUTER3 | —         | SLOT |
| NP-PX651X / NP-PX581W                                                                                                                                                             |        | —    | —         | —         | —    |
| * NP-PX620X / NP-PX550W                                                                                                                                                           |        | —    | —         | Component | —    |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           |        | —    | —         | —         | —    |
| NP-U321H                                                                                                                                                                          |        | —    | —         | —         | —    |
| * NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                       |        | —    | —         | —         | —    |
| NP-UM352W                                                                                                                                                                         |        | —    | —         | —         | —    |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     |        | —    | —         | —         | —    |
| * NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                   |        | —    | —         | —         | —    |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              |        | —    | —         | —         | —    |
| * NP-V311W / NP-V281W / NP-V311X                                                                                                                                                  |        | —    | —         | —         | —    |
| * NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                       |        | —    | —         | —         | —    |
| * NP-V230X / NP-V260 / NP-V230                                                                                                                                                    |        | —    | —         | —         | —    |
| * NP-V260R                                                                                                                                                                        |        | —    | —         | —         | —    |
| NP-VE303X / NP-VE303                                                                                                                                                              |        | —    | —         | —         | —    |
| * NP-VE281X / NP-VE281                                                                                                                                                            |        | —    | —         | —         | —    |
| * NP-VE280X / NP-VE280                                                                                                                                                            |        | —    | —         | —         | —    |

Supplement for "305-3. BASIC INFORMATION REQUEST"

| Parameter                      | Model name                                   |
|--------------------------------|----------------------------------------------|
| DATA04 Selection signal type 2 | NP-U300X / NP-U250X /<br>NP-U310W / NP-U260W |
| DATA07 Sound mute              | NP-M420XV                                    |
| DATA09 Freeze status           | NP4100 / NP4100W /<br>NP-PX620X / NP-PX550W  |

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

| Model name                                                                                                                                                                        | DATA03 | 03h  | 04h         | 04h  | 05h  |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|------|-------------|------|------|
|                                                                                                                                                                                   | DATA04 | 28h  | 07h         | 28h  | 07h  |
| * NP4100 / NP4100W                                                                                                                                                                |        | —    | —           | —    | —    |
| NP-M420X / NP-M420XV                                                                                                                                                              |        |      |             |      |      |
| * NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W /<br>NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS /<br>NP-M300WS / NP-M260WS                                               |        | —    | USB DISPLAY | —    | —    |
| NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W /<br>NP-M363W / NP-M323W / NP-M333XS / NP-M353WS /<br>NP-M303WS / NP-M403H / NP-M323H / NP-M353HS /<br>NP-M323HS / NP-M303HS |        | —    | USB-B       | —    | —    |
| NP-M402W / NP-M362W / NP-M402X / NP-M362X /<br>NP-M322X / NP-M282X / NP-M322W / NP-M352WS /<br>NP-M302WS / NP-M332XS                                                              |        | —    | USB-B       | —    | —    |
| * NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W                                                                                                                            |        | —    | USB DISPLAY | —    | —    |
| NP-ME403U / NP-ME423W / NP-ME383W / NP-ME453X<br>NP-MC423W / NP-MC393W / NP-MC453X / NP-MC363X                                                                                    |        | —    | —           | —    | —    |
| NP-ME382U / NP-ME342U / NP-ME372W / NP-ME402X<br>NP-MC382W / NP-MC332W / NP-MC422X / NP-MC372X<br>NP-MC342X / NP-MC302X                                                           |        | —    | USB DISPLAY | —    | —    |
| NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /<br>NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X                                                                                  |        | —    | USB-B       | —    | —    |
| * NP-ME360X / NP-ME310X / NP-ME270X                                                                                                                                               |        | —    | —           | —    | —    |
| NP-P627UL / NP-P547UL                                                                                                                                                             |        | —    | —           | —    | —    |
| NP-P603X / NP-P523X / NP-PE523X                                                                                                                                                   |        | —    | —           | —    | —    |
| NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X                                                                                                                              |        | —    | —           | —    | —    |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                                                                                 |        | —    | —           | —    | —    |
| NP-P506QL                                                                                                                                                                         |        | —    | —           | —    | —    |
| NP-P502HL / NP-P502WL                                                                                                                                                             |        | —    | —           | —    | APPS |
| NP-P502H / NP-P502W / NP-P452H / NP-P452W                                                                                                                                         |        | —    | —           | —    | —    |
| * NP-P501X / NP-P451X / NP-P451W / NP-P401W                                                                                                                                       |        | —    | USB DISPLAY | —    | —    |
| * NP-P420X / NP-P350X / NP-P350W                                                                                                                                                  |        | —    | USB DISPLAY | —    | —    |
| NP-PA1705UL / NP-PA1505UL                                                                                                                                                         |        | —    | —           | —    | —    |
| NP-PA1004UL / NP-PA804UL                                                                                                                                                          |        | —    | —           | —    | —    |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X                                                                  |        | —    | —           | —    | —    |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                                                                                          |        | —    | —           | —    | —    |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                                                                                          |        | —    | —           | —    | —    |
| * NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U                                                                                                                                   |        | —    | —           | —    | —    |
| * NP-PE506UL / NP-PE506WL                                                                                                                                                         |        | —    | —           | —    | —    |
| * NP-PE501X                                                                                                                                                                       |        | —    | USB DISPLAY | —    | —    |
| * NP-PE456USL / NP-PE456WSL                                                                                                                                                       |        | —    | —           | —    | —    |
| * NP-PE401H                                                                                                                                                                       |        | —    | —           | —    | —    |
| NP-PH3501QL / NP-PH2601QL                                                                                                                                                         |        | SDI3 | —           | SDI4 | —    |
| * NP-PH1400U                                                                                                                                                                      |        | —    | —           | —    | —    |
| NP-PH1202HL / NP-PH1002HL                                                                                                                                                         |        | —    | —           | —    | —    |
| * NP-PH1000U                                                                                                                                                                      |        | —    | —           | —    | —    |
| NP-PV800UL / NP-PV730UL / NP-PV710UL                                                                                                                                              |        | —    | —           | —    | —    |
| NP-PV710UL+                                                                                                                                                                       |        | —    | —           | —    | —    |
| NP-PX2201UL                                                                                                                                                                       |        | —    | —           | —    | —    |
| NP-PX2000UL                                                                                                                                                                       |        | —    | —           | —    | —    |
| NP-PX1005QL                                                                                                                                                                       |        | SDI3 | —           | SDI4 | —    |
| NP-PX1004UL                                                                                                                                                                       |        | —    | —           | —    | —    |
| NP-PX803UL                                                                                                                                                                        |        | —    | —           | —    | —    |
| * NP-PX750U / NP-PX700W / NP-PX800X                                                                                                                                               |        | —    | —           | —    | —    |
| NP-PX651X / NP-PX581W                                                                                                                                                             |        | —    | —           | —    | —    |
| * NP-PX620X / NP-PX550W                                                                                                                                                           |        | —    | —           | —    | —    |
| NP-PX602UL / NP-PX602WL                                                                                                                                                           |        | —    | —           | —    | —    |
| NP-U321H                                                                                                                                                                          |        | —    | —           | —    | —    |
| * NP-U300X / NP-U250X / NP-U310W / NP-U260W                                                                                                                                       |        | —    | —           | —    | —    |
| NP-UM352W                                                                                                                                                                         |        | —    | USB-B       | —    | APPS |
| NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X                                                                                                                                     |        | —    | USB-B       | —    | —    |
| * NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W                                                                                                                                   |        | —    | USB DISPLAY | —    | —    |
| NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H                                                                                                                              |        | —    | —           | —    | —    |
| * NP-V311W / NP-V281W / NP-V311X                                                                                                                                                  |        | —    | —           | —    | —    |
| * NP-V300X / NP-V260X / NP-V300W / NP-V260W                                                                                                                                       |        | —    | —           | —    | —    |
| * NP-V230X / NP-V260 / NP-V230                                                                                                                                                    |        | —    | —           | —    | —    |
| * NP-V260R                                                                                                                                                                        |        | —    | —           | —    | —    |
| NP-VE303X / NP-VE303                                                                                                                                                              |        | —    | —           | —    | —    |
| * NP-VE281X / NP-VE281                                                                                                                                                            |        | —    | —           | —    | —    |
| * NP-VE280X / NP-VE280                                                                                                                                                            |        | —    | —           | —    | —    |

Supplement for "305-3. BASIC INFORMATION REQUEST"

| Parameter                      | Model name                                   |
|--------------------------------|----------------------------------------------|
| DATA04 Selection signal type 2 | NP-U300X / NP-U250X /<br>NP-U310W / NP-U260W |
| DATA07 Sound mute              | NP-M420XV                                    |
| DATA09 Freeze status           | NP4100 / NP4100W /<br>NP-PX620X / NP-PX550W  |

## 4. Supplementary Information by Command

### 097-198. PIP/PICTURE BY PICTURE REQUEST

### 098-198. PIP/PICTURE BY PICTURE SET

※ ・ ・ ・ SUB2 INPUT and SUB3 INPUT are not supported.

#### ■ Sub input

| Model name                                                                                                       | DATA02 | DATA02  |          |       |       |              |          |     |
|------------------------------------------------------------------------------------------------------------------|--------|---------|----------|-------|-------|--------------|----------|-----|
|                                                                                                                  | 00h    | 01h     | 02h      | 03h   | 04h   | 05h          | 06h      | 07h |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                | OFF    | —       | —        | HDMI1 | HDMI2 | —            | COMPUTER | —   |
| NP-PA1705UL / NP-PA1505UL                                                                                        | OFF    | —       | —        | HDMI1 | HDMI2 | —            | —        | —   |
| NP-PA1004UL / NP-PA804UL                                                                                         | OFF    | —       | —        | HDMI1 | HDMI2 | DisplayPort  | COMPUTER | —   |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X | OFF    | —       | —        | HDMI1 | HDMI2 | DisplayPort  | COMPUTER | —   |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                         | OFF    | BNC(CV) | BNC(Y/C) | HDMI1 | HDMI2 | DisplayPort  | COMPUTER | BNC |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                         | OFF    | BNC(CV) | BNC(Y/C) | HDMI1 | HDMI2 | DisplayPort  | COMPUTER | BNC |
| NP-PH3501QL / NP-PH2601QL                                                                                        | —      | —       | —        | HDMI1 | HDMI2 | DisplayPort1 | —        | —   |
| NP-PH1202HL / NP-PH1002HL                                                                                        | OFF    | BNC(CV) | BNC(Y/C) | HDMI  | SLOT  | DisplayPort  | COMPUTER | BNC |
| NP-PX1005QL                                                                                                      | —      | —       | —        | HDMI1 | HDMI2 | DisplayPort1 | —        | —   |
| NP-PX1004UL<br>NP-PX803UL                                                                                        | OFF    | BNC(CV) | BNC(Y/C) | HDMI  | SLOT  | DisplayPort  | COMPUTER | BNC |
| NP-PX602UL / NP-PX602WL                                                                                          | OFF    | BNC(CV) | BNC(Y/C) | HDMI  | SLOT  | DisplayPort  | COMPUTER | BNC |

## 4. Supplementary Information by Co

### 097-198. PIP/PICTURE BY PICTURE REQUEST

### 098-198. PIP/PICTURE BY PICTURE SET

※・・・・SUB2 INPUT and SUB3 INPUT are not supported.

#### ■ Sub input

| Model name                                                                                                       | DATA02   |       |              |      |      |      |      |       |
|------------------------------------------------------------------------------------------------------------------|----------|-------|--------------|------|------|------|------|-------|
|                                                                                                                  | 08h      | 09h   | 0Ah          | 0Bh  | 0Ch  | 0Dh  | 0Eh  | 0Fh   |
| NP-P605UL / NP-P525UL / NP-P525WL                                                                                | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |
| NP-PA1705UL / NP-PA1505UL                                                                                        | HDBaseT  | —     | —            | SDI  | —    | —    | —    | —     |
| NP-PA1004UL / NP-PA804UL                                                                                         | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |
| NP-PA803UL / NP-PA703UL / NP-PA653UL<br>NP-PA803U / NP-PA723U / NP-PA653U /<br>NP-PA853W / NP-PA703W / NP-PA903X | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |
| NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X                                         | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |
| NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /<br>NP-PA721X / NP-PA621X                                         | ETHERNET | USB-A | —            | —    | —    | —    | —    | —     |
| NP-PH3501QL / NP-PH2601QL                                                                                        | HDBaseT※ | —     | DisplayPort2 | SDI1 | SDI2 | SDI3 | SDI4 | SLOT※ |
| NP-PH1202HL / NP-PH1002HL                                                                                        | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |
| NP-PX1005QL                                                                                                      | HDBaseT※ | —     | DisplayPort2 | SDI1 | SDI2 | SDI3 | SDI4 | SLOT※ |
| NP-PX1004UL<br>NP-PX803UL                                                                                        | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |
| NP-PX602UL / NP-PX602WL                                                                                          | HDBaseT  | —     | —            | —    | —    | —    | —    | —     |

## 4. Supplementary Information by Command

### 319-10. AUDIO SELECT SET

#### ■ Audio select

| Model name                                                                                             | DATA02 |       |             |                       |       |       |         |
|--------------------------------------------------------------------------------------------------------|--------|-------|-------------|-----------------------|-------|-------|---------|
|                                                                                                        | 00h    | 01h   | 02h         | 03h                   | 04h   | 05h   | 09h     |
| NP-PA1004UL / NP-PA804UL /<br>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W /<br>NP-PA722X / NP-PA622X | HDMI1  | HDMI2 | DisplayPort | HDBaseT               | USB-A | USB-B | —       |
| Other than the above models                                                                            | HDMI1  | HDMI2 | DisplayPort | ETHRENET<br>or<br>LAN | USB-A | USB-B | HDBaseT |