

Product Line
CISRACK

Type
RM-CI-T17

Supported Models **CISCO MERAKI MS130-8**
CISCO MERAKI MS130-8P

DIMENSIONS 1U

COLOR Metallic Blue

PRODUCT DIMENSIONS 44 x 482 x 217 mm
(height x width x depth) 1.73 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Use the torx key to remove 4 bolts on the corners of the bottom of the Cisco appliance.
2. Place your Cisco appliance on the rack with the connections facing the front.
3. Turn over the rack with the Cisco appliance.
4. Use the bolts to fix the Cisco appliance on the rack and turn it back over.
5. Place the power supply on the rack and tie it down with the 2 long zip ties.
6. Secure the power cable on the rack using a zip tie. See detail 1.
7. Plug in the power cable and tie the excess length of the power cable down with a zip tie.
8. Place your Cisco in your 19 inch rack.



Detail 1

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	CisRack
4	Zip ties
1	Torx key
4	Bolts



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 1 - 20-02-2024

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
559 S Interstate 35, Suite 350
Round Rock - TX 78664
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT