

60x10mm Replacement Ball Bearing Computer Case Fan w/ TX3 Connector

Product ID: FAN6X1TX3



This versatile 60mm fan is an ideal replacement fan for keeping your computer running cool. The fan can be powered through a TX3 connection, and features a dual ball bearing design that ensures reliable cooling and longer fan lifespan.

The fan can be used to replace the fan component of some CPU coolers or mounted to the side panel of a computer case and features a tachometer pin on the TX3 motherboard connector that provides the host system with fan operating status information.

Certifications, Reports and Compatibility



Applications

- Replace a noisy or failed computer case fan
- Install into a computer to increase air flow and cooling

Features

- Dual ball bearing design
- 3-pin connector with tachometer wire
- Includes a 3-pin to 4-pin LP4 Molex adapter

	Warranty	2 Years
Hardware	Fan Bearing Type	Ball Bearing
	Number of Conductors	3
Performance	Air Flow Rate	15.49 CFM
	Fan RPM	4000
	MTBF	56,609 Hours
	Noise Level	28 dBA
Connector(s)	Connector Type(s)	1 - Molex Fan (3 pin, TX3) Female
Power	Input Current	160mA
	Input Voltage	12 DC
	Power Consumption	1.92W
Environmental	Operating Temperature	-10 to 80
Physical Characteristics	Color	Black
	Enclosure Type	Plastic
	Product Height	2.4 in [60 mm]
	Product Length	2.4 in [60 mm]
	Product Weight	1.3 oz [38 g]
	Product Width	0.4 in [10 mm]
Packaging Information	Shipping (Package) Weight	0.2 lb [0.1 kg]
What's in the Box	Included in Package	1 - 6cm Case Fan 1 - 3-pin to 4-pin LP4 Molex Adapter Cable

Product appearance and specifications are subject to change without notice.