



## GS-68C SOUNDBAR WITH SUBWOOFER

2.1 channel soundbar for clear communication

### THE WORKPLACE AND HIGHER EDUCATION ARE EVOLVING – FAST

Integrated solutions that empower voice and video have become commonplace. The need for these solutions to provide clear communication is paramount given the time spent and reliance upon these technologies. The AVerMedia GS-68C Soundbar pairs perfectly with video solutions for hybrid classes, meetings and flex spaces giving employees, professors, students, and staff an audio experience that doesn't compromise their ability to engage and contribute.



### NEXT LEVEL SOUND

Crystal clear audio throughout the room



### VOICE ENHANCEMENT

Digital amplifier



### REMOTE CONTROL

Freely walk around the room and control the audio levels



### MOUNTABLE

Mount on wall or credenza



## GENERAL

- Audio output: 2.1 Channel with built in subwoofer
- Coaxial input
- Optical input
- Line in input
- USB input
- LED indicator
- Digital amplifier with DSP inside
- Plastic case, digital amplifier with DSP inside
- Remote control

## SPECIFICATIONS

- Power Supply: 120V ~ 60Hz
- Power Output: 20W\*2+40W = 80W R.M.S
- Driver Unit: 2"\*2+2.25"\*2
- Input Impedance: 4 Ω\*2+4Ω\*2
- S/N: ≥72 dB
- Frequency Response: 80Hz 20Khz
- Distortion: </=0.5%(1K/1W)
- Input Sensitivity: 800mV 50mV
- Bluetooth Version: 4.2+EDR
- Bluetooth Range: within 10m

## DIMENSIONS

- 2.75" (H) X 3.07" (D) X 35.43" (L)/70(H) X 78(D) X 900(L) mm

## ADDITIONAL FEATURES

- Audio enhancement for interactive touch display
- Designed to be mounted on the wall or on a credenza

## WHAT'S IN THE BOX

- Soundbar (GS 68C)
- One Remote Controller
- Remote Controller Battery
- Wall Mount Kit
- 1.5m 3.5mmAUX cable
- 1.5m Optical cable
- Quick Guide