

## Voltage Sensors

AC model detects voltage from 50 to 250 VAC and indicates Alarm or Normal. DC model is user-programmable with both the base and top voltage from 0 to 60 volts.



### Specifications

**Communications Cable** — RJ-45 jack to sensor using UTP CAT5 cable

**Maximum Extension Cable Length** — 1000 ft. (304.8-m) with approved low-capacitance shielded cable or UTP

**Measurement Indication** — EME1A1-005: Alarm or Normal

**Measurement Range** — EME1A1-005: Detects voltage at 50 to 250 VAC;

EME1D1-005: User-programmable from 0 to 250 VDC

**Measurement Rate** — Multiple readings every second

**Sensor Type** — Open/closed contact switch

### Overview

The Voltage Sensors monitor the presence or absence of AC or DC voltage. The AC model includes an Alarm/Normal indicator in the device firmware. Use up to two AC voltage sensors per AlertWerks™ ServSensor Junior (EME102A), and up to eight per ServSensor (EME108A).

Connect up to eight voltage sensors to AlertWerks V4E (EME134A) ServSensor Expansion Hub RJ-45 sensor ports.

The voltage sensors include an SNMP interface for alarm/normal status. Set these using the Web interface and configure them to send alerts as SNMP traps, e-mail, and SMS (text message).

For features, turn this page over...

### Customer Support Information

Order toll-free in the U.S.: Call 877-877-BBOX (outside U.S. call 724-746-5500)  
FREE technical support 24 hours a day, 7 days a week: Call 724-746-5500 or fax 724-746-0746  
Mailing address: Black Box Corporation, 1000 Park Drive, Lawrence, PA 15055-1018  
Web site: [www.blackbox.com](http://www.blackbox.com) • E-mail: [info@blackbox.com](mailto:info@blackbox.com)

## Features

- Powered by the AlertWerks Hub (EME102A or EME108A). Needs no additional power.
- Use up to two AC voltage sensors per EME102A, and up to eight per EME108A.
- Detects the presence of two dry contact sensors.
- Connect up to eight voltage sensors to each EME134A or EME108A, or EME1X8 RJ-45 sensor ports.
- Includes an autosensing disconnect alarm.



© Copyright 2011. Black Box Corporation. All rights reserved. Printed in U.S.A. Black Box® and the Double Diamond logo are registered trademarks, and AlertWerks is a trademark, of BB Technologies, Inc. Any third-party trademarks appearing in this publication are acknowledged to be the property of their respective owners.

EME1A1-005, version 1

FREE, live, 24/7 Tech Support is just 30 seconds away.  
724-746-5500 | [blackbox.com](http://blackbox.com)